



> PRINT > COPY > SCAN

ECOSYS M6030cdn

> PRINT > COPY > SCAN > FAX

ECOSYS M6530cdn

# OPERATION GUIDE



# Preface

Thank you for purchasing the ECOSYS M6030cdn/ECOSYS M6530cdn.

This Operation Guide is intended to help you operate the machine correctly, perform routine maintenance, and take simple troubleshooting measures as needed so that the machine can always be used in the optimum condition.

Please read this Operation Guide before using the machine.


## **We recommend the use of our own brand supplies.**

Please use our genuine toner containers, which have passed rigorous quality control testing.

The use of non-genuine toner containers may cause failure.

We will not be liable for any damages caused by the use of third party supplies in this machine.

A label is affixed to our genuine supplies as shown below.



# Contents

<b>Preface</b> .....	<b>i</b>
<b>Contents</b> .....	<b>ii</b>
<b>Overview</b> .....	<b>vii</b>
<b>Machine Features</b> .....	<b>viii</b>
<b>Color and Image Quality Functions</b> .....	<b>xii</b>
Basic Color Modes .....	xii
Adjusting Image Quality and Color .....	xiii
<b>Guides Provided with the Machine</b> .....	<b>xiv</b>
<b>About the Operation Guide (this Guide)</b> .....	<b>xvi</b>
Structure of the guide .....	xvi
Conventions Used in This Guide .....	xvii
<b>Menu Map</b> .....	<b>xix</b>

<b>1</b>	<b>Legal and Safety Information</b> .....	<b>1-1</b>
	<b>Notice</b> .....	<b>1-2</b>
	Safety Conventions in This Guide .....	1-2
	Environment .....	1-3
	Precautions for Use .....	1-4
	Laser Safety (Europe) .....	1-5
	Legal Restriction on Copying/Scanning .....	1-6
	EN ISO 7779 .....	1-6
	EK1-ITB 2000 .....	1-6
	Legal Information .....	1-7
	Energy Saving Control Function .....	1-13
	Automatic 2-Sided Print Function .....	1-13
	Resource Saving - Paper .....	1-13
	Environmental benefits of "Power Management" .....	1-13
	Energy Star (ENERGY STAR®) Program .....	1-14
<b>2</b>	<b>Installing and Setting up the Machine</b> .....	<b>2-1</b>
	<b>Part Names</b> .....	<b>2-2</b>
	Machine Exterior .....	2-2
	Connectors/Interior .....	2-4
	With Optional Equipments Attached .....	2-6
	<b>Connecting the Machine and Other Devices</b> .....	<b>2-7</b>
	<b>Connecting Cables</b> .....	<b>2-8</b>
	Connecting LAN Cable .....	2-8
	Connecting USB Cable .....	2-9
	Connecting the Power Cable .....	2-9
	<b>Power On/Off</b> .....	<b>2-10</b>
	Power On .....	2-10
	Power Off .....	2-10
	<b>Using the Operation Panel</b> .....	<b>2-11</b>
	Operation Panel Keys .....	2-11
	Operation Method .....	2-12
	Display for Originals and Paper .....	2-13
	Help Screen .....	2-13
	<b>Login/Logout</b> .....	<b>2-14</b>
	Login .....	2-14
	Logout .....	2-15
	<b>Default Settings of the Machine</b> .....	<b>2-16</b>
	Setting Date and Time .....	2-16
	Network Setup (LAN Cable Connection) .....	2-17
	<b>Energy Saver function</b> .....	<b>2-20</b>
	Sleep and Auto Sleep .....	2-20
	<b>Installing Software</b> .....	<b>2-22</b>
	Software on DVD (Windows) .....	2-22
	Installing Software in Windows .....	2-23
	Uninstalling the Software .....	2-29

	Installing Software in Mac Computer .....	2-30
	Setting TWAIN Driver .....	2-32
	Setting WIA Driver .....	2-34
	<b>Checking the Counter .....</b>	<b>2-35</b>
	<b>Additional Preparations for the Administrator .....</b>	<b>2-36</b>
	Sending Documents to a PC .....	2-36
	Strengthening the Security .....	2-36
	<b>Command Center RX .....</b>	<b>2-38</b>
	Accessing Command Center RX .....	2-39
	Changing Security Settings .....	2-40
	Changing Device Information .....	2-42
	E-mail Settings .....	2-44
	Registering Destinations .....	2-48
	Creating a New Custom Box .....	2-49
	Printing a document stored in a Custom Box .....	2-50
	<b>Transferring Data from Our Other Products .....</b>	<b>2-52</b>
	Migrating the Address Book .....	2-52
<b>3</b>	<b>Preparation before Use .....</b>	<b>3-1</b>
	<b>Loading Paper .....</b>	<b>3-2</b>
	Precaution for Loading Paper .....	3-3
	Loading in the Cassettes .....	3-4
	Loading Paper in the Multi Purpose Tray .....	3-7
	Specifying Paper Size and Media Type .....	3-10
	<b>Paper Stopper .....</b>	<b>3-12</b>
	<b>Preparation for Sending a Document to a Shared Folder in a PC .....</b>	<b>3-13</b>
	Making a note of the computer name and full computer name .....	3-13
	Making a note of the user name and domain name .....	3-14
	Creating a Shared Folder, Making a Note of a Shared Folder .....	3-15
	Configuring Windows Firewall .....	3-19
	<b>Registering Destinations in the Address Book .....</b>	<b>3-23</b>
	Adding a Destination (Address Book) .....	3-23
	Adding a Destination on One Touch Key (One Touch Key) .....	3-29
<b>4</b>	<b>Printing from PC .....</b>	<b>4-1</b>
	<b>Printing from PC .....</b>	<b>4-2</b>
	Printing on Non-standard Sized Paper .....	4-4
	Printer Driver Print Settings Screen .....	4-5
	Printer Driver Help .....	4-6
	Changing the Default Printer Driver Settings (Windows 7) .....	4-6
	Canceling Printing from a Computer .....	4-6
	<b>Printing by AirPrint .....</b>	<b>4-7</b>
	<b>Printing by Google Cloud Print .....</b>	<b>4-8</b>
	<b>Printing Data Saved on the Printer .....</b>	<b>4-9</b>
	Specifying the Job Box from a Computer and Storing the Job .....	4-9
	Printing Documents from Private Print Box .....	4-10
	Printing Document from Stored Job Box .....	4-12
	Printing Document from Quick Copy Box .....	4-14
	Printing Document from Proof and Hold Box .....	4-16
	<b>Status Monitor .....</b>	<b>4-18</b>
	Accessing the Status Monitor .....	4-18
	Exiting the Status Monitor .....	4-18
	Status Monitor Display .....	4-18
<b>5</b>	<b>Operation on the Machine .....</b>	<b>5-1</b>
	<b>Loading Originals .....</b>	<b>5-2</b>
	Placing Originals on the Platen .....	5-2
	Loading Originals in the Document Processor .....	5-3
	<b>Checking the Equipment's Serial Number .....</b>	<b>5-5</b>
	<b>Program .....</b>	<b>5-6</b>
	Registering Programs .....	5-6

Confirming the Registered Program .....	5-7
Recalling Program .....	5-7
Overwriting Program .....	5-8
Deleting Program .....	5-8
<b>Select Key Settings .....</b>	<b>5-9</b>
<b>Copying .....</b>	<b>5-10</b>
Basic Operation .....	5-10
Canceling Jobs .....	5-12
<b>Sending .....</b>	<b>5-13</b>
Basic Operation .....	5-14
Specifying Destination .....	5-15
Checking and Editing Destinations .....	5-21
Confirmation Screen of Destinations .....	5-22
Recall .....	5-23
Send to Me (E-mail) .....	5-23
Sending to Different Types of Destinations (Multi Sending) .....	5-24
Canceling Sending Jobs .....	5-25
WSD Scan .....	5-26
Scanning using TWAIN or WIA .....	5-28
<b>How to use the FAX Function .....</b>	<b>5-29</b>
<b>What is Document Box? .....</b>	<b>5-30</b>
<b>Using a Custom Box .....</b>	<b>5-32</b>
Creating a New Custom Box .....	5-32
Editing and Deleting Custom Box .....	5-34
Storing Documents .....	5-34
Printing Documents .....	5-35
Editing Documents .....	5-36
Deleting Documents .....	5-37
<b>Printing Documents Stored in Removable USB Memory .....</b>	<b>5-38</b>
<b>Saving Documents to USB Memory (Scan to USB) .....</b>	<b>5-40</b>
<b>Check the USB Memory Information .....</b>	<b>5-41</b>
<b>Removing USB Memory .....</b>	<b>5-42</b>
<b>Using the Manual Stapler .....</b>	<b>5-43</b>

## **6 Using Various Functions ..... 6-1**


<b>Functions Available on the Machine .....</b>	<b>6-2</b>
Copy .....	6-3
Send .....	6-4
Custom Box (Printing) .....	6-6
Removable Memory (Store File, Printing Documents) .....	6-7
<b>Functions .....</b>	<b>6-9</b>
Original Size .....	6-9
Paper Selection .....	6-10
Orig. Orientation (Original Orientation) .....	6-11
Mixed Size Originals .....	6-12
Collate .....	6-12
Density .....	6-12
Original Image .....	6-13
EcoPrint .....	6-13
Color Selection .....	6-14
Color Balance .....	6-15
Sharpness .....	6-16
Contrast .....	6-16
Background Density Adj. (Background Density Adjustment) .....	6-17
Saturation .....	6-17
Prevent Bleed-t (Prevent Bleed-thru) .....	6-18
Zoom .....	6-18
Combine .....	6-20
Duplex .....	6-22
Continuous Scan .....	6-24
Job Finish Notice .....	6-24
File Name Entry .....	6-24
Print Override .....	6-25
Quiet Mode .....	6-25
Skip Blank Page .....	6-25

	Duplex (2-sided Original) .....	6-26
	Sending Size .....	6-27
	File Format .....	6-28
	File Separation .....	6-32
	Scan Resolution .....	6-32
	Subject/Body .....	6-32
	FTP Encrypted TX .....	6-33
	Del. after Print (Delete after Printed) .....	6-33
	Storing Size .....	6-34
	Encrypted PDF .....	6-34
	JPEG/TIFF Print .....	6-35
	XPS FitTo Page .....	6-35
<b>7</b>	<b>Status/Job Cancel .....</b>	<b>7-1</b>
	<b>Checking Job Status .....</b>	<b>7-2</b>
	<b>Checking Job History .....</b>	<b>7-8</b>
	Sending the Log History .....	7-12
	<b>Job Operation .....</b>	<b>7-13</b>
	Pause and Resumption of Jobs .....	7-13
	Canceling of Jobs .....	7-13
	<b>Device/Communication .....</b>	<b>7-14</b>
	<b>Checking the Remaining Amount of Toner and Paper (Paper/Supplies) .....</b>	<b>7-15</b>
<b>8</b>	<b>Setup and Registration (System Menu) .....</b>	<b>8-1</b>
	<b>System Menu .....</b>	<b>8-2</b>
	System Menu Settings .....	8-3
	Report .....	8-5
	User Property .....	8-6
	Common Settings .....	8-7
	Copy .....	8-20
	Send .....	8-21
	Document Box .....	8-22
	FAX .....	8-23
	Edit Destination .....	8-23
	User/Job Account .....	8-23
	Printer .....	8-24
	System/Network .....	8-26
	Adjust/Maint. ....	8-34
<b>9</b>	<b>User Authentication and Accounting (User Login, Job Accounting) .....</b>	<b>9-1</b>
	<b>Overview of User Login Administration .....</b>	<b>9-2</b>
	<b>Enabling User Login Administration .....</b>	<b>9-3</b>
	<b>Setting User Login Administration .....</b>	<b>9-5</b>
	Authentication Security .....	9-5
	Adding a User (Local User List) .....	9-6
	Changing User Properties .....	9-9
	User Login Administration for Printing .....	9-11
	To Manage the Users to Scan Using TWAIN .....	9-13
	To Manage the Users to Scan Using WIA .....	9-14
	To Manage the Users that Send Faxes from a PC .....	9-15
	Local Authoriz. (Local Authorization) .....	9-16
	Group Auth. (Group Authorization Settings) .....	9-17
	Guest Authorization Set. ....	9-18
	NW User Property (Obtain Network User Property) .....	9-21
	ID Card Settings .....	9-22
	<b>Using User Login Administration .....</b>	<b>9-23</b>
	Login/Logout .....	9-23
	<b>Overview of Job Accounting .....</b>	<b>9-24</b>
	<b>Enabling Job Accounting .....</b>	<b>9-25</b>
	Job Accounting Access .....	9-26
	<b>Setting an Account .....</b>	<b>9-27</b>
	Adding an Account .....	9-27

	Restricting the Use of the Machine .....	9-29
	Editing an Account .....	9-30
	Deleting an Account .....	9-31
	Job Accounting for Printing .....	9-32
	Job Accounting for Scan Using TWAIN .....	9-33
	Job Accounting for Scan Using WIA .....	9-34
	Job Accounting for the FAX Transmitted from a Computer .....	9-35
	<b>Configuring Job Accounting .....</b>	<b>9-36</b>
	Default Setting .....	9-36
	Counting the Number of Pages Printed .....	9-37
	Print Accounting Report .....	9-38
	<b>Using Job Accounting .....</b>	<b>9-39</b>
	Login/Logout .....	9-39
	<b>Unknown ID Job .....</b>	<b>9-40</b>
<b>10</b>	<b>Troubleshooting .....</b>	<b>10-1</b>
	<b>Regular Maintenance .....</b>	<b>10-2</b>
	Cleaning .....	10-2
	Toner Container Replacement .....	10-4
	Waste Toner Box Replacement .....	10-8
	Replacing Staples .....	10-10
	<b>Troubleshooting .....</b>	<b>10-11</b>
	Solving Malfunctions .....	10-11
	Responding to Messages .....	10-17
	Adjustment/Maintenance .....	10-29
	Clearing Paper Jams .....	10-34
	Clearing a Staple Jam .....	10-49
<b>11</b>	<b>Appendix .....</b>	<b>11-1</b>
	<b>Optional Equipment .....</b>	<b>11-2</b>
	Overview of Optional Equipment .....	11-2
	Optional Applications .....	11-9
	<b>Character Entry Method .....</b>	<b>11-11</b>
	Using the Keys .....	11-11
	Selecting Type of Characters .....	11-12
	Characters That Can be Entered Using the Numeric Keys .....	11-12
	Entering Symbols .....	11-13
	Entering Characters .....	11-13
	Entering Using the Character Selection Screen .....	11-15
	<b>Paper .....</b>	<b>11-16</b>
	Basic Paper Specifications .....	11-16
	Choosing the Appropriate Paper .....	11-17
	Special Paper .....	11-20
	<b>Specifications .....</b>	<b>11-24</b>
	Machine .....	11-24
	Copy Functions .....	11-26
	Printer Functions .....	11-26
	Scanner Functions .....	11-27
	Document Processor .....	11-27
	Paper Feeder (500-sheet) (Option) .....	11-28
	Manual Stapler .....	11-28
	<b>Glossary .....</b>	<b>11-29</b>
	<b>Index .....</b>	<b>Index-1</b>

# Overview

This machine is equipped standard with copy and print functions, and a scanned image can be sent to an E-mail recipient as an attachment or to a computer on the same network. On products with a FAX function, it is also possible to use the fax function.



## NOTE

- Before using the machine, be sure to read the following:  
➔ [Legal and Safety Information \(page 1-1\)](#)
- For preparations for use of the machine such as cable connections and software installation, refer to the following:  
➔ [Installing and Setting up the Machine \(page 2-1\)](#)
- To learn how to load paper, set up shared folders, and add addresses to the address book, refer to the following:  
➔ [Preparation before Use \(page 3-1\)](#)









# Machine Features




The machine is equipped with many useful functions.




➔ [Using Various Functions \(page 6-1\)](#)




Here are some examples.




Optimize your office workflow		
<p><b>Access to frequently used functions with just one touch (Program)</b></p>  <p>You can preset frequently used functions. Once you register frequently used settings as favorite, you can call up the settings easily. Using this favorite brings the same results even if operated by another person.</p> <p>➔ <a href="#">Program (page 5-6)</a></p>	<p><b>Scan originals of different sizes at a time (Mixed Size Originals)</b></p>  <p>It is useful when preparing conference materials.</p> <p>You can set the different sized originals at one time so you don't need to reset the originals regardless of size.</p> <p>➔ <a href="#">Mixed Size Originals (page 6-12)</a></p>	<p><b>Scan a large number of originals in separate batches and produce as one job (Continuous Scan)</b></p>  <p>It is useful when preparing many-page handouts.</p> <p>When a large number of originals cannot be placed in the document processor at one time, the originals can be scanned in separate batches and then copied or sent as one job.</p> <p>➔ <a href="#">Continuous Scan (page 6-24)</a></p>




Optimize your office workflow		
<p><b>Send one time with multiple sending options (Multi Sending)</b></p>  <p>You can send a same document to the multiple destinations using a different method.</p> <p>You can specify multiple destinations of different send methods such as E-mail, SMB, and Fax.</p> <p>You can reduce your workflow by sending a job at once.</p> <p>➔ <a href="#">Sending to Different Types of Destinations (Multi Sending) (page 5-24)</a></p>	<p><b>Save frequently used documents in the machine (Custom Box)</b></p>  <p>You can save the frequently used document in the machine and print it when needed.</p> <p>➔ <a href="#">Using a Custom Box (page 5-32)</a></p>	<p><b>Send a FAX from a PC (Sending FAX from PC)</b></p>  <p>You can save the paper used for sending a FAX with this function.</p> <p>You can send a file to be faxed from the PC without printing the file, so that you can reduce the number of pieces of paper and perform sending jobs efficiently.</p> <p>➔ <b>FAX Operation Guide</b></p>

Save energy and cost		
<p><b>Save energy as needed (Energy Saver function)</b></p>  <p>The machine is equipped with Energy Saver function that automatically switched into Sleep Mode.</p> <p>➔ <a href="#">Energy Saver function (page 2-20)</a></p>	<p><b>Use less toner for printing (EcoPrint)</b></p>  <p>You can save toner consumption with this function.</p> <p>When you only need to check the printed content, such as a trial print run or documents for internal confirmation, use this function to save toner.</p> <p>Use this function when a high-quality print is not required.</p> <p>➔ <a href="#">EcoPrint (page 6-13)</a></p>	<p><b>Reduce paper use (Paper Saving Printing)</b></p>  <p>You can print originals on both sides of the paper. You can also print multiple originals onto one sheet.</p> <p>➔ <a href="#">Combine (page 6-20)</a>  <a href="#">Duplex (page 6-22)</a></p>

Save energy and cost		Create attractive documents
<p><b>Skip blank pages when printing (Skip Blank Page)</b></p>  <p>When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.</p> <p>➔ <a href="#">Skip Blank Page (page 6-25)</a></p>	<p><b>Send a FAX to reduce the communication cost (FAX Delayed Transmission)</b></p>  <p>You can reduce the communication cost with this function.</p> <p>The communication cost can be reduced by setting the timer to the time period during which the communication cost is low.</p> <p>➔ <b>FAX Operation Guide</b></p>	<p><b>Prevent image bleed-through (Prevent Bleed-through)</b></p>  <p>You can prevent image bleed-through from the reverse side when scanning thin originals.</p> <p>➔ <a href="#">Prevent Bleed-t (Prevent Bleed-thru) (page 6-18)</a></p>


Strengthen security		
<p><b>Password-protect a PDF file (PDF Encryption Functions)</b></p>  <p>Use the PDF format's password security options to restrict document viewing, printing and editing.</p> <p>➔ <a href="#">Encrypted PDF (page 6-34)</a></p>	<p><b>Protect data on the SSD (Encryption / Overwrite)</b></p>  <p>You can overwrite the unnecessary data that remains on the SSD automatically. To prevent an external leakage, the machine is able to encrypt data before writing it to the SSD.</p> <p>➔ <a href="#">Data Security (page 8-33)</a></p>	<p><b>Prevent loss of finished documents (Private Print)</b></p>  <p>You can temporarily save a printer document in the machine. By printing the document from the machine prevents someone takes your document.</p> <p>➔ <a href="#">Printing Data Saved on the Printer (page 4-9)</a></p>

Strengthen security		Use functions more efficiently
<p><b>Log in by ID card (Card Authentication)</b></p>  <p>You can log in simply by touching an ID card. You don't need to enter your user name and password.</p> <p>➔ <a href="#">Card Authentication Kit(B) "Card Authentication Kit" (page 11-3)</a></p>	<p><b>Strengthen security (Settings for Administrator)</b></p>  <p>Various functions are available for administrators to strengthen security.</p> <p>➔ <a href="#">Strengthening the Security (page 2-36)</a></p>	<p><b>Make the machine quiet (Quiet Mode)</b></p>  <p>You can make the machine quiet by reducing its running noise. You can configure this mode by job.</p> <p>➔ <a href="#">Quiet Mode (page 6-25)</a></p>

Use functions more efficiently		
<p><b>Install the machine without concerning the network cables (Wireless Network)</b></p>  <p>In an environment where the wireless LAN is used, you can install the machine without concerning the network cables.</p> <p>➔ <a href="#">Setup (page 8-30)</a></p>	<p><b>Use USB memory (USB Memory)</b></p>  <p>It is useful when you need to print document outside your office or you cannot print document from your PC.</p> <p>You can print the document from the USB memory by plugging it directly into the machine.</p> <p>Original scanned at the machine can be saved in the USB memory also.</p> <p>➔ <a href="#">Printing Documents Stored in Removable USB Memory (page 5-38)</a></p> <p>➔ <a href="#">Saving Documents to USB Memory (Scan to USB) (page 5-40)</a></p>	<p><b>Specify image file format (File Format)</b></p>  <p>You can select the various file formats when sending/storing images.</p> <p>➔ <a href="#">File Format (page 6-28)</a></p>

**Use functions more efficiently**

**Perform remote operation (Command Center RX)**



You can access to the machine remotely to print, send or download data.

Administrators can configure the machine behavior or management settings.






➔ [Command Center RX \(page 2-38\)](#)

# Color and Image Quality Functions

The machine is equipped with various color and image quality functions. You can adjust the scanned image as desired.

## Basic Color Modes

The basic color modes are as follows.

















Color mode	Description	Reference image		Reference page
		Before	After	
<b>Auto Color</b>	Automatically recognizes whether a document being scanned is color or black & white.			<a href="#">page 6-14</a>
<b>Full Color</b>	Scans a document in full color.			<a href="#">page 6-14</a>
<b>Grayscale</b>	Scans a document in grayscale.			<a href="#">page 6-14</a>
<b>Black &amp; White</b>	Scans a document in black & white.			<a href="#">page 6-14</a>

For details, refer to the following:

➔ [Color Selection \(page 6-14\)](#)

# Adjusting Image Quality and Color

To adjust the image quality or color of an image, use the following functions.

I want to...	Sample image		Function	Page
	Before	After		
<b>Adjust the color precisely.</b>				
Adjust the density.			Density	<a href="#">page 6-12</a>
Adjust the color by strengthening blue or red tones. Example: Strengthening red			Color Balance	<a href="#">page 6-15</a>
Adjust the saturation.			Saturation	<a href="#">page 6-17</a>
<b>Adjust the image quality precisely</b>				
Emphasize or blur the image outline. Example: Emphasize the image outlines			Sharpness	<a href="#">page 6-16</a>
Adjust the difference between dark and light parts of the image.			Contrast	<a href="#">page 6-16</a>
Darken or lighten the background (the area with no texts or images) of a document. Example: Lightening the background			Background Density	<a href="#">page 6-17</a>
Prevent bleed-through in 2-sided originals.			Prevent Bleed-through	<a href="#">page 6-18</a>
<b>Adjust the scanned image</b>				
Decrease the file size and produce the characters clearly.			File format [High Comp. PDF]	<a href="#">page 6-28</a>

# Guides Provided with the Machine

The following guides are provided with the machine. Refer to each guide as needed.

The contents of the guides are subject to change without notice for the purpose of improvement of machine performance.

## Printed guides

### Start using the machine quickly



#### Quick Guide

Explains how to use basic functions of the machine, how to use convenient features, how to perform routine maintenance, and what to do when problems occur.

### For safe use of the machine













#### Safety Guide

Provides safety and cautionary information for installation environment and use of the machine. Be sure to read this guide before using the machine.

#### Safety Guide (ECOSYS M6030cdn/ECOSYS M6530cdn)

Indicates the space required for machine installation, and describes the cautionary labels and other safety information. Be sure to read this guide before using the machine.

## Guides (PDF) on the DVD (Product Library)

<b>Use the machine thoughtfully</b>	 <b>Operation Guide (This Guide)</b> Explains how to load paper and perform copy, print and scan operations, and indicates default settings and other information.
<b>Use the fax functions</b>	 <b>FAX Operation Guide</b> Explains how to use the fax function.
<b>Use the ID card</b>	 <b>Card Authentication Kit (B) Operation Guide</b> Explains how to perform authentication using the ID card.
<b>Strengthen security</b>	 <b>Data Security Kit (E) Operation Guide</b> Explains how to introduce and use the Data Security kit (E), and how to overwrite and encrypt data.
<b>Easily register machine information and configure settings</b>	 <b>Command Center RX User Guide</b> Explains how to access the machine from a Web browser on your computer to check and change settings.
<b>Print data from a computer</b>	 <b>Printer Driver User Guide</b> Explains how to install the printer driver and use the printer function.
<b>Directly print a PDF file</b>	 <b>KYOCERA Net Direct Print Operation Guide</b> Explains how to print PDF files without launching Adobe Acrobat or Reader.
<b>Monitor the machine and printers on the network</b>	 <b>KYOCERA Net Viewer User Guide</b> Explains how to monitor your network printing system (the machine) with KYOCERA Net Viewer.
<b>Print without using the printer driver</b>	 <b>PRESCRIBE Commands Command Reference</b> Describes the native printer language (PRESCRIBE commands).
	<b>PRESCRIBE Commands Technical Reference</b> Describes the PRESCRIBE command functions and control for each type of emulation.
<b>Adjust the print or scan position</b>	 <b>Maintenance Menu User Guide</b> Maintenance Menu provides the explanation on how to configure the print, scan, and other settings.

Install the following versions of Adobe Reader to view the manuals on the DVD.  
Version 8.0 or later



# About the Operation Guide (this Guide)

## Structure of the guide

The Operation Guide contains the following chapters.


Chapter		Contents
1	<b>Legal and Safety Information</b>	Provides precautions regarding use of the machine and trademark information.
2	<b>Installing and Setting up the Machine</b>	Explains part names, cable connections, installation of the software, login, logout, and other matters related to administration of the machine.
3	<b>Preparation before Use</b>	Explains preparations and settings that are required in order to use the machine, such as how to use the operation panel, load paper, and create an address book.
4	<b>Printing from PC</b>	Explains functions that are available when the machine is used as a printer.
5	<b>Operation on the Machine</b>	Explains the basic procedures for using the machine, such as placing originals, making copies, sending documents, and using document boxes.
6	<b>Using Various Functions</b>	Explains convenient functions that are available on the machine.
7	<b>Status/Job Cancel</b>	Explains how to check the status of a job and the job history, and how to cancel jobs being printed or waiting to print. Also explains how to check paper and toner levels, how to check the device status, and how to cancel fax transmission.
8	<b>Setup and Registration (System Menu)</b>	Explains System Menu and how it relates to the operation of the machine.
9	<b>User Authentication and Accounting (User Login, Job Accounting)</b>	Explains user login and job accounting.
10	<b>Troubleshooting</b>	Explains what to do when toner runs out, an error is displayed, or a paper jam or other problem occurs.
11	<b>Appendix</b>	Describes convenient options that are available for the machine. Provides information on media types and paper sizes, and gives a glossary of terms. Explains how to enter characters, and lists the specifications of the machine.


# Conventions Used in This Guide


Adobe Reader XI is used as an example in the explanations below.

Click an item in the Table of Contents to jump to the corresponding page.


Click to move from the current page to the previously displayed page. This is convenient when you want to return to the page from which you jumped to the current page.



 **IMPORTANT**  
Indicates operational requirements and restrictions to operate the machine correctly, and avoid damage to the machine or property.

 **NOTE**  
Indicates supplemental explanations and reference information for operations.

**Refer to**  
Click the underlined text to jump to the corresponding page.

 **CAUTION**  
Indicates that personal injury or mechanical damage may result from insufficient attention to or incorrect compliance with the related points.

 **NOTE**

The items that appear in Adobe Reader vary depending on how it is used. If the Table of Contents or tools do not appear, refer to Adobe Reader Help.

Certain items are indicated in this guide by the conventions described below.

Convention	Description
[Bold]	Indicates keys and buttons.
"Regular"	Indicates a message or setting.

## Conventions used in procedures for operating the machine

In this Operation Guide, continuous operation is as follows:

Actual procedure	Procedure indicated in this guide
Select the <b>[System Menu/Counter]</b> key. ▼ Select the <b>[▲]</b> or <b>[▼]</b> key to select <b>[Common settings]</b> . ▼ Select the <b>[OK]</b> key.	<b>[System Menu/Counter]</b> key > <b>[▲]</b> <b>[▼]</b> key > <b>[Common Settings]</b> > <b>[OK]</b> key

# Menu Map

This is a list of menus displayed on the message display. Depending on the settings, some menus may not be displayed. Some menu names may differ from their reference titles.


## Copy




Function Menu



Quiet Mode ( <a href="#">page 6-25</a> )
Paper Selection ( <a href="#">page 6-10</a> )
Collate ( <a href="#">page 6-12</a> )
Duplex ( <a href="#">page 6-22</a> )
Zoom ( <a href="#">page 6-18</a> )
Combine ( <a href="#">page 6-20</a> )
Original Size ( <a href="#">page 6-9</a> )
Orig.Orientation ( <a href="#">page 6-11</a> )
Mixed Size Orig. ( <a href="#">page 6-12</a> )
Original Image ( <a href="#">page 6-13</a> )
Density ( <a href="#">page 6-12</a> )
EcoPrint ( <a href="#">page 6-13</a> )
Continuous Scan ( <a href="#">page 6-24</a> )
File Name Entry ( <a href="#">page 6-24</a> )
JobFinish Notice ( <a href="#">page 6-24</a> )
Print Override ( <a href="#">page 6-25</a> )
Color Selection ( <a href="#">page 6-14</a> )
Color Balance ( <a href="#">page 6-15</a> )
Sharpness ( <a href="#">page 6-16</a> )
Contrast ( <a href="#">page 6-16</a> )
Backgrnd Density ( <a href="#">page 6-17</a> )
Saturation ( <a href="#">page 6-17</a> )
Prevent Bleed-t ( <a href="#">page 6-18</a> )
Skip Blank Page ( <a href="#">page 6-25</a> )



Me(E-mail) ( <a href="#">page 5-23</a> )
E-mail ( <a href="#">page 5-17</a> )
Folder(SMB) ( <a href="#">page 5-18</a> )
Folder(FTP) ( <a href="#">page 5-18</a> )
WSD Scan ( <a href="#">page 5-27</a> )
FAX (Refer to <b>FAX Operation Guide.</b> )



Function Menu




Quiet Mode ( <a href="#">page 6-25</a> )
Color Selection ( <a href="#">page 6-14</a> )
Original Size ( <a href="#">page 6-9</a> )
Original Image ( <a href="#">page 6-13</a> )
Scan Resolution ( <a href="#">page 6-32</a> )
Sending Size ( <a href="#">page 6-27</a> )
Zoom ( <a href="#">page 6-18</a> )
Orig.Orientation ( <a href="#">page 6-11</a> )
Mixed Size Orig. ( <a href="#">page 6-12</a> )
Continuous Scan ( <a href="#">page 6-24</a> )
File Format ( <a href="#">page 6-28</a> )
File Name Entry ( <a href="#">page 6-24</a> )
Subject/Body ( <a href="#">page 6-32</a> )
JobFinish Notice ( <a href="#">page 6-24</a> )
FAX Resolution (Refer to <b>FAX Operation Guide.</b> )
FAX Delayed TX (Refer to <b>FAX Operation Guide.</b> )
FAX Direct TX (Refer to <b>FAX Operation Guide.</b> )
FAX RX Polling (Refer to <b>FAX Operation Guide.</b> )
FAX TX Report (Refer to <b>FAX Operation Guide.</b> )
Density ( <a href="#">page 6-12</a> )
Duplex ( <a href="#">page 6-22</a> )
FTP Encrypted TX ( <a href="#">page 6-33</a> )
File Separation ( <a href="#">page 6-32</a> )
Sharpness ( <a href="#">page 6-16</a> )
Contrast ( <a href="#">page 6-16</a> )
Backgrnd Density ( <a href="#">page 6-17</a> )
Prevent Bleed-t ( <a href="#">page 6-18</a> )
Skip Blank Page ( <a href="#">page 6-25</a> )

Document Box/USB



<b>Custom Box</b>	(File Selection)	<b>Print (ChangeSet)</b>	▶  ▶	Quiet Mode ( <a href="#">page 6-25</a> )
				Collate ( <a href="#">page 6-12</a> )
				Paper Selection ( <a href="#">page 6-10</a> )
				Duplex ( <a href="#">page 6-22</a> )
				EcoPrint ( <a href="#">page 6-13</a> )
				File Name Entry ( <a href="#">page 6-24</a> )
				JobFinish Notice ( <a href="#">page 6-24</a> )
				Print Override ( <a href="#">page 6-25</a> )
Del. After Print ( <a href="#">page 6-33</a> )				
<b>Sub Address Box (Refer to FAX Operation Guide.)</b>				
<b>Polling Box (Refer to FAX Operation Guide.)</b>				
<b>Job Box</b>	Private ( <a href="#">page 4-10</a> )			
	Quick Copy ( <a href="#">page 4-14</a> )			
<b>USB Memory</b>	<b>Store File</b>	▶  ▶	▶  ▶	Quiet Mode ( <a href="#">page 6-25</a> )
				Color Selection ( <a href="#">page 6-14</a> )
				Original Size ( <a href="#">page 6-9</a> )
				Original Image ( <a href="#">page 6-13</a> )
				Scan Resolution ( <a href="#">page 6-32</a> )
				Storing Size ( <a href="#">page 6-34</a> )
				Zoom ( <a href="#">page 6-18</a> )
				Orig.Orientation ( <a href="#">page 6-11</a> )
				Mixed Size Orig. ( <a href="#">page 6-12</a> )
				Continuous Scan ( <a href="#">page 6-24</a> )
				File Format ( <a href="#">page 6-28</a> )
				File Separation ( <a href="#">page 6-32</a> )
				File Name Entry ( <a href="#">page 6-24</a> )
				JobFinish Notice ( <a href="#">page 6-24</a> )
				Density ( <a href="#">page 6-12</a> )
				Duplex ( <a href="#">page 6-22</a> )
				Sharpness ( <a href="#">page 6-16</a> )
Contrast ( <a href="#">page 6-16</a> )				
Backgrnd Density ( <a href="#">page 6-17</a> )				
Prevent Bleed-t ( <a href="#">page 6-18</a> )				
Skip Blank Page ( <a href="#">page 6-25</a> )				

<b>USB Memory</b>	(File Selection)	<b>Print</b>	 Function Menu	Quiet Mode ( <a href="#">page 6-25</a> )
				Collate ( <a href="#">page 6-12</a> )
				Paper Selection ( <a href="#">page 6-10</a> )
				Duplex ( <a href="#">page 6-22</a> )
				EcoPrint ( <a href="#">page 6-13</a> )
				File Name Entry ( <a href="#">page 6-24</a> )
				JobFinish Notice ( <a href="#">page 6-24</a> )
				Print Override ( <a href="#">page 6-25</a> )
				Color Selection ( <a href="#">page 6-14</a> )
				Encrypted PDF ( <a href="#">page 6-34</a> )
				JPEG/TIFF Print ( <a href="#">page 6-35</a> )
				XPS FitTo Page ( <a href="#">page 6-35</a> )



Recall program. ( <a href="#">page 5-6</a> )
--

Status/  
Job Cancel



Print Job Status ( <a href="#">page 7-4</a> )
Send Job Status ( <a href="#">page 7-5</a> )
Store Job Status ( <a href="#">page 7-6</a> )
Scheduled Job ( <a href="#">page 7-7</a> )
Print Job Log ( <a href="#">page 7-10</a> )
Send Job Log ( <a href="#">page 7-11</a> )
Store Job Log ( <a href="#">page 7-12</a> )
FAX Job Log (Refer to <b>FAX Operation Guide.</b> )
Scanner ( <a href="#">page 7-14</a> )
Printer ( <a href="#">page 7-14</a> )
FAX (Refer to <b>FAX Operation Guide.</b> )
Toner Status ( <a href="#">page 7-15</a> )
Paper Status ( <a href="#">page 7-15</a> )
USB Memory ( <a href="#">page 7-14</a> )
SSD ( <a href="#">page 7-14</a> )
USB Keyboard ( <a href="#">page 7-14</a> )
Network ( <a href="#">page 7-14</a> )
Option Network ( <a href="#">page 7-14</a> )
Wireless Network ( <a href="#">page 7-14</a> )

System Menu/  
Counter



<b>Report</b>	<b>Report Print</b>	Menu Map ( <a href="#">page 8-5</a> )
		Status Page ( <a href="#">page 8-5</a> )
		Font List ( <a href="#">page 8-5</a> )
		Opt NW Status ( <a href="#">page 8-5</a> )
	Admin Rpt Set. (Refer to <b>FAX Operation Guide.</b> )	
	Result Rpt Set. ( <a href="#">page 8-6</a> )	
	<b>Job Log History</b>	Auto Sending ( <a href="#">page 8-6</a> )
		Send History ( <a href="#">page 8-6</a> )
		Destination ( <a href="#">page 8-6</a> )
		Subject ( <a href="#">page 8-6</a> )
Personal Info. ( <a href="#">page 8-6</a> )		
<b>Counter</b> ( <a href="#">page 2-35</a> )		



<b>System/Network</b>	<b>Network Setting</b>	<b>TCP/IP Settings</b>	TCP/IP ( <a href="#">page 8-26</a> )
			IPv4 Setting ( <a href="#">page 8-26</a> )
			IPv6 Setting ( <a href="#">page 8-26</a> )
			Bonjour ( <a href="#">page 8-26</a> )
			Protocol Detail ( <a href="#">page 8-27</a> )
		WSD-SCAN ( <a href="#">page 8-28</a> )	
		WSD-PRINT ( <a href="#">page 8-28</a> )	
		IPSec ( <a href="#">page 8-28</a> )	
		Secure Protocol ( <a href="#">page 8-29</a> )	
		Host Name ( <a href="#">page 8-26</a> )	
		LAN Interface ( <a href="#">page 8-29</a> )	
		Ping ( <a href="#">page 8-29</a> )	
		Restart Network ( <a href="#">page 8-29</a> )	
	<b>Optional Network</b>	Basic ( <a href="#">page 8-30</a> )	
	<b>Wireless Network</b>	Setup ( <a href="#">page 8-30</a> )	
		Basic ( <a href="#">page 8-30</a> )	
	NW InterfaceSend ( <a href="#">page 8-32</a> )		
	<b>I/F Block Set.</b>	USB Host ( <a href="#">page 8-32</a> )	
		USB Device ( <a href="#">page 8-32</a> )	
		USB Storage ( <a href="#">page 8-32</a> )	
		Option I/F 1 ( <a href="#">page 8-32</a> )	
		Option I/F 2 ( <a href="#">page 8-32</a> )	
	Security Level ( <a href="#">page 8-33</a> )		
	Data Security ( <a href="#">page 8-33</a> )		
	Restart ( <a href="#">page 8-33</a> )		
	Op Functions ( <a href="#">page 8-34</a> )		

<b>User/Job Account</b>	<b>User Login Set.</b>	User Login ( <a href="#">page 9-3</a> )		
		Local User List ( <a href="#">page 9-6</a> )		
		Local Authoriz. ( <a href="#">page 9-16</a> )		
		Account Lockout ( <a href="#">page 9-5</a> )		
		<b>ID Card Setting</b>	Key Login ( <a href="#">page 9-22</a> )	
			Additional Auth. ( <a href="#">page 9-22</a> )	
		Group Auth. ( <a href="#">page 9-17</a> )		
		Guest Auth. Set. ( <a href="#">page 9-18</a> )		
		NW User Property ( <a href="#">page 9-21</a> )		
		<b>Job Account.Set.</b>	Job Accounting ( <a href="#">page 9-25</a> )	
	AccountingAccess ( <a href="#">page 9-26</a> )			
	Account. Report ( <a href="#">page 9-38</a> )			
	Total Accounting ( <a href="#">page 9-37</a> )			
	Each Job Account ( <a href="#">page 9-37</a> )			
	Account. List ( <a href="#">page 9-27</a> )			
<b>Default Setting</b>	Apply Limit ( <a href="#">page 9-36</a> )			
	Copy/Print Count ( <a href="#">page 9-36</a> )			
	Counter Limit ( <a href="#">page 9-36</a> )			
Unknown ID Job ( <a href="#">page 9-40</a> )				
<b>User Property (<a href="#">page 9-10</a>)</b>				
<b>Common Settings</b>	Language ( <a href="#">page 8-3</a> )			
	Default Screen ( <a href="#">page 8-3</a> )			
	<b>Sound</b>	Buzzer ( <a href="#">page 8-7</a> )		
		FAX Speaker (Refer to <b>FAX Operation Guide.</b> )		
		FAX Monitor (Refer to <b>FAX Operation Guide.</b> )		
	Display Bright. ( <a href="#">page 8-7</a> )			
	<b>Orig./Paper Set.</b>	Custom Orig.Size ( <a href="#">page 8-8</a> )		
		Def. Orig. Size ( <a href="#">page 8-8</a> )		
		Custom PaperSize ( <a href="#">page 8-9</a> )		
		<b>Cassette 1 Set.</b>	Cassette 1 Size ( <a href="#">page 8-11</a> )	
			Cassette 1 Type ( <a href="#">page 8-11</a> )	
		<b>Cassette 2 Set.</b>	Cassette 2 Size ( <a href="#">page 8-11</a> )	
			Cassette 2 Type ( <a href="#">page 8-11</a> )	
		<b>Cassette 3 Set.</b>	Cassette 3 Size ( <a href="#">page 8-11</a> )	
			Cassette 3 Type ( <a href="#">page 8-11</a> )	
		<b>Cassette 4 Set.</b>	Cassette 4 Size ( <a href="#">page 8-11</a> )	
			Cassette 4 Type ( <a href="#">page 8-11</a> )	

<b>Common Settings</b>	<b>Orig./Paper Set.</b>	<b>MP Tray Set.</b>	MP Tray Size ( <a href="#">page 8-11</a> )	
			MP Tray Type ( <a href="#">page 8-11</a> )	
		Media Type Set. ( <a href="#">page 8-10</a> )		
		<b>Media for Auto</b>	Full Color ( <a href="#">page 8-10</a> )	
			Black & White ( <a href="#">page 8-10</a> )	
		Def. PaperSource ( <a href="#">page 8-10</a> )		
	SpicalPaper Act. ( <a href="#">page 8-10</a> )			
	Preset Limit ( <a href="#">page 8-15</a> )			
	Measurement ( <a href="#">page 8-15</a> )			
	<b>Error Handling</b>	DuplexPaperError ( <a href="#">page 8-15</a> )		
		PaperMismatchErr ( <a href="#">page 8-15</a> )		
	<b>Date Setting</b>	Date/Time ( <a href="#">page 8-17</a> )		
		Date Format ( <a href="#">page 8-17</a> )		
		Time Zone ( <a href="#">page 8-17</a> )		
		Summer Time ( <a href="#">page 8-17</a> )		
	<b>Timer Setting</b>	Auto Panel Reset ( <a href="#">page 8-18</a> )		
		PanelReset Timer ( <a href="#">page 8-18</a> )		
		Sleep Level (models except for Europe) ( <a href="#">page 8-18</a> )		
		Sleep Rules (models for Europe) ( <a href="#">page 8-18</a> )		
		Sleep Timer ( <a href="#">page 8-18</a> )		
Auto Err. Clear ( <a href="#">page 8-18</a> )				
Err. Clear Timer ( <a href="#">page 8-19</a> )				
Unusable Time (Refer to <b>FAX Operation Guide</b> .)				
Ping Timeout ( <a href="#">page 8-19</a> )				

Common Settings	Function Default	
		Color Selection ( <a href="#">page 8-13</a> )
		Scan Resolution ( <a href="#">page 8-13</a> )
		FAX Resolution (Refer to <b>FAX Operation Guide.</b> )
		Orig.Image(Copy) ( <a href="#">page 8-13</a> )
		Orig.Image(Send) ( <a href="#">page 8-13</a> )
		Zoom ( <a href="#">page 8-13</a> )
		Collate ( <a href="#">page 8-13</a> )
		Orig.Orientation ( <a href="#">page 8-13</a> )
		Backgrnd(Copy) ( <a href="#">page 8-13</a> )
		Backgrnd(Send) ( <a href="#">page 8-13</a> )
		EcoPrint ( <a href="#">page 8-13</a> )
		Prevent B-t Copy ( <a href="#">page 8-13</a> )
		Prevent B-t Send ( <a href="#">page 8-13</a> )
		Skip Blank(Copy) ( <a href="#">page 8-13</a> )
		Skip Blank(Send) ( <a href="#">page 8-13</a> )
		File Name Entry ( <a href="#">page 8-14</a> )
		Subject/Body ( <a href="#">page 8-14</a> )
		Con.scan-ExptFAX ( <a href="#">page 8-14</a> )
		Con.scan-FAX ( <a href="#">page 8-14</a> )
		File Format ( <a href="#">page 8-13</a> )
		File Separation ( <a href="#">page 8-13</a> )
		JPEG/TIFF Print ( <a href="#">page 8-14</a> )
		XPS FitTo Page ( <a href="#">page 8-14</a> )
		<b>Detail Setting</b>
		2 in 1 Layout ( <a href="#">page 8-14</a> )
		4 in 1 Layout ( <a href="#">page 8-14</a> )
		Border Line ( <a href="#">page 8-14</a> )
		Orig. Binding ( <a href="#">page 8-14</a> )
		Finish. Binding ( <a href="#">page 8-14</a> )
		Image Quality ( <a href="#">page 8-14</a> )
		Color TIFF Comp. ( <a href="#">page 8-14</a> )
		PDF/A ( <a href="#">page 8-14</a> )
		High Comp.PDF ( <a href="#">page 8-14</a> )
		Black Lvl(Copy) ( <a href="#">page 8-14</a> )
		Black Lvl(Send) ( <a href="#">page 8-14</a> )
		Login Operation ( <a href="#">page 8-20</a> )
		RAM Disk Mode ( <a href="#">page 8-19</a> )
		Format SSD ( <a href="#">page 8-16</a> )
		Format SD Card ( <a href="#">page 8-16</a> )

<b>Common Settings</b>	Optional Memory ( <a href="#">page 8-19</a> )
	Disp. Status/Log ( <a href="#">page 8-17</a> )
	USB KeyboardType ( <a href="#">page 8-16</a> )
	TonerAlert Level ( <a href="#">page 8-16</a> )
	Color Toner Empty ( <a href="#">page 8-15</a> )
<b>Copy</b>	Paper Selection ( <a href="#">page 8-20</a> )
	AutoPaperSelect. ( <a href="#">page 8-20</a> )
	Auto % Priority ( <a href="#">page 8-20</a> )
	Reserve Priority ( <a href="#">page 8-20</a> )
	DP Read Action ( <a href="#">page 8-20</a> )
	Select Key Set. ( <a href="#">page 8-20</a> )
<b>Printer</b>	Emulation Set. ( <a href="#">page 8-24</a> )
	Color Setting ( <a href="#">page 8-24</a> )
	EcoPrint ( <a href="#">page 8-24</a> )
	Override A4/LTR ( <a href="#">page 8-24</a> )
	Duplex ( <a href="#">page 8-24</a> )
	Copies ( <a href="#">page 8-24</a> )
	Orientation ( <a href="#">page 8-24</a> )
	Gloss Mode ( <a href="#">page 8-25</a> )
	Wide A4 ( <a href="#">page 8-24</a> )
	FormFeed TimeOut ( <a href="#">page 8-24</a> )
	LF Action ( <a href="#">page 8-24</a> )
	CR Action ( <a href="#">page 8-24</a> )
	Job Name ( <a href="#">page 8-25</a> )
	User Name ( <a href="#">page 8-25</a> )
	MP Tray Priority ( <a href="#">page 8-25</a> )
	Paper Feed Mode ( <a href="#">page 8-25</a> )
	Auto Cass. Change ( <a href="#">page 8-25</a> )
<b>Send</b>	Select Key Set. ( <a href="#">page 8-21</a> )
	DestinationCheck ( <a href="#">page 8-21</a> )
	New Dest. Entry ( <a href="#">page 8-21</a> )
	Recall Dest. ( <a href="#">page 8-21</a> )
	Default Screen ( <a href="#">page 8-21</a> )
	Send and Forward ( <a href="#">page 8-21</a> )
<b>FAX (Refer to FAX Operation Guide.)</b>	

<b>Document Box</b>	Custom Box ( <a href="#">page 5-32</a> )	
	Sub Address Box (Refer to <b>FAX Operation Guide.</b> )	
	<b>Job Box</b>	Quick Copy Jobs ( <a href="#">page 8-22</a> )
		JobRet. Deletion ( <a href="#">page 8-22</a> )
		Storage Media ( <a href="#">page 8-22</a> )
	Polling Box (Refer to <b>FAX Operation Guide.</b> )	
Select Key Set. ( <a href="#">page 8-20</a> )		
<b>Edit Destination</b>	Address Book ( <a href="#">page 8-23</a> )	
	Print List ( <a href="#">page 8-23</a> )	
	Addr Book Defaults ( <a href="#">page 8-23</a> )	
<b>Adjust/Maint.</b>	Quiet Mode ( <a href="#">page 8-34</a> )	
	Copy Dens. Adj. ( <a href="#">page 8-34</a> )	
	Send/Box Density ( <a href="#">page 8-34</a> )	
	Contrast (Copy) ( <a href="#">page 8-34</a> )	
	Contrast (Send) ( <a href="#">page 8-34</a> )	
	Backgrnd Density ( <a href="#">page 8-34</a> )	
	AutoColorCorrect ( <a href="#">page 8-34</a> )	
	ColorCalibration ( <a href="#">page 8-35</a> )	
	Color Regist. ( <a href="#">page 8-35</a> )	
	Correct. Bk Line ( <a href="#">page 8-34</a> )	
	Service Setting ( <a href="#">page 8-35</a> )	

# 1 Legal and Safety Information


Please read this information before using your machine. This chapter provides information on the following topics.


Notice .....	1-2
Safety Conventions in This Guide .....	1-2
Environment .....	1-3
Precautions for Use .....	1-4
Laser Safety (Europe) .....	1-5
Legal Restriction on Copying/Scanning .....	1-6
EN ISO 7779 .....	1-6
EK1-ITB 2000 .....	1-6
Legal Information .....	1-7
Energy Saving Control Function .....	1-13
Automatic 2-Sided Print Function .....	1-13
Resource Saving - Paper .....	1-13
Environmental benefits of "Power Management" .....	1-13
Energy Star (ENERGY STAR®) Program .....	1-14

# Notice


## Safety Conventions in This Guide


The sections of this guide and parts of the machine marked with symbols are safety warnings meant to protect the user, other individuals and surrounding objects, and ensure correct and safe usage of the machine. The symbols and their meanings are indicated below.


 **WARNING:** Indicates that serious injury or even death may result from insufficient attention to or incorrect compliance with the related points.


 **CAUTION:** Indicates that personal injury or mechanical damage may result from insufficient attention to or incorrect compliance with the related points.


## Symbols


The  symbol indicates that the related section includes safety warnings. Specific points of attention are indicated inside the symbol.


 ... [General warning]


 ... [Warning of high temperature]

The  symbol indicates that the related section includes information on prohibited actions. Specifics of the prohibited action are indicated inside the symbol.


 ... [Warning of prohibited action]

 ... [Disassembly prohibited]

The  symbol indicates that the related section includes information on actions which must be performed. Specifics of the required action are indicated inside the symbol.

 ... [Alert of required action]

 ... [Remove the power plug from the outlet]

 ... [Always connect the machine to an outlet with a ground connection]

Please contact your service representative to order a replacement if the safety warnings in this Operation Guide are illegible or if the guide itself is missing (fee required).

### NOTE

An original which resembles a bank note closely may not be copied properly in some rare cases because this machine is equipped with a counterfeiting prevention function.



## Environment

The service environmental conditions are as follows:

<b>Temperature</b>	50 to 90.5 °F (10 to 32.5 °C) (But humidity should be 70% or less when temperature is 90.5 °F (32.5 °C).)
<b>Humidity</b>	10 to 80% (But temperature should be 86 °F (30 °C) or less when humidity is 80%.)

Avoid the following locations when selecting a site for the machine.

- Avoid locations near a window or with exposure to direct sunlight.
- Avoid locations with vibrations.
- Avoid locations with drastic temperature fluctuations.
- Avoid locations with direct exposure to hot or cold air.
- Avoid poorly ventilated locations.

If the floor is delicate against casters, when this machine is moved after installation, the floor material may be damaged.

During copying, some ozone is released, but the amount does not cause any ill effect to one's health. If, however, the machine is used over a long period of time in a poorly ventilated room or when making an extremely large number of copies, the smell may become unpleasant. To maintain the appropriate environment for copy work, it is suggested that the room be properly ventilated.

## Precautions for Use

### Cautions when handling consumables

#### CAUTION

Do not attempt to incinerate parts which contain toner. Dangerous sparks may cause burns.

Keep parts which contain toner out of the reach of children.

If toner happens to spill from parts which contain toner, avoid inhalation and ingestion, as well as contact with your eyes and skin.

- If you do happen to inhale toner, move to a place with fresh air and gargle thoroughly with a large amount of water. If coughing develops, contact a physician.
- If you do happen to ingest toner, rinse your mouth with water and drink 1 or 2 cups of water to dilute the contents of your stomach. If necessary, contact a physician.
- If you do happen to get toner in your eyes, flush them thoroughly with water. If there is any remaining tenderness, contact a physician.
- If toner does happen to get on your skin, wash with soap and water.

Do not attempt to force open or destroy parts which contain toner.

### Other precautions

Return the exhausted toner container and waste toner box to your dealer or service representative. The collected toner container and waste toner box will be recycled or disposed in accordance with the relevant regulations.

Store the machine while avoiding exposure to direct sunlight.

Store the machine in a place where the temperature stays below 40 °C while avoiding sharp changes of temperature and humidity.

If the machine will not be used for an extended period of time, remove the paper from the cassette and the Multi Purpose (MP) Tray, return it to its original package and reseal it.


## Laser Safety (Europe)

Laser radiation could be hazardous to the human body. For this reason, laser radiation emitted inside this machine is hermetically sealed within the protective housing and external cover. In the normal operation of the product by user, no radiation can leak from the machine.


This machine is classified as Class 1 laser product under IEC/EN 60825-1:2007.

**Caution:** Performance of procedures other than those specified in this manual may result in hazardous radiation exposure.

These labels are attached to the laser scanner unit inside the machine and are not in a user access area.

	<b>DANGER</b>	• CLASS 3B LASER RADIATION WHEN OPEN. AVOID DIRECT EXPOSURE TO BEAM.	<b>VARO!</b> • AVATTAESSA OLET ALTTIINA LUOKAN 3B LASERSÄTEILYLLE. ÄLÄ KATSO SÄTEESEEN.
	<b>ATTENTION</b>	• CLASSE 3B RAYONNEMENT LASER EN CAS D'OUVERTURE. EXPOSITION DANGEREUSE AU FAISCEAU.	<b>警告</b> • 该产品为3B类激光产品，打开盖子后会有激光辐射，请避免光束照射。
	<b>VORSICHT</b>	• KLASSE 3B LASERSTRAHLUNG, WENN ABDECKUNG GEÖFFNET. NICHT DEM STRAHL AUSSETZEN.	<b>警告</b> • 該產品為3B類激光產品，打開蓋子後會有激光輻射，請避免光束照射。
	<b>ATTENZIONE</b>	• CLASSE 3B RADIAZIONE LASER IN CASO DI APERTURA. EVITARE L'ESPOSIZIONE AL FASCIO.	<b>위험</b> • CLASS 3B 가시 레이저광선을 직접 보지마십시오.
	<b>PRECAUCION</b>	• CLASSE 3B RADIACIONE LASER CUANDO SE ABRE. EVITAR EXPONERSE AL RAYO.	<b>警告</b> • ここを開くとクラス3Bレーザー光がでます。 ビームを直接見たり、触れないでください。

Regarding CLASS 1 laser products, information is provided on the rating label.



## **Legal Restriction on Copying/Scanning**

It may be prohibited to copy/scan copyrighted material without permission of the copyright owner.

Copying/Scanning the following items is prohibited and may be penalized by law. It may not be limited to these items. Do not knowingly copy/scan the items that are not to be copied/scanned.

- Paper money
- Bank note
- Securities
- Stamp
- Passport
- Certificate

Local laws and regulations may prohibit or restrict copying/scanning of other items not mentioned above.

## **EN ISO 7779**

Maschinenlärminformations-Verordnung 3. GPSGV, 06.01.2004: Der höchste Schalldruckpegel beträgt 70 dB (A) oder weniger gemäß EN ISO 7779.

## **EK1-ITB 2000**

Das Gerät ist nicht für die Benutzung im unmittelbaren Gesichtsfeld am Bildschirmarbeitsplatz vorgesehen. Um störende Reflexionen am Bildschirmarbeitsplatz zu vermeiden, darf dieses Produkt nicht im unmittelbaren Gesichtsfeld platziert werden.

## Legal Information

Copying or other reproduction of all or part of this guide without the prior written consent of KYOCERA Document Solutions Inc. is prohibited.

### Regarding Trade Names

- PRESCRIBE and ECOSYS are registered trademark of Kyocera Corporation.
- KPDL is a trademark of Kyocera Corporation.
- Microsoft, Windows, Windows XP, Windows Server 2003, Windows Vista, Windows Server 2008, Windows 7, Windows Server 2012, Windows 8, Windows 8.1 and Internet Explorer are registered trademarks or trademarks of Microsoft Corporation in the U.S.A. and/or other countries.
- PCL is a trademark of Hewlett-Packard Company.
- Adobe Acrobat, Adobe Reader and PostScript are trademarks of Adobe Systems, Incorporated.
- Ethernet is a registered trademark of Xerox Corporation.
- IBM and IBM PC/AT are trademarks of International Business Machines Corporation.
- AppleTalk, Bonjour, Macintosh, and Mac OS are trademarks of Apple Inc., registered in the U.S. and other countries.
- All European language fonts installed in this machine are used under licensing agreement with Monotype Imaging Inc.
- Helvetica, Palatino and Times are registered trademarks of Linotype GmbH.
- ITC Avant Garde Gothic, ITC Bookman, ITC ZapfChancery and ITC ZapfDingbats are registered trademarks of International Typeface Corporation.
- ThinPrint is a trademark of Cortado AG in Germany and other countries.
- UFST™ MicroType® fonts by Monotype Imaging Inc. are installed in this machine.
- This machine contains the software having modules developed by Independent JPEG Group.
- iPad, iPhone and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.
- AirPrint and the AirPrint logo are trademarks of Apple Inc.
- iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license by Apple Inc.
- Google and Google Cloud Print™ are trademarks and/or registered trademarks of Google Inc.

All other brands and product names are registered trademarks or trademarks of their respective companies. The designations ™ and ® will not be used in this Operation Guide.

## GPL/LGPL

This product contains GPL (<http://www.gnu.org/licenses/gpl.html>) and/or LGPL (<http://www.gnu.org/licenses/lgpl.html>) software as part of its firmware. You can get the source code, and you are permitted to copy, redistribute and modify it under the terms of GPL/LGPL. For further information including availability of the source code, visit <http://www.kyoceradocumentsolutions.com/gpl/>.

## OpenSSL License

Copyright (c) 1998-2006 The OpenSSL Project. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. All advertising materials mentioning features or use of this software must display the following acknowledgment: "This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit. (<http://www.openssl.org/>)"
4. The names "OpenSSL Toolkit" and "OpenSSL Project" must not be used to endorse or promote products derived from this software without prior written permission. For written permission, please contact [openssl-core@openssl.org](mailto:openssl-core@openssl.org).
5. Products derived from this software may not be called "OpenSSL" nor may "OpenSSL" appear in their names without prior written permission of the OpenSSL Project.
6. Redistributions of any form whatsoever must retain the following acknowledgment: "This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit (<http://www.openssl.org/>)"

THIS SOFTWARE IS PROVIDED BY THE OpenSSL PROJECT "AS IS" AND ANY EXPRESSED OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE OpenSSL PROJECT OR ITS CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

## Original SSLeay License

Copyright (C) 1995-1998 Eric Young ([ey@cryptsoft.com](mailto:ey@cryptsoft.com)) All rights reserved.

This package is an SSL implementation written by Eric Young ([ey@cryptsoft.com](mailto:ey@cryptsoft.com)). The implementation was written so as to conform with Netscape's SSL.

This library is free for commercial and non-commercial use as long as the following conditions are adhered to. The following conditions apply to all code found in this distribution, be it the RC4, RSA, lhash, DES, etc., code; not just the SSL code. The SSL documentation included with this distribution is covered by the same copyright terms except that the holder is Tim Hudson ([tjh@cryptsoft.com](mailto:tjh@cryptsoft.com)).

Copyright remains Eric Young's, and as such any Copyright notices in the code are not to be removed.

If this package is used in a product, Eric Young should be given attribution as the author of the parts of the library used.

This can be in the form of a textual message at program startup or in documentation (online or textual) provided with the package.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. All advertising materials mentioning features or use of this software must display the following acknowledgement:  
"This product includes cryptographic software written by Eric Young (eay@cryptsoft.com)"  
The word 'cryptographic' can be left out if the routines from the library being used are not cryptographic related :-).
4. If you include any Windows specific code (or a derivative thereof) from the apps directory (application code) you must include an acknowledgement: "This product includes software written by Tim Hudson (tjh@cryptsoft.com)"

THIS SOFTWARE IS PROVIDED BY ERIC YOUNG "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE AUTHOR OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

The licence and distribution terms for any publically available version or derivative of this code cannot be changed. i.e. this code cannot simply be copied and put under another distribution licence [including the GNU Public Licence.]

### **Monotype Imaging License Agreement**

- 1 *Software* shall mean the digitally encoded, machine readable, scalable outline data as encoded in a special format as well as the UFST Software.
- 2 You agree to accept a non-exclusive license to use the Software to reproduce and display weights, styles and versions of letters, numerals, characters and symbols (*Typefaces*) solely for your own customary business or personal purposes at the address stated on the registration card you return to Monotype Imaging. Under the terms of this License Agreement, you have the right to use the Fonts on up to three printers. If you need to have access to the fonts on more than three printers, you need to acquire a multiuser license agreement which can be obtained from Monotype Imaging. Monotype Imaging retains all rights, title and interest to the Software and Typefaces and no rights are granted to you other than a License to use the Software on the terms expressly set forth in this Agreement.
- 3 To protect proprietary rights of Monotype Imaging, you agree to maintain the Software and other proprietary information concerning the Typefaces in strict confidence and to establish reasonable procedures regulating access to and use of the Software and Typefaces.
- 4 You agree not to duplicate or copy the Software or Typefaces, except that you may make one backup copy. You agree that any such copy shall contain the same proprietary notices as those appearing on the original.
- 5 This License shall continue until the last use of the Software and Typefaces, unless sooner terminated. This License may be terminated by Monotype Imaging if you fail to comply with the terms of this License and such failure is not remedied within thirty (30) days after notice from Monotype Imaging. When this License expires or is terminated, you shall either return to Monotype Imaging or destroy all copies of the Software and Typefaces and documentation as requested.
- 6 You agree that you will not modify, alter, disassemble, decrypt, reverse engineer or decompile the Software.
- 7 Monotype Imaging warrants that for ninety (90) days after delivery, the Software will perform in accordance with Monotype Imaging-published specifications, and the diskette will be free from defects in material and workmanship. Monotype Imaging does not warrant that the Software is free from all bugs, errors and omissions.  
  
The parties agree that all other warranties, expressed or implied, including warranties of fitness for a particular purpose and merchantability, are excluded.
- 8 Your exclusive remedy and the sole liability of Monotype Imaging in connection with the Software and Typefaces is repair or replacement of defective parts, upon their return to Monotype Imaging.  
  
In no event will Monotype Imaging be liable for lost profits, lost data, or any other incidental or consequential damages, or any damages caused by abuse or misapplication of the Software and Typefaces.
- 9 Massachusetts U.S.A. law governs this Agreement.

- 10 You shall not sublicense, sell, lease, or otherwise transfer the Software and/or Typefaces without the prior written consent of Monotype Imaging.
- 11 Use, duplication or disclosure by the Government is subject to restrictions as set forth in the Rights in Technical Data and Computer Software clause at FAR 252-227-7013, subdivision (b)(3)(ii) or subparagraph (c)(1)(ii), as appropriate. Further use, duplication or disclosure is subject to restrictions applicable to restricted rights software as set forth in FAR 52.227-19 (c)(2).
- 12 You acknowledge that you have read this Agreement, understand it, and agree to be bound by its terms and conditions. Neither party shall be bound by any statement or representation not contained in this Agreement. No change in this Agreement is effective unless written and signed by properly authorized representatives of each party. By opening this diskette package, you agree to accept the terms and conditions of this Agreement.

### **Knopflerfish License**

This product includes software developed by the Knopflerfish Project.

<http://www.knopflerfish.org>

Copyright 2003-2010 The Knopflerfish Project. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- Neither the name of the KNOPFLERFISH project nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

### **Apache License (Version 2.0)**

Apache License  
Version 2.0, January 2004  
<http://www.apache.org/licenses/>

#### **TERMS AND CONDITIONS FOR USE, REPRODUCTION, AND DISTRIBUTION**

##### **1. Definitions.**

"License" shall mean the terms and conditions for use, reproduction, and distribution as defined by Sections 1 through 9 of this document.

"Licensor" shall mean the copyright owner or entity authorized by the copyright owner that is granting the License.

"Legal Entity" shall mean the union of the acting entity and all other entities that control, are controlled by, or are under common control with that entity. For the purposes of this definition, "control" means (i) the power, direct or indirect, to cause the direction or management of such entity, whether by contract or otherwise, or (ii) ownership of fifty percent (50%) or more of the outstanding shares, or (iii) beneficial ownership of such entity.

"You" (or "Your") shall mean an individual or Legal Entity exercising permissions granted by this License.

"Source" form shall mean the preferred form for making modifications, including but not limited to software source code, documentation source, and configuration files.



"Object" form shall mean any form resulting from mechanical transformation or translation of a Source form, including but not limited to compiled object code, generated documentation, and conversions to other media types.

"Work" shall mean the work of authorship, whether in Source or Object form, made available under the License, as indicated by a copyright notice that is included in or attached to the work (an example is provided in the Appendix below).

"Derivative Works" shall mean any work, whether in Source or Object form, that is based on (or derived from) the Work and for which the editorial revisions, annotations, elaborations, or other modifications represent, as a whole, an original work of authorship. For the purposes of this License, Derivative Works shall not include works that remain separable from, or merely link (or bind by name) to the interfaces of, the Work and Derivative Works thereof.

"Contribution" shall mean any work of authorship, including the original version of the Work and any modifications or additions to that Work or Derivative Works thereof, that is intentionally submitted to Licensor for inclusion in the Work by the copyright owner or by an individual or Legal Entity authorized to submit on behalf of the copyright owner. For the purposes of this definition, "submitted" means any form of electronic, verbal, or written communication sent to the Licensor or its representatives, including but not limited to communication on electronic mailing lists, source code control systems, and issue tracking systems that are managed by, or on behalf of, the Licensor for the purpose of discussing and improving the Work, but excluding communication that is conspicuously marked or otherwise designated in writing by the copyright owner as "Not a Contribution."

"Contributor" shall mean Licensor and any individual or Legal Entity on behalf of whom a Contribution has been received by Licensor and subsequently incorporated within the Work.

2. Grant of Copyright License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable copyright license to reproduce, prepare Derivative Works of, publicly display, publicly perform, sublicense, and distribute the Work and such Derivative Works in Source or Object form.
3. Grant of Patent License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable (except as stated in this section) patent license to make, have made, use, offer to sell, sell, import, and otherwise transfer the Work, where such license applies only to those patent claims licensable by such Contributor that are necessarily infringed by their Contribution(s) alone or by combination of their Contribution(s) with the Work to which such Contribution(s) was submitted. If You institute patent litigation against any entity (including a cross-claim or counterclaim in a lawsuit) alleging that the Work or a Contribution incorporated within the Work constitutes direct or contributory patent infringement, then any patent licenses granted to You under this License for that Work shall terminate as of the date such litigation is filed.
4. Redistribution. You may reproduce and distribute copies of the Work or Derivative Works thereof in any medium, with or without modifications, and in Source or Object form, provided that You meet the following conditions:
  - (a) You must give any other recipients of the Work or Derivative Works a copy of this License; and
  - (b) You must cause any modified files to carry prominent notices stating that You changed the files; and
  - (c) You must retain, in the Source form of any Derivative Works that You distribute, all copyright, patent, trademark, and attribution notices from the Source form of the Work, excluding those notices that do not pertain to any part of the Derivative Works; and
  - (d) If the Work includes a "NOTICE" text file as part of its distribution, then any Derivative Works that You distribute must include a readable copy of the attribution notices contained within such NOTICE file, excluding those notices that do not pertain to any part of the Derivative Works, in at least one of the following places: within a NOTICE text file distributed as part of the Derivative Works; within the Source form or documentation, if provided along with the Derivative Works; or, within a display generated by the Derivative Works, if and wherever such third-party notices normally appear. The contents of the NOTICE file are for informational purposes only and do not modify the License. You may add Your own attribution notices within Derivative Works that You distribute, alongside or as an addendum to the NOTICE text from the Work, provided that such additional attribution notices cannot be construed as modifying the License.

You may add Your own copyright statement to Your modifications and may provide additional or different license terms and conditions for use, reproduction, or distribution of Your modifications, or for any such Derivative Works as a whole, provided Your use, reproduction, and distribution of the Work otherwise complies with the conditions stated in this License.

5. **Submission of Contributions.** Unless You explicitly state otherwise, any Contribution intentionally submitted for inclusion in the Work by You to the Licensor shall be under the terms and conditions of this License, without any additional terms or conditions. Notwithstanding the above, nothing herein shall supersede or modify the terms of any separate license agreement you may have executed with Licensor regarding such Contributions.
6. **Trademarks.** This License does not grant permission to use the trade names, trademarks, service marks, or product names of the Licensor, except as required for reasonable and customary use in describing the origin of the Work and reproducing the content of the NOTICE file.
7. **Disclaimer of Warranty.** Unless required by applicable law or agreed to in writing, Licensor provides the Work (and each Contributor provides its Contributions) on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied, including, without limitation, any warranties or conditions of TITLE, NON-INFRINGEMENT, MERCHANTABILITY, or FITNESS FOR A PARTICULAR PURPOSE. You are solely responsible for determining the appropriateness of using or redistributing the Work and assume any risks associated with Your exercise of permissions under this License.
8. **Limitation of Liability.** In no event and under no legal theory, whether in tort (including negligence), contract, or otherwise, unless required by applicable law (such as deliberate and grossly negligent acts) or agreed to in writing, shall any Contributor be liable to You for damages, including any direct, indirect, special, incidental, or consequential damages of any character arising as a result of this License or out of the use or inability to use the Work (including but not limited to damages for loss of goodwill, work stoppage, computer failure or malfunction, or any and all other commercial damages or losses), even if such Contributor has been advised of the possibility of such damages.
9. **Accepting Warranty or Additional Liability.** While redistributing the Work or Derivative Works thereof, You may choose to offer, and charge a fee for, acceptance of support, warranty, indemnity, or other liability obligations and/or rights consistent with this License. However, in accepting such obligations, You may act only on Your own behalf and on Your sole responsibility, not on behalf of any other Contributor, and only if You agree to indemnify, defend, and hold each Contributor harmless for any liability incurred by, or claims asserted against, such Contributor by reason of your accepting any such warranty or additional liability.

END OF TERMS AND CONDITIONS

APPENDIX: How to apply the Apache License to your work.

To apply the Apache License to your work, attach the following boilerplate notice, with the fields enclosed by brackets "[ ]" replaced with your own identifying information. (Don't include the brackets!) The text should be enclosed in the appropriate comment syntax for the file format. We also recommend that a file or class name and description of purpose be included on the same "printed page" as the copyright notice for easier identification within third-party archives.

Copyright [yyyy] [name of copyright owner]

Licensed under the Apache License, Version 2.0 (the "License"); you may not use this file except in compliance with the License. You may obtain a copy of the License at

<http://www.apache.org/licenses/LICENSE-2.0>

Unless required by applicable law or agreed to in writing, software distributed under the License is distributed on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied. See the License for the specific language governing permissions and limitations under the License.

## Energy Saving Control Function

The device comes equipped with a **Sleep** where printer and fax functions remain in a waiting state but power consumption is reduced to a minimum after a certain amount of time elapses since the device was last used.

### Sleep

The device automatically enters Sleep when 1 minute has passed since the device was last used. The amount of time of no activity that must pass before Sleep is activated may be lengthened.

➔ [Sleep and Auto Sleep \(page 2-20\)](#)

## Automatic 2-Sided Print Function

This device includes 2-sided printing as a standard function. For example, by printing two 1-sided originals onto a single sheet of paper as a 2-sided print, it is possible to lower the amount of paper used.

➔ [Duplex \(page 6-22\)](#)

Printing in duplex mode reduces paper consumption and contributes to the conservation of forest resources. Duplex mode also reduces the amount of paper that must be purchased, and thereby reduces cost. It is recommended that machines capable of duplex printing be set to use duplex mode by default.

## Resource Saving - Paper

For the preservation and sustainable use of forest resources, it is recommended that recycled as well as virgin paper certified under environmental stewardship initiatives or carrying recognised ecolabels, which meet EN 12281:2002\* or an equivalent quality standard, be used.

This machine also supports printing on 64 g/m<sup>2</sup> paper. Using such paper containing less raw materials can lead to further saving of forest resources.

\* : EN12281:2002 "Printing and business paper - Requirements for copy paper for dry toner imaging processes"

Your sales or service representative can provide information about recommended paper types.

## Environmental benefits of "Power Management"

To reduce power consumption when idle, this machine is equipped with a power management function that automatically activates energy-saving mode when the machine is idle for a certain period of time.

Although it takes the machine a slight amount of time to return to READY mode when in energy-saving mode, a significant reduction in energy consumption is possible. It is recommended that the machine be used with the activation time for energy-saving mode set to the default setting.

## Energy Star (ENERGY STAR<sup>®</sup>) Program



We have determined as a participating company in the International Energy Star Program that this product is compliant with the standards laid out in the International Energy Star Program.

ENERGY STAR<sup>®</sup> is a voluntary energy efficiency program with the goal of developing and promoting the use of products with high energy efficiency in order to help prevent global warming. By purchasing

ENERGY STAR<sup>®</sup> qualified products, customers can help reduce emissions of greenhouse gases during product use and cut energy-related costs.


# 2 Installing and Setting up the Machine

This chapter provides information for the administrator of this machine, such as part names, cable connection, and software installation.

Part Names .....	2-2	Command Center RX .....	2-38
Machine Exterior .....	2-2	Accessing Command Center RX .....	2-39
Connectors/Interior .....	2-4	Changing Security Settings .....	2-40
With Optional Equipments Attached ...	2-6	Changing Device Information .....	2-42
Connecting the Machine and Other		E-mail Settings .....	2-44
Devices .....	2-7	Registering Destinations .....	2-48
Connecting Cables .....	2-8	Creating a New Custom Box .....	2-49
Connecting LAN Cable .....	2-8	Printing a document stored in a Custom	
Connecting USB Cable .....	2-9	Box .....	2-50
Connecting the Power Cable .....	2-9	Transferring Data from Our Other	
Power On/Off .....	2-10	Products .....	2-52
Power On .....	2-10	Migrating the Address Book .....	2-52
Power Off .....	2-10		
Using the Operation Panel .....	2-11		
Operation Panel Keys .....	2-11		
Operation Method .....	2-12		
Display for Originals and Paper .....	2-13		
Help Screen .....	2-13		
Login/Logout .....	2-14		
Login .....	2-14		
Logout .....	2-15		
Default Settings of the Machine .....	2-16		
Setting Date and Time .....	2-16		
Network Setup (LAN Cable			
Connection) .....	2-17		
Energy Saver function .....	2-20		
Sleep and Auto Sleep .....	2-20		
Installing Software .....	2-22		
Software on DVD (Windows) .....	2-22		
Installing Software in Windows .....	2-23		
Uninstalling the Software .....	2-29		
Installing Software			
in Mac Computer .....	2-30		
Setting TWAIN Driver .....	2-32		
Setting WIA Driver .....	2-34		
Checking the Counter .....	2-35		
Additional Preparations for			
the Administrator .....	2-36		
Sending Documents to a PC .....	2-36		
Strengthening the Security .....	2-36		


# Part Names

## Machine Exterior



- 1 Document Processor
- 2 Inner Tray
- 3 Paper Stopper
- 4 Cassette 1
- 5 Power Switch
- 6 USB Memory Slot
- 7 Scanner Unit Open Lever
- 8 Original Stopper


- 9 Original Eject Table
- 10 Original Table
- 11 Original Width Guides
- 12 Slit Glass
- 13 Handles
- 14 Operation Panel
- 15 Platen
- 16 Original Size Indicator Plates



17 Handles

18 Rear Cover 1


## Connectors/Interior



- 1 Network Interface Connector
- 2 USB Port
- 3 USB Interface Connector
- 4 Option Interface
- 5 LINE Connector
- 6 TEL Connector
- 7 Feed Cover

- 8 Size Dial
- 9 Paper Length Guide
- 10 Paper Width Guides
- 11 Multi Purpose Tray
- 12 Paper Width Guides
- 13 Fuser Cover






- 14 Toner Container (Black)
- 15 Toner Container (Magenta)
- 16 Toner Container (Cyan)
- 17 Toner Container (Yellow)

- 18 Toner Container Lock Lever
- 19 Waste Toner Cover
- 20 Waste Toner Box

## With Optional Equipments Attached



- 1 Cassette 2
- 2 Cassette 3
- 3 Cassette 4
- 4 Manual stapler


- 5 Rear Cover 2
- 6 Rear Cover 3
- 7 Rear Cover 4

➔ [Optional Equipment \(page 11-2\)](#)


# Connecting the Machine and Other Devices

Prepare the cables necessary to suit the environment and purpose of the machine use.

## When Connecting the Machine to the PC via USB



## When Connecting the Machine to the PC on the Network



### NOTE

If you are using the machine with the optional wireless interface kit attached, you do not need to connect the LAN cable. To use a wireless LAN, it is necessary to change the default settings for the machine using the System Menu.

➔ [Optional Network \(page 8-29\)](#)

## Cables that Can Be Used

Connection Environment	Function	Necessary Cable
Connect a LAN cable to the machine.	Printer/Scanner/Network FAX*1	LAN cable (10BASE-T, 100BASE-TX, 1000BASE-T)
Connect a USB cable to the machine.	Printer/Scanner (TWAIN/WIA)	USB2.0 compatible cable (Hi-Speed USB compliant, Max. 5.0 m)

\*1 Only on products with the fax function installed.

# Connecting Cables

## Connecting LAN Cable


✔ **IMPORTANT**

If the power is on, turn the power switch off.

➔ [Power Off \(page 2-10\)](#)

### 1 Connect the cable to the machine.

- 1 Connect the LAN cable to the network interface connector.



- 2 Connect the other end of the cable to the hub.

### 2 Power on the machine and configure the network.

➔ [Network Setup \(LAN Cable Connection\) \(page 2-17\)](#)

## Connecting USB Cable


✔ **IMPORTANT**

If the power is on, turn the power switch off.

➔ [Power Off \(page 2-10\)](#)

### 1 Connect the cable to the machine.

- 1 Connect the USB cable to the USB interface connector located on the left side of the body.




- 2 Connect the other end of the cable to the PC.

### 2 Power on the machine.

## Connecting the Power Cable

### 1 Connect the cable to the machine.

Connect one end of the supplied power cable to the machine and the other end to a power outlet.




✔ **IMPORTANT**

Only use the power cable that comes with the machine.

# Power On/Off

## Power On

### 1 Turn the power switch on.



#### ✔ IMPORTANT


When turning off the power switch, do not turn on the power switch again immediately. Wait more than 5 seconds, and then turn on the power switch.

## Power Off


#### ✔ IMPORTANT

When the [Processing] indicator or [Memory] indicator is lit up or blinked, the machine is operating. Turning off the power switch while the machine is operating may cause it to malfunction.

### 1 Turn the power switch off.



Check that the indicators are off.



### In case of not using the machine for an extended period of time...

#### ⚠ CAUTION



















If this machine will be left unused for an extended period (e.g. overnight), turn it off at the main power switch. If the machine will not be used for an even longer period of time (e.g. vacation), remove the power plug from the outlet as a safety precaution. If using the products equipped with the fax function, note that turning the machine off at the main power switch disables fax transmission and reception.

#### ✔ IMPORTANT

Remove paper from the cassettes and seal it in the paper storage bag to protect it from humidity.


# Using the Operation Panel






## Operation Panel Keys

 <p>Status/ Job Cancel</p>	Displays the Status/Job Cancel screen.	 <p>Function Menu</p>	Displays the function menu screen.	 <p>Numeric keys. Enter numbers and symbols.</p>
 <p>Document Box/USB</p>	Displays the Document Box/USB screen.	 <p>Increments or decrements numbers, or selects menu in the message display. In addition, moves the cursor when entering the characters.</p>	 <p>Clear</p>	Clears entered numbers and characters.
 <p>System Menu/ Counter</p>	Displays the System Menu/Counter screen.	 <p>Finalizes a function or menu, and numbers that have been entered.</p>	 <p>Reset</p>	Returns settings to their default states.
 <p>Copy</p>	Displays the Copy screen.	 <p>Returns to the previous display.</p>	 <p>Stop</p>	Cancels or pauses the job in progress.
 <p>Send</p>	Displays the screen for sending. You can change it to display the Address Book screen.	 <p>Auto Color</p>	 <p>Start</p>	Starts copying and scanning operations and processing for setting operations.
 <p>FAX</p>	Displays the FAX screen.	 <p>Full Color</p>		
		 <p>Black&amp;White</p>		

### Message display:

Displays the setting menu, machine status, and error messages.






 <p>Address Book</p>	Displays the Address Book screen.
 <p>Address Recall/Pause</p>	Calls the previous destination. Also used to enter a pause when entering a FAX number.
 <p>Confirm/Add Destination</p>	Confirms the destination or adds a destination.
 <p>On Hook</p>	Switches between on-hook and off-hook when manually sending a FAX.
	Recalls the destination registered for One Touch Keys.

**Select Key:** Selects the menu displayed at the bottom of the message display.

**Processing:** Blinks while printing or sending/receiving.

**Memory:** Blinks while the machine is accessing the machine memory, fax memory or USB memory (general purpose item).

**Attention:** Lights or blinks when an error occurs and a job is stopped.


 <p>Program</p>	Used to register or recall programs.	 <p>Energy Saver</p>	Puts the machine into Sleep Mode. Recovers from Sleep if in Sleep Mode.
		 <p>Authentication/ Logout</p>	Authenticates user switching, and exits the operation for the current user (i.e. log out).

## Operation Method

This section explains how to operate the setting menus on the message display.

### Displaying the Menus and Configuring Settings


Select the **[System Menu/Counter]** key or **[Function Menu]** key to display the setting menus. Select the **[▲]** key, **[▼]** key, **[◀]** key, **[▶]** key, **[OK]** key, or **[Back]** key to select a menu, and perform settings.





## Display for Originals and Paper

The copy screen displays the selected paper source.



- 1 Original size
- 2 Original orientation
- 3 Paper source
- 4 Paper size
- 5 Paper orientation

## Help Screen

If you have difficulty operating the machine, you can check how to operate it using the operation panel.

When **[Help]** is displayed on the message display, select **[Help]** to display the Help screen. The Help screen shows machine operation.



Select the **[▼]** key to display the next step or select the **[▲]** key to display the previous step.

Select the **[OK]** key to exit the Help screen.

# Login/Logout

If you are setting a function that requires administrator rights, or if user login administration is enabled, you must enter your login user name and login password.

## NOTE

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

You will be unable to login if you forget your login user name or login password. In this event, login with administrator privileges and change your login user name or login password.

## Login

### 1 Enter the login user name.

- 1 If the login screen is displayed during operations, select "Login User Name" and select the [OK] key.

#### NOTE

- If [Netwk Authentic.] is selected as the user authentication method, [Menu] is displayed. Select [Menu] and select [Login Type] and then it is possible to select the authentication destination as [Local Authentic.] or [Netwk Authentic.].
- Select [Menu] and select [Domain] and then it is possible to select from the domains registered.

- 2 Enter the login user name using the numeric keys and select the [OK] key.

#### NOTE

If Login Operation is [Select Character], then the screen is displayed to enter details by selecting from the characters on the message display.

➔ [Login Operation \(page 8-20\)](#)

➔ [Character Entry Method \(page 11-11\)](#)

### 2 Enter the login password.

- 1 Select "Login Password" and select the [OK] key.
- 2 Enter the login password and select the [OK] key.

➔ [Character Entry Method \(page 11-11\)](#)

### 3 Select [Login].

## Logout



To logout from the machine, select the [**Authentication/Logout**] key to return to the login user name/login password entry screen.

Users are automatically logged out in the following circumstances:

- When the machine enters the sleep state.
- When the auto panel reset function is activated.

# Default Settings of the Machine

Before using this machine, configure such settings as date and time, network configuration, and energy saving functions as needed.

## NOTE

The default settings of the machine can be changed in System Menu.  
For settings that are configurable from System Menu, refer to the following:

➔ [Setup and Registration \(System Menu\) \(page 8-1\)](#)

## Setting Date and Time

Follow the steps below to set the local date and time at the place of installation.

When you send an E-mail using the transmission function, the date and time as set here will be printed in the header of the E-mail message. Set the date, time and time difference from GMT of the region where the machine is used.

## NOTE

- If user login administration is enabled, you can only change the settings by logging in with administrator privileges. If user login administration is disabled, the user authentication screen appears. Enter a login user name and password, and select [Login].
- The factory default login user name and login password are set as shown below.  
**Login User Name: 3000**  
**Login Password: 3000**
- Be sure to set the time difference before setting the date and time.
- The correct time can be periodically set by obtaining the time from the network time server.

➔ [Command Center RX User Guide](#)

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Date Setting] > [OK] key

### 2 Configure the settings.

[▲] [▼] key > [Time Zone] > [OK] key > Select the time zone > [OK] key > [▲] [▼] key > [Date/Time] > [OK] key > Set the date/time > [OK] key > [▲] [▼] key > [Date Format] > [OK] key > Select the Date Format > [OK] key

Item	Description
<b>Time Zone</b>	Set the time difference from GMT. Choose the nearest listed location from the list. If you select a region that utilizes summer time, configure settings for summer time.
<b>Date/Time</b>	Set the date and time for the location where you use the machine. If you perform Send as E-mail, the date and time set here will be displayed on the header. <b>Value: Year (2000 to 2037), Month (1 to 12), Day (1 to 31), Hour (00 to 23), Minute (00 to 59), Second (00 to 59)</b>
<b>Date Format</b>	Select the display format of year, month, and date. The year is displayed in Western notation. <b>Value: Month/Day/Year, Day/Month/Year, Year/Month/Day</b>

## NOTE

Select the [▲] or [▼] key to enter a number.  
Select the [◀] or [▶] key to move the position being entered, which is shown highlighted.

## Network Setup (LAN Cable Connection)

The machine is equipped with network interface, which is compatible with network protocols such as TCP/IP (IPv4), TCP/IP (IPv6), NetBEUI, and IPsec. It enables network printing on the Windows, Macintosh, UNIX and other platforms.

Set up TCP/IP (IPv4) to connect to the Windows network.

The default settings are "TCP/IP Protocol: On, DHCP: On, Auto-IP: On".

### NOTE

If user login administration is enabled, you can only change the settings by logging in with administrator privileges. If user login administration is disabled, the user authentication screen appears. Enter a login user name and password, and select [Login].

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

## TCP/IP Settings

### IPv4 setting

Set up TCP/IP (IPv4) to connect to the Windows network.

### NOTE

Ask your network administrator for the IP address in advance, and have it ready when you configure this setting. In the following cases, set the IP address of DNS server on the Command Center RX.

Setting the IP Address of the DNS Server, refer to the following:

#### ► Command Center RX User Guide

- When using the host name with "DHCP" setting set to "Off"
- When using the DNS server with IP address that is not assigned by DHCP automatically.

## 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Network Setting] > [OK] key > [▲] [▼] key > [TCP/IP Settings] > [OK] key > [▲] [▼] key > [IPv4 Setting] > [OK] key

## 2 Configure the settings.

**When setting the static IP address**

- 1 [▲] [▼] key > [DHCP] > [OK] key > [▲] [▼] key > [Off] > [OK] key
- 2 [▲] [▼] key > [IP Address] > [OK] key
- 3 Set the IP address.

### NOTE

You can set any value between 000 and 255.

Use the numeric keys or select the [▲] or [▼] key to enter a number.

Select the [◀] or [▶] key to move the position being entered, which is shown highlighted.

- 4 Select the [OK] key.

5 [▲] [▼] key > **[Subnet Mask]** > **[OK]** key

6 Set the subnet mask.



**NOTE**

You can set any value between 000 and 255.  
Use the numeric keys or select the [▲] or [▼] key to enter a number.  
Select the [◀] or [▶] key to move the position being entered, which is shown highlighted.

7 Select the **[OK]** key.

8 [▲] [▼] key > **[Default Gateway]** > **[OK]** key

9 Set the default gateway.



**NOTE**

You can set any value between 000 and 255.  
Use the numeric keys or select the [▲] or [▼] key to enter a number.  
Select the [◀] or [▶] key to move the position being entered, which is shown highlighted.

10 Select the **[OK]** key.



**IMPORTANT**

**After changing the setting, restart the network from System Menu, or turn the machine OFF and then ON.**

➔ [Restart Network \(page 8-29\)](#)



**NOTE**

The network can be configured from the computer by using Command Center RX.

➔ **Command Center RX User Guide**

## Wireless Network Settings

When the optional Wireless Network Interface Kit is installed on the machine and the connection settings are configured, it is possible to print in a wireless network (wireless LAN) environment. The following is an introduction to the settings for connecting using the Quick Setup.

The following four settings can be configured in Quick Setup.

➔ [Setup \(page 8-30\)](#)

### Available Network

Displays access points to which the machine can connect.

### Push Button

If the access point supports the push button method, wireless settings can be configured using the push button. This setting executes push button, and the connection is started by pressing the push button on the access point.



#### NOTE

The push button method supports only the WPS.

### PIN (Device)

Starts connection using the machine's PIN code. Enter the PIN code into the access point. The PIN code of the machine is automatically generated.

### PIN (Terminal)

Starts connection using the PIN code of the access point. Enter the PIN code of the access point.

# Energy Saver function

If a certain period of time elapses after the machine is last used, the machine automatically enters sleep mode, which minimizes power consumption. If the machine is not used while in sleep mode, the power automatically turns off.

## Sleep and Auto Sleep

### NOTE

If user login administration is enabled, you can only change the settings by logging in with administrator privileges. If user login administration is disabled, the user authentication screen appears. Enter a login user name and password, and select **[Login]**.


The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

### Sleep

To enter Sleep, select the **[Energy Saver]** key. Message display and all indicators on the operation panel will go out to save a maximum amount of power except the Energy Saver indicator. This status is referred to as Sleep.



If print data is received during Sleep, the machine automatically wakes up and starts printing.

Also when fax data arrives while the machine is in Sleep, the machine automatically wakes up and starts printing.

To resume, perform the following actions.

- Select any key on the operation panel.

The machine will be ready to operate within 17 seconds.

Note that ambient environmental conditions, such as ventilation, may cause the machine to respond more slowly.

### Auto Sleep

Auto Sleep automatically switches the machine into Sleep if left idle for a preset time.

The default preset time is 1 minute.

To change the preset sleep time, refer to the following:

➔ [Sleep Timer \(page 8-18\)](#)

Follow the steps below to set the sleep timer for the machine to go into sleep mode when not in use.

#### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Timer Setting] > [OK] key > [▲] [▼] key > [Sleep Timer] > [OK] key



## 2 Set the Sleep time.

- 1 Enter the Sleep time.

### NOTE

You can set any value between 1 and 240.  
Use the numeric keys or select the [▲] or [▼] key to enter a number.

- 2 Select the [OK] key.

## Sleep Rules (models for Europe)

You can set whether sleep mode operates for each function. When the machine enters sleep mode, the ID card cannot be recognized.

For more information on Sleep Rules settings, refer to the following:

➔ [Sleep Rules \(models for Europe\) \(page 8-18\)](#)

## Sleep Level (Energy Saver and Quick Recovery) (models except for Europe)

For sleep level, you can toggle between the following two modes: Energy Saver mode and Quick Recovery mode. The default setting is Energy Saver mode.

Energy Saver mode reduces power consumption even more than Quick Recovery mode, and allows Sleep Mode to be set separately for each function. The ID card cannot be recognized.

### NOTE

If the optional Network Interface Kit is installed, this function will not be displayed.

To resume, select the [Energy Saver] key on the operation panel. If print data is received during Sleep, the machine automatically wakes up and starts printing.

For more information on Sleep Level settings, refer to the following:

➔ [Sleep Level \(models except for Europe\) \(page 8-18\)](#)

Follow the steps below to select the sleep level and use Energy Saver mode for each function.

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Timer Setting] > [OK] key > [▲] [▼] key > [Sleep Level] > [OK] key

### 2 Select the Sleep level.

[▲] [▼] key > [Quick Recovery] or [Energy Saver] > [OK] key

When [Energy Saver] is set, next go on to set whether or not to use Energy Saver mode for each function.

### 3 Set the Sleep rule.

- 1 Select the function to be set, and select the [OK] key.

[Card Reader] is displayed when the optional Card Authentication Kit is activated.

[FAX] is displayed only on products with the fax function installed.

- 2 [▲] [▼] key > [Off] or [On] > [OK] key

Repeat steps 3-1 to 3-2 to set for a different function.

# Installing Software

Install appropriate software on your PC from the included DVD (Product Library) if you want to use the printer function of this machine or perform TWAIN / WIA transmission or Network FAX transmission from your PC.

## Software on DVD (Windows)

You can use either [**Express Install**] or [**Custom Install**] can be selected for the installation method. [**Express Install**] is the standard installation method. To install components that cannot be installed by [**Express Install**], use [**Custom Install**].

For details on Custom Installation, refer to the following:

➔ [Custom Install \(page 2-26\)](#)

Software	Description	Express Install
KX DRIVER	This driver enables files on a computer to be printed by the machine. Multiple page description languages (PCL XL, KPDL, etc.) are supported by a single driver. This printer driver allows you to take full advantage of the features of the machine. Use this driver to create PDF files.	<input type="radio"/>
KX XPS DRIVER	This printer driver supports the XPS (XML Paper Specification) format developed by Microsoft Corporation.	-
KPDL mini-driver/PCL mini-driver	This is a Microsoft MiniDriver that supports PCL and KPDL. There are some restrictions on the machine features and option features that can be used with this driver.	-
FAX Driver	This makes it possible to send a document created in a computer software application as a fax via the machine.	-
Kyocera TWAIN Driver	This driver enables scanning on the machine using a TWAIN-compliant software application.	<input type="radio"/>
Kyocera WIA Driver	WIA (Windows Imaging Acquisition) is a function of Windows that enables reciprocal communication between an imaging device such as a scanner and an image processing software application. An image can be acquired using a WIA-compliant software application, which is convenient when a TWAIN-compliant software application is not installed in the computer.	-
KYOCERA Net Viewer	This is a utility that enables monitoring of the machine on the network.	-
Status Monitor	This is a utility that monitors the printer status and provides an ongoing reporting function.	<input type="radio"/>
KYOCERA Net Direct Print	This makes it possible to print a PDF file without starting Adobe Acrobat/Reader.	-
FONTS	These are display fonts that enable the machine's built-in fonts to be used in a software application.	<input type="radio"/>



### NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- Fax functionality can only be used on products equipped with fax capability.
- WIA Driver and KX XPS DRIVER cannot be installed on Windows XP.

## Installing Software in Windows


### Express Install

The following procedure is an example for installing the software in Windows 7 using **[Express Install]**.

For details on Custom Installation, refer to the following:

➔ [Custom Install \(page 2-26\)](#)


### 1 Insert the DVD.



#### NOTE


- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "**Welcome to the Found New Hardware Wizard**" dialog box displays, select **[Cancel]**.
- If the autorun screen is displayed, click **[Run setup.exe]**.
- If the user account management window appears, click **[Yes]** (**[Allow]**).

### 2 Display the screen.



- 1 Click **[View License Agreement]** and read the License Agreement.
- 2 Click **[Accept]**.

### 3 Install using [Express Install].




You can also select [**Use host name for port name**] and set to use the host name of the standard TCP/IP port. (A USB connection cannot be used.)




#### NOTE

- To install Status Monitor, it is necessary to install Microsoft .NET Framework 4.0 beforehand.



- The machine cannot be detected unless it is on. If the computer fails to detect the machine, verify that it is connected to the computer via a network or USB cable and that it is turned on and click **⌂** (Reload).
- If the Windows security window appears, click [**Install this driver software anyway**].

## 4 Finish the installation.



When "**Your software is ready to use**" appears, you can use the software. To print a test page, click the "**Print a test page**" checkbox and select the machine.

Click [**Finish**] to exit the wizard.



### NOTE

When you have selected [**Device settings**] in Windows XP, the dialog box for device setting will appear after [**Finish**] is clicked. Configure the settings for options installed on the machine. Device settings can be configured after the installation is completed.

#### ➔ **Printer Driver User Guide**

If a system restart message appears, restart the computer by following the screen prompts. This completes the printer driver installation procedure.


If you are installing the TWAIN driver, continue by configuring the following:

#### ➔ [Setting TWAIN Driver \(page 2-32\)](#)

## Custom Install

The following procedure is an example for installing the software in Windows 7 using [Custom Install].


### 1 Insert the DVD.



#### NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "Welcome to the Found New Hardware Wizard" dialog box displays, select [Cancel].
- If the autorun screen is displayed, click [Run setup.exe].
- If the user account management window appears, click [Yes] ([Allow]).


### 2 Display the screen.



- 1 Click [View License Agreement] and read the License Agreement.
- 2 Click [Accept].

### 3 Install using [Custom Install].

- 1 Select the device to be installed.



The following buttons can be used.



: This changes the display to icon and text display.




: Use this to select multiple items.




: If the desired device does not appear, select this button to directly select the device.


2 Select the driver to be installed.



3 Select the utility to be installed.




4 Click [Install].




 **NOTE**

- To install Status Monitor, it is necessary to install Microsoft .NET Framework 4.0 beforehand.



## 4 Finish the installation.



When "**Your software is ready to use**" appears, you can use the software. To print a test page, click the "**Print a test page**" checkbox and select the machine.

Click [**Finish**] to exit the wizard.



### NOTE

When you have selected [**Device settings**] in Windows XP, the dialog box for device setting will appear after [**Finish**] is clicked. Configure the settings for options installed on the machine. Device settings can be configured after the installation is completed.

#### ➔ **Printer Driver User Guide**

If a system restart message appears, restart the computer by following the screen prompts. This completes the printer driver installation procedure.

If you are installing the TWAIN driver, continue by configuring the following:

#### ➔ [Setting TWAIN Driver \(page 2-32\)](#)



## Uninstalling the Software

Perform the following procedure to delete the Software from your computer.



### NOTE

Uninstallation on Windows must be done by a user logged on with administrator privileges.

### 1 Display the screen.

Click **[Start]** button on the Windows and then select **[All Programs]**, **[Kyocera]**, and **[Uninstall Kyocera Product Library]** to display the Uninstall Wizard.




### NOTE

In Windows 8, click **[Search]** in charms, and enter "Uninstall Kyocera Product Library" in the search box. Select **[Uninstall Kyocera Product Library]** in the search list.

### 2 Uninstall the software.

Place a check in the check box of the software to be deleted.



### 3 Finish uninstalling.

If a system restart message appears, restart the computer by following the screen prompts. This completes the software uninstallation procedure.



### NOTE

- The software can also be uninstalled using the Product Library.
- In the Product Library screen, click **[Uninstall]**, and follow the on-screen instructions to uninstall the software.


# Installing Software in Mac Computer

The machine's printer functionality can be used by a Mac computer.

## NOTE


- Installation on MAC OS must be done by a user logged on with administrator privileges.
  - When printing from a Macintosh computer, set the machine's emulation to **[KPD(L)]** or **[KPD(L)(Auto)]**.
- ➔ [Printer \(page 8-24\)](#)
- If connecting by Bonjour, enable Bonjour in the machine's network settings.
- ➔ [Bonjour \(page 8-26\)](#)
- In the Authenticate screen, enter the name and password used to log in to the operating system.

## 1 Insert the DVD.



Double-click the **[Kyocera]** icon.

## 2 Display the screen.



Double-click **[Kyocera OS X x.x]** depending on your Mac OS version.

## 3 Install the Printer Driver.




Install the printer driver as directed by the instructions in the installation software.

This completes the printer driver installation.


If a USB connection is used, the machine is automatically recognized and connected.  
If an IP connection is used, the settings below are required.

## 4 Configure the printer.

1 Open System Preferences and add the printer.



2 Select [Default] and click the item that appears in "Name".




3 Select the driver in "Use".




### NOTE

When using an IP connection, click the IP icon for an IP connection and then enter the host name or IP address. The number entered in "Address" will automatically appear in "Name". Change if needed.

3 Select the options available for the machine.



4 The selected machine is added.



## Setting TWAIN Driver

Register this machine to the TWAIN Driver. Instructions are based on interface elements as they appear in Windows 7.


### 1 Display the screen.

- 1 Select **[Start]** button on the Windows, **[All Programs]**, **[Kyocera]** and then **[TWAIN Driver Setting]**. TWAIN Driver screen appears.

#### NOTE


In Windows 8, click **[Search]** in charms, and enter "TWAIN Driver Setting" in the search box. Select **[TWAIN Driver Setting]** in the search list.

- 2 Click **[Add]**.




### 2 Configure TWAIN Driver.

(Network)



- 1 Enter the machine name.
- 2 Select this machine from the list.
- 3 Enter the machine's IP address or host name.
- 4 Set units of measurement.
- 5 When using SSL, select the checkbox beside SSL.

(USB)




- 1 Enter the machine name.
- 2 Select this machine from the list.
- 3 Set units of measurement.
- 4 Set the Compression Level.



**NOTE**

When the machine's IP address or host name is unknown, contact Administrator.

**3 Finish registering.**



**NOTE**

Click [**Delete**] to delete the added machine. Click [**Edit**] to change names.

## Setting WIA Driver

Register this machine to the WIA Driver. Instructions are based on interface elements as they appear in Windows 7.


### 1 Display the screen.

- 1 Click **[Start]** button on the Windows and enter **[Scanner]** in **[Program and File Search]**. Click **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

#### NOTE


In Windows 8, click **[Search]** in charms, and enter "View scanners and cameras" in the search box. Select **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

- 2 Select the same name as this machine from WIA Drivers, and click **[Properties]**.




### 2 Configure WIA Driver.

(Network)



- 1 Click the **[Settings]** tab.
- 2 Enter the machine IP addresses or host name.
- 3 When using SSL, select the checkbox beside SSL.
- 4 Set units of measurement.
- 5 Click **[OK]**.

(USB)



- 1 Click the **[Settings]** tab.
- 2 Set the Compression Level.
- 3 Set units of measurement.
- 4 Click **[OK]**.

## Checking the Counter

Check the number of sheets printed and scanned.

**1 Display the screen.**

[System Menu/Counter] key > [▲] [▼] key > [Counter] > [OK] key

**2 Check the counter.**

Select the item you want to check, and select the [OK] key.

# Additional Preparations for the Administrator

In addition to the information provided in this chapter, the administrator of this machine should check the following, and configure the settings as needed.

## Sending Documents to a PC

### To Send to a Shared Folder (Send to Folder (SMB))

To send a document that has been loaded, you need to create a shared folder to receive the document on your computer.

➔ [Preparation for Sending a Document to a Shared Folder in a PC \(page 3-13\)](#)

### To E-mail Scanned Images (Send as E-mail)

You can send a scanned original image as an E-mail attachment.

➔ [E-mail Settings \(page 2-44\)](#)

## Strengthening the Security

This machine is shipped with two default users registered one with Machine Administrator rights, and another with Administrator rights. Logging in as this user will allow you to configure all settings; therefore, please change the login user name and password.

In addition, this machine is equipped with user authentication function, which can be configured to limit the access to this machine to only those who have a registered login name and password.

➔ [User Authentication and Accounting \(User Login, Job Accounting\) \(page 9-1\)](#)

I want to...	Function	Reference page
<b>Restrict the users of the machine.</b>	User Login	<a href="#">page 9-2</a>
	Auto Panel Reset	<a href="#">page 8-18</a>
	ID Card Settings <sup>*1</sup>	<a href="#">page 9-22</a>
<b>Restrict the basic functions that can be used.</b>	Local Authorization	<a href="#">page 9-16</a>
	Group Authorization Set.	<a href="#">page 9-17</a>
<b>Prevent another user from handling the documents stored in the machine.</b>	Custom Box <sup>*2</sup>	<a href="#">page 5-32</a>
<b>Prevent the data stored in the machine from being leaked.</b>	Data Overwrite <sup>*3</sup>	Refer to the <b>Data Security Kit (E) Operation Guide.</b>
	Encryption <sup>*3</sup>	
	PDF Encryption Functions	<a href="#">page 6-30</a>
<b>Completely delete the data on the machine before disposing of the machine.</b>	DataSanitization	<a href="#">page 8-33</a>

\*1 The optional Card Authentication Kit is required.

\*2 The optional SSD is required.

\*3 The optional Data Security Kit is required.



I want to...	Function	Reference page
<b>Protect the transmission from interception and wiretapping.</b>	IPP over SSL	<a href="#">page 8-27</a>
	HTTPS	<a href="#">page 8-27</a>
	LDAP Security	Refer to the <b>Command Center RX User Guide</b> .
	SMTP Security	<a href="#">page 8-29</a>
	POP3 Security	<a href="#">page 8-29</a>
	FTP Encrypted TX	<a href="#">page 6-33</a>
	IPSec	<a href="#">page 8-28</a>
	SNMPv3	<a href="#">page 8-27</a>

# Command Center RX

If the machine is connected to the network, you can configure various settings using Command Center RX.

This section explains how to access Command Center RX, and how to change security settings and the host name.

## ➔ Command Center RX User Guide

### NOTE

To fully access the features of the Command Center RX pages, enter the User Name and Password and click **[Login]**. Entering the predefined administrator password allows the user to access all pages, including Document Box, Address Book, and Settings on the navigation menu. The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

**Login User Name:** Admin

**Login Password:** Admin

Settings that the administrator and general users can configure in Command Center RX are as follows.

Setting	Description	Administ-rator	General User
<b>Device Information</b>	The machine's structure can be checked.	<input type="radio"/>	<input type="radio"/>
<b>Job Status</b>	Displays all device information, including print and scan jobs, storing jobs, scheduled jobs, and job log history.	<input type="radio"/>	<input type="radio"/>
<b>Document Box</b>	Add or delete document boxes, or delete documents within a document box.	<input type="radio"/>	<input type="radio"/> *1
<b>Address Book</b>	Create, edit, or delete addresses and address groups.	<input type="radio"/>	<input type="radio"/> *1
<b>Device Settings</b>	Configure the advanced settings of the machine.	<input type="radio"/>	-
<b>Function Settings</b>	Configure the advanced function settings.	<input type="radio"/>	-
<b>Network Settings</b>	Configure the network advanced settings.	<input type="radio"/>	-
<b>Security Settings</b>	Configure the security advanced settings.	<input type="radio"/>	-
<b>Management Settings</b>	Configure the advanced management settings.	<input type="radio"/>	-

\*1 The logged in user may not be able to configure some settings, depending on the permissions of the user.

### NOTE

- FAX functions are available only on products with the fax function installed.
- Here, information on the FAX settings has been omitted.

## ➔ FAX Operation Guide

## Accessing Command Center RX

### 1 Display the screen.

- 1 Launch your Web browser.
- 2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

Examples: <https://192.168.48.21/> (for IP address)  
<https://MFP001> (if the host name is "MFP001")



The web page displays basic information about the machine and Command Center RX as well as their current status.

#### NOTE

If the screen "There is a problem with this website's security certificate." is displayed, configure the certificate.

#### ➔ **Command Center RX User Guide**

You can also continue the operation without configuring the certificate.

### 2 Configure the function.

Select a category from the navigation bar on the left of the screen.

#### NOTE

To fully access the features of the Command Center RX pages, enter the User Name and Password and click [Login]. Entering the predefined administrator password allows the user to access all pages, including Document Box, Address Book, and Settings on the navigation menu. The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

**Login User Name:** Admin  
**Login Password:** Admin

## Changing Security Settings

This section explains how to change the security settings.


### 1 Display the screen.

- 1 Launch your Web browser.
- 2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

- 3 Log in with administrator privileges.



The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)


Login User Name: Admin

Login Password: Admin

- 4 Click [Security Settings].

## 2 Configure the Security Settings.

From the [Security Settings] menu, select the setting you want to configure.



### NOTE

For details on settings related to certificates, refer to the following:

➔ **Command Center RX User Guide**

## Changing Device Information

Change the device information of the machine.

### 1 Display the screen.

- 1 Launch your Web browser.
- 2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

- 3 Log in with administrator privileges.

The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin

Login Password: Admin

- 4 From the [Device Settings] menu, click [System].

## 2 Specify the host name.

Enter the device information, and then click **[Submit]**.

 **IMPORTANT**

**After changing the setting, restart the network or turn the machine OFF and then ON.**

**To restart the network interface card, click **[Reset]** in the **[Management Settings]** menu, and then click **[Restart Network]** in "Restart".**

## E-mail Settings

By configuring the SMTP settings, it is possible to send the images scanned by the machine as E-mail attachments and to send E-mail notices when jobs have been completed.

To use this function, this machine must be connected to a mail server using the SMTP protocol.

In addition, configure the following.

- SMTP settings  
Item: "SMTP Protocol" and "SMTP Server Name" in "SMTP"
- The sender address when the machine sends E-mails  
Item: "Sender Address" in "E-mail Send Settings"
- The setting to limit the size of E-mails  
Item: "E-mail Size Limit" in "E-mail Send Settings"

The procedure for specifying the SMTP settings is explained below.

### 1 Display the screen.

Display the SMTP Protocol screen.


1 Launch your Web browser.

2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

3 Log in with administrator privileges.




The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin

Login Password: Admin




**4** From the [Network Settings] menu, click [Protocol].



**2** Configure the settings.


Set "SMTP (E-mail TX)" to [On] in the "Send Protocols".



### 3 Display the screen.

Display the E-mail Settings screen.

From the [Function Settings] menu, click [E-mail].



## 4 Configure the settings.

Enter "SMTP" and "E-mail Send Settings" items.

Setting	Description
<b>SMTP</b>	Set to send e-mail from the machine.
<b>SMTP Protocol</b>	Displays the SMTP protocol settings. Check that "SMTP Protocol" is set to <b>[On]</b> . If <b>[Off]</b> is set, click <b>[Protocol]</b> and set the SMTP protocol to <b>[On]</b> .
<b>SMTP Server Name<sup>*1</sup></b>	Enter the host name or IP address of the SMTP server.
<b>SMTP Port Number</b>	Specify the port number to be used for SMTP. Use the SMTP default port 25.
<b>SMTP Server Timeout</b>	Set the amount of time to wait before time-out in seconds.
<b>Authentication Protocol</b>	To use SMTP authentication, enter the user information for authentication.
<b>SMTP Security</b>	Set SMTP security. Turn on "SMTP Security" in "SMTP (E-mail TX)" on the <b>[Protocol Settings]</b> page.
<b>Connection Test</b>	Tests to confirm that the settings are correct.
<b>Domain Restriction</b>	To restrict the domains, click the <b>[Domain List]</b> and enter the domain names of addresses to be allowed or rejected. Restriction can also be specified by e-mail address.
<b>POP3</b>	<p>You don't need to set the following items when you only enable the function of sending e-mail from the machine. Set the following items if you want to enable the function of receiving e-mail on the machine.</p> <p>➔ <b>Command Center RX User Guide</b></p>
<b>POP3 Protocol</b>	
<b>Check Interval</b>	
<b>Run once now</b>	
<b>Domain Restriction</b>	
<b>POP3 User Settings</b>	
<b>E-mail Send Settings</b>	
<b>E-mail Size Limit</b>	Enter the maximum size of E-mail that can be sent in kilobytes. When E-mail size is greater than this value, an error message appears and E-mail sending is cancelled. Use this setting if you have set E-mail Size Limit for SMTP server. If not, enter a value of 0 (zero) to enable E-mail sending regardless of the size limit.
<b>Sender Address<sup>*1</sup></b>	Specify the sender address for when the machine sends E-mails, such as the machine administrator, so that a reply or non-delivery report will go to a person rather than to the machine. The sender address must be entered correctly for SMTP authentication. The maximum length of the sender address is 128 characters.
<b>Signature</b>	Enter the signature. The signature is free form text that will appear at the end of the E-mail body. It is often used for further identification of the machine. The maximum length of the signature is 512 characters.
<b>Function Defaults</b>	Change the function default settings in <b>[Common/Job Default Settings]</b> page.

\*1 Be sure to enter the items.

## 5 Click **[Submit]**.

## Registering Destinations

You can register destinations to the machine's Address Book, from Command Center RX.

### 1 Display the screen.

1 Launch your Web browser.


2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

3 Log in with administrator privileges.


The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)



Login User Name: Admin

Login Password: Admin

4 From the [Address Book] menu, click [Machine Address Book].



5 Click [Add].

### 2 Populate the fields.

1 Enter the destination information.

Enter the information for the destination you want to register. The fields to populate are the same as when registering via operation panel.

➔ [Registering Destinations in the Address Book \(page 3-23\)](#)

2 Click [Submit].

## Creating a New Custom Box

You can register a custom box from Command Center RX.



### NOTE

To use Custom Box, an optional SSD must be installed in the machine.

## 1 Display the screen.

- 1 Launch your Web browser.
- 2 In the address or location bar, enter the machine's IP address or the host name.  
Print the status page to check the machine's IP address and the host name.  
[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]
- 3 From the [Document Box] menu, click [Custom Box].



- 4 Click [Add].

## 2 Configure the Custom Box.

- 1 Enter the box details.  
Enter the information for the custom box you want to register. For details on the fields to populate, refer to the following:  
➔ [Command Center RX User Guide](#)
- 2 Click [Submit].

## Printing a document stored in a Custom Box

A document stored in a Custom Box can be printed from Command Center RX.

### 1 Display the screen.

1 Launch your Web browser.

2 In the address or location bar, enter the machine's IP address or the host name.

Print the status page to check the machine's IP address and the host name.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key > [▲] [▼] key > [Status Page] > [OK] key > [Yes]

3 From the [Document Box] menu, click [Custom Box].



4 Click the number or name of the Custom Box in which the document is stored.

## 2 Print the document.



- 1 Select the document you wish to print.  
Select the checkbox of the document to be printed.
- 2 Click [**Print**].
- 3 Configure settings for printing, click [**Print**].

# Transferring Data from Our Other Products

By using the machine's utility, you can smoothly migrate address books when the machine is to be replaced. This section explains how to transfer data between our products.

## Migrating the Address Book

The Address Book registered on the machine can be backed up or migrated using the KYOCERA Net Viewer on the included DVD.

For details on operating the KYOCERA Net Viewer, refer to the following:


➔ [KYOCERA Net Viewer User Guide](#)

### Backing Up Address Book Data to PC

#### 1 Launch the KYOCERA Net Viewer.


#### 2 Create a backup.

- 1 Right-click on the model name from which you want to back up the Address Book, and select **[Advanced]** - **[Set multiple devices]**.




- 2 Click **[Next]**.

- 3 Select **[Device Address Book]** and click **[Next]**.







- 4 Select **[Create from device]** and remove the checkmark from **[Overwrite settings on target device]**, and then click **[Next]**.



- 5 Select the model you want to back up, and click **[Next]**.




 **NOTE**

If the "Admin Login" screen appears, enter the "Admin Login" and "Login Password", and then click **[OK]**. The default settings are as follows (Upper case and lower case letters are distinguished (case sensitive)).


**Login User Name:** Admin  
**Login Password:** Admin

- 6 Click on **[Save to file]**.



- 7 Specify the location to save the file, enter the file name, and then click **[Save]**.  
For "Save as type", make sure to select "XML File".

- 8 After saving the file, always click [**Cancel**] to close the screen.




Please note that selecting [**Finish**] will write the data to the machine's Address Book.

## Writing Address Book Data to the Machine


- 1 **Launch the KYOCERA Net Viewer.**

- 2 **Load the Address Book data.**


- 1 Right-click on the model name to which you want to transfer the Address Book, and select [**Advanced**] - [**Set multiple devices**].



- 2 Click [**Next**].
- 3 Select [**Device Address Book**] and click [**Next**].




- 4 Select **[Create from file]** and remove the checkmark from **[Overwrite settings on target device]**, and then click **[Next]**.




Selecting the **[Overwrite settings on target device]** checkbox will overwrite the machine's Address Book from entry No.1.

- 5 Click **[Browse]** and select the backup Address Book file, and then click **[Next]**.



- 6 Click **[Finish]**.



The write process of the Address Book data starts.

- 7 Once the write process is complete, click **[Close]**.

# 3 Preparation before Use


This chapter explains the following operations.

Loading Paper .....	3-2
Precaution for Loading Paper .....	3-3
Loading in the Cassettes .....	3-4
Loading Paper in the Multi Purpose Tray .....	3-7
Specifying Paper Size and Media Type .....	3-10
Paper Stopper .....	3-12
Preparation for Sending a Document to a Shared Folder in a PC .....	3-13
Making a note of the computer name and full computer name .....	3-13
Making a note of the user name and domain name .....	3-14
Creating a Shared Folder, Making a Note of a Shared Folder .....	3-15
Configuring Windows Firewall .....	3-19
Registering Destinations in the Address Book .....	3-23
Adding a Destination (Address Book) .....	3-23
Adding a Destination on One Touch Key (One Touch Key) .....	3-29

# Loading Paper

Load paper in the cassettes and multipurpose tray.

For the paper load methods for each cassette, refer to the page below.




No.	Name	Page
1	Cassette 1	<a href="#">page 3-4</a>
2	Cassette 2	<a href="#">page 3-4</a>
3	Cassette 3	<a href="#">page 3-4</a>
4	Cassette 4	<a href="#">page 3-4</a>
5	Multi Purpose Tray	<a href="#">page 3-7</a>

## NOTE

- The number of sheets that can be held varies depending on your environment and paper type.
- You should not use inkjet printer paper or any paper with a special surface coating. (Such paper may cause paper jams or other faults.)
- For higher quality color printing, use special color paper.

## Precaution for Loading Paper

When you open a new package of paper, fan the sheets to separate them slightly prior to loading in the following steps.



Fan the paper, then tap it on a level surface.

In addition, note the following points.

- If the paper is curled or folded, straighten it before loading. Paper that is curled or folded may cause a jam.
- Avoid exposing opened paper to high temperatures and high humidity as dampness can be a cause of problems. Seal any remaining paper after loading in the multi purpose tray or cassettes back in the paper storage bag.
- If the machine will not be used for a prolonged period, protect all paper from humidity by removing it from the cassettes and sealing it in the paper storage bag.

### ✔ IMPORTANT

**If you copy onto used paper (paper already used for printing), do not use paper that is stapled or clipped together. This may damage the machine or cause poor image quality.**

### 💡 NOTE

If you use special paper such as letterhead, paper with holes or paper with pre-prints like logo or company name, refer to the following:

➔ [Paper \(page 11-16\)](#)

## Loading in the Cassettes

The cassettes can hold plain paper, recycled paper or color paper.

The number of sheets that can be loaded in each cassette is shown below.

Cassette	No. Sheets
Cassette 1	250 sheets (Plain paper: 80 g/m <sup>2</sup> )
Cassette 2 to 4	500 sheets (Plain paper: 80 g/m <sup>2</sup> )

For details of the supported paper sizes, refer to the following:

➔ [Choosing the Appropriate Paper \(page 11-17\)](#)

### NOTE

A6 paper cannot be loaded in cassettes 2 to 4.


For the paper type setting, refer to the following:

➔ [Media Type Setting \(page 8-12\)](#)

### IMPORTANT

The cassettes 1 can hold paper with weight between 60 - 163 g/m<sup>2</sup>. The cassettes 2 to 4 can hold paper with weight between 60 - 220 g/m<sup>2</sup>.

## 1 Pull the cassette completely out of the machine.




### NOTE


When pulling the cassette out of the machine, ensure it is supported and does not fall out.

## 2 Adjust the cassette size.


- Adjust the position of the paper width guides located on the left and right sides of the cassette. Press the paper width adjusting tab and slide the guides to the paper size required. Paper sizes are marked on the cassette.



- 2 Adjust the paper length guide to the paper size required. Press the paper length adjusting tab and slide the guides to the paper size required.



- 3 Turn the size dial so that the size of the paper you are going to use appears in the paper size window.




 **NOTE**

When the size dial is set to "Other" the paper size must be set into the machine on the operation panel.

➔ [Paper Size and Media Type for the Cassettes \(page 3-10\)](#)

### 3 Load paper.

- 1 Fan the paper, then tap it on a level surface to avoid paper jams or skewed printing.
- 2 Load the paper in the cassette.






✔ **IMPORTANT**


- Load the paper with the print side facing up.
- After removing new paper from its packaging, fan the paper before loading it in the multi-purpose tray.
- ➔ [Precaution for Loading Paper \(page 3-3\)](#)
- Before loading the paper, be sure that it is not curled or folded. Paper that is curled or folded may cause paper jams.
- Ensure that the loaded paper does not exceed the level indicator (see illustration above).
- If paper is loaded without adjusting the paper length guide and paper width guide, the paper may skew or become jammed.

**4 Gently push the cassette back in.**



**NOTE**

There is a paper gauge on the right side of the front of the cassette to indicate the remaining paper supply.



**5 Specify the type of paper loaded in the cassette using the operation panel.**

- ➔ [Paper Size and Media Type for the Cassettes \(page 3-10\)](#)

## Loading Paper in the Multi Purpose Tray

The multi purpose tray will hold up to 100 sheets of plain paper (80 g/m<sup>2</sup>).

For details of the supported paper sizes, refer to the following:

➔ [Choosing the Appropriate Paper \(page 11-17\)](#)

For the paper type setting, refer to the following:

➔ [Media Type Setting \(page 8-12\)](#)

Be sure to use the multi purpose tray when you print on any special paper.

### ✔ IMPORTANT

- If you are using a paper weight of 106 g/m<sup>2</sup> or more, set the media type to Thick and set the weight of the paper you are using.
- Remove each transparency from the inner tray as it is printed. Leaving transparencies in the inner tray may cause a paper jam.


The capacity of the multi purpose tray is as follows.

- Plain paper (80 g/m<sup>2</sup>), recycled paper or color paper: 100 sheets
- Thick paper (209 g/m<sup>2</sup>): 15 sheets
- Thick paper (157 g/m<sup>2</sup>): 30 sheets
- Thick paper (104.7 g/m<sup>2</sup>): 50 sheets
- Hagaki (Cardstock): 30 sheets
- Envelope DL, Envelope C5, Envelope #10, Envelope #9, Envelope #6 3/4, Envelope Monarch, Youkei 4, Youkei 2: 5 sheets
- OHP film: 1 sheet
- Coated: 30 sheets

### 💡 NOTE


- When you load custom size paper, enter the paper size by referring to the following:  
➔ [Paper Size and Media Type for the Multi Purpose Tray \(MP Tray Setting\) \(page 3-11\)](#)
- When you use special paper such as transparencies or thick paper, select the media type by referring to the following:  
➔ [Paper Size and Media Type for the Multi Purpose Tray \(MP Tray Setting\) \(page 3-11\)](#)

### 1 Open the multi purpose tray.




## 2 Adjust the multi purpose tray size.

Paper sizes are marked on the multi purpose tray.



## 3 Load paper.



Insert the paper along the paper width guides into the tray until it stops.

After removing new paper from its packaging, fan the paper before loading it in the multi purpose tray.

➔ [Precaution for Loading Paper \(page 3-3\)](#)

### ✔ IMPORTANT

- When loading the paper, keep the print side facing up.
- Curled paper must be uncurled before use.
- When loading paper into the multi purpose tray, check that there is no paper left over in the tray from a previous job before loading the paper. If there is just a small amount of paper left over in the multi purpose tray and you want to add more, first remove the left-over paper from the tray and include it with the new paper before loading the paper back into the tray.
- If there is a gap between the paper and the paper width guides, readjust the guides to fit the paper in order to prevent skewed feeding and paper jams.
- Ensure that the loaded paper does not exceed the load limits.

## 4 Specify the type of paper loaded in the multi purpose tray using the operation panel.


➔ [Paper Size and Media Type for the Multi Purpose Tray \(MP Tray Setting\) \(page 3-11\)](#)

## When you load envelopes or cardstock in the multi purpose tray

Load the paper with the print side facing up. For the procedure for printing, refer to the following:

### ▶ Printer Driver User Guide

Example: When printing the address.



### ✔ IMPORTANT

- Use unfolded Oufuku hagaki (Return postcard).
- How to load envelopes (orientation and facing) will differ depending on the type of envelope. Be sure to load it in correctly, otherwise printing may be done in the wrong direction or on the wrong face.

### 💡 NOTE

When you load envelopes in the multi purpose tray, select the envelope type by referring to the following:

- ▶ [Paper Size and Media Type for the Multi Purpose Tray \(MP Tray Setting\) \(page 3-11\)](#)

## Specifying Paper Size and Media Type

The default paper size setting for cassette 1, for the multi purpose tray and for the optional paper feeder (cassettes 2 to 4) is "A4" or "Letter", and the default media type setting is "Plain".

To change the type of paper to be used in cassettes, specify the paper size and media type setting.

### Paper Size and Media Type for the Cassettes

Specify the paper size and media type of paper to be used in cassettes.

Item	Description
<b>Cassette 1 (to 4) Size</b> <sup>*1</sup>	Available options are as follows: <b>Value</b> <b>Cassette 1: A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Custom</b> <b>Cassettes 2 to 4: A4, A5, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Youkei 4, Youkei 2, Custom</b>
<b>Cassette 1 (to 4) Type</b> <sup>*2</sup>	Select the media type. <b>Value</b> <b>Cassette 1: Plain (60 to 105 g/m<sup>2</sup>), Rough, Vellum (60 to 105 g/m<sup>2</sup>), Recycled, Preprinted<sup>*3</sup>, Bond, Color, Prepunched<sup>*3</sup>, Letterhead<sup>*3</sup>, Thick (106 to 163 g/m<sup>2</sup>), High Quality, Custom 1 - 8</b> <b>Cassettes 2 to 4: Plain (60 to 105 g/m<sup>2</sup>), Rough, Vellum (60 to 105 g/m<sup>2</sup>), Labels, Recycled, Preprinted<sup>*3</sup>, Bond, Color, Prepunched<sup>*3</sup>, Letterhead<sup>*3</sup>, Envelope, Thick (106 to 220 g/m<sup>2</sup>), Coated, High Quality, Custom 1 - 8</b>

\*1 Only set this when the size dial on the cassette is set to "Other".

\*2 To change to a media type other than Plain, refer to the following:

➔ [MP Tray Set. \(MP Tray Settings\) \(page 8-11\)](#)

When a paper weight that cannot be loaded in the cassette is set for a media type, that media type does not appear.

\*3 To print on preprinted or prepunched paper or on letterhead, refer to the following:

➔ [SpecialPaper Act. \(page 8-10\)](#)



#### NOTE

- The available media types for printing received faxes are as shown below.  
Plain, Labels, Recycled, Bond, Vellum, Color, Envelope, Coated, Thick, High Quality, Rough and Custom 1 to 8
- Set the paper size of the cassette used for fax reception as follows:  
Inch models: Letter, Legal, Statement  
Metric models: A4, B5, A5, Folio  
If the above setting is changed, it will not be possible to print faxes.

## 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Orig./Paper Set.] > [OK] key > [▲] [▼] key > [Cassette 1 (to 4) Set.] > [OK] key



#### NOTE

[Cassette 2] to [Cassette 4] are shown when the optional paper feeder is installed.

## 2 Specify the paper size.

1 [▲] [▼] key > [Cassette 1 (to 4) Size] > [OK] key

2 Select the paper size, and select the [OK] key.

### 3 Specify the media type.

- 1 [▲] [▼] key > [Cassette 1 (to 4) Type] > [OK] key
- 2 Select the media type, and select the [OK] key.

#### Paper Size and Media Type for the Multi Purpose Tray (MP Tray Setting)

Specify the paper size and media type of paper to be used in the multi purpose tray.

Item	Description
MP Tray Size	Available options are as follows: <b>Value:</b> A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom*1
MP Tray Type*2	Select the media type. <b>Values:</b> Plain (60 to 105 g/m <sup>2</sup> ), Transparency, Rough, Vellum (60 to 105 g/m <sup>2</sup> ), Labels, Recycled, Preprinted*3, Bond, Cardstock, Color, Prepunched*3, Letterhead*3, Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1-8

\*1 For instructions on how to specify the custom paper size, refer to the following:

➔ [Custom PaperSize \(page 8-9\)](#)

\*2 To change to a media type other than "Plain", refer to the following:

➔ [MP Tray Set. \(MP Tray Settings\) \(page 8-11\)](#)

\*3 To print on preprinted or prepunched paper or on letterhead, refer to the following:

➔ [SpecialPaper Act. \(page 8-10\)](#)



#### NOTE

- The available media types for printing received faxes are as shown below.  
Plain, Label, Recycled, Bond, Vellum, Color, Envelope, Cardstock, Coated, Thick, High Quality, Rough and Custom 1 to 8
- Set the paper size of the multi purpose tray used for fax reception as follows:  
Inch models: Letter, Legal, Statement  
Metric models: A4, B5, A5, Folio  
If the above setting is changed, it will not be possible to print faxes.

### 1 Display the screen.

[System Menu/Counter] > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Orig./Paper Set.] > [OK] key > [▲] [▼] key > [MP Tray Set.] > [OK] key

### 2 Specify the paper size.


- 1 [▲] [▼] key > [MP Tray Size] > [OK] key
- 2 Select the paper size, and select the [OK] key.

### 3 Specify the media type.

- 1 [▲] [▼] key > [MP Tray Type] > [OK] key
- 2 Select the media type, and select the [OK] key.

## Paper Stopper

When using paper large than A4/Letter, open the paper stopper shown in the figure.



# Preparation for Sending a Document to a Shared Folder in a PC

Check the information that needs to be set on the machine and create a folder to receive the document on your computer. Screens of Windows 7 are used in the following explanation. The details of the screens will vary in other versions of Windows.



## NOTE

Log on to Windows with administrator privileges.

## Making a note of the computer name and full computer name

Check the name of the computer name and full computer name.

### 1 Display the screen.

From [Start] button on the Windows, select [Computer] and then [System Properties].




## NOTE

In Windows XP, right-click [My Computer] and select [Properties]. The [System Properties] dialog box appears. Click the [Computer Name] tab in the window that appears.

In Windows 8, select the desktop in the Start screen, right-click [Computer] from [Libraries], and then select [Properties].

In Windows 8.1, select the desktop in the Start screen, right-click [PC] from the desktop [Explorer] and select [Properties]. Or, right-click the Window icon and select [System].

### 2 Check the computer name.



Check the computer name and full computer name.

Screen example:

Computer name: PC001


Full computer name: PC001.abcdnet.com

#### Windows XP:

If the full computer name does not have a dot (.), the full computer name and the computer name are the same.

If the full computer name has a dot (.), the text string in front of the dot (.) in the full computer name is the computer name.

Example: PC001.abcdnet.com  
PC001 is the computer name  
PC001.abcdnet.com is the full computer name

After checking the computer name, click the  [Close] button to close the "System Properties" screen.

In Windows XP, after checking the computer name, click the [Cancel] button to close the "System Properties" screen.



## Making a note of the user name and domain name

Check the domain name and user name for logging onto Windows.

### 1 Display the screen.


From [Start] button on the Windows, select [All Programs] (or [Programs]), [Accessories] and then [Command Prompt].

In Windows 8, display [Apps] on [Search] in charms on the Start screen, and select [Command Prompt].

The Command Prompt window appears.

### 2 Check the domain name and user name.

At the Command Prompt, enter "net config workstation" and then press [Enter].



```
Microsoft Windows [Version 6.1.7600]
Copyright (c) 2009 Microsoft Corporation. All rights reserved.

C:\Users\james.smith>net config workstation
Computer name
Full Computer name
User name          james.smith
Workstation active on
NetBI_Tcpip_(<XXXXXXXX-XXXX-XXXX-XXXX-XXXXXXXXXXXX> <XXXXXXXXXXXX>)
Software version   Windows 7 Ultimate
Workstation domain
Logon domain       ABCDNET
COM Open Timeout (sec)      0
COM Send Count (byte)      16
COM Send Timeout (msec)    250
The command completed successfully.

C:\Users\james.smith>
```

Check the user name and domain name.

Screen example:

User Name: james.smith  
Domain Name: ABCDNET


## Creating a Shared Folder, Making a Note of a Shared Folder

Create a shared folder to receive the document in the destination computer.

### NOTE

If there is a workgroup in System Properties, configure the settings below to limit folder access to a specific user or group.


- 1 From [Start] button on the Windows, select [Control Panel], [Appearance and Personalization], and then [Folder Options].



In Windows XP, click [My Computer] and select [Folder Options] in [Tools].

In Windows 8, select [Settings] in charms on Desktop, and select [Control Panel], [Appearance and Personalization], and then [Folder Options].

- 2



Make sure that the [View] tab is selected.


Remove the checkmark from [Use Sharing Wizard (Recommended)] in "Advanced settings".

In Windows XP, click the [View] tab and remove the checkmark from [Use Simple File Sharing (Recommended)] in "Advanced settings".


## 1 Create a folder.

- 1 Create a folder on your computer.

For example, create a folder with the name "scannerdata" on the desktop.



- 2 Right-click the "scannerdata" folder and click [Share] and [Advanced sharing]. Click the [Advanced Sharing] button.




- 1 Make sure that the [Sharing] tab is selected.

In Windows XP, right-click the "scannerdata" folder and select [Sharing and Security] (or [Sharing]).

## 2 Configure permission settings.


- 1 Select the [Share this folder] checkbox and click the [Permissions] button.




- 3 Make a note of the [Share name].

In Windows XP, select [Share this folder] and click the [Permissions] button.

- 2 Click the [Add] button.



**3** Specify the location.



- 1 If the computer name that you made a note of on page [Making a note of the computer name and full computer name on page 3-13](#) is the same as the domain name: If the computer name is not shown in "From this location", click the [**Locations**] button, select the computer name, and click the [**OK**] button.

Example: PC001


If the computer name that you made a note of on page [Making a note of the computer name and full computer name on page 3-13](#) is not the same as the domain name:

If the text after the first dot (.) in the full computer name that you made a note of does not appear in "From this location", click the [**Locations**] button, select the text after the dot (.), and click the [**OK**] button.

Example: abcdnet.com

- 2 Enter the user name that you made a note of on page [Making a note of the user name and domain name on page 3-14](#) in the text box, and click the [**OK**] button. Also the user name can be made by clicking the [**Advanced**] button and selecting a user.

**4** Set the access permission for the user selected.



- 1 Select the user you entered.

Select the [**Allow**] checkbox of the "Change" and "Read" permissions and press [**OK**].


In Windows XP, go to step 6.

**NOTE**

"Everyone" gives sharing permission to everyone on the network. To strengthen security, it is recommended that you select "Everyone" and remove the "Read" [**Allow**] checkmark.

- 5 Click the [**OK**] button in the "Advanced Sharing" screen to close the screen.

6 Check the details set in the [Security] tab.



- 1 Select the [Security] tab.
- 2 Select the user you entered.  
If the user does not appear on "Group or user names", click [Edit] button to add user in a similar way of step 2 ([Configure permission settings.](#)).
- 3 Make sure that checkmarks appear on [Allow] checkbox for the "Modify" and "Read & execute" permissions.
- 4 Click the [Close] button.

In Windows XP, make sure that checkmarks appear on [Allow] checkbox for the "Modify" and "Read & execute" permissions, and click the [OK] button.

# Configuring Windows Firewall


Permit sharing of files and printers and set the port used for SMB transmission.

## NOTE

Log on to Windows with administrator privileges.

## 1 Check file and printer sharing.


- 1 From [Start] button on the Windows, select [Control Panel], [System and Security], and [Allow a program through Windows Firewall].



## NOTE


If the User Account Control dialog box appears, click the [Continue] button.

- 2 Select the [File and Printer Sharing] checkbox.




## 2 Add a port.


- 1 From [Start] button on the Windows, select [Control Panel], [System and Security], and [Check firewall status].




**2** Select [Advanced settings].




**3** Select [Inbound Rules].




**4** Select [New Rules].




**5** Select [Port].




- 6 Select **[TCP]** as the port to apply the rule to. Then select **[Specific local ports]** and enter "445" then click **[Next]**.



- 7 Select **[Allow the connection]** and click the **[Next]** button.




- 8 Make sure all checkboxes are selected and click the **[Next]** button.





- 9 Enter "**Scan to SMB**" in "**Name**" and click [**Finish**].



### In Windows XP or Windows Vista

- 1 In Windows XP, from [**Start**] button on the Windows, select [**Control Panel**], and then [**Windows Firewall**].  
In Windows Vista, from [**Start**] button on the Windows, select [**Control Panel**], [**Security**], and then [**Turn Windows Firewall on or off**].  
If the User Account Control dialog box appears, click the [**Continue**] button.
- 2 Click the [**Exceptions**] tab and then the [**Add port...**] button.
- 3 Specify Add a Port settings.  
Enter any name in "**Name**" (example: Scan to SMB). This will be the name of the new port.  
Enter "445" in "**Port Number**". Select [**TCP**] for "**Protocol**".
- 4 Click [**OK**] button.

### In Windows 8

- 1 In charms on Desktop, click [**Settings**], [**Control Panel**], [**System and Security**], and then [**Windows Firewall**].  
If the User Account Control dialog box appears, click the [**Continue**] button.
- 2 Configure the settings
  - ➔ [Configuring Windows Firewall \(page 3-19\)](#)

# Registering Destinations in the Address Book

Save frequently used destinations to the Address Book or One Touch Keys. The saved destinations can be changed. The destinations are available for Send as E-mail, Send to Folder, and Fax Transmission (Only on products with the fax function installed).



## NOTE

Registering and editing of the Address Book can also be done in Command Center RX.

➔ [Registering Destinations \(page 2-48\)](#)

## Adding a Destination (Address Book)

Add a new destination to the Address Book. There are two registering methods, contacts and groups. When adding a group, enter the group name and select group members from the Address Book.



## NOTE

If user login administration is enabled, you can only edit destinations in the Address Book by logging in with administrator privileges.

### Contact (Up to 200)

Each address can include the information such as destination name, E-mail address, FTP server folder path, computer folder path, and FAX No. (Only on products with the fax function installed).

#### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [Address Book] > [OK] key > [Menu] > [▲] [▼] key > [Add Address] > [OK] key > [▲] [▼] key > [Contact] > [OK] key

#### 2 Add the name.

1 [◀] [▶] key > [Contact Name] > [Edit]

2 Enter the destination name displayed on the Address Book and select the [OK] key.



## NOTE

Up to 32 characters can be entered.  
Refer to the following for details on entering characters.

➔ [Character Entry Method \(page 11-11\)](#)

#### 3 Add the address.

##### E-mail Address

1 [◀] [▶] key > [E-mailAddress] > [Edit]

2 Enter the E-mail address > [OK] key



## NOTE

Up to 128 characters can be entered.  
Refer to the following for details on entering characters.

➔ [Character Entry Method \(page 11-11\)](#)

**The Folder (SMB) Address**

- 1 [◀] [▶] key > **[Folder (SMB)]** > **[Edit]**
- 2 Enter the information for "Host Name (SMB)", "Path", "Login User Name" and "Login Password" > **[OK]** key

 **NOTE**


For the computer name, share name, domain name, and user name, enter the information that you noted when you created the shared folder. For details on creating shared folders, refer to the following:

➔ [Preparation for Sending a Document to a Shared Folder in a PC \(page 3-13\)](#)

The table below explains the items to be entered.

Item	Description	Max. No. of Characters
<b>Host Name (SMB)*1</b>	Computer name	Up to 64 characters
<b>Path</b>	Share name For example: scannerdata If saving in a folder in the shared folder: share name\folder name in shared folder	Up to 128 characters
<b>Login User Name</b>	If the computer name and domain name are the same: User Name For example: james.smith If the computer name and domain name are different: Domain name\User name For example: abcdnet\james.smith	Up to 64 characters
<b>Login Password</b>	Windows logon password (Case sensitive.)	Up to 64 characters

\*1 To specify a port number different from the default (445), enter using the format "Host name: port number" (Example: SMBhostname:140).  
To enter the IPv6 address, enclose the address in brackets [ ].  
(Example: [3ae3:9a0:cd05:b1d2:28a:1fc0:a1:10ae]:140)

 **NOTE**

Refer to the following for details on entering characters.

➔ [Character Entry Method \(page 11-11\)](#)

- 3 The connection confirmation screen appears. Select **[Yes]** to check the connection and **[No]** to not check it.

"Connected." appears when connection to the destination is correctly established. If "Cannot connect." appears, review the entry.

**The Folder (FTP) Address**

- 1 [◀] [▶] key > **[Folder (FTP)]** > **[Edit]**
- 2 Enter the information for "Host Name (FTP)", "Path", "Login User Name" and "Login Password" > **[OK]** key

The table below explains the items to be entered.

Item	Descriptions	Max. No. of Characters
<b>Host Name (FTP)*1</b>	Host name or IP address of FTP server	Up to 64 characters
<b>Path*2</b>	Path for the file to be stored For example: User\ScanData If no path is entered, the file is stored in the home directory.	Up to 128 characters
<b>Login User Name</b>	FTP server login user name	Up to 64 characters
<b>Login Password</b>	FTP server login password	Up to 64 characters

\*1 If you specify a port number other than the default (21), use the "Host name: port number" (Example: FTPhostname:140).

To enter the IPv6 address, enclose the address in brackets [ ].  
(Example: [3ae3:9a0:cd05:b1d2:28a:1fc0:a1:10ae]:140)

\*2 When the FTP server is based on Linux/UNIX, the path including the sub-folder is combined by the slash "/" not using the back-slash.

**NOTE**

Refer to the following for details on entering characters.

➔ [Character Entry Method \(page 11-11\)](#)

- 3 The connection confirmation screen appears. Select **[Yes]** to check the connection and **[No]** to not check it.

"Connected." appears when connection to the destination is correctly established. If "Cannot connect." appears, review the entry.

**4 Specify the address number.**

- 1 [◀] [▶] key > **[Address Number]** > **[Edit]**
- 2 Enter an address number.

**NOTE**

You can set any value between 1 and 250.

Use the numeric keys or select the [▲] or [▼] key to enter a number.

Address Number is an ID for a destination. You can select any available number.

If you specify an address number that is already in use, an error message appears when you select the **[OK]** key and the number cannot be registered.

- 3 Select the **[OK]** key.

**5 Check if the destination entry is correct and select the [OK] key.**

The destination is added to the Address Book.

## Group (Up to 50)

Compile two or more contacts into a group. Designations in the group can be added at the same time.

### NOTE

To add a group, you need individually added destinations. Register one or more individual destinations as needed before proceeding. Up to 100 individually registered destinations and a combined total of up to 5 SMB and FTP destination folders can be registered in a single group.

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [Address Book] > [OK] key > [Menu] > [▲] [▼] key > [Add Address] > [OK] key > [▲] [▼] key > [Group] > [OK] key

### 2 Add the name.

1 [◀] [▶] key > [Group Name] > [Edit]

2 Enter the group name displayed on the Address Book and select the [OK] key.

### NOTE

Up to 32 characters can be entered.  
Refer to the following for details on entering characters.

➔ [Character Entry Method \(page 11-11\)](#)

### 3 Select the members (destinations).

1 [◀] [▶] key > [Group Member] > [Edit] > [Menu] > [▲] [▼] key > [Add Member] > [OK] key

2 Select the member you want to add, and select the [OK] key.

### NOTE

Select [Menu] and select [Search(Name)] to search using a name.

3 Select the destination to be registered in the group from the destinations registered in the contact addresses and select the [OK] key.

The selected member is added to group member.

Members can be added by repeating steps 3-1 to 3-3.

4 Select the [Back] key.

## 4 Specify the address number.

- 1 [◀] [▶] key > [Address Number] > [Edit]
- 2 Enter an address number.



### NOTE

- You can set any value between 1 and 250.
- Use the numeric keys or select the [▲] or [▼] key to enter a number.
- Address Number is an ID for a destination. A free number can be selected.
- If you specify an address number that is already in use, an error message appears when you select the [OK] key and the number cannot be registered.

- 3 Select the [OK] key.

## 5 Select the [OK] key.

The group is added to the Address Book.

## Editing and Deleting Address Book Entries

Edit and delete the destinations (contacts) you added to the Address Book.

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [Address Book] > [OK] key

### 2 Edit or delete the destination.

#### Editing a Contact

- 1 Select the destination (contacts) to edit, and select the [OK] key.



#### NOTE

Select [Menu] and select [Search(Name)] to search using a name.

- 2 Change "Contact Name", destination type and address, and "Address Number".

➔ [Contact \(Up to 200\) \(page 3-23\)](#)

- 3 After you have completed the changes, [OK] key > [Yes]

Register the changed destination.

#### Editing a Group

- 1 Select the group to edit, and select the [OK] key.

- 2 Change "Group Name" and "Address Number".

➔ [Group \(Up to 50\) \(page 3-26\)](#)

- 3 [◀] [▶] key > [Group Member] > [Edit]

- 4 To delete the destination from the group, select the destination > [Menu] > [▲] [▼] key > [Delete] > [OK] key



#### NOTE

Select the destination and select the [OK] key to show the detailed information of the destination.

To add the destination, select [Add Member].

➔ [Group \(Up to 50\) \(page 3-26\)](#)

- 5 Select [Yes].

- 6 After you have completed the changes, [OK] key > [Yes]

Register the changed group.

#### Deleting a Contact or Group

Select the destination (contacts) or group to delete, [Menu] > [▲] [▼] key > [Delete] > [OK] key > [Yes]

## Adding a Destination on One Touch Key (One Touch Key)


Assign a new destination (contact or group) to an one touch key. A maximum of 22 destinations can be registered.

### NOTE

- Numbers 1 to 11 are the One Touch Key numbers while the **[Shift Lock]** indicator is switched off. Numbers 12 to 22 are the One Touch Key numbers while the **[Shift Lock]** indicator is switched on by selecting the **[Shift Lock]** key.
- Refer to the following for use of One Touch Key.
  - ➔ [Specifying Destination \(page 5-15\)](#)
  - You can add One Touch keys and change their settings on Command Center RX.
  - ➔ [Registering Destinations \(page 2-48\)](#)

## 1 Select the One Touch Key to be registered.

- 1 In the Send or FAX screen, press the One Touch Key that you want to register and hold it (2 seconds or more).



- 2 **[▲]** **[▼]** key > key number > **[OK]** key  
Select a One Touch Key number with no registered destination.

## 2 Select the destinations.

- 1 Select the destination (contact or group) you want to register to the One touch key from the Address Book.

### NOTE

Select **[Menu]** and select **[Search(Name)]** to search using a name.

- 2 Select the destination to be registered to the One touch key from the destinations registered in the addresses and select the **[OK]** key.  
The destination will be added to the One Touch Key.




## Editing and Deleting One Touch Key

Edit and delete the destinations you added to One Touch Key.

### 1 Select the One Touch Key to edit or delete.

- 1 Press the One Touch Key to edit or delete and hold it (2 seconds or more).



- 2 [▲] [▼] key > key number > [OK] key

When an unregistered One Touch Key number is selected, the Address Book appears. The One Touch Key can be registered by selecting the destination from the Address Book.

### 2 Edit or delete the destination.

#### Changing the Registered Information

- 1 [▲] [▼] key > [Edit] > [OK] key



#### NOTE

Select [Detail] and select the [OK] key to show the detailed information of the destination.

- 2 Select the new destination, and select the [OK] key > [Yes]

Register the changed destination.

#### Deleting the Registered Information

- [▲] [▼] key > [Delete] > [OK] key > [Yes]

Deletion of the data registered in the One Touch Key.

# 4 Printing from PC

This chapter explains the following topics:

Printing from PC .....	4-2
Printing on Non-standard Sized Paper .....	4-4
Printer Driver Print Settings Screen .....	4-5
Printer Driver Help .....	4-6
Changing the Default Printer Driver Settings (Windows 7) .....	4-6
Canceling Printing from a Computer .....	4-6
Printing by AirPrint .....	4-7
Printing by Google Cloud Print .....	4-8
Printing Data Saved on the Printer .....	4-9
Specifying the Job Box from a Computer and Storing the Job .....	4-9
Printing Documents from Private Print Box .....	4-10
Printing Document from Stored Job Box .....	4-12
Printing Document from Quick Copy Box .....	4-14
Printing Document from Proof and Hold Box .....	4-16
Status Monitor .....	4-18
Accessing the Status Monitor .....	4-18
Exiting the Status Monitor .....	4-18
Status Monitor Display .....	4-18


# Printing from PC

Follow the steps below to print documents from applications.

This section provides the printing method using the KX DRIVER.

## NOTE

- To print the document from applications, install the printer driver on your computer from the supplied DVD (Product Library).
- In some environments, the current settings are displayed at the bottom of the printer driver.



- When printing the cardstock or envelopes, load the cardstock or envelopes in the multi purpose tray before performing the following procedure.


➔ [When you load envelopes or cardstock in the multi purpose tray \(page 3-9\)](#)

## 1 Display the screen.

Click [File] and select [Print] in the application.

## 2 Configure the settings.

- 1 Select the machine from the "Name" menu and click the [Properties] button.




2 Select the **[Basic]** tab.

3 Click "Print size" menu and select the paper size to use for printing.

To load the paper of size that is not included in print sizes of the machine such as cardstock or envelopes, the paper size needs to be registered.

➔ [Printing on Non-standard Sized Paper \(page 4-4\)](#)

To print on the special paper such as thick paper or transparency, click "Media type" menu and select the media type.



4 Click **[OK]** button to return to the Print dialog box.

### 3 Start printing.

Click the **[OK]** button.

## Printing on Non-standard Sized Paper

If you loaded a paper size that is not included in the print sizes of the machine, register the paper size in the **[Basic]** tab of the print settings screen of the printer driver.

The registered size can be selected from the "Print size" menu.


### NOTE

To execute printing at the machine, set the paper size and type in the following:

➔ [Paper Size and Media Type for the Multi Purpose Tray \(MP Tray Setting\) \(page 3-11\)](#)

**1 Display the print settings screen.**

**2 Register the paper size.**



1 Click the **[Basic]** tab.

2 Click the **[Page Size...]** button.

3 Click the **[New]** button.

4 Enter the paper size.

5 Enter the name of the paper.


6 Click the **[Save]** button.

7 Click the **[OK]** button.

8 In the "Print size" menu, select the paper size (name) that you registered in steps 4 to 7.

9 Select the type of paper in the "Media type" menu.

10 Click **[MP tray]** in the "Source" menu.




### NOTE


If you loaded a postcard or envelope, select **[Cardstock]** or **[Envelope]** in the "Media type" menu.

# Printer Driver Print Settings Screen

The printer driver print settings screen allows you to configure a variety of print-related settings.


➔ **Printer Driver User Guide**



No.	Description
1	<p><b>[Quick Print] tab</b> Provides icons that can be used to easily configure frequently used functions. Each time you click an icon, it changes to an image resembling the print results and applies the settings.</p>  <p><b>[Basic] tab</b> This tab groups basic functions that are frequently used. You can use it to configure the paper size, destination, and duplex printing.</p> <p><b>[Layout] tab</b> This tab lets you configure settings for printing various layouts, including booklet printing, combine mode, poster printing, and scaling.</p> <p><b>[Imaging] tab</b> This tab lets you configure settings related to the quality of the print results.</p> <p><b>[Publishing] tab</b> This tab lets you create covers and inserts for print jobs and put inserts between sheets of OHP film.</p> <p><b>[Job] tab</b> This tab lets you configure settings for saving print data from the computer to the machine. Regularly used documents and other data can be saved to the machine for easy printing later. Since saved documents can be printed directly from the machine, this function is also convenient when you wish to print a document that you don't want others to see.</p> <p><b>[Advanced] tab</b> This tab lets you configure settings for adding text pages or watermarks to print data.</p>
2	<p><b>[Profiles]</b> Printer driver settings can be saved as a profile. Saved profiles can be recalled at any time, so it's a convenient practice to save frequently used settings.</p>
3	<p><b>[Reset]</b> Click to revert settings to their initial values.</p>

## Printer Driver Help

The printer driver includes Help. To learn about print settings, open the printer driver print settings screen and display Help as explained below.



- 1 Click the [?] button in the upper right corner of the screen and then click the item you want to know about.
- 2 Click the item you want to know about and press the [F1] key on your keyboard.

## Changing the Default Printer Driver Settings (Windows 7)

The default printer driver settings can be changed. By selecting frequently used settings, you can omit steps when printing. For the settings, refer to the following:

### ➔ Printer Driver User Guide

- 1 Click [Start] button on the Windows, and then click [Devices and Printers].
- 2 Right-click the printer driver icon of the machine, and click the [Printer properties] menu of the printer driver.
- 3 Click the [Basic] button on the [General] tab.
- 4 Select the default settings and click the [OK] button.

## Canceling Printing from a Computer


To cancel a print job executed using the printer driver before the printer begins printing, do the following:



### NOTE

When canceling printing from this machine, refer to the following:

➔ [Canceling Jobs \(page 5-12\)](#)

- 1 Double-click the printer icon (  ) displayed on the taskbar at the bottom right of the Windows desktop to display a dialog box for the printer.
- 2 Click the file for which you wish to cancel printing and select [Cancel] from the "Document" menu.

## Printing by AirPrint

AirPrint is a printing function that is included standard in iOS 4.2 and later products, and Mac OS X 10.7 and later products.

This function enables you to connect and print to any AirPrint compatible device without installing a printer driver.

To allow the machine to be found when printing by AirPrint, you can set machine location information in Command Center RX.

➔ **Command Center RX User Guide**





# Printing by Google Cloud Print

Google Cloud Print is a printing service provided by Google and does not require a printer driver. This service enables a user with a Google account to print from a machine connected to the Internet.

The machine can be configured in the Command Center RX.

➔ **Command Center RX User Guide**



## **NOTE**

A Google account is necessary to use Google Cloud Print. Obtain a Google account if you do not have one.

It is also necessary to register the machine with the Google Cloud Print service in advance. The machine can be registered from a PC connected to the same network.

# Printing Data Saved on the Printer

If you configure settings in the **[Job]** tab of the printer driver and then print, the print job will be saved in the Job Box (memory) and printing can be executed at the machine.

Follow the work flow below when using Job Box.

Specifying the Job Box from a computer and sending the print job. ([page 4-9](#))



Using the operation panel to specify a file within a Box and printing it.

You can print the documents from the following boxes.

- ➔ [Printing Documents from Private Print Box \(page 4-10\)](#)
- ➔ [Printing Document from Stored Job Box \(page 4-12\)](#)
- ➔ [Printing Document from Quick Copy Box \(page 4-14\)](#)
- ➔ [Printing Document from Proof and Hold Box \(page 4-16\)](#)

## Specifying the Job Box from a Computer and Storing the Job

Use the procedure below to store data in a Job Box.

- 1** Click **[File]** and select **[Print]** in the application. The Print dialog box displays.
- 2** Select the machine from the "Name" menu.
- 3** Click the **[Properties]** button. The Properties dialog box displays.
- 4** Click the **[Job]** tab and select the **[Job storage (e-MPS)]** check box to set the function.



### NOTE

- To use Stored Job Box and Quick Copy Box, an optional SSD must be installed in the machine.
- For information on how to use the printer driver software, refer to the following:

➔ **Printer Driver User Guide**

## Printing Documents from Private Print Box

In Private Printing, you can specify that a job is not to be printed until you operate the machine. When sending the job from the application software, specify a 4-digit access code in the printer driver. The job is released for printing by entering the access code on the operation panel, ensuring confidentiality of the print job. The data will be deleted upon completion of the print job or after the power switch is turned off.

The following operations are possible:

- ➔ [Printing the Documents \(page 4-10\)](#)
- ➔ [Deleting the Documents \(page 4-11\)](#)

### Printing the Documents

Print the documents stored in a Private Print box. The procedure is as follows.

#### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Private] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

#### 2 Print the document.

- 1 Select the document to print, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Print] > [OK] key

- 3 Specify the number of copies to print as desired, and the [OK] key > [Yes].

Printing starts.

Upon completion of printing, the Private Print job is automatically deleted.



#### NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

## Deleting the Documents

Delete the documents stored in a Private Print box. The procedure is as follows.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Private] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

### 2 Delete the document.

- 1 Select the document to delete, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

The document is deleted.



#### NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

## Printing Document from Stored Job Box

In Stored Job, the print data sent from the application is saved to the machine. You can set up an access code as necessary. If you set up an access code, enter the access code when printing. Print data will be stored in the Stored Job Box after printing. This will allow printing of the same print data repeatedly.

The following operations are possible:

- ➔ [Printing the Documents \(page 4-12\)](#)
- ➔ [Deleting the Documents \(page 4-13\)](#)

### Printing the Documents

Print the documents stored in a Stored Job box. The procedure is as follows.

#### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Private] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

#### 2 Print the document.

- 1 Select the document to print, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.

##### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Print] > [OK] key
- 3 Specify the number of copies to print as desired, and the [OK] key > [Yes].  
Printing starts.

##### NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

## Deleting the Documents

Delete the documents stored in a Stored Job box. The procedure is as follows.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Private] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

### 2 Print and delete the document.

- 1 Select the document to delete, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

The document is deleted.



#### NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

## Printing Document from Quick Copy Box

Quick Copy feature facilitates additional prints of a document already printed. Activating Quick Copy and printing a document using the printer driver allow the print data to be stored in the Quick Copy Job Box. When additional copies are required, you can reprint the required number of copies from the operation panel. By default, up to 32 documents can be stored. When power is turned off, all stored jobs will be deleted.

### NOTE

- When the number of jobs reaches the limit, the oldest job will be overwritten by the new one.
- To maintain free space on the box, you can set the maximum number of stored jobs.

➔ [Quick Copy Jobs \(page 8-22\)](#)

The following operations are possible:

➔ [Printing the Documents \(page 4-14\)](#)

➔ [Deleting the Documents \(page 4-15\)](#)

### Printing the Documents

You can print the documents stored in the Quick Copy box. The procedure is as follows.

#### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Quick Copy] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

#### 2 Print the document.

- 1 Select the document to print, and [Select] > [OK] key.  
The file is selected. A checkmark will be placed on the right of the selected file.  
Select the checkmarked file and select [Select] again to cancel the selection.
- 2 [▲] [▼] key > [Print] > [OK] key

### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 3 Specify the number of copies to print as desired, and the [OK] key > [Yes].  
Printing starts.

## Deleting the Documents

You can delete the documents stored in the Quick Copy box. The procedure is as follows.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Quick Copy] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

### 2 Delete the document.

- 1 Select the document to delete, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

The document is deleted.



## Printing Document from Proof and Hold Box

The Proof and Hold feature produces only a single proof print of multiple-print job and holds printing of the remaining copies. Printing a multiple-print job in Proof and Hold using the printer driver allows only a single copy to be printed while maintaining the document data in the Job Box. To continue to print the remaining copies, use the operation panel. You can change the number of copies to print.

The following operations are possible:

- ➔ [Printing the Documents \(page 4-16\)](#)
- ➔ [Deleting the Documents \(page 4-17\)](#)

### Printing the Documents

You can print the documents stored in the Proof and Hold box. The procedure is as follows.

#### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Quick Copy] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

#### 2 Print the document.

- 1 Select the document to print, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Print] > [OK] key
- 3 Specify the number of copies to print as desired, and the [OK] key > [Yes].  
Printing starts.

## Deleting the Documents

You can delete the documents stored in the Proof and Hold box. The procedure is as follows.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Job Box] > [OK] key > [▲] [▼] key > [Quick Copy] > [OK] key
- 2 Select the creator of the document, and select the [OK] key.

### 2 Delete the document.

- 1 Select the document to delete, and [Select] > [OK] key.

The file is selected. A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Detail]: Display the details for the selected document.

- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

The document is deleted.

# Status Monitor

The Status Monitor monitors the printer status and provides an ongoing reporting function.

## NOTE

When you activate Status Monitor, check the status below.

- KX DRIVER is installed.

## Accessing the Status Monitor

The Status Monitor also starts up when printing is started.

## Exiting the Status Monitor

Use either of the methods listed below to exit the Status Monitor.


- Exit manually:  
Click the settings icon and select Exit in the menu to exit the Status Monitor.
- Exit automatically:  
The Status Monitor automatically shuts down after 7 minutes if it is not being used.

## Status Monitor Display

The display of the Status Monitor is as follows.

### Quick View State


The status of the printer is displayed using icons. Detailed information is displayed when the Expand button is clicked.



Detailed information is displayed by clicking on each icon tab.

## Printing Progress Tab


The status of the print jobs is displayed.



Select a job on the job list and it can be canceled using the menu displayed with a right-click.


## Paper Tray Status Tab

Information is displayed about the paper in the printer and about the amount of paper remaining.




## Toner Status Tab

The amount of toner remaining is displayed.




## Alert Tab

If an error occurs, a notice is displayed using a 3D image and a message.



## Status Monitor Context Menu


The following menu is displayed when the settings icon is clicked.



- **Command Center RX**  
If the printer is connected to a TCP/IP network and has its own IP address, use a web browser to access the Command Center RX to modify or confirm the network settings. This menu is not displayed when using USB connection.  
➔ **Command Center RX User Guide**
- **Notification...**  
This sets the display of the Status Monitor.  
➔ [Status Monitor Notification Settings \(page 4-21\)](#)
- **www.kyoceradocumentsolutions.com**  
Open our website.
- **Exit**  
Exits the Status Monitor.

## Status Monitor Notification Settings

The Status Monitor settings and event list details are displayed.



Select whether notification is performed when an error in the event list occurs.


### 1 Select Enable event notification.

If this setting is set to Off, then the Status Monitor will not start up even when printing is executed.

### 2 Select an event to use with the text to speech function in Available events.

### 3 Click Sound file / Text to Speech column.

Click the browse (...) button to notify the event by sound file.



#### NOTE

The available file format is WAV.

When customizing the message texts to read on the screen aloud, enter the texts in the text box.

# 5 Operation on the Machine


This chapter explains the following topics:

Loading Originals .....	5-2
Placing Originals on the Platen .....	5-2
Loading Originals in the Document Processor .....	5-3
Checking the Equipment's Serial Number .....	5-5
Program .....	5-6
Registering Programs .....	5-6
Confirming the Registered Program .....	5-7
Recalling Program .....	5-7
Overwriting Program .....	5-8
Deleting Program .....	5-8
Select Key Settings .....	5-9
Copying .....	5-10
Basic Operation .....	5-10
Canceling Jobs .....	5-12
Sending .....	5-13
Basic Operation .....	5-14
Specifying Destination .....	5-15
Checking and Editing Destinations .....	5-21
Confirmation Screen of Destinations .....	5-22
Recall .....	5-23
Send to Me (E-mail) .....	5-23
Sending to Different Types of Destinations (Multi Sending) .....	5-24
Canceling Sending Jobs .....	5-25
WSD Scan .....	5-26
Scanning using TWAIN or WIA .....	5-28
How to use the FAX Function .....	5-29
What is Document Box? .....	5-30
Using a Custom Box .....	5-32
Creating a New Custom Box .....	5-32
Editing and Deleting Custom Box .....	5-34
Storing Documents .....	5-34
Printing Documents .....	5-35
Editing Documents .....	5-36
Deleting Documents .....	5-37
Printing Documents Stored in Removable USB Memory .....	5-38
Saving Documents to USB Memory (Scan to USB) .....	5-40
Check the USB Memory Information .....	5-41
Removing USB Memory .....	5-42
Using the Manual Stapler .....	5-43

# Loading Originals

## Placing Originals on the Platen

You may place books or magazines on the platen in addition to ordinary sheet originals.




- 1 Put the scanning side facedown.
- 2 Align it flush against the original size indicator plates with the back left corner as the reference point.

### NOTE

For details on Original Orientation, refer to the following:

➔ [Orig. Orientation \(Original Orientation\) \(page 6-11\)](#)

### When you place envelopes or cardstock on the platen



- 1 Put the scanning side facedown.
- 2 Align it flush against the original size indicator plates with the back left corner as the reference point.

### NOTE

For the procedure for feeding envelopes or cardstock, refer to the following:

➔ [When you load envelopes or cardstock in the multi purpose tray \(page 3-9\)](#)

### CAUTION

Do not leave the document processor open as there is a danger of personal injury.

### IMPORTANT

- Do not push the document processor forcefully when you close it. Excessive pressure may crack the platen glass.
- When placing books or magazines on the machine, do so with the document processor in the open position.



## Loading Originals in the Document Processor

The document processor automatically scans each sheet of multiple originals. Both sides of two-sided originals are scanned.

### Originals Supported by the Document Processor

The document processor supports the following types of originals.

<b>Weight</b>	50 to 120 g/m <sup>2</sup> (duplex: 50 to 120 g/m <sup>2</sup> )
<b>Sizes</b>	Maximum Folio (Legal) to Minimum A6-R (Statement-R)
<b>No. of sheets</b>	75 sheets or less (50 to 80 g/m <sup>2</sup> )

### Originals Not Supported by the Document Processor

Do not use the document processor for the following types of originals. Otherwise, the originals may be jammed or the document processor may become dirty.


- Originals bound with clips or staples (Remove the clips or staples and straighten curls, wrinkles or creases before loading. Failure to do so may cause the originals to jam.)
- Originals with adhesive tape or glue
- Originals with cut-out sections
- Curled original
- Originals with folds (Straighten the folds before loading. Failure to do so may cause the originals to jam.)
- Carbon paper
- Crumpled paper

### How to Load Originals

#### ✔ IMPORTANT


- Before loading originals, be sure that there are no originals left on the original eject table. Originals left on the original eject table may cause the new originals to jam.
- Do not make an impact on the document processor top cover, such as aligning the originals on the top cover. It may cause an error in the document processor.

#### 1 Adjust the original width guides.



## 2 Place the originals.

- 1 Put the side to be scanned (or the first side of two-sided originals) face-up. Slide the leading edge into the document processor as far as it will go.




### NOTE

For details on Original Orientation, refer to the following:

➔ [Orig. Orientation \(Original Orientation\) \(page 6-11\)](#)

### IMPORTANT

Confirm that the original width guides exactly fit the originals. If there is a gap, readjust the original width guides. The gap may cause the originals to jam.





Ensure that loaded originals do not exceed the level indicator. Exceeding the maximum level may cause the originals to jam.

Originals with punched holes or perforated lines should be placed in such a way that the holes or perforations will be scanned last (not first).

- 2 Open the original stopper to fit the size of the original set.


A4, Letter, Legal

B5 or less



## Checking the Equipment's Serial Number

The equipment's serial number is printed in the location shown in the figure.



### NOTE

You'll need the equipment's serial number when contacting your Service Representative. Please check the number before contacting your Service Representative.

# Program

By registering sets of frequently used functions as a single program, you can simply select one of the [Program I] to [Program IV] keys as needed to recall those functions.

The following functions are already registered in [Program I] key. This function allows you to copy the front and back sides of ID card or other document that is smaller than Statement or A5 size onto a single page. Although the functions are deleted by overwriting [Program I] key, you can register the same settings using the [Function Menu] key.

- Paper Selection: Cassette 1
- Zoom: Auto
- Combine: 2 in 1
- Color Selection: Black & White
- Original Size: Statement (Inch models)/A5 (Metric models)
- Continuous Scan: On



- NOTE**
- It is possible to register the copy function, sending function and fax function in a program. (The fax function can be registered or recalled only on products with the fax function installed).
  - If user login administration is enabled, you can only register functions by logging in with administrator privileges.

## Registering Programs

Use the procedure below to register a program.

### 1 Configure the settings of the functions.

Configure the settings of the functions you want to register in a program.


For the settings of functions, refer to the following:

- ➔ [Using Various Functions \(page 6-1\)](#)

- NOTE**
- In the case of the sending function and fax function, a destination is also registered in the program.

## 2 Register the program.

Press the one of the [Program I] to [Program IV] keys where you want to register the settings and hold it (2 seconds or more).



The current settings are registered to the selected program key.

## Confirming the Registered Program

The settings of the registered program can be confirmed by recalling the program.

➔ [Recalling Program \(page 5-7\)](#)

## Recalling Program

Select the one of the [Program I] to [Program IV] keys where the settings you want to recall are registered. The current settings of various functions are replaced with the registered settings.

Place the originals and press the [Start] key.

## Overwriting Program

You can change program. Use the procedure below to edit the program.

### 1 Configure the settings of the functions.

Set the function to change.

For the settings of functions, refer to the following:

➔ [Using Various Functions \(page 6-1\)](#)




#### NOTE

In the case of the sending function and fax function, a destination is also registered in the program.

### 2 Overwrite the program.

- 1 Press the one of the [Program I] to [Program IV] keys to change and hold it (2 seconds or more).



- 2 [▲] [▼] key > [Overwrite] > [OK] key > [Yes]

Register the changed program.

## Deleting Program

You can delete program.

### 1 Display the screen.

Press the one of the [Program I] to [Program IV] keys to delete and hold it (2 seconds or more).

### 2 Delete the program.

[▲] [▼] key > [Delete] > [OK] key > [Yes]

## Select Key Settings

Commonly used functions can be registered to the Select key. Functions can be easily configured by selecting the Select key.

Functions can be registered in Select keys from the system menu.

- ➔ [Copy \(page 8-20\)](#)
- [Send \(page 8-21\)](#)
- [Document Box \(page 8-22\)](#)

# Copying


## Basic Operation

Follow the steps as below for basic copying.


**1 Select the [Copy] key.**

**2 Place the originals.**

Place the originals.



➔ [Loading Originals \(page 5-2\)](#)



- 1 Original size
- 2 Paper size

Check the original size and the paper size.



### NOTE

For selecting the original size, refer to the following:

➔ [Original Size \(page 6-9\)](#)

For selecting the paper source, refer to the following:

➔ [Paper Selection \(page 6-10\)](#)



### 3 Select the color mode.

Auto Color



Full Color



Black&White



<b>Auto Color</b>	Automatically recognizes whether a document is color or black & white and then scans the document.
<b>Full Color</b>	Scans all documents in full color.
<b>Black &amp; White</b>	Scans all documents in black & white.

To make more detailed settings, refer to the following:

➔ [Color Selection \(page 6-14\)](#)

### 4 Select the functions.

Select the [Function Menu] key to select the copier functions to use.

➔ [Copy \(page 6-3\)](#)

### 5 Use the numeric keys to enter the copy quantity.

Specify the desired number up to 999.

### 6 Press the [Start] key.


Copying begins.



#### NOTE

This function allows you to reserve the next job during printing. Using this function, the original will be scanned while the machine is printing. When the current print job ends, the reserved copy job is printed. If "Reserve Priority" is set to [Off], [NextCopy] will appear. Select [NextCopy] and configure the necessary settings for the copy job.

➔ [Reserve Priority \(page 8-20\)](#)



## Canceling Jobs

You can also cancel jobs by selecting the **[Stop]** key.

**1 Select the **[Stop]** key with the copy screen displayed.**

**2 Cancel a job.**

**1** **[▲][▼]** key > **[Cancel Print Job]** > **[OK]** key

**2** Select the job to cancel, and **[Menu]**.

**3** **[▲][▼]** key > **[Cancel Job]** > **[OK]** key



### NOTE

Select **[Detail]** and the **[OK]** key to show the detailed information of the job.

**4** Select **[Yes]**.

The job is canceled.



### NOTE

During scanning, the job can be canceled by selecting the **[Stop]** key or **[Cancel]**.


# Sending

This machine can send a scanned image as an attachment of an E-mail message or to a PC linked to the network. In order to do this, it is necessary to register the sender and destination (recipient) address on the network.


A network environment which enables the machine to connect to a mail server is required in order to send E-mail. It is recommended that a Local Area Network (LAN) be used to assist with transmission speed and security issues.

Follow the steps below for basic sending. The following four options are available.

- Send as E-mail (E-mail Addr Entry): Sends a scanned original image as an E-mail attachment. (Refer to [page 5-15](#) and [page 5-17](#).)



- Send to Folder (SMB): Stores a scanned original image in a shared folder of any PC. (Refer to [page 5-14](#).)
- Send to Folder (FTP): Stores a scanned original image in a folder of an FTP server. (Refer to [page 5-14](#).)



- Image Data Scanning with TWAIN / WIA: Scan the document using a TWAIN or WIA compatible application program. (Refer to [page 5-28](#).)

## NOTE


- Different sending options can be specified in combination.
- ➔ [Sending to Different Types of Destinations \(Multi Sending\) \(page 5-24\)](#)
- The fax function can be used on products equipped with fax capability.
- ➔ **FAX Operation Guide**

## Basic Operation


### 1 Select the [Send] key.

### 2 Place the originals.

Place the originals.



➔ [Loading Originals \(page 5-2\)](#)



### 3 Specify the destination.

Select the destination to which to send an image.

➔ [Specifying Destination \(page 5-15\)](#)

#### Choosing a Destination from the External Address Book

For details on the External Address Book, refer to the following:

➔ **Command Center RX User Guide**

#### Choosing a Destination from the FAX

For more information on using the FAX, refer to the following:

➔ **FAX Operation Guide**

### 4 Select the functions.

Select the [Function Menu] key to select the send functions to use.

➔ [Send \(page 6-4\)](#)

### 5 Press the [Start] key.

Sending starts.

## Specifying Destination

Select the destination using either of the following methods:

[Choosing from the Address Book \(page 5-15\)](#)

Choosing from the External Address Book

For details on the External Address Book, refer to the following:

➔ **Command Center RX User Guide**

[Choosing from the One Touch Key \(page 5-17\)](#)

[Entering an E-mail Address \(page 5-17\)](#)

[Specifying a New PC Folder \(page 5-18\)](#)

Choosing from the FAX

➔ **FAX Operation Guide**



### NOTE

- You can set the machine up so that the address book screen appears when you select the **[Send]** key.  
➔ [Default Screen \(page 8-21\)](#)
- If you are using the products equipped with the fax function, you can specify the fax destination. Enter the other party number using the numeric keypad.

## Choosing from the Address Book

Select a destination registered in the Address Book.

For more information about how to register destinations in the Address Book, refer to the following:

➔ [Registering Destinations in the Address Book \(page 3-23\)](#)

**1 In the basic screen for sending, select the [Address Book] key.**

**2 Select the destinations.**

**1** [▲] [▼] key > **[Address Book]** > **[OK]** key



### NOTE

For details on the External Address Book, refer to the following:

➔ **Command Center RX User Guide**

**2** Select the destination.



### NOTE

When checking information of the destination, select **[Menu]** > **[Details]** > **[OK]** key

## Destination Search

The destination can be searched by name.

- 1 [Menu] > [▲] [▼] key > [Search (Name)] > [OK] key
- 2 Enter characters to search using the numeric keys.



### NOTE

For details on entering characters, refer to the following:

➔ [Character Entry Method \(page 11-11\)](#)

- 3 Select the [OK] key.  
The searched destination is displayed.

## 3 Select the [OK] key.

To send to multiple destinations, repeat steps 1 to 3. You can send to as many as 100 destinations at once.

Destinations can be changed later.

➔ [Checking and Editing Destinations \(page 5-21\)](#)

## Choosing from the One Touch Key


Select the destination using the One Touch Keys.

In the basic screen for sending, select the One Touch Keys where the destination is registered.


### NOTE

This procedure assumes that One Touch Keys have already been registered. For more information on adding One Touch keys, refer to the following:

➔ [Adding a Destination on One Touch Key \(One Touch Key\) \(page 3-29\)](#)



When selecting One Touch Key numbers 12 to 22, the One touch Key needs to be selected after switching on the [**Shift Lock**] indicator by selecting the [**Shift Lock**] key.



Destinations can be changed later.

➔ [Checking and Editing Destinations \(page 5-21\)](#)

## Entering an E-mail Address

Enter the desired E-mail address.

### NOTE

To send an E-mail, configure the environment settings necessary.

➔ [E-mail Settings \(page 2-44\)](#)

**1 In the basic screen for sending, select [**▲**] [**▼**] key > [**E-mail**] > [**OK**] key**

**2 Enter destination E-mail address.**

### NOTE

For details on entering characters, refer to the following:

➔ [Character Entry Method \(page 11-11\)](#)

**3 Select the [**OK**] key.**

To send to multiple destinations, select the [**Confirm/Add Destination**] key. You can send to as many as 100 destinations at once.

Destinations can be changed later.

➔ [Checking and Editing Destinations \(page 5-21\)](#)



**NOTE**

When selecting [On] for Entry Check for New Destination, the confirmation screen appears.

➔ [Check New Dest. \(page 8-21\)](#)

Enter the same E-mail address again, and select the [OK] key.

## Specifying a New PC Folder

Specify either the desired shared folder on a computer or an FTP server as the destination.



**NOTE**

- For the method for setting a shared folder destination on a PC, refer to the following:

➔ [Preparation for Sending a Document to a Shared Folder in a PC \(page 3-13\)](#)

- For details on how to share a folder, refer to the following:

➔ [Creating a Shared Folder, Making a Note of a Shared Folder \(page 3-15\)](#)

- Be sure that SMB Protocol or FTP is On.

➔ [Protocol Detail \(page 8-27\)](#)

**1 In the basic screen for sending, select [▲] [▼] key > [Folder(SMB)] or [Folder(FTP)] > [OK] key**

**2 Enter the destination information.**

The table below explains the items to be entered. Enter the information for each item and select the [OK] key.



**NOTE**

- For the computer name, share name, domain name, and user name, enter the information that you noted when you created the shared folder. For details on creating shared folders, refer to the following:

➔ [Making a note of the computer name and full computer name \(page 3-13\)](#)

- For details on entering characters, refer to the following:

➔ [Character Entry Method \(page 11-11\)](#)



**For send to folder (SMB)**

Item	Detail	Max. characters
<b>Host Name (SMB)*<sup>1</sup></b>	Computer name	Up to 64 characters
<b>Path</b>	Share name For example: scannerdata If saving in a folder in the shared folder: share name\folder name in shared folder	Up to 128 characters
<b>Login User Name</b>	If the computer name and domain name are the same: User Name For example: james.smith If the computer name and domain name are different: Domain name\User name For example: abcdnet\james.smith	Up to 64 characters
<b>Login Password</b>	Windows logon password <b>(Case sensitive.)</b>	Up to 64 characters

\*1 To specify a port number different from the default (445), enter using the format "Host name: port number" (Example: SMBhostname:140).  
To enter the IPv6 address, enclose the address in brackets [ ].  
(Example: [3ae3:9a0:cd05:b1d2:28a:1fc0:a1:10ae]:140)

**For send to folder (FTP)**

Item	Data to be entered	Max. characters
<b>Host Name (FTP)*<sup>1</sup></b>	Host name or IP address of FTP server	Up to 64 characters
<b>Path*<sup>2</sup></b>	Path to the receiving folder For example: User\ScanData Otherwise the data will be saved in the home directory.	Up to 128 characters
<b>Login User Name</b>	FTP server login user name	Up to 64 characters
<b>Login Password</b>	FTP server login password <b>(Case sensitive.)</b>	Up to 64 characters

\*1 If you specify a port number other than the default (21), use the "Host name: port number" (Example: FTPhostname:140).  
To enter the IPv6 address, enclose the address in brackets [ ].  
(Example: [3ae3:9a0:cd05:b1d2:28a:1fc0:a1:10ae]:140)

\*2 When the FTP server is based on Linux/UNIX, the path including the sub-folder is combined by the slash "/" not using the back-slash.

### **3 Confirm the information.**

The connection confirmation screen appears. Select [**Yes**] to check the connection and [**No**] to not check it.

"Connected." appears when connection to the destination is correctly established. If "Cannot connect." appears, review the entry.

To send to multiple destinations, repeat steps 1 to 3.

Destinations can be changed later.

➔ [Checking and Editing Destinations \(page 5-21\)](#)

# Checking and Editing Destinations

Check and edit a selected destination.

## 1 Display the screen.

Specify the destination.

➔ [Specifying Destination \(page 5-15\)](#)

## 2 Check and edit the destination.

Select the [Confirm/Add Destination] key.

### Add the destination

1 Select [Add].

2 Set the destinations to be added.

➔ [Specifying Destination \(page 5-15\)](#)

### Edit the destination

1 Select the destination you want to edit, and select the [OK] key.

2 [▲] [▼] key > [Detail/Edit] > [OK] key

3 Edit the destinations > [OK] key

➔ [Specifying Destination \(page 5-15\)](#)



#### NOTE

To edit a destination registered in the address book or a One Touch Key, refer to the following:

➔ [Editing and Deleting Address Book Entries \(page 3-28\)](#)

[Editing and Deleting One Touch Key \(page 3-30\)](#)

### Delete the destination

1 Select the destination you want to delete, and select the [OK] key.

2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

## 3 Select [Exit].



#### NOTE

When selecting [On] for Destination Check before Send, the confirmation screen appears after pressing the [Start] key.

➔ [Check beforeSend \(page 8-21\)](#)

[Confirmation Screen of Destinations \(page 5-22\)](#)

## Confirmation Screen of Destinations

When selecting [**On**] for Destination Check before Send, the confirmation screen of destinations appears after pressing the [**Start**] key.

➔ [DestinationCheck \(page 8-21\)](#)

Follow the steps below to confirm the destinations.

**1** Confirm all destination.

To show the detailed information of the destination, select the destination and [**OK**] key > [**▲**] [**▼**] key > [**Detail**] > [**OK**] key

To delete the destination, select the destination you want to delete and [**OK**] key > [**▲**] [**▼**] key > [**Delete**] > [**OK**] key > [**Yes**]  
The destination is deleted.

**2** Select [**Next**].



**NOTE**

Be sure to confirm all destination by displaying them on the message display. You cannot select [**Next**] unless you have confirmed all destination.

## Recall

Recall is a function allowing you to send the last entered destination once again. When you want to send the image to the same destination, select the **[Address Recall/Pause]** key, and you can call the destination you sent on the destination list.

- 1 Select the **[Address Recall/Pause]** key.

The destination you sent is displayed on the destination list.

### NOTE

When the last sending included FAX, computers and E-mail destinations, they are also displayed. If necessary, add or delete the destination.

- 2 Press the **[Start]** key.

Sending starts.

### NOTE

- When **[On]** is selected in "Check beforeSend", a destination confirmation screen is displayed when you press the **[Start]** key.

➔ [Confirmation Screen of Destinations \(page 5-22\)](#)

- Recall information is canceled in the following conditions.
  - When you turn the power off
  - When you send a next image (new recall information is registered)
  - When you log out

## Send to Me (E-mail)

When user login is enabled, the document is sent to the E-mail address of the logged in user.

- 1 **In the basic screen for sending, select **[▲]** **[▼]** key > **[Me(E-mail)]** > **[OK]** key**


### NOTE

An E-mail address must be set in user login for the user who logs in.

➔ [Adding a User \(Local User List\) \(page 9-6\)](#)

## Sending to Different Types of Destinations (Multi Sending)

You can specify destinations that combine E-mail addresses, folders (SMB or FTP) and fax numbers (Fax functionality can only be used on products equipped with fax capability.). This is referred to as Multi Sending. This is useful for sending to different types of destination (E-mail addresses, folders, etc.) in a single operation.



No. of broadcast items

E-mail: Up to 100

Folders (SMB, FTP): Total of 5 SMB and FTP

FAX: Up to 100

Procedures are the same as used in specifying the destinations of respective types. Continue to enter E-mail address or folder path so that they appear in the destination list. Press the **[Start]** key to start transmission to all destinations at one time.



### NOTE

If the destinations include a fax, the images sent to all destinations will be black and white.

## Canceling Sending Jobs

You can also cancel jobs by selecting the **[Stop]** key.

### 1 Select the **[Stop]** key with the send screen displayed.

The **[Job Cancel List]** menu appears.



#### NOTE

Selecting the **[Stop]** key will not temporarily stop a job that you have already started sending.

### 2 Cancel jobs.

1 **[▲]** **[▼]** key > **[Cancel Send Job]** > **[OK]** key

2 Select the job to cancel, and **[Menu]**.

3 **[▲]** **[▼]** key > **[Cancel Job]** > **[OK]** key



#### NOTE

Select **[Detail]** and the **[OK]** key to show the detailed information of the job.

4 Select **[Yes]**.

The job is canceled.



#### NOTE

During scanning, the job can be canceled by selecting the **[Stop]** key or **[Cancel]**.

## WSD Scan

WSD Scan saves images of originals scanned on this machine as files on a WSD-compatible computer.

### NOTE

- To use WSD Scan, confirm that the computer used for WSD scanning and the machine is network-connected, and "WSD-SCAN" is set to **[On]** in the network settings.

➔ [WSD-SCAN \(page 8-28\)](#)

- For information on operating the computer, refer to the computer's help or the operation guide of your software.

## Installing Driver Software (for Windows 7)

### 1 Display **[Network]** in the Start menu.

Click **[Start]** button on the Windows and then select **[Network]**.

#### NOTE

When **[Network]** does not appear in the Start menu, perform the following procedure.

- 1 Right-click **[Start]** and click **[Property]** in the menu that appears.
- 2 Select the **[[Start] menu]** tab in the "Task bar and **[Start] menu properties**" screen, and click **[Customize]**.
- 3 When the "Customize **[Start] menu**" screen appears, select the "**Network**" check box and click **[OK]**.

### 2 Install the driver.

Right-click the machine's icon and then click **[Install]**.

#### NOTE

If the "**User Account Control**" window appears, click **[Continue]**.

If the "**Found New Hardware**" window appears, click **[Cancel]**.

During the installation, double-click the icon shown on the task bar to display the "**Driver Software Installation**" screen. When "**Your devices are ready to use**" is displayed on the **[Driver Software Installation]** screen, the installation is completed.

## Installing Driver Software (for Windows 8 and Microsoft Windows Server 2012)

### 1 Click **[Search]** in charms, **[Control Panel]**, and then **[View devices and printers]**.

### 2 Install the driver.



Click **[Add a device]**. Select the machine's icon and then click **[Next]**.

When the machine's icon is displayed in "**Printers**" on the **[Devices and Printers]** screen, the installation is completed.



## WSD scan

### 1 Place the originals.



➔ [Loading Originals \(page 5-2\)](#)

### 2 Display the screen.

[Send] key > [▲] [▼] key > [WSD Scan] > [OK] key

### 3 Scan the originals.

#### Procedure using this machine

- 1 [▲] [▼] key > [From Oper. Panel] > [OK] key
- 2 Select the destination computer, and select the [OK] key.  
You can view information on the selected computer by selecting [Detail].
- 3 Select the [Function Menu] key to set the type of original, file format, etc., as desired.
- 4 Press the [Start] key.  
Sending begins and the software installed on the computer is activated.

#### Procedure from Your Computer

- 1 [▲] [▼] key > [From Computer] > [OK] key
- 2 Use the software installed on the computer to send the images.

## Scanning using TWAIN or WIA

This section explains how to scan an original using TWAIN. The WIA driver is used in the same way.

### 1 Display the screen.

- 1 Activate the TWAIN compatible application software.
- 2 Select the machine using the application and display the dialog box.



#### NOTE

For selecting the machine, see the Operation Guide or Help for each application software.

### 2 Configure the scan settings.


Select scanning settings in the dialog box that opens.



#### NOTE

For the settings, refer to Help in the dialog box.

### 3 Place the originals.



➔ [Loading Originals \(page 5-2\)](#)



### 4 Scan the originals.

Click the [Scan] button. The document data is scanned.

## How to use the FAX Function

On products with a FAX function, it is possible to use the FAX function.

➔ **FAX Operation Guide**

# What is Document Box?

Document Box contains four types of component boxes which provide the following functions.

The following types of document boxes are available.

## Custom Box ([page 5-32](#))

Custom Box is a component box which you can create within the Document Box and store data for later retrieval. You can create or delete a Custom Box, and manipulate data in various ways as described below:

- ➔ [Creating a New Custom Box \(page 5-32\)](#)
- [Storing Documents \(page 5-34\)](#)
- [Printing Documents \(page 5-35\)](#)
- [Editing Documents \(page 5-36\)](#)
- [Deleting Documents \(page 5-37\)](#)



### NOTE

To use Custom Box, an optional SSD must be installed in the machine.

## Job Box

This is a box to save jobs executed from a PC.



### NOTE

- You can set up the machine so that temporary documents in job boxes are automatically deleted.
  - ➔ [JobRet. Deletion \(page 8-22\)](#)
- For details on operating the Job Box, refer to the following:
  - ➔ [Printing Data Saved on the Printer \(page 4-9\)](#)

## Private Print/Stored Job Box ([page 4-10](#), [page 4-12](#))

In Private Printing, you can specify that a job is not to be printed until you operate the machine. When sending the job from the application software, specify a 4-digit access code in the printer driver. The job is released for printing by entering the access code on the operation panel, ensuring confidentiality of the print job. The data will be deleted upon completion of the print job or after the power switch is turned off.

In Stored Job, the print data sent from the application is saved to the machine. You can set up an access code as necessary. If you set up an access code, enter the access code when printing. Print data will be stored in the Job Box after printing. This will allow printing of the same print data repeatedly.

## Quick Copy/Proof and Hold Box ([page 4-14](#), [page 4-16](#))

Quick Copy feature facilitates additional prints of a document already printed. Activating Quick Copy and printing a document using the printer driver allow the print data to be stored in the Job Box. When additional copies are required, you can reprint the required number of copies from the operation panel. By default, up to 32 documents can be stored. When power is turned off, all stored jobs will be deleted.



### NOTE

When you attempt to store documents in excess of the above maximum, the oldest document data will be overwritten by the latest document data.

The Proof and Hold feature produces only a single proof print of multiple-print job and holds printing of the remaining copies. Printing a multiple-print job in Proof and Hold using the printer driver allows only a single copy to be printed while maintaining the document data in the Job Box. To continue to print the remaining copies, use the operation panel. You can change the number of copies to print.

## **Removable Memory Box ([page 5-38](#))**

A USB memory stick can be connected to the USB memory slot on the machine to print a saved file. You can print data directly from the USB memory without a PC. Image files scanned using this machine can also be saved to USB memory in the PDF, TIFF, JPEG, XPS, OpenXPS or high compression PDF format (Scan to USB).

## **Sub Address Box/Polling Box**

Sub Address Box/Polling Box store the fax data.

➔ **FAX Operation Guide**

# Using a Custom Box

Custom Box is a component box which you can create within the Document Box and store data for later retrieval. You can create or delete a Custom Box, and manipulate data in various ways as described below:

➔ [Creating a New Custom Box \(page 5-32\)](#)

[Storing Documents \(page 5-34\)](#)

[Printing Documents \(page 5-35\)](#)

[Editing Documents \(page 5-36\)](#)

[Deleting Documents \(page 5-37\)](#)



## NOTE

The operation on Custom Box you perform from operation panel can also be made using Command Center RX.

➔ [Command Center RX User Guide](#)

## Creating a New Custom Box



## NOTE

- To use Custom Box, an optional SSD must be installed in the machine.
- If user login administration is enabled, you can only change the settings by logging in with administrator privileges. The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- If user login administration is enabled, log in with administrator privileges to perform the following operations. They cannot be performed with user privileges.
  - Creating a box
  - Deleting a box of which owner is another user.

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Document Box] > [OK] key > [▲] [▼] key > [Custom Box] > [OK] key > [▲] [▼] key > [Detail/Edit] > [OK] key > [Menu]

### 2 Create a custom box.

1 [▲] [▼] key > [Add Box] > [OK] key

2 Enter the box name and select the [OK] key.




## NOTE

Up to 32 characters can be entered.

For details on entering characters, refer to the following:

➔ [Character Entry Method \(page 11-11\)](#)

- 3 Enter a box number and select the [OK] key.

 **NOTE**

You can set any value between 0001 and 1000.  
Use the [▲] or [▼] key or the numeric keys to enter a number.

If you specify a box number that is already in use, an error message appears when you select the [OK] key and the number cannot be registered. If you enter 0000, the smallest number available will be automatically assigned.

- 4 To complete the box registration, select [▲] [▼] key > [Exit] > [OK] key.  
The Custom Box is created.  
To register further Box information, select [▲] [▼] key > [Detail] > [OK] key.  
Proceed to next step.

### 3 Enter the box information.

Select [Edit] or [Change] on each item and enter the information then select the [OK] key. Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen. The table below lists the items to be set.

Item	Description
<b>Box Name</b>	Enter a box name consisting of up to 32 characters. <a href="#">▶ Character Entry Method (page 11-11)</a>
<b>Owner</b> *1 *2	Set the owner of the box. Select the owner from the user list that appears.
<b>Permission</b> *1	Select whether to share the box.
<b>Box Password</b>	User access to the box can be restricted by specifying a password to protect the box. Entering a password is not mandatory. Enter a password of up to 16 characters and select the [OK] key. Reenter the same password for confirmation and select the [OK] key. This can be set if [Shared] is selected in "Permission".
<b>Box Number</b>	Enter the box number by using the numeric keys or using the [▲] or [▼] key. The box number can be from 0001 to 1000. A Custom Box should have a unique number. If you enter 0000, the smallest number available will be automatically assigned.
<b>Usage Restrict.</b>	The usage for a box can be restricted. To enable a capacity restriction enter a value for the storage capacity of the Custom Box in megabytes by using the numeric keys or using the [▲] or [▼] key. You can enter a limit between 1 and 30,000 (MB).
<b>Auto File Del.</b>	Automatically deletes stored documents after a set period of time. To enable automatic deletion, select [▲] [▼] key > [On] > [OK] key. Use the numeric keys or use the [▲] or [▼] key to enter the number of days for which documents are stored. You can enter any number between 1 and 31 (day(s)). To disable automatic file deletion, select [▲] [▼] key > [Off] > [OK] key.
<b>Free Space</b>	Displays the free space on the box.
<b>OverwriteSetting</b>	Specifies whether or not old stored documents are overwritten when new documents are stored. To overwrite old documents, select [▲] [▼] key > [Permit] > [OK] key. To retain old documents, select [▲] [▼] key > [Prohibit] > [OK] key.
<b>Del. afterPrint</b>	Automatically delete a document from the box once printing is complete. To delete the document, select [▲] [▼] key > [On] > [OK] key. To retain the document, select [▲] [▼] key > [Off] > [OK] key.

\*1 Displayed when the user login administration is enabled.

\*2 Displayed when the user has logged in as administrator.

## Editing and Deleting Custom Box

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Document Box] > [OK] key > [▲] [▼] key > [Custom Box] > [OK] key > [▲] [▼] key > [Detail/Edit] > [OK] key

### 2 Edit the custom box.

#### To edit

- 1 Select the box you want edit and select the [OK] key.



#### NOTE

- When you have logged in as a user, you can only edit a box whose owner is set to that user.
- When you have logged in as administrator, you can edit all boxes.
- If a custom box is protected by a password, enter the correct password.

- 2 Change the box information.

➔ [Creating a New Custom Box \(page 5-32\)](#)

#### To delete

- 1 Select the box you want delete and [Menu].



#### NOTE

- When you have logged in as a user, you can only delete a box whose owner is set to that user.
- When you have logged in as administrator, you can delete all boxes.

- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]



#### NOTE

If a custom box is protected by a password, enter the correct password.

## Storing Documents

Custom box stores the print data which is sent from a PC. For the operation of the printing from the PC, refer to the following:

➔ **Printer Driver User Guide**



# Printing Documents

The procedure for printing documents in a custom box is explained below.

## 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Custom Box] > [OK] key
- 2 Select the box containing the document you want to print, and select the [OK] key.

### NOTE

- If a custom box is protected by a password, enter the correct password.
- Select [Menu] to perform the following operations.
  - [Open]: Open the selected box.
  - [Detail]: Display the details for the selected box.
  - [Sort(No.)], [Sort(Name)]: Sort the boxes.
  - [Search(No.)], [Search(Name)]: Search using the box number or the box name.

## 2 Print the document.

- 1 Select the document you want to print, and select [Select].

A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.

### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Search(Name)]: Search using a file name.
- [Detail]: Display the details for the selected file.

- 2 Select the [OK] key.

To use the settings used at the time of printing (when the document was saved), select [▲] [▼] key > [Print] > [OK] key.

To change the print settings, select [▲] [▼] key > [Print(ChangeSet)] > [OK] key.

If [Print] is selected, change the number of copies to print as necessary.

If [Print (ChangeSet)] is selected, change the print settings. For the features that can be selected, refer to the following:

➔ [Custom Box \(Printing\) \(page 6-6\)](#)

- 3 Press the [Start] key.

Printing of the selected document begins.

## Editing Documents

This function allows you to move documents stored in custom boxes into other boxes. The procedure for moving documents is explained below.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Custom Box] > [OK] key
- 2 Select the box containing the document you want to move, and select the [OK] key.



#### NOTE

- If a custom box is protected by a password, enter the correct password.
- Select [Menu] to perform the following operations.
  - [Open]: Open the selected box.
  - [Detail]: Display the details for the selected box.
  - [Sort(No.)], [Sort(Name)]: Sort the boxes.
  - [Search(No.)], [Search(Name)]: Search using the box number or the box name.

### 2 Move the documents.

- 1 Select the document you want to move, and select [Select].

A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

Select [Menu] to perform the following operations.

- [Select All]: Select all files.
- [Clear All]: Cancel all the file selections.
- [Search(Name)]: Search using a file name.
- [Detail]: Display the details for the selected file.

- 2 [OK] key > [▲] [▼] key > [Move] > [OK] key
- 3 Select the destination box, and the [OK] key.

The selected document is moved.



#### NOTE

If the box to which the document is to be moved is protected by a password, enter the correct password.

## Deleting Documents

The procedure for deleting documents in a custom box is explained below.

### 1 Display the screen.

- 1 [Document Box/USB] key > [▲] [▼] key > [Custom Box] > [OK] key
- 2 Select the box containing the document you want to delete, and select the [OK] key.



#### NOTE

- If a custom box is protected by a password, enter the correct password.
- Select [Menu] to perform the following operations.
  - [Open]: Open the selected box.
  - [Detail]: Display the details for the selected box.
  - [Sort(No.)], [Sort(Name)]: Sort the boxes.
  - [Search(No.)], [Search(Name)]: Search using the box number or the box name.

### 2 Delete the document.

- 1 Select the document you want to delete, and select [Select].

A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [Select] again to cancel the selection.



#### NOTE

- Select [Menu] to perform the following operations.
- [Select All]: Select all files.
  - [Clear All]: Cancel all the file selections.
  - [Search(Name)]: Search using a file name.
  - [Detail]: Display the details for the selected file.

- 2 [OK] key > [▲] [▼] key > [Delete] > [OK] key > [Yes]

# Printing Documents Stored in Removable USB Memory

Plugging USB memory directly into the machine enables you to quickly and easily print the files stored in the USB memory without having to use a computer.

The following file types can be printed:

PDF file (Version 1.7 or older)

TIFF file (TIFF V6/TTN2 format)

JPEG file

XPS file


OpenXPS file

Encrypted PDF file

- PDF files you wish to print should have an extension (.pdf).
- Files to be printed should be saved no further down than the top 3 folder levels, including the root folder.
- Plug the USB memory directly into the USB Memory Slot.

## 1 Plug the USB memory.

Plug the USB memory into the USB Memory Slot.



## 2 Display the screen.

[Document Box/USB] key > [▲] [▼] key > [USB Memory] > [OK] key

## 3 Print the document.

- 1 Select the folder containing the file to be printed, and select the [OK] key.

The machine will display documents in the top 3 folder levels, including the root folder.

### NOTE

- 1,000 documents can be displayed.
- To return to a higher level folder, select the [Back] key.

- 2 Select the document you want to print, and [**Select**].

A checkmark will be placed on the right of the selected file.

Select the checkmarked file and select [**Select**] again to cancel the selection.



#### **NOTE**

Select [**Menu**] to perform the following operations.

- [**Select All**]: Select all files.
- [**Clear All**]: Cancel all the file selections.
- [**Detail**]: Display the details for the selected file.
- [**Memory Detail**]: Display the detail for the USB memory.
- [**Remove Memory**]: Remove the USB memory.

- 3 [**OK**] key > [**▲**] [**▼**] key > [**Print**] > [**OK**] key

- 4 Change the number of copies, duplex printing, etc. as desired.

For the features that can be selected, refer to the following:

➔ [Removable Memory \(Store File, Printing Documents\) \(page 6-7\)](#)

- 5 Press the [**Start**] key.

Printing of the selected file begins.


# Saving Documents to USB Memory (Scan to USB)

This function allows you to store scanned image files in USB memory connected to the machine. You can store files in PDF, TIFF, JPEG, XPS, OpenXPS or high-compression PDF format.

## NOTE

The maximum number of the storable files is 1,000.


### 1 Place the originals.



➔ [Loading Originals \(page 5-2\)](#)

### 2 Plug the USB memory.

Plug the USB memory into the USB Memory Slot.



### 3 Display the screen.

[Document Box/USB] key > [▲] [▼] key > [USB Memory] > [OK] key

### 4 Store the document.

- 1 Select the folder where the file will be stored, and the [OK] key.  
The machine will display the top 3 folder levels, including the root folder.
- 2 [▲] [▼] key > [Store File] > [OK] key
- 3 Set the type of original, file format, etc., as desired.  
For the features that can be set, refer to the following:  
➔ [Removable Memory \(Store File. Printing Documents\) \(page 6-7\)](#)
- 4 Press the [Start] key.  
The original is scanned and the data is stored in the USB memory.

# Check the USB Memory Information

You can check the USB memory information.

## 1 Display the screen.


[Document Box/USB] key > [▲] [▼] key > [USB Memory] > [OK] key > [Menu] > [▲] [▼] key > [Memory Detail] > [OK] key

## 2 Check the information.

Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen. Once you confirm the information, select the [OK] key.

# Removing USB Memory

Follow the steps below to remove the USB memory.

 **IMPORTANT**

Be sure to follow the proper procedure to avoid damaging the data or USB memory.

**1 Display the screen.**

[Reset] key > [Document Box/USB] key > [▲] [▼] key > [USB Memory] > [OK] key

**2 Select [Remove Memory].**

[Menu] > [▲] [▼] key > [Remove Memory] > [OK]

**3 Remove the USB memory.**

When "USB memory can be safely removed." is displayed, select [OK] and then remove the USB memory.



**NOTE**

USB memory can also be removed after checking the status of the device.

➔ [Device/Communication \(page 7-14\)](#)



# Using the Manual Stapler

You can staple copied paper manually without any print operation.



## NOTE

If the machine is out of staples, add more staples.


➔ [Replacing Staples \(page 10-10\)](#)

## Maximum number of sheets available for manual stapling

Paper weight	Number of stapled sheets
80 g/m <sup>2</sup>	20 sheets maximum <sup>*1</sup>
90 g/m <sup>2</sup> or less	15 sheets maximum <sup>*1</sup>

\*1 Paper stack up to 2 mm thick.

- 1 Straighten the edges of the stack of paper, and with the front side facing up, insert the paper into the manual stapler.**



When the paper is inserted all the way in, stapling takes place.



## NOTE

Manual stapling cannot be used while the machine is in sleep mode.

To use manual stapling, select the **[Energy Saver]** key.

# 6 Using Various Functions


This chapter explains the following topics:

Functions Available on the Machine .....	6-2
Copy .....	6-3
Send .....	6-4
Custom Box (Printing) .....	6-6
Removable Memory (Store File, Printing Documents) .....	6-7
Functions .....	6-9
Original Size .....	6-9
Paper Selection .....	6-10
Orig. Orientation (Original Orientation) .....	6-11
Mixed Size Originals .....	6-12
Collate .....	6-12
Density .....	6-12
Original Image .....	6-13
EcoPrint .....	6-13
Color Selection .....	6-14
Color Balance .....	6-15
Sharpness .....	6-16
Contrast .....	6-16
Background Density Adj. (Background Density Adjustment) .....	6-17
Saturation .....	6-17
Prevent Bleed-t (Prevent Bleed-thru) .....	6-18
Zoom .....	6-18
Combine .....	6-20
Duplex .....	6-22
Continuous Scan .....	6-24
Job Finish Notice .....	6-24
File Name Entry .....	6-24
Print Override .....	6-25
Quiet Mode .....	6-25
Skip Blank Page .....	6-25
Duplex (2-sided Original) .....	6-26
Sending Size .....	6-27
File Format .....	6-28
File Separation .....	6-32
Scan Resolution .....	6-32
Subject/Body .....	6-32
FTP Encrypted TX .....	6-33
Del. after Print (Delete after Printed) .....	6-33
Storing Size .....	6-34
Encrypted PDF .....	6-34
JPEG/TIFF Print .....	6-35
XPS FitTo Page .....	6-35

# Functions Available on the Machine

To configure the settings for functions, select the **[Function Menu]** key.



➔ [Operation Method \(page 2-12\)](#)



- 1 Displays the function menu.
- 2 Selects the item displayed or changes the numeric value.
- 3 Confirms the selected setting.
- 4 Cancels the current menu setting to return to the menu one level higher.


## Copy



For details on each function, see the table below.

Key	Function	Description	Reference page
☰ Function Menu 	<b>Quiet Mode</b>	Lower print and scan speed for quiet processing.	<a href="#">page 6-25</a>
	<b>Paper Selection</b>	Select the cassette or multi-purpose tray that contains the required paper size.	<a href="#">page 6-10</a>
	<b>Collate</b>	Offsets the output by page or set.	<a href="#">page 6-12</a>
	<b>Duplex</b>	Produces two-sided copies. You can also create single-sided copies from two-sided originals.	<a href="#">page 6-22</a>
	<b>Zoom</b>	Adjust the zoom to reduce or enlarge the image.	<a href="#">page 6-18</a>
	<b>Combine</b>	Combines 2 or 4 original sheets into 1 printed page.	<a href="#">page 6-20</a>
	<b>Original Size</b>	Specify the original size to be scanned.	<a href="#">page 6-9</a>
	<b>Orig. Orientation</b>	Select the orientation of the original document top edge to scan correct direction.	<a href="#">page 6-11</a>
	<b>Mixed Size Originals</b>	Scans all sheets in the document processor, even if they are of different sizes.	<a href="#">page 6-12</a>
	<b>Original Image</b>	Select original image type for best results.	<a href="#">page 6-13</a>
	<b>Density</b>	Adjust density.	<a href="#">page 6-12</a>
	<b>EcoPrint</b>	EcoPrint saves toner when printing.	<a href="#">page 6-13</a>
	<b>Continuous Scan</b>	Scans a large number of originals in separate batches and then produce as one job.	<a href="#">page 6-24</a>
	<b>File Name Entry</b>	Adds a file name.	<a href="#">page 6-24</a>
	<b>JobFinish Notice</b>	Sends E-mail notice when a job is complete.	<a href="#">page 6-24</a>
	<b>Print Override</b>	Suspends the current job and gives a new job top priority.	<a href="#">page 6-25</a>
	<b>Color Selection</b>	Select the color mode setting.	<a href="#">page 6-14</a>
	<b>Color Balance</b>	Adjust the strength of cyan, magenta, yellow, and black.	<a href="#">page 6-15</a>
	<b>Sharpness</b>	Adjusts the sharpness of image outlines.	<a href="#">page 6-16</a>
	<b>Contrast</b>	You can adjust the contrast between light and dark areas of the image.	<a href="#">page 6-16</a>
	<b>Backgrnd Density</b>	Removes dark background from originals, such as newspapers.	<a href="#">page 6-17</a>
	<b>Saturation</b>	Adjust the color saturation of the image.	<a href="#">page 6-17</a>
	<b>Prevent Bleed-t</b>	Hides background colors and image bleed-through when scanning thin original.	<a href="#">page 6-18</a>
	<b>Skip Blank Page</b>	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	<a href="#">page 6-25</a>

# Send


For details on each function, see the table below.

Key	Function	Description	Reference page
	<b>Quiet Mode</b>	Lower print and scan speed for quiet processing.	<a href="#">page 6-25</a>
	<b>Color Selection</b>	Select the color mode setting.	<a href="#">page 6-14</a>
	<b>Original Size</b>	Specify the original size to be scanned.	<a href="#">page 6-9</a>
	<b>Original Image</b>	Select original image type for best results.	<a href="#">page 6-13</a>
	<b>Scan Resolution</b>	Select fineness of scanning resolution.	<a href="#">page 6-32</a>
	<b>Sending Size</b>	Select size of image to be sent.	<a href="#">page 6-27</a>
	<b>Zoom</b>	Adjust the zoom to reduce or enlarge the image.	<a href="#">page 6-18</a>
	<b>Orig. Orientation</b>	Select the orientation of the original document top edge to scan correct direction.	<a href="#">page 6-11</a>
	<b>Mixed Size Originals</b>	Scans all sheets in the document processor, even if they are of different sizes.	<a href="#">page 6-12</a>
	<b>Continuous Scan</b>	Scans a large number of originals in separate batches and then produce as one job.	<a href="#">page 6-24</a>
	<b>File Format</b>	Specify the image file format. Image quality level can also be adjusted.	<a href="#">page 6-28</a>
	<b>File Name Entry</b>	Adds a file name.	<a href="#">page 6-24</a>
	<b>Subject/Body</b>	Adds subject and body when sending a document.	<a href="#">page 6-32</a>
	<b>JobFinish Notice</b>	Sends E-mail notice when a job is complete.	<a href="#">page 6-24</a>
	<b>FAX Resolution</b>	Select fineness of images when sending FAX.	Refer to the <b>FAX Operation Guide</b> .
	<b>FAX Delayed TX</b>	Set a send time.	
	<b>FAX Direct TX</b>	Sends FAX directly without reading original data into memory.	
	<b>FAX RX Polling</b>	Automatically makes a machine with a stored document send the document to your machine.	
	<b>FAX TX Report</b>	Prints a report when transmission of a document is successful, or when an error occurs and transmission fails.	
	<b>Density</b>	Adjust density.	<a href="#">page 6-12</a>
	<b>Duplex</b>	Select the type and orientation of the binding based on the original.	<a href="#">page 6-26</a>
	<b>FTP Encrypted TX</b>	Encrypts images when sending via FTP.	<a href="#">page 6-33</a>
	<b>File Separation</b>	Creates several files by dividing scanned original data page by page, and sends the files.	<a href="#">page 6-32</a>
	<b>Sharpness</b>	Adjusts the sharpness of image outlines.	<a href="#">page 6-16</a>
	<b>Contrast</b>	You can adjust the contrast between light and dark areas of the image.	<a href="#">page 6-16</a>
	<b>Backgrnd Density</b>	Removes dark background from originals, such as newspapers.	<a href="#">page 6-17</a>

Key	Function	Description	Reference page
 Function Menu 	<b>Prevent Bleed-t</b>	Hides background colors and image bleed-through when scanning thin original.	<a href="#">page 6-18</a>
	<b>Skip Blank Page</b>	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	<a href="#">page 6-25</a>

## Custom Box (Printing)


For details on each function, see the table below.

Key	Function	Description	Reference page
 Function Menu	<b>Quiet Mode</b>	Lower print and scan speed for quiet processing.	<a href="#">page 6-25</a>
	<b>Collate</b>	Offsets the output by page or set.	<a href="#">page 6-12</a>
	<b>Paper Selection</b>	Select the cassette or multi-purpose tray that contains the required paper size.	<a href="#">page 6-10</a>
	<b>Duplex</b>	Print a document on both sides of the paper.	<a href="#">page 6-23</a>
	<b>EcoPrint</b>	EcoPrint saves toner when printing.	<a href="#">page 6-13</a>
	<b>File Name Entry</b>	Adds a file name.	<a href="#">page 6-24</a>
	<b>JobFinish Notice</b>	Sends E-mail notice when a job is complete.	<a href="#">page 6-24</a>
	<b>Print Override</b>	Suspends the current job and gives a new job top priority.	<a href="#">page 6-25</a>
	<b>Del. after Print</b>	Automatically deletes a document from the box once printing is complete.	<a href="#">page 6-33</a>

## Removable Memory (Store File, Printing Documents)



For details on each function, see the table below.

### Store File

Key	Function	Description	Reference page
 Function Menu	<b>Quiet Mode</b>	Lower print and scan speed for quiet processing.	<a href="#">page 6-25</a>
	<b>Color Selection</b>	Select the color mode setting.	<a href="#">page 6-14</a>
	<b>Original Size</b>	Specify the original size to be scanned.	<a href="#">page 6-9</a>
	<b>Original Image</b>	Select original image type for best results.	<a href="#">page 6-13</a>
	<b>Scan Resolution</b>	Select fineness of scanning resolution.	<a href="#">page 6-32</a>
	<b>Storing Size</b>	Select size of image to be stored.	<a href="#">page 6-34</a>
	<b>Zoom</b>	Adjust the zoom to reduce or enlarge the image.	<a href="#">page 6-18</a>
	<b>Orig. Orientation</b>	Select the orientation of the original document top edge to scan correct direction.	<a href="#">page 6-11</a>
	<b>Mixed Size Originals</b>	Scans all sheets in the document processor, even if they are of different sizes.	<a href="#">page 6-12</a>
	<b>Continuous Scan</b>	Scans a large number of originals in separate batches and then produce as one job.	<a href="#">page 6-24</a>
	<b>File Format</b>	Specify the image file format. Image quality level can also be adjusted.	<a href="#">page 6-28</a>
	<b>File Separation</b>	Creates several files by dividing scanned original data page by page, and sends the files.	<a href="#">page 6-32</a>
	<b>File Name Entry</b>	Adds a file name.	<a href="#">page 6-24</a>
	<b>JobFinish Notice</b>	Sends E-mail notice when a job is complete.	<a href="#">page 6-24</a>
	<b>Density</b>	Adjust density.	<a href="#">page 6-12</a>
	<b>Duplex</b>	Select the type and orientation of the binding based on the original.	<a href="#">page 6-26</a>
	<b>Contrast</b>	You can adjust the contrast between light and dark areas of the image.	<a href="#">page 6-16</a>
	<b>Sharpness</b>	Adjusts the sharpness of image outlines.	<a href="#">page 6-16</a>
	<b>Backgrnd Density</b>	Removes dark background from originals, such as newspapers.	<a href="#">page 6-17</a>
	<b>Prevent Bleed-t</b>	Hides background colors and image bleed-through when scanning thin original.	<a href="#">page 6-18</a>
<b>Skip Blank Page</b>	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	<a href="#">page 6-25</a>	



## Printing Documents

Key
 Function Menu 




Function	Description	Reference page
<b>Quiet Mode</b>	Lower print and scan speed for quiet processing.	<a href="#">page 6-25</a>
<b>Collate</b>	Offsets the output by page or set.	<a href="#">page 6-12</a>
<b>Paper Selection</b>	Select the cassette or multi-purpose tray that contains the required paper size.	<a href="#">page 6-10</a>
<b>Duplex</b>	Print a document on both sides of the paper.	<a href="#">page 6-23</a>
<b>EcoPrint</b>	EcoPrint saves toner when printing.	<a href="#">page 6-13</a>
<b>File Name Entry</b>	Adds a file name.	<a href="#">page 6-24</a>
<b>JobFinish Notice</b>	Sends E-mail notice when a job is complete.	<a href="#">page 6-24</a>
<b>Print Override</b>	Suspends the current job and gives a new job top priority.	<a href="#">page 6-25</a>
<b>Color Selection</b>	Select the color mode setting.	<a href="#">page 6-14</a>
<b>Encrypted PDF</b>	Enter the preassigned password to print the PDF data.	<a href="#">page 6-34</a>
<b>JPEG/TIFF Print</b>	Select the image size when printing JPEG or TIFF files.	<a href="#">page 6-35</a>
<b>XPS FitTo Page</b>	Reduces or enlarges the image size to fit to the selected paper size when printing XPS file.	<a href="#">page 6-35</a>

# Functions

On pages that explain a convenient function, the modes in which that function can be used are indicated by icons.

Printing:   

Sending: 

Storing: 

## Original Size

Specify the original size to be scanned.

Item	Description
<b>A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom<sup>*1</sup></b>	Select from standard sizes and custom size.

\*1 For instructions on how to specify the custom original size, refer to the following:

➔ [Custom Orig. Size \(page 8-8\)](#)



### NOTE

Be sure to always specify the original size when using custom size original.

## Paper Selection

Copy

Print from  
BoxPrint from  
USB

Select the cassette or multi-purpose tray that contains the required paper size.

Select from [1] (Cassette 1) to [4] (Cassette 4) to use the paper contained in that cassette.

If **[Auto]** is selected, the paper matching the size of the original is selected automatically.



### NOTE

- Specify in advance the size and type of the paper loaded in the cassette.

➔ [Cassette 1 \(to 4\) Set. \(Cassette 1 \(to 4\) Settings\) \(page 8-11\)](#)

➔ [MP Tray Set. \(MP Tray Settings\) \(page 8-11\)](#)

- Cassettes 2 to 4 are displayed when the optional paper feeder is installed.

Before selecting **[MP Tray]**, you need to select **[MP Tray Set.]** and specify the paper size and media type. The available paper sizes and media types are shown in the table below.

Item	Value	Description
<b>Auto</b>		The paper matching the size of the original is selected automatically.
<b>Cassette 1 (to 4) *1</b>		Feed paper from cassette 1 (to 4).
<b>MP Tray</b>		Feed paper from the multi purpose tray.
<b>MP Tray Set.</b>		Before selecting <b>[MP Tray]</b> , you need to select <b>[MP Tray Set.]</b> and specify the paper size and media type.
<b>Standard Size</b>	A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom*2	Select from the standard sizes and custom size.
<b>Size Entry</b>	Set the sizes of <b>[Y]</b> (vertical). Metric: 148 to 356 mm (in 1 mm increments) Inch: 5.83 to 14.02" (in 0.01" increments)  Set the sizes of <b>[X]</b> (horizontal). Metric: 70 to 216 mm (in 1 mm increments) Inch: 2.76 to 8.50" (in 0.01" increments)	Enter the size not included in the standard size.*3 When you have selected <b>[Size Entry]</b> , use <b>[▲]</b> / <b>[▼]</b> or the numeric keys to set the sizes of "X" (horizontal) and "Y" (vertical).
<b>Media Type</b>	Plain (60 to 105 g/m <sup>2</sup> ), Transparency, Rough, Vellum (60 to 105 g/m <sup>2</sup> ), Labels, Recycled, Preprinted*4, Bond, Cardstock, Color, Prepunched*4, Letterhead*4, Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1 to 8*4	Select the media type. Displayed after <b>[Standard Size]</b> or <b>[Size Entry]</b> is set in <b>[MP Tray Set.]</b> .

\*1 Cassette 2 to Cassette 4 are displayed when the optional paper feeder is installed.

\*2 For instructions on how to specify the custom paper sizes, refer to the following:

➔ [Custom PaperSize \(page 8-9\)](#)

\*3 The input units can be changed in System Menu.

➔ [Measurement \(page 8-15\)](#)

\*4 For instructions on how to specify the custom paper types 1 to 8, refer to the following:

➔ [Media Type Setting \(page 8-12\)](#)

To print on preprinted or prepunched paper or on letterhead, refer to the following:

➔ [SpecialPaper Act. \(page 8-10\)](#)

**NOTE**

- You can conveniently select in advance the size and type of paper that will be used often and set them as default.

➔ [MP Tray Set. \(MP Tray Settings\) \(page 8-11\)](#)

- If the specified size of paper is not loaded in the paper source cassette or multi purpose tray, a confirmation screen appears. Load the required paper in the multi purpose tray and select **[OK]** to start copying.

## Orig. Orientation (Original Orientation)







Select the orientation of the original document top edge to scan correct direction.

To use any of the following functions, the document's original orientation must be set.

- Duplex
- Combine
- Duplex (2-sided Original)

Select original orientation from **[Top Edge on Top]** or **[Top Edge on Left]**.

Item	Image	
<b>Top Edge on Top</b>	 <p data-bbox="584 1144 676 1173">Original</p>	 <p data-bbox="903 1144 1129 1173">Original orientation</p>
<b>Top Edge on Left</b>	 <p data-bbox="584 1402 676 1431">Original</p>	 <p data-bbox="903 1402 1129 1431">Original orientation</p>

**NOTE**

The default setting for Original Orientation can be changed.

➔ [Original Orientation \(page 8-13\)](#)

## Mixed Size Originals




Scans all sheets in the document processor, even if they are of different sizes.

(Value: [Off] / [On])

### Supported Combinations of Originals

Legal and Letter (Folio and A4)



## Collate



Offsets the output by page or set.

(Value: [Off] / [On])



## Density



Adjust density.

Adjust density selecting [-4] (Lighter) to [+4] (Darker).



## Original Image



Select original image type for best results.

### Copying

In each setting, if you want to bring out text or lines marked with a highlighter pen, select [**Highlight**] and then [**On**]. The color of the highlighter pen will be reproduced as much as possible.

Item	Description
<b>Text+Photo</b> <sup>*1</sup>	Best for mixed text and photo documents.
<b>Photo</b>	Best for photos taken with a camera.
<b>Text</b>	Best for documents that are mostly text.
<b>Map</b>	Best for graphics and maps.
<b>Printed Document</b>	Best for documents printed on this machine originally.

\*1 If gray text is not printed completely using [**Text + Photo**], selecting [**Text**] may improve the result.

### Printing/Sending/Storing

Item	Description
<b>Text+Photo</b>	Best for mixed text and photo documents.
<b>Photo</b>	Best for photos taken with a camera.
<b>Text</b>	Best for documents that are mostly text.
<b>For OCR</b> <sup>*1</sup>	Scanning produces an image that is suitable for OCR.
<b>Light Text/Fine Line</b>	Clearly reproduces faint characters written in pencil, etc., and thin lines on map originals or diagrams.

\*1 This function is only available when "Color Selection" is set to [**Black & White**]. For details, refer to the following:

➔ [Color Selection \(page 6-14\)](#)


## EcoPrint



EcoPrint saves toner when printing.

Use this function for test prints or any other occasion when high quality print is not required.

(**Value:** [**Off**] / [**On**])



## Color Selection



Select the color mode setting.

### Copying

Item	Description
<b>Auto Color</b>	Automatically recognizes whether documents are color or black and white.
<b>Full Color</b>	Prints documents in full color.
<b>Black &amp; White</b>	Prints documents in black and white.

### Printing

Item	Description
<b>Full Color</b>	Prints documents in full color.
<b>Black &amp; White</b>	Prints documents in black and white.

### Sending/Storing

Item	Description
<b>Auto (Color/Gray)</b>	Automatically recognizes whether the document is color or black and white, and scan color documents in Full Color and black and white documents in Grayscale.
<b>Auto (Color/B &amp; W)</b>	Automatically recognizes whether the document is color or black and white, and scan color documents in Full Color and black and white documents in Black and White.
<b>Full Color</b>	Scans the document in full color.
<b>Grayscale</b>	Scans the document in grayscale. Produces a smooth, detailed image.
<b>Black &amp; White</b>	Scans the document in black and white.

## Color Balance

Copy

Adjust the strength of cyan, magenta, yellow, and black.

Example:

Less Magenta



Original



More Magenta



Item		Value	Description
Off			
On	Cyan	-5 to 5	Select the [▲] or [▼] key to select the intensity of the color. A large negative value makes the color weaker, and a large positive value makes the color stronger.
	Magenta		
	Yellow		
	Black		



### NOTE

This feature is used with full color and auto color copying.



## Sharpness

Copy

Send

Scan to  
USB

Adjusts the sharpness of image outlines.

When copying penciled originals with rough or broken lines, clear copies can be taken by adjusting sharpness toward "Sharpen". When copying images made up of patterned dots such as magazine photos, in which moire<sup>\*1</sup> patterns appear, edge softening and weakening of the moire effect can be obtained by setting the sharpness toward "Blur".


Less Sharp



Original



More Sharp



Item	Description
1 to 3 (Sharpen)	Emphasizes the image outline.
-1 to -3 (Blur)	Blurs the image outline. Can weaken a Moire <sup>*1</sup> effect.

\*1 Patterns that are created by irregular distribution of halftone dots.

## Contrast

Copy

Send

Scan to  
USB

You can adjust the contrast between light and dark areas of the image.


Lower



Original



Higher



Item	Description
1 to 4 (Higher)	Increases the sharpness of colors.
-1 to -4 (Lower)	Creates smoother colors.

## Background Density Adj. (Background Density Adjustment)

Copy

Send

Scan to  
USB

Removes dark background from originals, such as newspapers.

This feature is used with full color and auto color. Background Density Adjustment is disabled if Auto Color detects black and white originals.

If the ground color is obtrusive, select [**Auto**]. If [**Auto**] does not remove the ground color, select [**Manual**] and adjust the density of the ground color.

Item	Description
<b>Off</b>	Does not adjust the ground color.
<b>Auto</b>	Automatically adjusts the background density based on the original.
<b>Manual</b>	Select [ <b>1</b> ] to [ <b>5</b> ] (Lighter - Darker) to adjust the background density manually.

## Saturation

Copy

Adjust the color saturation of the image.

Grayish



Results in paler color.

Original



Vivid



Results in more vivid color.



### NOTE

This feature is used with full color and auto color. Saturation is disabled if Auto Color detects black and white originals.


Item	Description
<b>-1 to -3 (Grayish)</b>	Results in paler color.
<b>1 to 3 (Vivid)</b>	Results in more vivid color.

## Prevent Bleed-t (Prevent Bleed-thru)



Hides background colors and image bleed-through when scanning thin original.

(Value: [Off] / [On])



## Zoom




Adjust the zoom to reduce or enlarge the image.

### Copying

The following zoom options are available.

#### Auto

Adjusts the image to match the paper size.



#### Standard Zoom

Reduces or enlarges at preset magnifications.

Model	Zoom Level (Original Copy)		Model	Zoom Level (Original Copy)	
Metric Models	400%	90% FOL >> A4	Inch Models	400%	78% LGL >> LTR
	200%	86% A4 >> B5		200%	64% LTR >> STMT
	141% A5 >> A4	70% A4 >> A5		129% STMT >> LTR	50%
	115% B5 >> A4	50%		100%	25%
	100%	25%			


#### Others

Reduces or enlarges at magnifications other than the Standard Zoom.

Model	Zoom Level (Original Copy)		Model	Zoom Level (Original Copy)	
Metric Models	129% STMT >> LTR		Inch Models	141% A5 >> A4	86% A4 >> B5
	78% LGL >> LTR			115% B5 >> A4	70% A4 >> A5
	64% LTR >> STMT			90% FOL >> A4	

## Zoom Entry

Manually reduces or enlarges the original image in 1% increments between 25% and 400%. Use the numeric keys or select [▲] or [▼] to enter the any magnification.



## Sending/Storing

Item	Description
100%	Reproduces the original size.
Auto	Reduces or enlarges original to sending/storing size.



### NOTE

To reduce or enlarge the image, select the paper size, sending size, or storing size.

- ➔ [Paper Selection \(page 6-10\)](#)
- [Sending Size \(page 6-27\)](#)
- [Storing Size \(page 6-34\)](#)


# Combine



Combines 2 or 4 original sheets into 1 printed page.

You can select the page layout and the type of boundary lines around the pages.

The following types of the boundary lines are available.



Select **[2 in 1]** or **[4 in 1]**, select **[Detail]**, and configure the function.

Item	Value	Description	
<b>Off</b>	—	Disables the function.	
<b>2 in 1</b>	—	Select the <b>[OK]</b> key to copy the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>	
	<b>2 in 1 Layout</b>	L to R T to B, R to L	Select the page layout of scanned originals, and select the <b>[OK]</b> key.
	<b>Border Line</b>	None, Solid Line, Dotted Line, Positioning Mark	Select the page boundary line, and select the <b>[OK]</b> key.
	<b>Orig. Orientation</b>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction. Choose orientation of the originals, either <b>[Top Edge on Top]</b> or <b>[Top Edge on Left]</b> . Then select the <b>[OK]</b> key.
<b>4 in 1</b>	—	Select the <b>[OK]</b> key to copy the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>	
	<b>4 in 1 Layout</b>	Right then Down, Down then Right, Left then Down, Down then Left	Select the page layout of scanned originals, and select the <b>[OK]</b> key.
	<b>Border Line</b>	None, Solid Line, Dotted Line, Positioning Mark	Select the page boundary line, and select the <b>[OK]</b> key.
	<b>Orig. Orientation</b>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction. Choose orientation of the originals, either <b>[Top Edge on Top]</b> or <b>[Top Edge on Left]</b> . Then select the <b>[OK]</b> key.

Layout image

Item	Image	Image
2 in 1	L to R/T to B	
	R to L	
4 in 1	Right then Down	
	Left then Down	
	Down then Right	
	Down then Left	

**NOTE**

- The paper sizes supported in Combine mode are A4, A5, B5, Folio, 216 × 340 mm, Letter, Legal, Statement, Oficio II, and 16K.
- When placing the original on the platen, be sure to copy the originals in page order.

# Duplex


Copy

Print from  
BoxPrint from  
USB


Produces two-sided copies. You can also create single-sided copies from two-sided originals.

The following modes are available.

## One-sided to Two-sided




Produces two-sided copies from one-sided originals. In case of an odd number of originals, the back side of the last copy will be blank.



The following binding options are available.

- A Original Left/Right to Binding Left/Right: Images on the second sides are not rotated.
- B Original Left/Right to Binding Top: Images on the second sides are rotated 180 degrees. Copies can be bound on the top edge, facing the same orientation when turning the pages.

## Two-sided to One-sided




Copies each side of a two-sided original onto two individual sheets.

The following binding options are available.

- Binding Left/Right: Images on the second sides are not rotated.
- Binding Top: Images on the second sides are rotated 180 degrees.

## Two-sided to Two-sided



Produces two-sided copies from two-sided originals.

### NOTE

The paper sizes supported in Two-sided to Two-sided mode are A4, B5, A5, Legal, Letter, Executive, Statement, Oficio II, 216 × 340 mm, Folio, ISO B5, and 16K.

## Copying

Prints 1-sided originals to 2-sided, or 2-sided originals to 1-sided. Select the binding orientation for original and finished documents.

Item	Value	Description
<b>1-sided&gt;&gt;1-sided</b>	—	Disables the function.
<b>1-sided&gt;&gt;2-sided</b>	—	Select the <b>[OK]</b> key to copy the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Finish. Binding</b>	Left/Right, Top	Select <b>[Detail]</b> to display the <b>[Finish. Binding]</b> screen. Select the binding orientation of copies, and select the <b>[OK]</b> key.
<b>Orig. Orientation</b>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction. Choose orientation of the originals, either <b>[Top Edge on Top]</b> or <b>[Top Edge on Left]</b> . Then select the <b>[OK]</b> key.
<b>2-sided&gt;&gt;1-sided</b>	—	Select the <b>[OK]</b> key to copy the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Orig. Binding</b>	Left/Right, Top	Select <b>[Detail]</b> to display the <b>[Orig. Binding]</b> screen. Select the binding orientation of originals, and select the <b>[OK]</b> key.
<b>Orig. Orientation</b>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction. Choose orientation of the originals, either <b>[Top Edge on Top]</b> or <b>[Top Edge on Left]</b> . Then select the <b>[OK]</b> key.
<b>2-sided&gt;&gt;2-sided</b>	—	Select the <b>[OK]</b> key to copy the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Orig. Binding</b>	Left/Right, Top	Select <b>[Detail]</b> to display the <b>[Orig. Binding]</b> screen. Select the binding direction of originals, and select the <b>[OK]</b> key.
<b>Finish. Binding</b>	Left/Right, Top	Select the binding orientation of copies, and select the <b>[OK]</b> key.
<b>Orig. Orientation</b>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction. Choose orientation of the originals, either <b>[Top Edge on Top]</b> or <b>[Top Edge on Left]</b> . Then select the <b>[OK]</b> key.

When placing the original on the platen, consecutively replace each original and press the **[Start]** key.

After scanning all originals, select **[Finish Scan]** to start copying.

## Printing

Print a document on both sides of the paper.

Item	Value	Description
<b>1-sided</b>	—	Disables the function.
<b>2-sided</b>	—	Select the <b>[OK]</b> key to print a 2-sided document with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Finish. Binding</b>	Left/Right, Top	Select <b>[Detail]</b> to display the <b>[Finish. Binding]</b> screen. Select the binding orientation of copies, and select the <b>[OK]</b> key.




## Continuous Scan



Scans a large number of originals in separate batches and then produce as one job.

Originals will be scanned continuously until you select **[End Scan]**.

(Value: **[Off]** / **[On]**)



## Job Finish Notice



Sends E-mail notice when a job is complete.

Users can be notified of the completion of a job while working at a remote desk, saving the time spent waiting beside the machine to finish.

### NOTE

PC should be configured in advance so that E-mail can be used.

➔ [Command Center RX \(page 2-38\)](#)

E-mail can be sent to a single destination.

Item		Description
<b>Off</b>		Disables the function.
<b>On</b>	<b>Address Book</b>	Select the notification destination from the Address Book or External Address Book. Select the destination on the Address Book or Ext Address Book screen, then select the <b>[OK]</b> key.
	<b>Address Entry</b>	Enter E-mail address directly. Enter the address (up to 128 characters) and select the <b>[OK]</b> key.

## File Name Entry



Adds a file name.

Additional information such as job number and date and time can also be set. You can check a job history or job status using the file name, date and time, or job number specified here.

Enter the file name (up to 32 characters), and select the **[OK]** key.

To add date and time, select **[Date]** and the **[OK]** key. To add job number, select **[Job No.]** and the **[OK]** key. To add both, select **[Job No. + Date]** or **[Date + Job No.]** and the **[OK]** key.

## Print Override



Suspends the current job and gives a new job top priority.

The suspended job resumes after the other job is finished.

(Value: [Off] / [On])

### NOTE

- This function is not available if current job was an override.
- Print override may not be available depending on the status of the current print job and memory usage.

## Quiet Mode



Lower print and scan speed for quiet processing.

Select this mode when the running noise is uncomfortable.

It is possible to set the use of Quiet Mode for each function, such as copying and sending.

(Value: [Off] / [On])

### NOTE

- The processing speed will be slower than normal when in Quiet Mode.
- This cannot be used when [Prohibit] is set for "Each Job".

➔ [Each Job \(page 8-34\)](#)

## Skip Blank Page



When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.

When set to [High], the level at which blank paper is recognized is higher.

The machine detects blank pages, saving unnecessary printing without the need to check for blank pages in the document.

Select [On], [Level], and then [Low], [Middle] or [High].

### NOTE

The originals with punched holes or originals printed on a colored substrate may not be recognized as blank pages.

## Duplex (2-sided Original)



Send

Scan to  
USB

Select the type and orientation of the binding based on the original.

Item	Value	Description
1-sided	—	Disables the function.
2-sided	—	Select the <b>[OK]</b> key to scan the original with the default setting. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
	Orig. Binding	Left/Right, Top Select <b>[Detail]</b> to display the <b>[Orig. Binding]</b> screen. Select the binding direction of originals, and select the <b>[OK]</b> key.
	Orig. Orientation	Top Edge Top, Top Edge Left Select the orientation of the original document top edge to scan correct direction, and select the <b>[OK]</b> key.

### Sample image

Value		Image
2-sided	Binding Left/Right	
	Binding Top	

## Sending Size


 Send

Select size of image to be sent.

Item	Description
Same as OrigSize	Send an image the same size as the original.
A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2	Select from standard sizes.

### Relationship between Original Size, Sending Size, and Zoom

[Original Size \(page 6-9\)](#), Sending Size, and [Zoom \(page 6-18\)](#) are related to each other. For details, see the table below.

Original size and sending size are	the same	different
<a href="#">Original Size (page 6-9)</a>	Specify as necessary.	Specify as necessary.
<b>Sending Size</b>	Select [ <b>Same as Original Size</b> ].	Select the desired size.
<a href="#">Zoom (page 6-18)</a>	Select [ <b>100%</b> ] (or [ <b>Auto</b> ]).	Select [ <b>Auto</b> ].



#### NOTE

When you specify the sending size that is different from the original size, and select the zoom of [**100%**], you can send the image as the actual size (No Zoom).

## File Format




Specify the image file format. Image quality level can also be adjusted.

Select the file format from [PDF], [TIFF], [XPS], [OpenXPS], [JPEG] and [High Comp. PDF].

When the color mode in scanning has been selected for Grayscale or Full Color, set the image quality.

If you selected [PDF] or [High Comp. PDF], you can specify encryption or PDF/A settings.



Item	Value	Description
PDF	—	Select the [OK] key to save or send a PDF file. The image quality and PDF/A settings will be the default settings. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
	Image Quality	1 Low(High Comp) to 5 High(Low Comp) Select [Detail] to display the [Image Quality] screen. Select the image quality and select the [OK] key.
	PDF/A	Off, PDF/A-1a, PDF/A-1b Select PDF/A-1 format type and select the [OK] key.
	Encryption	Off, On Set the PDF encryption and then select the [OK] key. If [On] is selected, refer to the following: ➔ <a href="#">PDF Encryption Functions (page 6-30)</a>
TIFF	—	Select the [OK] key to save or send a TIFF file. The Image Quality settings will be the default values. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
	Image Quality	1 Low(High Comp) to 5 High(Low Comp) Select [Detail] to display the [Image Quality] screen. Select the image quality and select the [OK] key.
XPS	—	Select the [OK] key to save or send a XPS file. The Image Quality settings will be the default values. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
	Image Quality	1 Low(High Comp) to 5 High(Low Comp) Select [Detail] to display the [Image Quality] screen. Select the image quality and select the [OK] key.
OpenXPS	—	Select the [OK] key to save or send a OpenXPS file. The Image Quality settings will be the default values. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
	Image Quality	1 Low(High Comp) to 5 High(Low Comp) Select [Detail] to display the [Image Quality] screen. Select the image quality and select the [OK] key.

Item	Value	Description
<b>JPEG</b>	—	Select the <b>[OK]</b> key to save or send a JPEG file. The Image Quality settings will be the default values. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Image Quality</b>	1 Low(High Comp) to 5 High(Low Comp)	Select <b>[Detail]</b> to display the <b>[Image Quality]</b> screen. Select the image quality and select the <b>[OK]</b> key.
<b>High Comp. PDF</b>	—	Select the <b>[OK]</b> key to save or send a High Comp. PDF file. The image quality and PDF/A settings will be the default settings. For the default settings, refer to the following: ➔ <a href="#">Function Defaults (page 8-13)</a>
<b>Image Quality</b>	Comp. Priority, Standard, Quality Priority	Select <b>[Detail]</b> to display the <b>[Image Quality]</b> screen. Select the image quality and select the <b>[OK]</b> key.
<b>PDF/A</b>	Off, PDF/A-1a, PDF/A-1b	Select PDF/A-1 format type and select the <b>[OK]</b> key.
<b>Encryption</b>	Off, On	Set the PDF encryption and then select the <b>[OK]</b> key. If <b>[On]</b> is selected, refer to to the following: ➔ <a href="#">PDF Encryption Functions (page 6-30)</a>

**NOTE**

- You can use PDF encryption functions.
- ➔ [PDF Encryption Functions \(page 6-30\)](#)
- If encryption is enabled, PDF/A settings cannot be specified.

## PDF Encryption Functions

If you have selected PDF or High Comp. PDF for file format, you can restrict the access level for displaying, printing, and editing PDF's by assigning a secure password.

Items that can be set vary depending on the setting selected in [**Compatibility**].

### When [Acrobat3.0&Later] is selected in "Compatibility"

Item		Value	Description
Password	Open Document	Off, On	Enter the password to open the PDF file. Select [ <b>On</b> ] and select the [ <b>OK</b> ] key. Enter a password (up to 256 characters) and then select the [ <b>OK</b> ] key. Enter the password again for confirmation, and select the [ <b>OK</b> ] key.
	Edit/Print Doc.	Off, On	Enter the password to edit the PDF file. Select [ <b>On</b> ] and select the [ <b>OK</b> ] key. Enter a password (up to 256 characters) and then select the [ <b>OK</b> ] key. Enter the password again for confirmation, and select the [ <b>OK</b> ] key.
	Printing Allowed	Not Allowed, Allowed	Restricts printing of the PDF file. Then select the [ <b>OK</b> ] key.
	Changes Allowed	Not Allowed, Commenting, Page Layout, Any Changes	Restricts editing of the PDF file. Select from the following restrictions then select the [ <b>OK</b> ] key. Not Allowed: Disables the change to the PDF file. Commenting: Can only add commenting. Page Layout: Can change the page layout except extracting the pages of the PDF file. Any Changes: Can conduct all operations except extracting the pages of the PDF file.
	Copying Contents	Disable, Enable	Restricts the copying of text and objects on the PDF file. Then select the [ <b>OK</b> ] key.

## When [Acrobat5.0&amp;Later] is selected in "Compatibility"

Item		Value	Description
<b>Password</b>	<b>Open Document</b>	Off, On	Enter the password to open the PDF file. Select [ <b>On</b> ] and select the [ <b>OK</b> ] key. Enter a password (up to 256 characters) and then select the [ <b>OK</b> ] key. Enter the password again for confirmation, and select the [ <b>OK</b> ] key.
	<b>Edit/Print Doc.</b>	Off, On	Enter the password to edit the PDF file. Select [ <b>On</b> ] and select the [ <b>OK</b> ] key. Enter a password (up to 256 characters) and then select the [ <b>OK</b> ] key. Enter the password again for confirmation, and select the [ <b>OK</b> ] key.
	<b>Printing Allowed</b>	Not Allowed, Allowed (Low Res.), Allowed	Restricts printing of the PDF file. Select from the following restrictions then select the [ <b>OK</b> ] key. Not Allowed: Disables the printing of PDF file. Allowed (Low Res.): Can print the PDF file only in low resolution. Allowed: Can print the PDF file in original resolution.
	<b>Changes Allowed</b>	Not Allowed, Ins./Del./Rotat, Commenting, Any Changes	Specifically limit the operation. Select from the following restrictions then select the [ <b>OK</b> ] key. Not Allowed: Disables the change to the PDF file. Ins./Del./Rotat: Can only insert, delete, and rotate the pages of the PDF file. Commenting: Can only add commenting. Any Changes: Can conduct all operations except extracting the pages of the PDF file.
	<b>Copying Contents</b>	Disable, Enable	Restricts the copying of text and objects on the PDF file. Then select the [ <b>OK</b> ] key.




## File Separation



Creates several files by dividing scanned original data page by page, and sends the files.

(Value: [Off] / [Each Page])

Select [Each Page] to set File Separation.



### NOTE


A three-digit serial number such as "abc\_001.pdf, abc\_002.pdf..." is attached to the end of the file name.

## Scan Resolution



Select fineness of scanning resolution.

(Value: [200 × 100dpi Norm] / [200 × 200dpi Fine] / [200 × 400dpi S.Fin] / [300 × 300dpi] / [400 × 400dpi U.Fin] / [600 × 600dpi])



### NOTE


The larger the number, the better the image resolution. However, better resolution also means larger file sizes and longer send times.

## Subject/Body



Adds subject and body when sending a document.

Select [Subject] / [Body] to enter the E-mail subject/body.



### NOTE

The subject can include up to 60 characters, and the body can include up to 500 characters.

## FTP Encrypted TX

Send

Encrypts images when sending via FTP.

Encryption secures the document transmission.

(Value: [Off] / [On])



### NOTE

Click [**Security Settings**], and then [**Network Security**] in the Command Center RX. Be sure that "SSL" of Secure Protocol Settings is "On" and one or more effective encryption are selected in Client side settings.

➔ [Command Center RX User Guide](#)

## Del. after Print (Delete after Printed)

Print from  
Box

Automatically deletes a document from the box once printing is complete.

(Value: [Off] / [On])

## Storing Size



Select size of image to be stored.

Item	Description
Same as OrigSize	Store an image the same size as the original.
A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2	Select from standard sizes.

### Relationship between Original Size, Storing Size, and Zoom

[Original Size \(page 6-9\)](#), Storing Size, and [Zoom \(page 6-18\)](#) are related to each other. For details, see the table below.

Original Size and the size you wish to store as are	the same	different
<a href="#">Original Size (page 6-9)</a>	Specify as necessary.	Specify as necessary.
Storing Size	Select [ <b>Same as Original Size</b> ].	Select the desired size.
<a href="#">Zoom (page 6-18)</a>	Select [ <b>100%</b> ] (or [ <b>Auto</b> ]).	Select [ <b>Auto</b> ].



#### NOTE

When you select Storing Size that is different from Original Size, and select the Zoom [**100%**], you can store the image as the actual size (No Zoom).

## Encrypted PDF



Enter the preassigned password to print the PDF data.

Enter the Password, and select [**OK**].



#### NOTE

For details on entering the password, refer to the following:


➔ [Character Entry Method \(page 11-11\)](#)

## JPEG/TIFF Print



Select the image size when printing JPEG or TIFF files.

(Value: [Paper Size] / [Image Resolution] / [Print Resolution])




Item	Description
Paper Size	Fits the image size to the selected paper size.
Image Resolution	Prints at resolution of the actual image.
Print Resolution	Fits the image size to the print resolution.

## XPS FitTo Page



Reduces or enlarges the image size to fit to the selected paper size when printing XPS file.

(Value: [Off] / [On])



# 7 Status/Job Cancel

This chapter explains the following topics:

Checking Job Status .....	7-2
Checking Job History .....	7-8
Sending the Log History .....	7-12
Job Operation .....	7-13
Pause and Resumption of Jobs .....	7-13
Canceling of Jobs .....	7-13
Device/Communication .....	7-14
Checking the Remaining Amount of Toner and Paper (Paper/Supplies) .....	7-15

# Checking Job Status

Check the status of jobs being processed or waiting to be printed.

## Available Status Screens

The processing and waiting statuses of jobs are displayed as a list on the message display in four different screens - Printing Jobs, Sending Jobs, Storing Jobs, and Scheduled Jobs.

The following job statuses are available.

Status Display	Job status to be displayed
Print Job Status	<ul style="list-style-type: none"> <li>• Copy</li> <li>• Printer</li> <li>• FAX reception</li> <li>• E-mail reception</li> <li>• Printing from Document Box</li> <li>• Printing data from removable memory</li> <li>• Job Report/List</li> </ul>
Send Job Status	<ul style="list-style-type: none"> <li>• FAX transmission</li> <li>• E-mail</li> <li>• Folder transmission</li> <li>• Application</li> <li>• Multiple destination</li> </ul>
Store Job Status	<ul style="list-style-type: none"> <li>• Scan</li> <li>• FAX</li> <li>• Printer</li> </ul>
Scheduled Job	<ul style="list-style-type: none"> <li>• Sending Job FAX using Delayed transmission</li> </ul>

## Displaying Status Screens

### 1 Display the screen.

[Status/Job Cancel] key > [▲] [▼] key > [Print Job Status], [Send Job Status], [Store Job Status] or [Scheduled Job] > [OK] key

### 2 Select the job you want to check.

1 Select the job you want to check, and [Menu].

#### NOTE

You can show the job statuses of all users, or only the statuses of your own jobs.

➔ [Disp. Status/Log \(page 8-17\)](#)

This setting can also be changed from Command Center RX.

➔ [Command Center RX User Guide](#)

**2** [▲] [▼] key > [Detail] > [OK] key

Jobs Detail Status is displayed.



**NOTE**


- If a FAX job is selected in [Send Job Status] then [PriorityOverride] is displayed. Select [PriorityOverride] and select the [OK] key to suspend the current job and gives the selected job top priority.
- For [Scheduled Job], [Start Now] is displayed. Select [Start Now] and select the [OK] key to send the selected job immediately.

**3 Check the status.**

Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.

- ➔ [Print Job Status \(page 7-4\)](#)
- [Send Job Status \(page 7-5\)](#)
- [Store Job Status \(page 7-6\)](#)
- [Scheduled Job Status \(page 7-7\)](#)



**Print Job Status**

Item	Description
<b>Status</b>	Status of job <b>[Processing]</b> : The status before starting to print. <b>[Pause]</b> : Pausing print job or error <b>[Canceling]</b> : Canceling the job <b>[----]</b> : The job is finished.
<b>Accepted Time</b>	Accepted Time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. Select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[Copy]</b> : Copy job <b>[FAX]<sup>*1</sup></b> : FAX reception <b>[Box]</b> : Job from Document Box <b>[Printer]</b> : Printer job <b>[Report]</b> : Report/List <b>[E-mail]</b> : E-mail reception <b>[USB]</b> : Data from removable memory
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Page and Copy</b>	<ul style="list-style-type: none"> <li>• Number of pages printed</li> <li>• Number of copies printed / Total number of copies to be printed</li> </ul>
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Color/B &amp; W]</b> <b>[Full Color]</b> <b>[Black &amp; White]</b> <b>[Auto Color]</b> <b>[Mixed]</b>
<b>Sender Info.</b>	The sender information is displayed. <b>When receiving a FAX</b> If the name of the sender is provided when receiving a FAX, the name is displayed. If only the number of the sender is provided, the number is displayed. If there is no information about the sender or if a FAX is not received, [----] appears. <b>For E-mails</b> The E-mail address is displayed. In other cases, [----] is displayed.  <b>NOTE</b> When the sender information is displayed in a short form, select <b>[Detail]</b> to see the complete sender Information. Select the <b>[OK]</b> key to return to the previous screen.

\*1 Displayed only on products with the fax function installed.




**Send Job Status**

Item	Description
<b>Status</b>	Status of job <b>[Processing]</b> : The status before starting sending such as during scanning originals <b>[Pause]</b> : Pausing the job <b>[Canceling]</b> : Canceling the job
<b>Accepted Time</b>	Accepted Time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. Select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[FAX]<sup>*1</sup></b> : Sending Job FAX <b>[E-mail]</b> : Sending Job E-mail <b>[Folder]</b> : Sending Job Folder (SMB/FTP) <b>[Application]</b> : Sending Job Application <b>[Multi]</b> : Multi Sending
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Color/B &amp; W]</b> <b>[Full Color]</b> <b>[Black &amp; White]</b> <b>[Grayscale]</b> <b>[Mixed]</b> <b>[Auto (Color/Gray)]</b> <b>[Auto (Color/B &amp; W)]</b>
<b>Destination</b>	The destination is displayed. <b>If there is one destination:</b> Destination (Either destination name, FAX number, E-mail address, or server name)  <b>NOTE</b> When the destination is displayed in a short form, select <b>[Detail]</b> to see the complete destination. Select the <b>[OK]</b> key to return to the previous screen. <b>If there are multiple destinations:</b> <b>[Broadcast]</b> is displayed. When <b>[List]</b> is selected, all destinations are displayed. Select <b>[Exit]</b> to return to the original screen.  <b>NOTE</b> When the destination in a short form, select the destination and then select the <b>[OK]</b> key to see the complete destination. Select the <b>[OK]</b> key to return to the previous screen.

\*1 Displayed only on products with the fax function installed.

**Store Job Status**

Item	Description
<b>Status</b>	Status of job <b>[Processing]</b> : The status before starting sending such as during scanning originals <b>[Canceling]</b> : Canceling the job
<b>Accepted Time</b>	Accepted Time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. Select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[FAX]<sup>*1</sup></b> : Storing Job FAX <b>[SCAN]</b> : Storing Job Scan <b>[Printer]</b> : Storing Job Printer
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Color/B &amp; W]</b> <b>[Full Color]</b> <b>[Black &amp; White]</b> <b>[Grayscale]</b> <b>[Mixed]</b> <b>[Auto (Color/Gray)]</b> <b>[Auto (Color/B &amp; W)]</b>
<b>Sender Info.</b>	The sender information is displayed. <b>When receiving a FAX</b> If the name of the sender is provided when receiving a FAX, the name is displayed. If only the number of the sender is provided, the number is displayed. If there is no information about the sender or if a FAX is not received, [----] appears. In other cases, [----] is displayed.  <b>NOTE</b> When the sender Information is displayed in a short form, select <b>[Detail]</b> to see the complete sender Information. Select the <b>[OK]</b> key to return to the previous screen.

\*1 Displayed only on products with the fax function installed.

**Scheduled Job Status**

Item	Description
<b>Status</b>	Status of job <b>[Waiting]:</b> Waiting Sending
<b>Start Time</b>	Time to start the scheduled job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. Select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[FAX]</b> is displayed.
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Black &amp; White]</b>
<b>Destination</b>	The destination is displayed. ➔ <a href="#">Destination (page 7-5)</a>

# Checking Job History

Check the history of completed jobs.



**NOTE**

Job history is also available by Command Center RX or KYOCERA Net Viewer from the computer.

- ➔ **Command Center RX User Guide**
- ➔ **KYOCERA Net Viewer User Guide**

## Available Job History Screens

The job histories are displayed separately in four screens - Printing Jobs, Sending Jobs, Storing Jobs, and FAX Jobs. The following job histories are available.

Screen	Job histories to be displayed
Print Job Log	<ul style="list-style-type: none"> <li>• Copy</li> <li>• Printer</li> <li>• FAX reception</li> <li>• E-mail reception</li> <li>• Printing from Document Box</li> <li>• Job Report/List</li> <li>• Printing data from removable memory</li> <li>• Application</li> </ul>
Send Job Log	<ul style="list-style-type: none"> <li>• FAX</li> <li>• E-mail</li> <li>• Folder</li> <li>• Application</li> <li>• Multiple destination</li> </ul>
Store Job Log	<ul style="list-style-type: none"> <li>• Scan</li> <li>• FAX</li> <li>• Printer</li> </ul>
FAX Job Log	➔ <b>FAX Operation Guide</b>

## Displaying Job History Screen

### 1 Display the screen.

[Status/Job Cancel] key > [▲] [▼] key > [Print Job Log], [Send Job Log], [Store Job Log] or [FAX Job Log] > [OK] key



#### NOTE

For [FAX Job Log], refer to the following:

➔ [FAX Operation Guide](#)

### 2 Select the job you want to check.

Select the job you want to check, and [Detail].

A job result icon is displayed on the extreme right of each job.

- : The job has been completed.
- : An error has occurred.
- : The job has been canceled.



#### NOTE

You can show the job log of all users, or only your own job log.

➔ [Disp. Status/Log \(page 8-17\)](#)

This setting can also be changed from Command Center RX.

➔ [Command Center RX User Guide](#)

### 3 Check the job history.

Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.

- ➔ [Print Job Log \(page 7-10\)](#)
- ➔ [Send Job Log \(page 7-11\)](#)
- ➔ [Store Job Log \(page 7-12\)](#)

**Print Job Log**

Item	Description
<b>Result</b>	Result of job [OK]: The job has been completed. [Error]: An error has occurred. [Cancel]: The job has been canceled.
<b>Accepted Time</b>	Accepted time of job
<b>End Time</b>	Completed time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select [Detail] to see the complete job name. Select the [OK] key to return to the previous screen.
<b>Job Type</b>	[Copy]: Copy job [FAX] <sup>*1</sup> : FAX reception [Box]: Job from Document Box [Printer]: Printer job [Report]: Report/List [E-mail]: E-mail reception [USB]: Data from removable memory
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Page and Copy</b>	<ul style="list-style-type: none"> <li>• Number of pages printed</li> <li>• Number of copies printed / Total number of copies to be printed</li> </ul>
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode [Color/B & W] [Full color] [Black & White] [Auto Color] [Mixed]
<b>Sender Info.</b>	The sender information is displayed. ➔ <a href="#">Sender Info. (page 7-4)</a>

\*1 Displayed only on products with the fax function installed.

**Send Job Log**

Item	Description
<b>Result</b>	Result of job <b>[OK]:</b> The job has been completed. <b>[Error]:</b> An error has occurred. <b>[Cancel]:</b> The job has been canceled.
<b>Accepted Time</b>	Accepted Time of job
<b>End Time</b>	Completed time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[E-mail]:</b> Sending Job E-mail <b>[Folder]:</b> Sending Job Folder (SMB/FTP) <b>[FAX]<sup>*1</sup>:</b> Sending Job FAX <b>[Application]:</b> Sending Job Application <b>[Multi]:</b> Multi Sending
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Color/B &amp; W]</b> <b>[Full Color]</b> <b>[Black &amp; White]</b> <b>[Grayscale]</b> <b>[Mixed]</b>
<b>Destination</b>	The destination is displayed. ➔ <a href="#">Destination (page 7-5)</a>

\*1 Displayed only on products with the fax function installed.



**NOTE**

If the login user name entry screen appears during operations, log in by referring to the following:

➔ [Login \(page 2-14\)](#)

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

**Store Job Log**

Item	Description
<b>Result</b>	Result of job <b>[OK]:</b> The job has been completed. <b>[Error]:</b> An error has occurred. <b>[Cancel]:</b> The job has been canceled.
<b>Accepted Time</b>	Accepted Time of job
<b>End Time</b>	Completed time of job
<b>Job Name</b>	When the job name in Job Name is displayed in a short form, select <b>[Detail]</b> to see the complete job name. Select the <b>[OK]</b> key to return to the previous screen.
<b>Job Type</b>	<b>[FAX]<sup>*1</sup>:</b> Storing Job FAX <b>[SCAN]:</b> Storing Job Scan <b>[Printer]:</b> Storing Job Printer
<b>User Name</b>	User Name for the executed job If user login administration is disabled, [----] appears.
<b>Original Pages</b>	Number of original pages
<b>Color/B &amp; W</b>	Color mode <b>[Color/B &amp; W]</b> <b>[Full Color]</b> <b>[Black &amp; White]</b> <b>[Grayscale]</b> <b>[Mixed]</b>
<b>Sender Info.</b>	The sender information is displayed. ➔ <a href="#">Sender Info. (page 7-6)</a>

\*1 Displayed only on products with the fax function installed.

## Sending the Log History

You can send the log history by E-mail. You can either send it manually as needed or have it sent automatically whenever a set number of jobs is reached.

➔ [Send History \(page 8-6\)](#)



# Job Operation

## Pause and Resumption of Jobs

Pause/resume all printing jobs in printing/waiting.

### 1 Display the screen.

Select the **[Status/Job Cancel]** key.

### 2 Select **[Pause]**.

Printing is paused.

When resuming the printing of jobs that have been paused, select **[Resume]**.



#### NOTE

If the **[Back]** key or other function key, such as the **[Copy]** key, is selected during Pause, "Resume paused jobs. Are you sure?" appears. If **[Yes]** is selected and then the **[OK]** key is selected, the job is resumed and the following screen appears. If **[No]** is selected and then the **[OK]** key is selected, the following screen appears while the job is paused.

## Canceling of Jobs

A job in printing/waiting status can be canceled.

### 1 Display the screen.

**[Status/Job Cancel]** key > **[▲]** **[▼]** key > **[Print Job Status]**, **[Send Job Status]**, **[Store Job Status]** or **[Scheduled Job]** > **[OK]** key

### 2 Cancel a job.

#### Print Job Status

1 Select the job to be canceled, and **[Menu]**.

2 **[▲]** **[▼]** key > **[Cancel Job]** > **[OK]** key > **[Yes]**



#### NOTE

When FAX reception job is selected, **[Cannot cancel FAX reception jobs.]** is displayed and the job cannot be canceled.

#### Send Job Status, Store Job Status or Scheduled Job Status

1 Select the job to be canceled, and **[Cancel]**.



#### NOTE

A job can be canceled by selecting **[Menu]**, selecting **[Cancel Job]** and then selecting the **[OK]** key.

2 Select **[Yes]**.

# Device/Communication

Configure the devices/lines installed or connected to this machine or check their status.

## 1 Display the screen.

Select the **[Status/Job Cancel]** key.

## 2 Check the status.

Select the items you want to check. Then, select the **[OK]** key to show the status of the selected device.

The items you can check are described below.

### "Scanner"

The status of an original scanning or the error information (paper jam, opened cover, etc.) is displayed.

### "Printer"

Error information such as paper jam, out of toner, or out of paper, and status such as waiting or printing are displayed.

### "FAX"

- The information such as sending/receiving and dialing is displayed.
- Select **[Line Off]** to cancel a fax in sending/receiving.

➔ **FAX Operation Guide**

### "USB Memory"

- The usage, capacity and free space of the external media connected to this machine are displayed.
- Select **[Remove]** to safely remove the external media.

### "SSD"

The status of the optional SSD is displayed.

### "USB Keyboard"

The status of the optional USB Keyboard is displayed.

### "Network"

The network connection status appears.

### "Option Network"

The connection status of the optional Network Interface Kit is displayed.

### "Wireless Network"

The connection status of the Wireless Network Interface Kit is displayed.

# Checking the Remaining Amount of Toner and Paper (Paper/Supplies)

Check the remaining amount of toner, and paper on the message display.

## 1 Display the screen.

Select the [Status/Job Cancel] key.

## 2 Check the status.

[▲] [▼] key > [Toner Status] or [Paper Status] > [OK] key

The items you can check are described below.

### "Toner Status"

The amount of toner remaining is shown in levels.

### "Paper Status"

The status of the source is displayed. Select the [▶] key to view the next source. Select the [◀] key to return to the previous screen.

# 8 Setup and Registration (System Menu)

This chapter explains the following topics:


System Menu .....	8-2
System Menu Settings .....	8-3
Report .....	8-5
User Property .....	8-6
Common Settings .....	8-7
Copy .....	8-20
Send .....	8-21
Document Box .....	8-22
FAX .....	8-23
Edit Destination .....	8-23
User/Job Account .....	8-23
Printer .....	8-24
System/Network .....	8-26
Adjust/Maint. ....	8-34

# System Menu

Configure settings related to overall machine operation.

Select the [**System Menu/Counter**] key to show the settings on the message display. Then, select from the settings displayed.

➔ [Operation Method \(page 2-12\)](#)



- 1 Displays the System Menu items.
- 2 Selects the item displayed or changes the numeric value.
- 3 Confirms the selected setting.
- 4 Cancels the current menu setting to return to the menu one level higher.



## NOTE

- In order to change settings that require administrator privileges, you must log in with administrator privileges. The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

- If function default settings have been changed, the [**Reset**] key can be selected in each function screen to immediately change the settings.

Refer to [System Menu Settings](#) on the following page and configure as needed.

## System Menu Settings

This section explains the functions that can be configured in System Menu. To configure the settings, select the item in System Menu and select the setting item. For details on each function, see the table below.

Item	Description	Reference Page
<b>Print Report</b>	Configure settings for printing reports and histories.	<a href="#">page 8-5</a>
<b>Admin Rpt Set.</b>		Refer to the <b>FAX Operation Guide</b> .
<b>Result Rpt Set.</b>		<a href="#">page 8-6</a>
<b>Job Log History</b>		<a href="#">page 8-6</a>
<b>Counter</b>	This counts the number of pages printed or scanned.	<a href="#">page 2-35</a>
<b>User Property</b>	Allows you to view information about logged in users and edit some of that information.	<a href="#">page 8-6</a>
<b>Cassette 1 (to 4) Set. (Cassette 1 (to 4) Settings)</b>	Select type of paper in Cassette 1 (to 4).	<a href="#">page 8-11</a>
<b>MP Tray Set. (MP Tray Settings)</b>	Select type of paper in multi purpose tray.	<a href="#">page 8-11</a>
<b>Language</b>	Select the language displayed on the message display.	<a href="#">page 8-7</a>
<b>Default Screen</b>	Select the screen appearing right after start-up (default screen).	<a href="#">page 8-7</a>
<b>Sound</b>	Set options for buzzer sound during the machine operations.	<a href="#">page 8-7</a>
<b>Function Defaults</b>	Defaults are the values automatically set after the warm-up is completed or the <b>[Reset]</b> key is selected.  Set the defaults for available settings such as copying and sending. Setting the frequently-used values as defaults makes subsequent jobs easier.	<a href="#">page 8-13</a>
<b>Preset Limit</b>	Restrict the number of copies that can be made at one time.	<a href="#">page 8-15</a>
<b>Error Handling</b>	Select whether to cancel or continue the job when error has occurred.	<a href="#">page 8-15</a>
<b>ColorToner Empty</b>	Select whether printing is prohibited or the Print in Black and White setting is used for printing once the color toner runs out.	<a href="#">page 8-15</a>
<b>Measurement</b>	Select inch or metric for the unit for paper dimensions.	<a href="#">page 8-15</a>
<b>TonerAlert Level</b>	Set the amount of remaining toner to notify the administrator when to order a toner when the toner is running low.	<a href="#">page 8-16</a>
<b>USB KeyboardType</b>	Select the type of USB keyboard that you want to use.	<a href="#">page 8-16</a>
<b>Format SSD</b>	Format an optional SSD.	<a href="#">page 8-16</a>
<b>Format SD Card</b>	Format an optional SD/SDHC memory card.	<a href="#">page 8-16</a>
<b>Disp. Status/Log</b>	Set the display method of the Status/Log.	<a href="#">page 8-17</a>
<b>Display Bright.</b>	Set the brightness of the message display.	<a href="#">page 8-7</a>
<b>Orig./Paper Set.</b>	Configure settings for originals.	<a href="#">page 8-8</a>
<b>Date Setting</b>	Configure settings related to the date and time.	<a href="#">page 8-17</a>
<b>Timer Setting</b>	Configure settings related to the time.	<a href="#">page 8-18</a>
<b>RAM Disk Mode</b>	A RAM disk can be created and its size can be set.	<a href="#">page 8-19</a>
<b>Optional Memory</b>	When optional memory is installed, select the memory allocation scheme based on the application in which you are using the equipment.	<a href="#">page 8-19</a>
<b>Login Operation</b>	Select the screen to enter the login user name and password when logging in.	<a href="#">page 8-20</a>

Item	Description	Reference Page
<b>Copy</b>	Configures settings for copying functions.	<a href="#">page 8-20</a>
<b>Send</b>	Configures settings for sending functions.	<a href="#">page 8-21</a>
<b>Document Box</b>	Configures settings related to the Custom Box, Job Box, Sub Address Box and Polling Box. ➔ <b>FAX Operation Guide</b>	<a href="#">page 8-22</a>
<b>FAX</b>	Configures settings for fax functions. ➔ <b>FAX Operation Guide</b>	—
<b>Edit Destination</b>	Configures Address Book and One Touch Key settings. Address Book: ➔ <a href="#">Adding a Destination (Address Book) (page 3-23)</a> One Touch Key: ➔ <a href="#">Adding a Destination on One Touch Key (One Touch Key) (page 3-29)</a>	<a href="#">page 8-23</a>
<b>User/Job Account</b>	Configures settings related to machine management. User Login: ➔ <a href="#">Overview of User Login Administration (page 9-2)</a> Job Accounting: ➔ <a href="#">Overview of Job Accounting (page 9-24)</a>	—
<b>Printer</b>	Printing from computers, settings are generally made on the application software screen. However, the following settings are available for configuring the defaults to customize the machine.	<a href="#">page 8-24</a>
<b>Network Setting</b>	Configures network settings.	<a href="#">page 8-26</a>
<b>Optional Network</b>	Configure settings for the optional Network Interface Kit.	<a href="#">page 8-29</a>
<b>Wireless Network</b>	Configure settings for the optional Wireless Network Interface Kit.	<a href="#">page 8-30</a>
<b>NW InterfaceSend</b>	Specify the network interface card to be used for the send function, the network authentication and connecting to external address book.	<a href="#">page 8-32</a>
<b>I/F Block Set.</b>	This allows you to protect this machine by blocking the interface with external devices such as USB hosts or optional interfaces.	<a href="#">page 8-32</a>
<b>Security Level</b>	The Security Level setting is primarily a menu option used by service personnel for maintenance work. There is no need for customers to use this menu.	—
<b>Restart</b>	Restart the CPU without turning the power switch off. Use this to deal with any unstable operation by the machine. (Same as the computer restart.)	<a href="#">page 8-33</a>
<b>Data Security</b>	Configure settings for data stored in the optional SSD and machine's memory.	<a href="#">page 8-33</a>
<b>Op Functions</b>	You can use the optional applications installed on this machine.	<a href="#">page 8-34</a>
<b>Adjust/Maint.</b>	Adjust printing quality and conduct machine maintenance.	<a href="#">page 8-34</a>





# Report

Print reports to check the machine settings and status.

Default settings for printing the result reports can also be configured.

## Report Print

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Report Print] > [OK] key

Item	Description
<p><b>Menu Map</b></p>	<p>Prints Menu Map to check the settings of the machine.</p> 
<p><b>Status Page</b></p>	<p>Prints the status page, allowing you to check the information including current settings, available memory space, and optional equipment installed.</p> 
<p><b>Font List</b></p>	<p>Prints the font list, allowing you to check the font samples installed in the machine.</p> 
<p><b>Opt NW Status</b></p>	<p>Prints the optional network status, allowing you to check the information including optional network interface firmware version, network address and protocol.</p> <p> <b>NOTE</b> This function is displayed when the optional Network Interface Kit or Wireless Network Interface Kit is installed.</p>



## Admin Rpt Set.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Admin Rpt Set.] > [OK] key

Configure settings for fax functions.

➔ [FAX Operation Guide](#)

## Result Rpt Set.

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Result Rpt Set.] > [OK] key


Item	Description
<b>Send Result</b>	Automatically print a report of transmission result when a transmission is complete.
<b>E-mail/Folder</b>	Automatically print a report of transmission result when E-mail or SMB/FTP transmission is complete. <b>Value: Off, On, Error Only</b>
<b>FAX<sup>*1</sup></b>	➔ <a href="#">FAX Operation Guide</a>
<b>CancelBeforeSend<sup>*2</sup></b>	Print a send result report if the job is canceled before being sent. <b>Value: Off, On</b>
<b>Dest. Info.<sup>*2</sup></b>	Select the Recipient Format for the send result report. <b>Value: Dest. or Name, Dest. and Name</b>
<b>FAX RX Result<sup>*1</sup></b>	➔ <a href="#">FAX Operation Guide</a>
<b>JobFinish Notice</b>	Attaches sent images to job finish notices. <b>Value: Do Not Attach Image, Attach SendImage</b>

\*1 Only on products with the fax function installed.

\*2 When "E-mail/Folder" and "FAX" are set to [Off], this function will not be displayed.

## Job Log History

[System Menu/Counter] key > [▲] [▼] key > [Report] > [OK] key > [▲] [▼] key > [Job Log History] > [OK] key

Item	Description
<b>Send History</b>	You can also send the log history to the specified destinations manually.
<b>Auto Sending</b>	This function automatically sends the log history to the specified destinations whenever a set number of jobs has been logged. <b>Value: Off, On</b>  <b>NOTE</b> If [On] is selected, specify the number of job histories. The setting range is 1 to 16.
<b>Destination</b>	Set the destination to which log histories are sent. Only E-mail address can be set.
<b>Subject</b>	Set the subject automatically entered when sending log histories by E-mail. <b>Value: Up to 60 characters</b>
<b>Personal Info.</b>	Select whether to include personal information in the job log. <b>Value: Include, Exclude</b>

## User Property

[System Menu/Counter] key > [▲] [▼] key > [User Property] > [OK] key

Allows you to view information about logged in users and edit some of that information.

➔ [Enabling User Login Administration \(page 9-3\)](#)

## Common Settings

Configures overall machine operation.

### Language

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Language] > [OK] key

Item	Description
Language	Select the language displayed on the message display.

### Default Screen

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Default Screen] > [OK] key

Item	Description
Default Screen	Select the screen appearing right after start-up (default screen). <b>Value:</b> Status, Copy, Send, FAX, Document Box

### Sound

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Sound] > [OK] key

Item	Description
<b>Buzzer</b>	Set options for buzzer sound during the machine operations.
<b>Key Confirmation</b>	Emit a sound when the operation panel keys are selected. <b>Value:</b> Off, On
<b>Job Finish</b>	Emit a sound when a print job is normally completed. <b>Value:</b> Off, On, FAX RX Only* <sup>1</sup>
<b>Ready</b>	Emit a sound when the warm-up is completed. <b>Value:</b> Off, On
<b>Warning</b>	Emit a sound when errors occur. <b>Value:</b> Off, On
<b>Keyboard Confirm</b>	Emit a sound to confirm keypresses with a sound. <b>Value:</b> Off, On
<b>FAX Speaker*<sup>1</sup></b>	➔ FAX Operation Guide
<b>FAX Monitor*<sup>1</sup></b>	➔ FAX Operation Guide

\*<sup>1</sup> Only on products with the fax function installed.

### Display Bright. (Display Brightness)


[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Display Bright.] > [OK] key




Item	Description
Display Bright.	Set the brightness of the message display. <b>Value:</b> Darker -3, Darker -2, Darker -1, Normal 0, Lighter +1, Lighter +2, Lighter +3

## Orig./Paper Set.












[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Orig./Paper Set.] > [OK] key

Configure settings for originals.

Item	Description
<p><b>Custom Orig. Size</b></p>	<p>Set up frequently-used custom original size. The custom size option is displayed on the screen to select original size.</p> <p><b>Value</b></p> <p><b>Metric</b>  <b>X: 50 to 356 mm (in 1 mm increments)</b>  <b>Y: 50 to 216 mm (in 1 mm increments)</b></p> <p><b>Inch</b>  <b>X: 1.97 to 14.02" (in 0.01" increments)</b>  <b>Y: 1.97 to 8.50" (in 0.01" increments)</b></p> <p><b>X=Length, Y=Width</b></p> <div style="text-align: center;"> <p>Horizontal</p>  </div>
<p><b>Def. Orig. Size</b></p>	<p>Set the default original size.</p> <p><b>Value: A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K</b></p>

Item	Description
<b>Custom PaperSize</b>	Set up frequently-used custom paper size. One custom paper size is set for each paper supply source. The custom size option is displayed on the screen to select paper size.
<b>Cassette 1 Size*<sup>1</sup></b>	Register the custom paper size to be used in Cassette 1. <b>Value</b> <b>Metric</b> <b>X: 105 to 216 mm (in 1 mm increments)</b> <b>Y: 148 to 356 mm (in 1 mm increments)</b> <b>Inch</b> <b>X: 4.13 to 8.50" (in 0.01" increments)</b> <b>Y: 5.83 to 14.02" (in 0.01" increments)</b> <b>X=Length, Y=Width</b> <div style="text-align: center;">  <p>A diagram showing a vertical sheet of paper with a light blue background. Red dimension lines indicate the width as 'X' and the height as 'Y'.</p> </div>
<b>Cassette 2 (to 4) Size*<sup>1</sup></b>	Register the custom paper size to be used in Cassettes 2 to 4. <b>Value</b> <b>Metric</b> <b>X: 92 to 216 mm (in 1 mm increments)</b> <b>Y: 162 to 356 mm (in 1 mm increments)</b> <b>Inch</b> <b>X: 3.62 to 8.50" (in 0.01" increments)</b> <b>Y: 6.38 to 14.02" (in 0.01" increments)</b>
<b>MP Tray Size</b>	Register the custom paper size to be used in the multi purpose tray. <b>Value</b> <b>Metric</b> <b>X: 70 to 216 mm (in 1 mm increments)</b> <b>Y: 148 to 356 mm (in 1 mm increments)</b> <b>Inch</b> <b>X: 2.76 to 8.50" (in 0.01" increments)</b> <b>Y: 5.83 to 14.02" (in 0.01" increments)</b> <b>X=Length, Y=Width</b> <div style="display: flex; justify-content: space-around; align-items: center;"> <div style="text-align: center;"> <p>Vertical</p>  </div> <div style="text-align: center;"> <p>Horizontal</p>  </div> </div>
<b>Cassette 1 (to 4) Set.</b>	Select the paper size and media type for cassettes 1 to 4. ➔ <a href="#">Cassette 1 (to 4) Set. (Cassette 1 (to 4) Settings) (page 8-11)</a>
<b>MP Tray Set.</b>	Select the paper size and media type for the multi purpose tray. ➔ <a href="#">MP Tray Set. (MP Tray Settings) (page 8-11)</a>

\*1 Only set this when the size dial on the cassette is set to "Other".

Item		Description
<b>Media Type Set.</b>		<p>Select weight for each media type.</p> <p>For Custom 1-8, settings for duplex printing and media type name can be changed.</p> <p>➔ <a href="#">Media Type Setting (page 8-12)</a></p>
<b>Def. PaperSource</b>		<p>Select the default paper source from Cassette 1-4 and multi purpose tray.</p> <p><b>Value: Cassette 1 to 4, MP Tray</b></p> <p> <b>NOTE</b></p> <p>[Cassette 2] to [Cassette 4] are displayed when optional paper feeder is installed.</p>
<b>Media for Auto</b>	<b>Full Color</b>	<p>Select a default media type for auto paper selection when [Auto] is selected of Paper Selection. If [Plain] is selected, the paper source with plain paper loaded in the specific size is selected. Select [All Media Types] for the paper source with any kind of paper loaded in the specific size.</p> <p><b>Value: All Media Types, Plain, Transparency, Rough, Vellum, Labels, Recycled, Preprinted, Bond, Cardstock, Color, Prepunched, Letterhead, Envelope, Thick, Coated, High Quality, Custom 1 to 8</b></p>
	<b>Black &amp; White</b>	
<b>SpecialPaper Act.</b>		<p>When printing on Prepunched, Preprint, and Letterhead, punch-holes might not be aligned or the print direction might be upside-down depending on how originals are set and the combination of copying functions. In such a case, select [Adj. PrintDirect] to adjust the print direction. When paper orientation is not important, select [Speed Priority].</p> <p>If [Adj. PrintDirect] is selected, load paper according to the steps below.</p> <p>Example: copying on Letterhead</p> <div style="display: flex; justify-content: space-around; align-items: center;"> <div style="text-align: center;">  Original         </div> <div style="text-align: center;">  Paper         </div> <div style="text-align: center;">  Finished         </div> <div style="text-align: center;">  Cassette         </div> <div style="text-align: center;">  Multi Purpose Tray         </div> </div> <div style="display: flex; justify-content: space-around; align-items: center; margin-top: 10px;"> <div style="text-align: center;">  Original         </div> <div style="text-align: center;">  Paper         </div> <div style="text-align: center;">  Finished         </div> <div style="text-align: center;">  Cassette         </div> <div style="text-align: center;">  Multi Purpose Tray         </div> </div> <p><b>Value: Adj. PrintDirect, Speed Priority</b></p>

### Cassette 1 (to 4) Set. (Cassette 1 (to 4) Settings)

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Orig./Paper Set.] > [OK] key > [▲] [▼] key > [Cassette 1 (to 4) Set.] > [OK] key

Select paper size and media type for Cassettes 1 to 4.

Item	Description
<b>Cassette 1 (to 4) Size</b> <sup>*1</sup>	Available options are as follows: <b>Value</b> Cassette 1: A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Custom Cassettes 2 to 4: A4, A5, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Youkei 4, Youkei 2, Custom
<b>Cassette 1 (to 4) Type</b> <sup>*2</sup>	Select the media type. <b>Value</b> Cassette 1: Plain (60 to 105 g/m <sup>2</sup> ), Rough, Vellum (60 to 105 g/m <sup>2</sup> ), Recycled, Preprinted <sup>*3</sup> , Bond, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Thick (106 to 163 g/m <sup>2</sup> ), High Quality, Custom 1 - 8 Cassettes 2 to 4: Plain (60 to 105 g/m <sup>2</sup> ), Rough, Vellum (60 to 105 g/m <sup>2</sup> ), Labels, Recycled, Preprinted <sup>*3</sup> , Bond, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1 - 8

\*1 Only set this when the size dial on the cassette is set to "Other".

\*2 To change to a media type other than "Plain".

➔ [Media Type Setting \(page 8-12\)](#).

When a paper weight that cannot be loaded in the cassette is set for a media type, that media type does not appear.

\*3 To print on preprinted or prepunched paper or on letterhead.

➔ [SpecialPaper Act. \(page 8-10\)](#)

### MP Tray Set. (MP Tray Settings)

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Orig./Paper Set.] > [OK] key > [▲] [▼] key > [MP Tray Set.] > [OK] key

Select paper size and media type for the multi purpose tray.

Item	Description
<b>MP Tray Size</b>	Available options are as follows: <b>Value:</b> A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom <sup>*1</sup>
<b>MP Tray Type</b> <sup>*2</sup>	Select the media type. <b>Values:</b> Plain (60 to 105 g/m <sup>2</sup> ), Transparency, Rough, Vellum (60 to 105 g/m <sup>2</sup> ), Labels, Recycled, Preprinted <sup>*3</sup> , Bond, Cardstock, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1-8

\*1 For instructions on how to specify the custom paper size.

➔ [Custom PaperSize \(page 8-9\)](#)

\*2 To change to a media type other than "Plain".

➔ [Media Type Setting \(page 8-12\)](#)

\*3 To print on preprinted or prepunched paper or on letterhead.

➔ [SpecialPaper Act. \(page 8-10\)](#)

**Media Type Setting**

The following media type and paper weight combinations are available.

Paper Weight	Weight (g/m <sup>2</sup> )	Paper Weight	Weight (g/m <sup>2</sup> )
Light	52 g/m <sup>2</sup> to 59 g/m <sup>2</sup>	Heavy 1	106 g/m <sup>2</sup> to 135 g/m <sup>2</sup>
Normal 1	60 g/m <sup>2</sup> to 74 g/m <sup>2</sup>	Heavy 2	136 g/m <sup>2</sup> to 163 g/m <sup>2</sup>
Normal 2	75 g/m <sup>2</sup> to 90 g/m <sup>2</sup>	Heavy 3	164 g/m <sup>2</sup> to 220 g/m <sup>2</sup>
Normal 3	91 g/m <sup>2</sup> to 105 g/m <sup>2</sup>	Extra Heavy	Transparencies

Each media type's default weight is indicated.

Media Type	Default	Media Type	Default
Plain	Normal 2	Color	Normal 2
Rough	Normal 3	Prepunched	Normal 2
Vellum	Normal 1	Letterhead	Normal 2
Labels	Heavy 1	Envelope	Heavy 2
Recycled	Normal 2	Thick	Heavy 2
Preprinted	Normal 2	High Quality	Normal 2
Bond	Normal 3	Coated	Heavy 1
Cardstock	Heavy 1	Custom 1 - 8	Normal 2

For Custom 1-8, settings for duplex printing and media type name can be changed.

Item		Description
Duplex Print	Prohibit	Duplex printing allowed.
	Permit	Duplex printing not allowed.
Name		Change names for Custom 1-8. Names should be not more than 16 characters. Selecting media type at multi purpose tray, the name after change will be displayed. <a href="#">▶ Character Entry Method (page 11-11)</a>

## Function Defaults

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Function Defaults] > [OK] key

Item		Description
File Format		Select the default type of the files to be sent. <b>Value: PDF, TIFF, XPS, JPEG, OpenXPS, High Comp. PDF</b>
Original Orientation		Set the original orientation defaults. <b>Value: Top Edge on Top, Top Edge on Left</b>
Collate		Set the defaults for Collate. <b>Value: Off, On</b>
File Separation		Select the default file separation setting. <b>Value: Off, Each Page</b>
Scan Resolution		Select the default scanning resolution. <b>Value: 200×100dpi Norm., 200×200dpi Fine, 200×400dpi S.Fin, 300×300dpi, 400×400dpi U.Fin, 600×600dpi</b>
Color Selection	Copy	Set the default copying color mode setting. <b>Value: Auto Color, Full Color, Black &amp; White</b>
	Send/Store	Select the default color mode for scanning documents. <b>Value: Auto (Color/Gray), Auto (Color/B &amp; W), Full Color, Grayscale, Black &amp; White</b>
Orig.Image(Copy)		Set the default original document type for copying. <b>Value: Text+Photo, Photo, Text,Map, Printed Document</b>
Orig.Image(Send)		Set the default original document type for sending. <b>Value: Text+Photo, Photo, Text, for OCR, Light Text/Line</b>   <b>NOTE</b> [for OCR] is only available when "Color Selection" is set to [Auto (Color/B & W)] or [Black & White].
Backgrnd(Copy)		Set the default Backgrnd Density (Copy). <b>Value: Off, Auto, Manual (Darker 5)</b>
Backgrnd(Send)		Set the default Backgrnd Density (Send). <b>Value: Off, Auto, Manual (Darker 5)</b>
EcoPrint		Select the EcoPrint default. <b>Value: Off, On</b>
Prevent B-t Copy		Set the default value for preventing bleed-through (Copy). <b>Value: Off, On</b>
Prevent B-t Send		Set the default Prevent Bleed (Send). <b>Value: Off, On</b>
Skip Blank(Copy)		Set the default Skip Blank(Copy) settings. <b>Value: Off, On</b>
Skip Blank(Send)		Set the default Skip Blank(Send) settings. <b>Value: Off, On</b>
FAX Resolution		➔ <b>FAX Operation Guide</b>
Zoom		Select the enlarged/reduced default when paper size/sending size changed after the originals set. <b>Value: 100%, Auto</b>



Item	Description
Con.scan-ExptFAX	Set the continuous scan defaults. <b>Value: Off, On</b>
Con.scan-FAX	➔ <b>FAX Operation Guide</b>
File Name Entry	Set an automatically entered name (default) for jobs. Additional information such as Date and Job No. can also be set. <b>Value</b> <b>File Name: Up to 32 characters can be entered.</b> <b>Additional Info: None, Date, Job No., Job No. + Date, Date + Job No.</b>
Subject/Body	Set the subject and body automatically entered (default subject and body) when sending the scanned originals by E-mail. <b>Value</b> <b>Subject: Up to 60 characters can be entered.</b> <b>Body: Up to 500 characters can be entered.</b>
JPEG/TIFF Print	Select the image size (resolution) when printing JPEG or TIFF file. <b>Value: Paper Size, Image Resolution, Print Resolution</b>
XPS FitTo Page	Set the default value for the XPS fit to page function. <b>Value: Off, On</b>
Detail Settings	—
2 in 1 Layout	Set the default for the 2-in-1 layout of Combine copies. <b>Value: L to R T to B, R to L</b>
4 in 1 Layout	Set the default for the 4-in-1 layout of Combine copies. <b>Value: Right then Down, Down then Right, Left then Down, Down then Left</b>
Border Line	Set the default for the border line of Combine copies. <b>Value: None, Solid Line, Dotted Line, Positioning Mark</b>
Orig. Binding	Set the default binding side for duplex scanning. <b>Value: Left/Right, Top</b>
Finish. Binding	Set the default for the binding orientation of finished two-sided copies. <b>Value: Left/Right, Top</b>
Image Quality	Select the default PDF/TIFF/JPEG/XPS/OpenXPS file quality. <b>Value: 1 Low(High Comp) to 5 High(Low Comp)</b>
Color TIFF Comp.	Select the compression method for sending the color documents in the TIFF format. <b>Value: TIFF V6, TTN2</b>
PDF/A	Select the default PDF/A setting. <b>Value: Off, PDF/A-1a, PDF/A-1b</b>
High Comp. PDF	Select the default quality setting for high compressed PDF files. <b>Value: Comp. Priority, Standard, Quality Priority</b>
Blank Lvl (Copy)	Select the default Blank Detection Level (Copy) settings. <b>Value: Low, Middle, High</b>
Blank Lvl (Send)	Select the default Blank Detection Level (Send/Store) settings. <b>Value: Low, Middle, High</b>

## Preset Limit

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Preset Limit] > [OK] key

Item	Description
Preset Limit	Restrict the number of copies that can be made at one time. <b>Value: 1 to 999 copies.</b>

## Error Handling

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Error Handling] > [OK] key

Select whether to cancel or continue the job when error has occurred.

Item	Description
DuplexPaperError	Select what to do when duplex printing is not possible for the selected paper size and media type. <b>Value</b> <b>1-sided: Printed in 1-sided</b> <b>Display Error: Message to cancel printing is displayed.</b>
PaperMismatchErr	Select what to do when the selected paper size or type does not match paper size or type loaded in the specified paper source while printing from the computer by specifying the cassette or multi-purpose tray. <b>Value</b> <b>Ignore: The setting is ignored and the job is printed.</b> <b>Display Error: Message to cancel printing is displayed.</b>

## ColorToner Empty

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [ColorToner Empty] > [OK] key

Item	Description
ColorToner Empty	Select whether printing is prohibited or the Print in Black and White setting is used for printing once the color toner runs out. <b>Value: Stop printing, Print in B &amp; W</b>


## Measurement

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Measurement] > [OK] key

Item	Description
Measurement	Select inch or metric for the unit for paper dimensions. <b>Value: inch, mm</b>

## TonerAlert Level

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [TonerAlert Level] > [OK] key

Item	Description
TonerAlert Level	<p>Set the amount of remaining toner to notify the administrator when to order a toner when the toner is running low.</p> <p><b>Value:</b> Off, On</p> <p> <b>NOTE</b></p> <p>Selecting [Off] alerts you low toner when the amount of remaining toner becomes 5%. If [On] is selected, set the amount of remaining toner to alert. The setting range is 5 to 100% (in 1% increments).</p>

## USB KeyboardType

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [USB KeyboardType] > [OK] key

Item	Description
USB KeyboardType	<p>Select the type of USB keyboard that you want to use.</p> <p><b>Value:</b> US, Europe US, France, Germany</p>

## Format SSD

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Format SSD] > [OK] key

Format an optional SSD.

When an optional SSD is inserted into the printer for the first time, it must be formatted before use.

### IMPORTANT

Formatting will destroy any existing data on a storage device including a used SSD.

### NOTE

This function will not be displayed when the optional Data Security Kit is installed.

## Format SD Card

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Format SD Card] > [OK] key

Format an optional SD/SDHC memory card.

A new SD card must be formatted before it can be used in the machine.

### IMPORTANT

- Formatting will destroy any existing data on a storage device including a used SD card.
- If you have installed application, do not format the SD card to avoid the removal of the application in the SD card.

## Disp. Status/Log

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Disp. Status/Log] > [OK] key


Item	Description
<b>Disp. Status/Log</b>	Set the display method of the Status/Log.
JobsDetailStatus	<b>Value:</b> Show All, My Jobs Only, Hide All
Jobs Log	<b>Value:</b> Show All, My Jobs Only, Hide All
FAX Log <sup>*1</sup>	<b>Value:</b> Show All, Hide All

\*1 Only on products with the fax function installed.

## Date Setting

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Date Setting] > [OK] key





Configure settings related to the date and time.



Item	Description
<b>Date/Time</b>	<p>Set the date and time for the location where you use the machine. When you send an E-mail using the transmission function, the date and time as set here will be printed in the header of the E-mail message.</p> <p><b>Value:</b> Year (2000 to 2037), Month (01 to 12), Day (01 to 31), Hour (00 to 23), Minute (00 to 59), Second (00 to 59)</p> <p>➔ <a href="#">Setting Date and Time (page 2-16)</a></p> <p> <b>NOTE</b></p> <p>If you change the date/time while using the trial version of an application, you will no longer be able to use the application.</p>
<b>Date Format</b>	<p>Select the display format of year, month, and date. The year is displayed in Western notation.</p> <p><b>Value:</b> Month/Day/Year, Day/Month/Year, Year/Month/Day</p>
<b>Time Zone</b>	<p>Set the time difference from GMT. Choose the nearest listed location from the list. If you select a region that utilizes summer time, configure settings for summer time.</p>
<b>Summer Time</b>	<p>➔ <a href="#">Setting Date and Time (page 2-16)</a></p>

## Timer Setting

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Timer Setting] > [OK] key

Configure settings related to the time.

Item	Description
<b>Auto Panel Reset</b>	<p>If no jobs are run for a certain period of time, automatically reset settings and return to the default setting. Select to use Auto Panel Reset or not.</p> <p><b>Value: Off, On</b></p> <p> <b>NOTE</b></p> <p>The time allowed to elapse before the panel is reset is set with the "PanelReset TimerPanel Reset Timer".</p> <p>➔ <a href="#">PanelReset Timer (page 8-18)</a></p>
<b>PanelReset Timer</b>	<p>If you select [On] for Auto Panel Reset, set the amount of time to wait before Auto Panel Reset.</p> <p><b>Value: 5 to 495 seconds (in 5 second increments)</b></p> <p> <b>NOTE</b></p> <p>This function is displayed when [Auto Panel Reset] is set to [On].</p>
<b>Sleep Level (models except for Europe)*<sup>1</sup></b>	<p>Select the Sleep level.</p> <p>Set the Energy Saver mode to reduce power consumption even more than Quick Recovery mode.</p> <p><b>Value: Quick Recovery, Energy Saver</b></p> <p><b>(Detailed settings)</b></p> <p>Set whether to use the Energy Saver mode for the following functions individually:</p> <ul style="list-style-type: none"> <li>• Network</li> <li>• Card Reader*<sup>2</sup></li> <li>• FAX*<sup>3</sup></li> </ul> <p><b>Value: Off, On</b></p> <p> <b>NOTE</b></p> <p>When the machine enters Energy Saver, the ID card cannot be recognized.</p>
<b>Sleep Rules (models for Europe)</b>	<p>Select whether to use the Sleep mode for the following functions individually:</p> <ul style="list-style-type: none"> <li>• Network</li> <li>• Card Reader*<sup>2</sup></li> <li>• FAX*<sup>3</sup></li> </ul> <p><b>Value: Off, On</b></p> <p> <b>NOTE</b></p> <p>When the machine enters Energy Saver, the ID card cannot be recognized.</p>
<b>Sleep Timer</b>	<p>Set amount of time before entering Sleep.</p> <p><b>Value</b></p> <p><b>For Europe</b>  <b>1 to 60 minutes (1 minute increments)</b></p> <p><b>Except for Europe</b>  <b>1 to 240 minutes (1 minute increments)</b></p> <p>➔ <a href="#">Sleep and Auto Sleep (page 2-20)</a></p>
<b>Auto Err. Clear</b>	<p>If an error occurs during processing, processing stops to wait for the next step to be taken by the user. In the Auto Error Clear mode, automatically clear the error after a set amount of time elapses.</p> <p><b>Value: Off, On</b></p>

Item	Description
<b>Err. Clear Timer</b>	If you select <b>[On]</b> for Auto Error Clear, set the amount of time to wait before automatically clearing errors. <b>Value: 5 to 495 seconds (in 5 second increments)</b>  <b>NOTE</b> This function is displayed when <b>[Auto Err. Clear]</b> is set to <b>[On]</b> .
<b>Unusable Time</b> *3	 <b>FAX Operation Guide</b>
<b>Ping Timeout</b>	Set the time until timeout occurs when <b>[Ping]</b> is executed in "System/Network". <b>Value: 1 to 30 seconds (in 1 second increments)</b>

\*1 When the optional Network Interface Kit is installed, this is not displayed.

\*2 Displayed only when the optional Card Authentication Kit is activated.

\*3 Displayed only on products with the fax function installed.

## RAM Disk Mode

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [RAM Disk Mode] > [OK] key

### NOTE

This function will not be displayed when the optional SSD is installed.

Item	Description
<b>RAM Disk Mode</b>	A RAM disk can be created and its size can be set. Creating a RAM disk makes it possible to print from a Job Box. <b>Value</b> <b>RAM Disk Mode:</b> <b>RAM Disk Size: The setting range varies depending on the amount of memory installed and the option memory usage setting.</b>

### IMPORTANT

After changing the setting, restart the network or turn the machine OFF and then ON.

## Optional Memory

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Optional Memory] > [OK] key

Item	Description
<b>Optional Memory</b>	When optional memory is installed, select the memory allocation scheme based on the application in which you are using the equipment. <b>Value: Normal, Printer Priority, Copy Priority</b>

### IMPORTANT

After changing the setting, restart the network or turn the machine OFF and then ON.

## Login Operation

[System Menu/Counter] key > [▲] [▼] key > [Common Settings] > [OK] key > [▲] [▼] key > [Login Operation] > [OK] key

Item	Description
<b>Login Operation</b>	Select the screen to enter the login user name and password when logging in. <b>Value:</b> Use Numeric Key, Select Character

## Copy

[System Menu/Counter] key > [▲] [▼] key > [Copy] > [OK] key



Configures settings for copying functions.

Item	Description
<b>Paper Selection</b>	Set the default paper selection. <b>Value:</b> Auto, Def. PaperSource
<b>AutoPaperSelect.</b>	If [Auto] is selected for Paper Selection, set the paper size selection method when the zoom changes. <b>Value</b> <b>MostSuitableSize:</b> Select paper based on the current zoom and the size of the original. <b>Same as OrigSize:</b> Select paper that matches the size of the original, regardless the zoom.
<b>Auto % Priority</b>	When a paper source of different size from the original is selected, select whether automatic zoom (reduce/zoom) is performed. <b>Value:</b> Off, On
<b>Reserve Priority</b>	Specify whether the default screen appears when a subsequent copy job is reserved while printing is in progress. To have the default screen appear, select [On]. <b>Value:</b> Off, On
<b>DP Read Action</b>	When the document processor is used, select the scanning operation for the document processor. <b>Value</b> <b>Speed Priority:</b> Gives priority to scanning speed. <b>Quality Priority:</b> Gives priority to image quality at a slightly slower scan speed.
<b>Select Key Set.</b>	Commonly used copying functions can be registered to the Select key. Functions can be easily configured by selecting the Select key. <b>Value:</b> None, Quiet Mode, Paper Selection, Collate, Duplex, Zoom, Combine, Original Size, Orig. Orientation, Mixed Size Orig., Original Image, Density, EcoPrint, Continuous Scan, File Name Entry, JobFinish Notice, Print Override, Color Selection, Color Balance, Sharpness, Contrast, Backgrnd Density, Saturation, Prevent Bleed-t, Skip Blank Page

## Send

[System Menu/Counter] key > [▲] [▼] key > [Send] > [OK] key

Configures settings for sending functions.

Item	Description
<b>Select Key Set.</b>	Commonly used sending functions can be registered to the Select key. Functions can be easily configured by selecting the Select key. <b>Value:</b> None, Quiet Mode, Color Selection, Original Size, Original Image, Scan Resolution, Sending Size, Zoom, Orig. Orientation, Mixed Size Orig., Continuous Scan, File Format, File Name Entry, Subject/Body, JobFinish Notice, FAX Resolution <sup>*1</sup> , FAX Direct TX <sup>*1</sup> , FAX Delayed TX <sup>*1</sup> , FAX RX Polling <sup>*1</sup> , FAX TX Report <sup>*1</sup> , Density, Duplex, FTP Encrypted TX, File Separation, Sharpness, Backgrnd Density, Prevent Bleed-t, Skip Blank Page
<b>DestinationCheck</b>	Set the confirmation of destinations. <sup>*2</sup>
<b>Check beforeSend</b>	Select whether to display the confirmation screen of destinations after pressing the [Start] key when performing sending jobs. <b>Value:</b> Off, On
<b>Check New Dest.</b>	When adding new destination, select whether to display the entry check screen to check the entered destination. <b>Value:</b> Off, On
<b>Send and Forward</b>	Set whether to send the original to another destination and store it when sending images.
<b>Forward</b>	Set the rule to send the original. <b>Value:</b> Off, On  <b>NOTE</b> When selecting [On], select rules to forward from [E-mail], [Folder (SMB)], [Folder (FTP)] and [FAX] <sup>*1</sup> .
<b>Destination</b>	Set the destination to which the original is forwarded. One destination can be set. You can check and edit the set address. Follow the steps below to register the destination. <ul style="list-style-type: none"> <li>• Address Book</li> <li>• Address Entry</li> </ul>  <a href="#">Specifying Destination (page 5-15)</a>
<b>Default Screen</b>	Use this procedure to set the default screen displayed when you select the [Send] key. <b>Value:</b> Destination, Address Book
<b>New Dest. Entry</b>	Select whether to permit direct entry of destination. <sup>*2</sup> <b>Value:</b> Permit, Prohibit
<b>Recall Dest.</b>	Select whether to permit usage of [Recall] on the Send screen. <sup>*2</sup> <b>Value:</b> Permit, Prohibit

\*1 Only on products with the fax function installed.




\*2 Also applies when sending the fax.



## Document Box

[System Menu/Counter] key > [▲] [▼] key > [Document Box] > [OK] key

Configures settings related to the Custom Box, Job Box, Sub Address Box and Polling Box.

Item	Description
<b>Custom Box</b>	Configure settings for Custom Box.
Detail/Edit	➔ <a href="#">Using a Custom Box (page 5-32)</a>
File Del. Time	Set the time to automatically delete stored documents. <b>Value: Hour (00 to 23), Minute (00 to 59)</b>
<b>Sub Address Box<sup>*1</sup></b>	➔ <b>FAX Operation Guide</b>
<b>Job Box</b>	Configure settings for Job Box.
Quick Copy Jobs	To maintain free space on the box, you can set the maximum number of stored jobs. <b>Value: number between 0 and 300</b>   <b>NOTE</b> When 0 is set, Quick Copy cannot be used.
JobRet. Deletion	This setting specifies that documents, such as Private Printing, Quick Copying, or Proof and Hold Printing, saved temporarily in the job box are automatically deleted after they have been saved for a set time. <b>Value: Off, 1 hour, 4 hours, 1 day, 1 week</b>   <b>NOTE</b> This function is valid for documents saved after the function is set. Regardless of this function setting, temporary documents are deleted when the main power switch is turned off.
Storage Media	Select which storage media to use. <b>Value: SSD, SD Card</b>   <b>NOTE</b> This setting is not displayed if the optional SSD or SD card is not installed.
<b>Polling Box<sup>*1</sup></b>	➔ <b>FAX Operation Guide</b>
<b>Select Key Set.</b>	Commonly used printing and storing functions can be registered to the Select key. Functions used when printing and when saving can both be registered. Functions can be easily configured by selecting the Select key. <b>Value</b> <b>Print: None, Quiet Mode, Collate<sup>*2</sup>, Paper Selection<sup>*2</sup>, Duplex<sup>*2</sup>, EcoPrint<sup>*2</sup>, File Name Entry, JobFinish Notice, Print Override, Color Selection<sup>*3</sup>, Encrypted PDF<sup>*3</sup>, JPEG/TIFF Print<sup>*3</sup>, XPS FitTo Page<sup>*3</sup>, Del. after Print<sup>*4</sup></b> <b>Store: None, Quiet Mode, Color Selection<sup>*5</sup>, Original Size, Original Image, Scan Resolution, Storing Size<sup>*5</sup>, Zoom<sup>*5</sup>, Orig. Orientation, Mixed Size Org., Continuous Scan, File Format<sup>*5</sup>, File Separation<sup>*5</sup>, File Name Entry, JobFinish Notice, Density, Duplex, Sharpness<sup>*5</sup>, Contrast<sup>*5</sup>, Backgrnd Density<sup>*5</sup>, Prevent Bleed-t<sup>*5</sup>, Skip Blank Page</b>

\*1 Only on products with the fax function installed.

\*2 Only displayed when printing from USB memory and Custom Box.

\*3 Only displayed when printing from USB memory.

\*4 Only displayed when printing from Sub Address Box and Custom Box.

\*5 Not displayed when saving to Polling Box.

## FAX

[System Menu/Counter] key > [▲] [▼] key > [FAX] > [OK] key

Configure settings for FAX.

➔ [FAX Operation Guide](#)

## Edit Destination

### Address Book

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [Address Book] > [OK] key

Configure settings for address book.

➔ [Adding a Destination \(Address Book\) \(page 3-23\)](#)

### AddBookDefaults

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [AddBookDefaults] > [OK] key



#### NOTE

This function does not appear when the External Address Book is not set.

Item	Description
Address Book	Set the type of address book that appears when the address book is displayed. <b>Value:</b> Machine AddrBook, Ext Address Book

### Print List

[System Menu/Counter] key > [▲] [▼] key > [Edit Destination] > [OK] key > [▲] [▼] key > [Print List] > [OK] key

➔ [FAX Operation Guide](#)

## User/Job Account

[System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

Configure settings related to machine management.

➔ [Overview of User Login Administration \(page 9-2\)](#)


[Overview of Job Accounting \(page 9-24\)](#)




[Unknown ID Job \(page 9-40\)](#)

## Printer

[System Menu/Counter] key > [▲] [▼] key > [Printer] > [OK] key

Printing from computers, settings are generally made on the application software screen. However, the following settings are available for configuring the defaults to customize the machine.

Item	Description
<b>Emulation Set.</b>	Select the emulation for operating this machine by commands oriented to other types of printers. <b>Value: PCL6, KPDL, KPDL (Auto)</b>
	 <b>NOTE</b> When you have selected [KPDL] or [KPDL (Auto)], set "KPDL Error Rpt", too.
<b>KPDL Error Rpt</b>	When an error has occurred during printing in KPDL emulation mode, set whether or not the error report is output. <b>Value: Off, On</b>
<b>Color Setting</b>	You can choose whether reports are printed in color or black and white. <b>Value: Color, Black &amp; White</b>
<b>EcoPrint</b>	EcoPrint conserves toner when printing. This is recommended for test copies where faded printing is not a problem. <b>Value: Off, On</b>
<b>Override A4/LTR</b>	Select whether to treat A4 size and Letter, which are similar in size, as the same size when printing. <b>Value</b> <b>Off: A4 and Letter are not regarded as the same in size.</b> <b>On: A4 and Letter are regarded as the same in size. The machine will use whichever size is in the paper source.</b>
<b>Duplex</b>	Select binding orientation for duplex mode. <b>Value: Off, Bind Long Edge, Bind Short Edge</b>
<b>Copies</b>	Set the default number of copies, from 1 to 999. <b>Value: 1 to 999 copies</b>
<b>Orientation</b>	Set the default orientation, [Portrait] or [Landscape]. <b>Value: Portrait, Landscape</b>
<b>Wide A4</b>	Turn this to on to increase the maximum number of characters that can be printed in a line for an A4 page (78 characters at 10 pitch) and Letter size page (80 characters at 10 pitch). This setting is only effective in PCL6 emulation. <b>Value: Off, On</b>
<b>FormFeed TimeOut</b>	Receiving print data from the computer, the machine may sometimes wait if there is no information signaling that the last page does not have any more data to be printed. When the preset timeout passes, the machine automatically prints paper. The options are between 5 and 495 seconds. <b>Value: 5 to 495 seconds (in 5 second increments)</b>
<b>LF Action</b>	Set the line feed action when the machine receives the line feed code (character code 0AH). <b>Value: LF Only, LF and CR, Ignore LF</b>
<b>CR Action</b>	Set the character return action when the machine receives the character return code (character code 0DH). <b>Value: CR Only, LF and CR, Ignore CR</b>

Item	Description
<b>Job Name</b>	<p>Set whether the job name set in the printer driver is displayed.  <b>Value:</b> Off, On</p> <p> <b>NOTE</b></p> <p>When selecting [On], select the job name to be displayed from [Job Name], [Job No.+Job Name], or [Job Name+Job No.].</p>
<b>User Name</b>	<p>Set whether the user name set in the printer driver is displayed.  <b>Value:</b> Off, On</p>
<b>MP Tray Priority</b>	<p>If paper is set in the MP Tray then it is possible for priority to be given to that MP tray in the paper feed.  <b>Value</b></p> <p><b>Off:</b> The printer driver settings are followed.</p> <p><b>Auto Feed:</b> If Auto is selected in the printer driver and there is paper in the MP tray then the paper feed will be from the MP tray.</p> <p><b>Always:</b> If there is paper in the MP tray then the paper feed will be from the MP tray regardless of what is set in the printer driver.</p>
<b>Paper Feed Mode</b>	<p>While printing from the computer, select how to feed paper when the paper source and type are specified.  <b>Value</b></p> <p><b>Auto:</b> Search the paper source that matches the selected paper size and type.</p> <p><b>Fixed:</b> Print on paper loaded in the specified paper source.</p>
<b>Auto Cass.Change</b>	<p>Select the following actions when the paper runs out in the paper source while printing.  <b>Value:</b> Off, On</p> <p> <b>NOTE</b></p> <p>When selecting [Off], the machine displays "Load paper in cassette #." (# is a cassette number) or "Load paper in MP Tray", and stops printing.</p> <p>Load the paper according to the paper source displayed to resume printing.</p> <p>To print from the other paper source, select [Paper]. Select the desired paper source, and then select the [OK] key.</p> <p>When selecting [On], the machine continues printing automatically when the other cassette contains the same paper as the currently-used cassette.</p>
<b>Gloss Mode</b>	<p>Gloss Mode increases the effect of glossiness in printing. However, printing takes longer time.  <b>Value:</b> Off, On</p> <p> <b>IMPORTANT</b></p> <p><b>Gloss Mode is not available when [Labels] or [Transparency] is selected as the paper type setting.</b></p> <p>➔ <a href="#">Cassette 1 (to 4) Set. (Cassette 1 (to 4) Settings) (page 8-11)</a>  <a href="#">MP Tray Set. (MP Tray Settings) (page 8-11)</a></p> <p><b>Depending on the paper used, printing in gloss mode may cause curl in paper. To reduce curl, try using thicker paper.</b></p>

## System/Network


Configures machine system settings.

### Network Setting






[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Network Setting] > [OK] key

Configures network settings.

#### Host Name


Item	Description
Host Name	Check the host name of the machine. Host name can be changed from Command Center RX.  <a href="#">Changing Device Information (page 2-42)</a>

#### TCP/IP Settings

Item	Description
TCP/IP	Set up TCP/IP to connect to the Windows network. <b>Value: Off, On</b>
IPv4 Setting	Set up TCP/IP (IPv4) to connect to the network.
DHCP	Select whether or not to use the DHCP (IPv4) server. <b>Value: Off, On</b>
Auto-IP	Select whether to use Auto-IP. <b>Value: Off, On</b>
IP Address	Set the IP addresses. <b>Value: ###.###.###.###</b>   <b>NOTE</b> If DHCP is set to [On], this item is displayed only and cannot be entered.
Subnet Mask	Set the IP subnet masks. <b>Value: ###.###.###.###</b>   <b>NOTE</b> If DHCP is set to [On], this item is displayed only and cannot be entered.
Default Gateway	Set the IP gateway addresses. <b>Value: ###.###.###.###</b>   <b>NOTE</b> If DHCP is set to [On], this item is displayed only and cannot be entered.
IPv6 Setting	Select whether to use IPv6. <b>Value: Off, On</b>   <b>NOTE</b> This setting is available when [TCP/IP] is [On]. The IPv6 settings are configured from the Command Center RX.  <b>Command Center RX User Guide</b>
Bonjour	Select whether or not to use Bonjour. <b>Value: Off, On</b>

#### IMPORTANT



After changing the setting, restart the network or turn the machine OFF and then ON.

Item	Description
<b>Protocol Detail</b>	—
<b>NetBEUI</b>	Selects whether or not to receive documents using NetBEUI.* <sup>1</sup> <b>Value: Off, On</b>
<b>LPD</b>	Select whether or not to receive documents using LPD.* <sup>1</sup> <b>Value: Off, On</b>
<b>SMTP</b>	Select whether or not to send e-mail using SMTP. <b>Value: Off, On</b>
<b>POP3</b>	Select whether or not to receive e-mail using POP3. <b>Value: Off, On</b>
<b>FTP(Client)</b>	Select whether or not to send documents using FTP. When selecting <b>[On]</b> , set the FTP Port Number. Use the FTP default port 21. <b>Value: Off, On (Port Number: 1-65535)</b>
<b>FTP(Server)</b>	Select whether or not to receive documents using FTP.* <sup>1</sup> <b>Value: Off, On</b>
<b>SMB</b>	Select whether or not to send documents using SMB. <b>Value: Off, On (Port Number: 1-65535)</b>
<b>LDAP</b>	Select whether or not to use LDAP. <b>Value: Off, On</b>
<b>SNMP</b>	Select whether or not to communicate using SNMP.* <sup>1</sup> <b>Value: Off, On</b>
<b>SNMPv3</b>	Select whether or not to communicate using SNMPv3.* <sup>1</sup> <b>Value: Off, On</b>
<b>HTTP</b>	Select whether or not to communicate using HTTP.* <sup>1</sup> <b>Value: Off, On</b>
<b>HTTPS</b>	Select whether or not to communicate using HTTPS.* <sup>1</sup> * <sup>2</sup> <b>Value: Off, On</b>
<b>IPP</b>	Select whether or not to receive documents using IPP. When selecting <b>[On]</b> , set the IPP default Port Number. Use the IPP default port 631.* <sup>1</sup> * <sup>2</sup> <b>Value: Off, On (Port Number: 1-32767)</b>
<b>IPP over SSL</b>	Select whether or not to use IPP over SSL. <b>Value: Off, On (Port Number: 1-32767)</b>   <b>NOTE</b> When selecting <b>[On]</b> , the certificates must be installed. ➔ <b>Command Center RX User Guide</b>
<b>RAW Port</b>	Select whether or not to receive documents using RAW Port.* <sup>1</sup> <b>Value: Off, On</b>

\*<sup>1</sup> The setting will be changed after restarting the device or the network for the machine.

\*<sup>2</sup> Set "SSL" to **[On]** in "Secure Protocol".

➔ [Secure Protocol \(page 8-29\)](#)

Item	Description
<b>ThinPrint</b>	<p>Select whether to use ThinPrint. When selecting <b>[On]</b>, set the ThinPrint default Port Number. Use the default port 4000.*<sup>1</sup> *<sup>2</sup></p> <p><b>Value: Off, On (Port Number: 1 to 32767)</b></p> <p> <b>NOTE</b></p> <p>This function is displayed only when the optional ThinPrint Option is activated.</p>
<b>ThinPrintOver SSL</b>	<p>To use Thin Print over SSL, select <b>[ThinPrintOver SSL]</b> and select <b>[On]</b>.</p> <p><b>Value: Off, On</b></p> <p> <b>NOTE</b></p> <p>When selecting <b>[On]</b>, the certificates must be installed.</p> <p>➔ <b>Command Center RX User Guide</b></p>

\*1 The setting will be changed after restarting the device or the network for the machine.

\*2 Set "SSL" to **[On]** in "Secure Protocol".

➔ [Secure Protocol \(page 8-29\)](#)

### WSD-SCAN

Item	Description
<b>WSD-SCAN</b>	<p>Select whether or not to use WSD Scan.*<sup>1</sup></p> <p><b>Value: Off, On</b></p>

\*1 The setting will be changed after restarting the device or the network for the machine.

### WSD-PRINT

Item	Description
<b>WSD-PRINT</b>	<p>Set whether to use our proprietary web services. WIA driver, TWAIN driver and Network FAX driver use this Enhanced WSD web service.*<sup>1</sup></p> <p><b>Value: Off, On</b></p>

\*1 The setting will be changed after restarting the device or the network for the machine.



### IMPORTANT

**After changing the setting, restart the network or turn the machine OFF and then ON.**

### IPSec

Item	Description
<b>IPSec</b>	<p>Make this setting when you use IPSec.</p> <p><b>Value: Off, On</b></p>

**Secure Protocol**

Item	Description
<b>SSL</b>	Select whether or not to use SSL. <b>Value: Off, On</b>
<b>IPP Security</b>	Select the IPP security level. This setup is available when SSL is [On]. <b>Value: IPP/IPP over SSL, IPPoverSSL only</b>
<b>HTTP Security</b>	Select the HTTP security level. This setup is available when SSL is [On]. <b>Value: HTTP/HTTPS, HTTPS only</b>
<b>SMTP Security</b>	Select the communication protocol according to the type of security employed by the SMTP server. This setup is available when SSL is [On]. <b>Value: Off, SSL/TLS, STARTTLS</b>
<b>POP3 Security 1</b>	Select the communication protocol according to the type of security employed by the POP3 server. This setup is available when POP3 is [On]. <b>Value: Off, SSL/TLS, STARTTLS</b>
<b>POP3 Security 2</b>	
<b>POP3 Security 3</b>	

**LAN Interface**

Item	Description
<b>LAN Interface</b>	Specify the settings for the LAN interface to be used. <b>Value: Auto, 10Base-Half, 10Base-Full, 100Base-Half, 100Base-Full, 1000BASE-T</b>

**IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

**Ping**

Item	Description
<b>Ping</b>	Checks if communication with the destination by entering the host name or IP address of the destination is possible.  <b>NOTE</b> If [NW InterfaceSend] is set to [Option NIC], this item is not displayed.

**Restart Network**

Item	Description
<b>Restart Network</b>	Restarts the network.

**Optional Network**

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Optional Network] > [OK] key


Configure settings for the optional Network Interface Kit.

**NOTE**

This menu is displayed when the optional Network Interface Kit or Wireless Network Interface Kit is installed.



**Basic**

Item	Description
<b>Host Name</b>	Check the host name of the machine. Host name can be changed from Command Center RX. ➔ <a href="#">Changing Device Information (page 2-42)</a>
<b>TCP/IP Settings</b>	For details on setting value. ➔ <a href="#">TCP/IP Settings (page 8-26)</a> <a href="#">IPSec (page 8-28)</a>
<b>Bonjour</b>	Select whether to use Bonjour. <b>Value: Off, On</b>
<b>IPSec</b>	Select whether to use IPSec. <b>Value: Off, On</b>
<b>LAN Interface</b>	Select the LAN Interface type.*1 <b>Value: Auto, 10Base-Half, 10Base-Full, 100Base-Half, 100Base-Full, 1000Base-T</b>  <b>NOTE</b> This function is displayed when the optional Network Interface Kit is installed.
<b>MACAddressFilter</b>	Select whether to use MAC Address Filter. ➔ <b>Operation Guide</b> for the optional Network Interface Kit <b>Value: Off, On</b>
<b>Restart Network</b>	Restarts the network card of the device.

\*1 The setting will be changed after restarting the device or network.


**Wireless Network**





[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Wireless Network] > [OK] key

Configure settings for the optional Wireless Network Interface Kit.

**Setup** **NOTE**

This function is displayed when the optional Wireless Network Interface Kit is installed.

Item	Description
<b>ConnectionStatus</b>	When the optional Wireless Network Interface Kit is installed, you can check the wireless LAN status.
<b>Quick Setup</b>	If the machine will connect to an access point that supports the automatic wireless network setup, connection settings can be configured by Quick Setup.
<b>AvailableNetwork</b>	Displays access points to which the machine can connect.
<b>Push Button</b>	If the access point supports the push button method, wireless settings can be configured using the push button. This setting executes push button, and the connection is started by pressing the push button on the access point.  <b>NOTE</b> The push button method supports only the WPS.
<b>PIN (Device)</b>	Starts connection using the machine's PIN code. Enter the PIN code into the access point. The PIN code of the machine is automatically generated.
<b>PIN (Terminal)</b>	Starts connection using the PIN code of the access point. Enter the PIN code of the access point.

Item	Description
<b>Custom Setup</b>	The detailed settings for wireless LAN can be changed. You can check the connection with a wireless network by selecting [ <b>Connect</b> ].
<b>Netwk Name(SSID)</b>	Set the SSID (Service Set Identifier) of the wireless LAN to which the machine connects.  <b>NOTE</b> Up to 32 characters can be entered.
<b>Connection Mode</b>	Set the connection mode. <b>Value: Ad Hoc, Infrastructure</b>  <b>NOTE</b> <b>Ad Hoc:</b> Directly communicates with the device without going through an access point. This method cannot be used to connect to two or more devices. <b>Infrastructure:</b> Performs communication through an access point.
<b>Channel</b>	Set channel. Use [ <b>▲</b> ] or [ <b>▼</b> ] or the numeric keys to enter a number. <b>Value: 1 to 11</b>
<b>Netwk Authentic.</b>	Select network authentication type. To select other options, open the device home page from a computer. <b>Value: Open, Shared, WPA-PSK<sup>*1</sup>, WPA2-PSK<sup>*1</sup></b>
<b>Encryption</b>	Select encryption settings. The setting values vary depending on the "Netwk Authentic." setting.
<b>Data Encryption</b>	Set the encryption method. <b>When "Netwk Authentic." is set to [Open] or [Shared]:</b> <b>Value: Disable, WEP</b> <b>When "Netwk Authentic." is set to [WPA-PSK] or [WPA2-PSK]:</b> <b>Value: TKIP<sup>*2</sup>, AES, Auto<sup>*2</sup></b>
<b>WEP Key</b>	Register the WEP key. Select [ <b>Edit</b> ] and Enter the WEP Key using the numeric keys.  <b>NOTE</b> Up to 26 characters can be entered. ➔ <a href="#">Character Entry Method (page 11-11)</a>
<b>Preshared Key<sup>*3</sup></b>	Register the Preshared Key. Select [ <b>Edit</b> ] and Enter the Preshared Key using the numeric keys.  <b>NOTE</b> The number of characters is between 8 and 64. ➔ <a href="#">Character Entry Method (page 11-11)</a>

\*1 Not displayed if you selected [**Ad Hoc**] for "Connection Mode".\*2 Not displayed if you selected [**WPA2-PSK**] for "Netwk Authentic.".\*3 Displayed if you selected [**WPA-PSK**] or [**WPA2-PSK**] for "Netwk Authentic.".

## NW InterfaceSend

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [NW InterfaceSend] > [OK] key

### NOTE



This function is displayed when the optional Network Interface Kit or Wireless Network Interface Kit is installed.

Item	Description
NW InterfaceSend	Specify the network interface card to be used for the send function, the network authentication and connecting to external address book. <b>Value: Standard, Option NIC</b>

## I/F Block Set.

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [I/F Block Set.] > [OK] key

This allows you to protect this machine by blocking the interface with external devices such as USB hosts or optional interfaces.

Item	Description
USB Host	This locks and protects the USB port (USB host). <b>Value: Unblock, Block</b>
USB Device	This locks and protects the USB interface connector (USB Device). <b>Value: Unblock, Block</b>
USB Storage	This locks and protects the USB memory slot. <b>Value: Unblock, Block</b>   <b>NOTE</b> This function is available when USB Host is set to [Unblock].
Option I/F 1 *1	This locks and protects the optional interface slots. <b>Value: Unblock, Block</b>
Option I/F 2 *2	  <b>NOTE</b> If the machine has two optional interface slots, you can set this feature for each slot.

\*1 [Optional Interface] is displayed on ECOSYS M6530cdn.

\*2 Only on products with the fax function installed.

### IMPORTANT

After changing the setting, restart the network or turn the machine OFF and then ON.

## Security Level

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Security Level] > [OK] key

Item	Description
Security Level	<p>Specify the security level.</p> <p><b>Value</b></p> <p><b>Low:</b> This mode is used during maintenance. Do not use normally.</p> <p><b>High:</b> This is the security setting we recommend. Use this setting normally.</p> <p><b>Very High:</b> In addition to [High] setting, this setting disables the machine settings to be changed from external command.</p>

## Restart




[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Restart] > [OK] key

Item	Description
Restart	Restart the CPU without turning the power switch off. Use this to deal with any unstable operation by the machine. (Same as the computer restart.)

## Data Security

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Data Security] > [OK] key

Configure settings for data stored in the optional SSD and machine's memory.

Item	Description
SSD Initializ.	<p>Initialize data saved on an optional SSD.</p> <p>➔ <b>Data Security Kit (E) Operation Guide</b></p> <p> <b>NOTE</b></p> <p>This function is displayed when the optional SSD is installed and the optional Data Security Kit is activated.</p>
DataSanitization	<p>Return the following information registered in the machine to the factory defaults.</p> <ul style="list-style-type: none"> <li>• Address Book</li> <li>• System settings</li> <li>• Fax transmission and reception / forwarding data</li> <li>• Transmission histories</li> <li>• Data saved in Custom Box</li> <li>• Optional applications</li> </ul> <p> <b>IMPORTANT</b></p> <p><b>Data saved in an application or SD card cannot be erased. To erase data on an SD card, you must format the SD card.</b></p> <p>➔ <a href="#">Format SD Card (page 8-16)</a></p> <p> <b>NOTE</b></p> <p>Once in progress, the processing cannot canceled.</p> <p>Before executing this function, disconnect modular, network, and other cables.</p> <p>Do not turn off the main power switch while sanitizing the data. If the main power is turned off during data erasing, erasing will be executed automatically when the power is restored, however, complete erasure cannot be guaranteed.</p>

## Op Functions

[System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key > [▲] [▼] key > [Op Functions] > [OK] key

Item	Description
Op Functions	You can use the optional applications installed on this machine. ➔ <a href="#">Optional Applications (page 11-9)</a>

## Adjust/Maint.

[System Menu/Counter] key > [▲] [▼] key > [Adjust/Maint.] > [OK] key

Adjust printing quality and conduct machine maintenance.

Item	Description
Quiet Mode	Lower print and scan speed for quiet processing.
Quiet Mode	Set the Quiet Mode. Select this mode when the running noise is uncomfortable. <b>Value: Off, On</b>
Each Job	It is possible to set the use of Quiet Mode for each job, such as copying and sending. Set whether or not to permit the setting for each job. <b>Value: Permit, Prohibit</b>
Copy Dens. Adj.	Adjust copy density. <b>Value: -3 Lighter, -2, -1, 0 Normal, +1, +2, +3 Darker</b>
Send/Box Density	Adjust scan density when sending or storing the data in Document Box. <b>Value: -3 Lighter, -2, -1, 0 Normal, +1, +2, +3 Darker</b>
Contrast (Copy)	Increases or decreases the overall contrast of copies. <b>Value: -3, -2, -1, 0, 1, 2, 3</b>
Contrast (Send)	Increases or decreases the overall contrast when documents are sent or saved in a document box. <b>Value: -3, -2, -1, 0, 1, 2, 3</b>
Background Density	Darkens or lightens overall background density adjustment.
Copy (Auto)	Darkens or lightens overall background density adjustment during copying. <b>Value: -3 Lighter, -2, -1, 0 Normal, +1, +2, +3 Darker</b>
Send/Box (Auto)	Darkens or lightens overall background density when sending images or storing them in the Document Box. <b>Value: -3 Lighter, -2, -1, 0 Normal, +1, +2, +3 Darker</b>
AutoColorCorrect	This setting allows you to adjust the detection level used by the machine to determine whether the original is color or black and white during Auto Color Mode. Setting a lower value will result in more originals being identified as color, while a larger value will tend to increase the number of originals being identified as black and white. <b>Value: 1 to 5</b>
Correct. Bk Line	Correct fine lines (streaks caused by contamination), which may appear on the image, when the document processor is used. <b>Value</b> <b>Off: No correction performed. Select this when you want to reproduce fine lines in the original more clearly than with [On (Low)].</b> <b>On (Low): Correction performed.</b> <b>On (High): Select this item if a streak remains after using [On (Low)]. The reproduction of fine lines on the original may become lighter than when using On (Low).</b>

Item	Description
<b>ColorCalibration</b>	<p>This machine contains a calibration function that automatically makes adjustments to compensate for changes that occur over time due to variations in the ambient temperature and humidity. This function can be used for fine adjustment of tone and color drift to print in the optimum color.</p> <p>➔ <a href="#">ColorCalibration (page 10-29)</a></p> <p>If color tone does not improve or color drift does not improve after executing this color adjustment, refer to the following:</p> <p>➔ <a href="#">Color Registration Procedure (page 10-29)</a></p>
<b>Color Regist.</b>	<p>When first installing the machine or moving it to a new location, color drift during printing may occur. Use this function to correct the color position of each of cyan, magenta and yellow to resolve color drift.</p> <p>➔ <a href="#">Color Registration Procedure (page 10-29)</a></p>
<b>Service Setting</b>	<p>Settings for machine maintenance and inspection. This menu is primarily used by service technicians to perform maintenance.</p>

# 9 User Authentication and Accounting (User Login, Job Accounting)


This chapter explains the following topics:

Overview of User Login Administration .....	9-2
Enabling User Login Administration .....	9-3
Setting User Login Administration .....	9-5
Authentication Security .....	9-5
Adding a User (Local User List) .....	9-6
Changing User Properties .....	9-9
User Login Administration for Printing .....	9-11
To Manage the Users to Scan Using TWAIN .....	9-13
To Manage the Users to Scan Using WIA .....	9-14
To Manage the Users that Send Faxes from a PC .....	9-15
Local Authoriz. (Local Authorization) .....	9-16
Group Auth. (Group Authorization Settings) .....	9-17
Guest Authorization Set. ....	9-18
NW User Property (Obtain Network User Property) .....	9-21
ID Card Settings .....	9-22
Using User Login Administration .....	9-23
Login/Logout .....	9-23
Overview of Job Accounting .....	9-24
Enabling Job Accounting .....	9-25
Job Accounting Access .....	9-26
Setting an Account .....	9-27
Adding an Account .....	9-27
Restricting the Use of the Machine .....	9-29
Editing an Account .....	9-30
Deleting an Account .....	9-31
Job Accounting for Printing .....	9-32
Job Accounting for Scan Using TWAIN .....	9-33
Job Accounting for Scan Using WIA .....	9-34
Job Accounting for the FAX Transmitted from a Computer .....	9-35
Configuring Job Accounting .....	9-36
Default Setting .....	9-36
Counting the Number of Pages Printed .....	9-37
Print Accounting Report .....	9-38
Using Job Accounting .....	9-39
Login/Logout .....	9-39
Unknown ID Job .....	9-40


# Overview of User Login Administration

User login administration specifies how the user access is administered on this machine. Enter a correct login user name and password for user authentication to login.


- 1 Enable User Login Administration ([page 9-3](#))



- 2 Set the user ([page 9-6](#))



- 3 Enter the login user name and password and execute the job ([page 9-23](#))



Access are in three levels - "User", "Administrator", and "Machine Administrator". The security levels can be modified only by the "Machine Administrator".


## To manage the job account from PC

In addition to the above settings, the following are necessary to manage the job account from PC.

### To Manage the Users to Print from PCs

Printer driver settings are necessary to manage the users that print on the machine from PCs.

- 1 Set the User Login Administration on the printer driver ([page 9-11](#))
- 2 Print



### To Manage the Users to Use TWAIN for Scanning

TWAIN driver settings on the PC are necessary to manage the users that use TWAIN for scanning.

➔ [To Manage the Users to Scan Using TWAIN \(page 9-13\)](#)

### To Manage the Users to Use WIA for Scanning

WIA driver settings on the PC are necessary to manage the users that use WIA for scanning.

➔ [To Manage the Users to Scan Using WIA \(page 9-14\)](#)

### To Manage the Users to Send Faxes from a PC\*1

FAX driver settings on the PC are necessary to manage the users that send faxes from a PC.

➔ [To Manage the Users that Send Faxes from a PC \(page 9-15\)](#)

\*1 Only on products with the fax function installed.



# Enabling User Login Administration

This enables user login administration. Select one of the following authentication methods:

Item	Descriptions
<b>Local Authentication</b>	User authentication based on user properties on the local user list stored in the machine.
<b>Network Authentication</b>	User authentication based on Authentication Server. Use a user property stored in Authentication Server to access the network authentication login page.

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key

## 2 Configure the settings.

- 1 [▲] [▼] key > [User Login] > [OK] key > [▲] [▼] key > [Local Authentic.] or [Netwk Authentic.] > [OK] key

### NOTE

Select [Off] to disable user login administration.

### When selecting [Netwk Authentic.]

- 1 [▲] [▼] key > [NTLM], [Kerberos] or [Ext.] > [OK] key
- 2 Enter the host name (64 characters or less) for the Authentication Server and select the [OK] key.
- 3 Select the domain name for the Authentication Server, and select the [OK] key.  
If the domain has not been set, select the number where "-----" is displayed and select [Menu]. Select [Edit] and select the [OK] key then enter the domain name (in 256 characters or less). Select the [OK] key and the domain will be registered.  
To edit or delete a domain name that has already been registered, select that domain name and select [Menu].

### NOTE

Up to 10 domain names can be registered.

- 4 When selecting [**Ext.**] as the server type, enter the port number and select the [**OK**] key.



**NOTE**

If the login user name and password are rejected, check the following settings.

- Network Authentication setting of the machine
- User property of the Authentication Server
- Date and time setting of the machine and the Authentication Server

If you cannot login because of the setting of the machine, login with any administrator registered in the local user list and correct the settings.

# Setting User Login Administration

This registers, alters and deletes users and configures the settings for User Login Administration.

## Authentication Security

If user authentication is enabled, configure the user authentication settings.

### User Account Lockout Setting

You can prohibit the use of a user account if an incorrect password is entered repeatedly to login with that account.

#### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key > [▲] [▼] key > [Account Lockout] > [OK] key

#### 2 Configure the settings.

The following settings can be selected.

Item	Descriptions
<b>Lockout</b>	Select whether or not account lockout policy is enabled. <b>Value:</b> Off, On
<b>Lockout Policy</b>	Specify the conditions and the extent to which the account lockout is applied.
<b>Number of Retries</b>	Specify how many login retries are allowed until the account is locked out. <b>Value:</b> 1 to 10 times
<b>Lockout Duration</b>	Specify how long the account is to be locked out until it is unlocked. <b>Value:</b> 1 to 60 minutes
<b>Lockout Target</b>	Specify the extent to which the account lockout is applied. [Remote Only] locks out all operations from outside the operation panel. <b>Value:</b> All, Remote Only
<b>Locked out Users</b>	Displays a list of locked out users. <b>To cancel the locks:</b> Select the [▲] or [▼] key to select the user in the list, and [Select]. A checkmark will be placed on the right of the selected user. Select [Menu]. Select [Unlock] and the [OK] key.

## Adding a User (Local User List)

This adds a new user. You can add up to 100 users (including the default login user name).

### NOTE

By default, one of each default user with machine administrator rights and administrator privileges is already stored. Each user's properties are:

#### Machine Administrator

User Name: DeviceAdmin

**Login User Name: 3000**

**Login Password: 3000**

Access Level: Machine Administrator

#### Administrator

User Name: Admin

Login User Name: Admin

Login Password: Admin

Access Level: Administrator

\* Upper case and lower case letters are distinguished (case sensitive).

It is recommended to periodically change the user name, login user name and login password regularly for your security.

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

- 2 [▲] [▼] key > [User Login Set.] > [OK] key > [▲] [▼] key > [Local User List] > [OK] key > [Menu] > [▲] [▼] key > [Add User] > [OK] key

## 2 Enter the user information.

- 1 Enter the name displayed on the user list (up to 32 characters) and select the **[OK]** key.



### NOTE

For details on entering characters, refer to the the following:

➔ [Character Entry Method \(page 11-11\)](#)

- 2 Enter the login user name to login (up to 64 characters) and select the **[OK]** key.



### NOTE

The same login user name cannot be registered.

- 3 To enter detailed user information, select **[▲]** **[▼]** key > **[Detail]** > **[OK]** key  
To exit the operation, select **[▲]** **[▼]** key > **[Exit]** > **[OK]** key
- 4 Enter the detailed user information.

Select **[Edit]**, **[Change]** or **[Detail]** on each item, enter the information and then select the **[OK]** key. Select the **[▶]** key to view the next screen. Select the **[◀]** key to return to the previous screen. The table below explains the user information to be registered.

Item	Descriptions
<b>User Name</b> *1	Enter the name displayed on the user list (up to 32 characters).
<b>Login User Name</b> *1	Enter the login user name to login (up to 64 characters). The same login user name cannot be registered.
<b>Login Password</b>	Enter the password to login (up to 64 characters). Reenter the same password for confirmation and select the <b>[OK]</b> key.
<b>E-mail Address</b>	The user can register his/her E-mail address. The registered address will be automatically selected for subsequent operations that need any E-mail function.
<b>Access Level</b> *1	Select "Administrator" or "User" for user access privileges.
<b>Account Name</b>	Add an account where the user belongs. The user, who registered his/her account name, can login without entering the account ID. ➔ <a href="#">Overview of Job Accounting (page 9-24)</a>
<b>ID Card Information</b>	Register ID card information. Select <b>[Read]</b> and the <b>[OK]</b> key. Place the ID card on the ID card reader, and select <b>[Read]</b> .  <b>NOTE</b> This function is displayed when the optional ID Card Authentication Kit is activated. ➔ <a href="#">Card Authentication Kit(B) "Card Authentication Kit" (page 11-3)</a>  To delete ID card information, select <b>[Delete]</b> > <b>[OK]</b> key.

\*1 Mandatory at user registration.

Item	Descriptions
<b>Local Authorization</b> *1	Set usage authority for each user. Select <b>[Edit]</b> for each item, change the restrictions and then select the <b>[OK]</b> key. Select the <b>[▶]</b> key to view the next screen. Select the <b>[◀]</b> key to return to the previous screen. The following restriction items are available: <b>Print Restrict: Printer</b> Select whether or not use of the print function of the printer is prohibited. <b>Print Restrict: Printer (Full Color)</b> Select whether or not to reject usage of full-color print functions for the printer. <b>Print Restrict: Copy</b> Select whether or not use of the copy print function is prohibited. <b>Print Restrict: Copy (Full Color)</b> Select whether or not to reject usage of full-color print functions for copies. <b>Duplex Restrict:</b> Select whether only duplex printing is allowed. <b>CombineRestrict:</b> Specify whether only Combine is allowed. <b>EcoPrint Restr.:</b> Specify whether only EcoPrint is allowed. <b>Send Restrict.:</b> Select whether or not use of the send function is prohibited. <b>FAX Restrict.*2:</b> Select whether or not use of the fax send function is prohibited. <b>Storing in Box:</b> Select whether or not use of the box store function is prohibited. <b>StoringinMemory:</b> Select whether or not use of the removable memory store function is prohibited.
<b>My Panel</b>	You can register the language selection, and initial screen for each user. Settings registered here can be applied simply by logging in.

\*1 Displayed when Local Authoriz. is enabled.

➔ [Local Authoriz. \(Local Authorization\) \(page 9-16\)](#)

\*2 Only on products with the fax function installed.

### 3 Select the **[OK]** key.

A new user is added on the local user list.

## Changing User Properties

User properties can be changed. Types of user properties that could be changed may be different depending on user access privilege.

### NOTE

To change the user information of the machine administrator, you must log in with machine administrator authority. You can only view user information if you log in as a regular user.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

### For a user with administrator rights who logs in

User properties can be changed and users can be deleted. The items, which can be added, are all able to be changed.

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key > [▲] [▼] key > [Local User List] > [OK] key

## 2 Change the user properties.

### Changing user properties

- 1 Select the user whose properties you wish to change, and the [OK] key.
- 2 Refer to step 2 of "Adding a User (Local User List)" to change a user property.

➔ [Adding a User \(Local User List\) \(page 9-6\)](#)

- 3 [OK] key > [Yes]

The user information is changed.

### Deleting a user

- 1 Select the user whose properties you wish to delete, and [Menu].
- 2 [▲] [▼] key > [Delete] > [OK] key > [Yes]

The selected user will be deleted.

### NOTE

The default user with machine administrator rights cannot be deleted.

## To change the user information of logged in user (User Property)

These users can partially change their own user properties including user name, login password, E-mail address, and Simple Login.

Although "Login User Name", "Access Level", or "Account Name" cannot be changed, the users can check the present status.



### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [User Property] > [OK] key

### 2 Change the user properties.

1 Refer to step 2 of "Adding a User (Local User List)" to change a user property.

➔ [Adding a User \(Local User List\) \(page 9-6\)](#)

Item	Description
<b>User Name</b>	Changes the name shown on the user list. Up to 32 characters can be entered.
<b>Login User Name</b>	Displays the login user name that is entered at login.
<b>Login Password</b>	Changes the password that is entered at login. Up to 64 characters can be entered.
<b>E-mail Address</b>	Changes the user's e-mail address. Up to 128 characters can be entered.   <b>NOTE</b> This cannot be changed for network authentication.
<b>Access Level</b>	Displays the user's access level.
<b>Account Name</b>	Displays the account where the user belongs.
<b>ID Card Information</b>	Displays the ID card information of the logged in user.   <b>NOTE</b> This function is displayed when the optional ID Card Authentication Kit is activated.  ➔ <a href="#">Card Authentication Kit(B) "Card Authentication Kit" (page 11-3)</a>  This function does not appear when the server type is set to [Ext.] in Network Authentication, and logged in with the user account certificated in the server specified as the [Ext.] server type.
<b>Local Authoriz.*1</b>	Set usage authority for each user.  ➔ <a href="#">Local Authorization (page 9-8)</a>
<b>My Panel</b>	Register the language and default screen for each user.  ➔ <a href="#">My Panel (page 9-8)</a>  Network users are not displayed.

\*1 Displayed when Local Authorization is enabled.

➔ [Local Authoriz. \(Local Authorization\) \(page 9-16\)](#)

2 [OK] key > [Yes]

The user information is changed.



## User Login Administration for Printing

It is possible to manage the users that print on this machine from a PC.

### Setting Printer Driver

To manage the users that print on this machine from a PC, the following settings are necessary in the printer driver.

#### 1 Display the screen.

- 1 Click **[Start]** button on the Windows, and then click **[Devices and Printers]**.




#### NOTE

In Windows 8, select **[Settings]** in charms on Desktop, and select **[Control Panel]**, and then **[Devices and Printers]**.

- 2 Right-click the printer driver icon of the machine, and click the **[Printer properties]** menu of the printer driver.
- 3 Click **[Administrator]** on the **[Device Settings]** tab.

#### 2 Configure the settings.

- 1 Select **[User Login]** on the **[User Login]** tab.



- 2 Set the User Login Administration.

**[Use specific name]:** This option can be used to specify a user name and password to use the same User login for every print job. If this option is selected, the user does not have to type the name and password for each print job.

**[Prompt for name]:** A screen for entering the user name and password will be displayed when attempting a printing. The user name and password must be entered each time a printing is attempted.

**[Prompt for name and validate]:** A screen for entering the user name and password will be displayed when attempting a printing. The user name and password stored in the Login user name list needs to be entered. The user name and password must be entered each time a printing is attempted.

**[Validate user name (computer) or prompt for login user name]:** When printing, the Windows user name is searched in the "Login user names" and printing is possible if the name is registered. If the name is not registered, the printing will be canceled for users with only user authority. If the user has administrator privileges, the screen to enter the user name and password will appear.

- 3 Click **[OK]**.



**NOTE**

For other settings of job accounting, refer to the following:

➔ **Printer Driver User Guide**

## To Manage the Users to Scan Using TWAIN

It is possible to manage the users that scan using TWAIN.

### Setting TWAIN Driver

To manage the users that scan using TWAIN, the following settings are necessary in the TWAIN driver.

#### 1 Display the screen.


- 1 Select **[Start]** button on the Windows, **[All Programs]**, **[Kyocera]** and then **[TWAIN Driver Setting]**.

TWAIN Driver screen appears.

#### NOTE


In Windows 8, select **[Search]** in charms, **[Apps]**, and then **[TWAIN Driver Setting]**.

- 2 Select the machine, and click **[Edit]**.



#### 2 Configure the settings.

- 1 Click **[User Authentication Settings]**.
- 2 Select the checkbox beside **[Authentication]**, and enter Login User Name and Password.



- 3 Click **[OK]**.

## To Manage the Users to Scan Using WIA

It is possible to manage the users that scan using WIA.

### Setting WIA Driver

To manage the users that scan using WIA, the following settings are necessary in the WIA driver.


#### 1 Display the screen.

- 1 Click **[Start]** button on the Windows and enter **[Scanner]** in **[Program and File Search]**. Click **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

#### NOTE


In Windows 8, click **[Search]** in charms, and then **[Settings]**, and enter "Scanner" in the search box. Click **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

- 2 Select the same name as this machine from WIA Drivers, and press **[Properties]**.



#### 2 Configure the settings.

- 1 Select the checkbox beside **[Authentication]** on the **[Settings]** tab, and enter Login User Name and Password.



- 2 Click **[OK]**.

## To Manage the Users that Send Faxes from a PC

It is possible to manage the users that send faxes from a PC.

### Setting FAX Driver

To manage the users that send faxes from a PC, the following settings are necessary in the FAX driver.

#### 1 Display the screen.

- 1 Click **[Start]** button on the Windows, and then click **[Devices and Printers]**.


#### NOTE

In Windows 8, select **[Settings]** in charms on Desktop, and select **[Control Panel]**, and then **[Devices and Printers]**.

- 2 Right-click the printer driver icon of the machine, and click the **[Printer properties]** menu of the printer driver.
- 3 Click **[FAX TX Setting]** on the **[Printing Preferences]** window.

#### 2 Configure the settings.

- 1 Select **[User Login]** on the **[Authentication]** tab.



- 2 Set the User Login Administration.

**[Use Specific Login User Name]:** This option can be used to specify a user name and password to use the same User login for every FAX job. If this option is selected, the user does not have to type the name and password for each FAX job.

**[Prompt for Login User Name]:** A screen for entering the user name and password will be displayed when attempting a transmission. The user name and password must be entered each time a transmission is attempted.

- 3 Click **[OK]**.

## Local Authoriz. (Local Authorization)

Select whether or not to use Local Authorization.

### NOTE

When using Local Authorization, the user authentication type must be set to **[Local Authoriz.]**.

➔ [Enabling User Login Administration \(page 9-3\)](#)

## 1 Display the screen.

1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select **[Login]**. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

2 [▲] [▼] key > [User Login Set.] > [OK] key

## 2 Configure the setting.

[▲] [▼] key > [Local Authoriz.] > [OK] key > [▲] [▼] key > [Off] or [On] > [OK] key

## Group Auth. (Group Authorization Settings)

Set restrictions of the machine usage by each individual group registered in the authentication server.

### NOTE

- To use the group authorization settings, [**Netwk Authentic.**] must be selected for the authentication method in "Enabling User Login Administration". Select "On" for "LDAP" in "Protocol Detail".
- ➔ [Enabling User Login Administration \(page 9-3\)](#)  
[Protocol Detail \(page 8-27\)](#)
- Setting to use group authorization is performed from the operation panel. The groups should be registered with Command Center RX.
- ➔ [Command Center RX User Guide](#)

## Group Authorization

Use the group authorization.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key

### 2 Configure the setting.

- 1 [▲] [▼] key > [Group Auth.] > [OK] key > [▲] [▼] key > [Off] or [On] > [OK] key

## Guest Authorization Set.

When User Login Administration is enabled, set the functions that guest users who cannot log in to the machine are allowed to use.

### NOTE

To use Guest Authorization Set., User Login Administration must be enabled in "Enabling User Login Administration".

➔ [Enabling User Login Administration \(page 9-3\)](#)

## Guest Authorization

Use the guest authorization.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key > [▲] [▼] key > [Guest Auth. Set.] > [OK] key > [▲] [▼] key > [Guest Auth.] > [OK] key

### 2 Configure the setting.

- [▲] [▼] key > [On] or [Off] > [OK] key

### NOTE

If the guest authorization setting is enabled, the [Authentication/Logout] key must be selected when logging in.

In the guest user default settings, only monochrome copying can be used. If you wish to use a different function, log in as a user who can use that function, or change the settings in the guest properties.



## Guest Property

Register guest user information and functions that are restricted.

The table below explains the user information to be registered.

Item	Descriptions
<b>User Name</b>	Enter the name displayed on the user list (up to 32 characters). The default setting is "Guest User".
<b>Access Level</b>	The authority of the user appears. This cannot be changed.
<b>Account Name</b>	Add an account where the user belongs.
<b>Authorization Rules</b>	<p>Set usage authority for each user. The items you can restrict the access level with are as follows.</p> <p><b>Print Restrict: Printer</b> Select whether or not use of the print function of the printer is prohibited.</p> <p><b>Print Restrict: Printer (Full Color)</b> Select whether or not use of the print function (color) of the printer is prohibited.</p> <p><b>Print Restrict: Copy</b> Select whether or not use of the copy print function is prohibited.</p> <p><b>Print Restrict: Copy (Full Color)</b> Select whether or not use of the copy print function (full color) is prohibited.</p> <p><b>Duplex Restrict</b> Select whether only duplex printing is allowed.</p> <p><b>Combine Restrict</b> Specify whether only Combine is allowed.</p> <p><b>EcoPrint Restr.</b> Specify whether only EcoPrint is allowed.</p> <p><b>Send Restrict</b> Select whether or not use of the send function is prohibited.</p> <p><b>FAX Restrict.*1</b> Select whether or not use of the fax send function is prohibited.</p> <p><b>Storing in Box:</b> Select whether or not use of the box store function is prohibited.</p> <p><b>Storing in Memory:</b> Select whether or not use of the removable memory store function is prohibited.</p>

\*1 Only on products with the fax function installed.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

- 2 [▲] [▼] key > [User Login Set.] > [OK] key

## **2 Configure the settings.**

**1** [▲][▼] key > [Guest Auth. Set.] > [OK] key > [▲][▼] key > [Guest Property] > [OK] key

**2** Register guest user information and functions that are restricted.

Select [Edit], [Change] or [Detail] on each item, enter the information and then select the [OK] key.

Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.

## **3 Select the [OK] key.**

## NW User Property (Obtain Network User Property)

Set the required information to obtain the network user property from the LDAP server. The user name and E-mail address obtained with this setting is shown in the user information, the status confirmation screen, and the header of E-mail.

### NOTE

- To obtain the network user property from the LDAP server, [**Netwk Authentic.**] must be selected for the authentication method in "Enabling User Login Administration". Select "On" for "LDAP" in "Protocol Detail".
- ➔ [Enabling User Login Administration \(page 9-3\)](#)  
[Protocol Detail \(page 8-27\)](#)
- Setting to obtain network user information is performed from the operation panel. The details of the information to be obtained should be set with Command Center RX.
- ➔ **Command Center RX User Guide**

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [User Login Set.] > [OK] key

## 2 Configure the settings.

- [▲] [▼] key > [NW User Property] > [OK] key > [▲] [▼] key > [Off] or [On] > [OK] key

## ID Card Settings

If ID card authentication is enabled, select the authentication type.

### NOTE

This functions appears when the Card Authentication kit is activated.

➔ [Card Authentication Kit\(B\) "Card Authentication Kit" \(page 11-3\)](#)

## 1 Display the screen.

1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

2 [▲] [▼] key > [User Login Set.] > [OK] key

## 2 Configure the settings.

[▲] [▼] key > [ID Card Settings] > [OK] key

The following settings can be selected.

Item	Descriptions
<b>Key Login</b>	When ID card authentication is enabled, select whether or not login by keyboard is allowed. <b>Value:</b> Permit, Prohibit
<b>Additional Auth.*1</b>	Select whether or not to require password entry after authenticating by ID card. <b>Value:</b> Off, Use Password

\*1 This function does not appear when the server type is set to [NTLM] or [Kerberos] in "Network Authentication".

# Using User Login Administration

This section explains procedures while setting job accounting.

## Login/Logout

If user login administration is enabled, the login user name and login password entry screen appears each time you use this machine.

Use the procedure below to login and logout.

### Login

If the login user name entry screen appears during operations, log in by referring to the following:

➔ [Login \(page 2-14\)](#)


### Logout

When the operations are complete, select the **[Authentication/Logout]** key to return to the login user name and login password entry screen.

# Overview of Job Accounting

Job accounting manages the copy/print/scan/FAX count accumulated by individual accounts by assigning an ID to each account.

- 1** Enable job accounting. (Refer to [page 9-25.](#))
- 2** Setting an account. (Refer to [page 9-27.](#))
- 3** Enter the assigned account ID when performing the job. (Refer to [page 9-23.](#))
- 4** Count the number of pages copied, printed, scanned and faxed.




## To manage the job account from PC

In addition to the above settings, the following are necessary to manage the job account from PC.

### To Manage the Number of Sheets Used on Jobs Printed from a PC

To manage the number of jobs to be printed from the PC on the network, you need to configure settings by using the printer driver on the PC.

- 1** Set Job Accounting for the PC on the network by using the printer driver. (Refer to [page 9-32.](#))
- 2** Execute printing.
- 3** Count the number of pages printed.



### To Manage the Scan Job Account by Using TWAIN

To manage the scan job account by using TWAIN, you need to configure the TWAIN driver settings on the computer connected to the machine.

➔ [Job Accounting for Scan Using TWAIN \(page 9-33\)](#)

### To Manage the Scan Job Account by Using WIA

To manage the scan job account by using WIA, you need to configure the WIA driver settings on the computer connected to the machine.

➔ [Job Accounting for Scan Using WIA \(page 9-34\)](#)

### To Manage the FAX Job Transmitted from a PC \*1

To manage the number of FAX jobs transmitted from the PC, you need to configure the settings by using the FAX Driver on the PC.

➔ [Job Accounting for the FAX Transmitted from a Computer \(page 9-35\)](#)

\*1 Only on products with the fax function installed.

# Enabling Job Accounting

Enable job accounting. Use the procedure below.

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [Job Account.Set.] > [OK] key

## 2 Configure the settings.

- [▲] [▼] key > [Job Accounting] > [OK] key > [▲] [▼] key > [On] > [OK] key

### NOTE

- To disable job accounting, select [**Off**].
- When the display returns to System Menu default screen, logout is automatically executed and the screen to enter the Account ID appears. To continue the operation, enter the Account ID.

## Job Accounting Access

Set the job accounting access.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [Job Account.Set.] > [OK] key

### 2 Configure the settings.

- [▲] [▼] key > [AccountingAccess] > [OK] key > [▲] [▼] key > [Local] or [Network] > [OK] key



# Setting an Account

You can add, change and delete an account and set the restriction for each account.

## Adding an Account

Up to 100 individual accounts can be added. The following entries are required.

Item	Descriptions
Account Name	Enter the account name (up to 32 characters).
Account ID	Enter the account ID as many as eight digits (between 0 and 99999999).
Restriction	This prohibits printing/scanning or restricts the number of sheets to load. ➔ <a href="#">Restricting the Use of the Machine (page 9-29)</a>

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [Job Account.Set.] > [OK] key > [▲] [▼] key > [Account. List] > [OK] key > [Menu] > [▲] [▼] key > [Add Account] > [OK] key

### 2 Enter the account information.

- 1 Enter the account name > [OK] key

#### NOTE

For details on entering characters, refer to the the following:

➔ [Character Entry Method \(page 11-11\)](#)

- 2 Enter the account ID > [OK] key

#### NOTE

Any "Account ID" that has already registered cannot be used. Enter any other account ID.

- 3 To apply restriction to the account ID, select [▲] [▼] key > [Detail] > [OK] key.  
To exit the operation, select [▲] [▼] key > [Exit] > [OK] key.

- 4 Check the account name and account ID and set the use restrictions.

To change the details, select **[Edit]**, enter the information and then select the **[OK]** key. Select the **[▶]** key to view the next screen. Select the **[◀]** key to return to the previous screen.

➔ [Restricting the Use of the Machine \(page 9-29\)](#)

- 5 Select the **[OK]** key.

A new account is added on the account list.

## Restricting the Use of the Machine

This section explains how to restrict the use of the machine by account or the number of sheets available.

The items that can be restricted differ depending on whether "Individual" or "Total" is selected for "Copy/Print Count".

➔ [Copy/Print Count \(page 9-36\)](#)

### Restriction Items

"Individual" selected for Copy/Printer Count "Split" selected for Copy/Printer Count

Item	Descriptions
<b>Print Restrict Copy (Total)</b>	Limits the number of sheets used for copying.
<b>Print Restrict Copy (Full Color)</b>	Limits the number of pages used for full-color copying.
<b>Print Restrict Printer (Total)</b>	Limits the number of sheets used for printing.
<b>Print Restrict Printer (Full Color)</b>	Limits the number of pages used for color printing.
<b>Scan Restrict. Others</b>	Limits the number of sheets scanned (excludes copying).
<b>FAX TX Restrict</b>	Limits the number of sheets sent by fax. This is displayed only on products with the fax function installed.

"Total" selected for Copy/Printer Count

Item	Descriptions
<b>Print Restrict Total</b>	Limits the total number of sheets used for copying and printing.
<b>Print Restrict Full Color</b>	Limits the number of pages used for full-color printing.
<b>Scan Restrict. Others</b>	Limits the number of sheets scanned (excludes copying).
<b>FAX TX Restrict</b>	Limits the number of sheets sent by fax. This is displayed only on products with the fax function installed.

### Applying Restriction

Restriction can be applied in the following modes:

Item	Descriptions
<b>Off</b>	No restriction is applied.
<b>Counter Limit*<sup>1</sup></b>	Restricts the print counter in one-page increments up to 9,999,999 copies.
<b>Reject Usage</b>	Restriction is applied.

\*1 If [Counter Limit] is selected, the [Limit Pages] screen appears after the [OK] key is selected. Enter a counter limit on pages using the numeric keys, and select the [OK] key.

## Editing an Account

This changes the registered account information.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [Job Account.Set.] > [OK] key > [▲] [▼] key > [Account. List] > [OK] key

### 2 Edit an account.

- 1 Select the account you want to change and select the [OK] key.

#### NOTE

The account information can be changed by selecting [**Menu**], selecting [**Detail/Edit**] and then selecting the [OK] key.

- 2 Refer to step 2 of "Adding an Account" and "Restricting the Use of the Machine" to change account information.

➔ [Adding an Account \(page 9-27\)](#)  
[Restricting the Use of the Machine \(page 9-29\)](#)

- 3 [OK] key > [Yes]

The account information is changed.

## Deleting an Account

This deletes the account.

### 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key



#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

- 2 [▲] [▼] key > [Job Account.Set.] > [OK] key > [▲] [▼] key > [Account. List] > [OK] key

### 2 Delete an account.

- 1 Select the account you want to delete and [**Menu**].
- 2 [▲] [▼] key > [**Delete**] > [OK] key > [**Yes**]

The account is deleted.

## Job Accounting for Printing

The number of jobs to be printed from the computer can be managed by Job Accounting.

### Setting Printer Driver

To manage the number of jobs to be printed from the PC on the network, you need configure the following settings by using the printer driver on the PC.

#### 1 Display the screen.

- 1 Click **[Start]** button on the Windows, and then click **[Devices and Printers]**.


#### NOTE

In Windows 8, select **[Settings]** in charms on Desktop, and select **[Control Panel]**, and then **[Devices and Printers]**.

- 2 Right-click the printer driver icon of the machine, and click the **[Printer properties]** menu of the printer driver.
- 3 Click **[Administrator]** on the **[Device Settings]** tab.

#### 2 Configure the settings.

- 1 Select **[Job accounting]** on the **[Job Accounting]** tab.



- 2 Set the Account ID.

**[Use specific account ID]:** Enter the Account ID. Printing will be performed using the entered Account ID. If this option is selected, the user does not have to enter the Account ID for each print job.

**[Prompt for account ID]:** A screen for entering the Account ID will be displayed when attempting a printing. The Account ID must be entered each time a printing is attempted.

**[Prompt for account ID and validate]:** A screen for entering the Account ID will be displayed when attempting a printing. The Account ID stored in the Account ID list needs to be entered. The Account ID must be entered each time a printing is attempted.

**[Display account ID list]:** The Account ID list is displayed when printing. The Account ID to be used needs to be selected from the list.

- 3 Click **[OK]**.

#### NOTE

For other settings of job accounting, refer to the following:

➔ **Printer Driver User Guide**

## Job Accounting for Scan Using TWAIN

The number of jobs scanned by using TWAIN can be managed by Job Accounting.

### Setting TWAIN Driver

To manage the number of jobs scanned by using TWAIN, you need to configure the following settings by using the TWAIN Driver on the computer.

#### 1 Display the screen.

- 1 Select **[Start]** button on the Windows, **[All Programs]**, **[Kyocera]** and then **[TWAIN Driver Setting]**.


TWAIN Driver screen appears.



#### NOTE


In Windows 8, select **[Search]** in charms, **[Apps]**, and then **[TWAIN Driver Setting]**.

- 2 Select the machine, click **[Edit]**.



#### 2 Configure the settings.

- 1 Click **[User Authentication Settings]**.
- 2 Select the checkbox beside **[Account ID]**, and enter the account ID.



- 3 Click **[OK]**.

## Job Accounting for Scan Using WIA

The number of jobs scanned by using WIA can be managed by Job Accounting.

### Setting WIA Driver

To manage the number of jobs scanned by using WIA, you need to configure the following settings by using the WIA Driver on the computer.


#### 1 Display the screen.

- 1 Click **[Start]** button on the Windows and enter **[Scanner]** in **[Program and File Search]**. Click **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

#### NOTE


In Windows 8, click **[Search]** in charms, and then **[Settings]**, and enter "Scanner" in the search box. Click **[View scanners and cameras]** in the search list then the Scanners and Cameras screen appears.

- 2 Select the same name as this machine from WIA Drivers, and press **[Properties]**.



#### 2 Configure WIA Driver.

- 1 Select the checkbox beside **[Account ID]** on the **[Settings]** tab, and enter the Account ID.



- 2 Click **[OK]**.



# Job Accounting for the FAX Transmitted from a Computer

The number of FAX jobs transmitted from the computer can be managed by Job Accounting.



### NOTE

FAX functions are available only on products with the fax function installed.

## Setting FAX Driver

To manage the number of FAX jobs transmitted from the computer, you need to configure the following settings by using the FAX Driver on the computer.

### 1 Display the screen.

- 1 Click **[Start]** button on the Windows, and then click **[Devices and Printers]**.




### NOTE

In Windows 8, select **[Settings]** in charms on Desktop, and select **[Control Panel]**, and then **[Devices and Printers]**.

- 2 Right click the name of the machine to be used as the FAX Driver and select **[Printing preferences]** from the resulting pull-down menu.
- 3 Click **[FAX TX Setting]** in the **[Printing Preferences]** window.

### 2 Configure the settings.

- 1 Select **[Job Accounting]** on the **[Authentication]** tab.



- 2 Set the Job Accounting.

**[Use Specific Account ID]:** This option can be used to specify an account ID to use the same Account ID for every FAX job. If this option is selected, the user does not have to enter the Account ID for each FAX job.

**[Prompt for Account ID]:** A screen for entering the Account ID will be displayed when attempting a transmission. The Account ID must be entered each time a transmission is attempted.

- 3 Click **[OK]**.

# Configuring Job Accounting

## Default Setting

Set the defaults for job accounting. To configure the settings, select the item in Default Setting and select the setting item.

[System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key > [▲] [▼] key > [Job Account.Set.] > [OK] key > [▲] [▼] key > [Default Setting] > [OK] key

For details on each function, see the table below.

Item	Description
<b>Apply Limit</b>	<p>This specifies how the machine behaves when the counter has reached the limit of restriction. The table below describes the action taken.</p> <p><b>Value</b></p> <p><b>Immediately: Job stops when the counter reaches its limit. The next job will be prohibited in sending or in storing in the box.</b></p> <p><b>Subsequently: Printing/scanning of the job continues but the subsequent job will be rejected.</b></p> <p><b>Alert Only: Job continues while displaying an alert message.</b></p>
<b>Copy/Print Count</b>	<p>You can select how the copying and printing page counts are shown - either the total of both or each of copying and printing individually (Split). The selection may influence restriction on the count and count method.</p> <p><b>Value: Total, Split</b></p> <p>➔ <a href="#">Restricting the Use of the Machine (page 9-29)</a>  <a href="#">Print Accounting Report (page 9-38)</a></p>
<b>Counter Limit</b>	<p>When you add a new account, you can change the default restrictions on the number of sheets used. You can set any number from 1 to 9,999,999.</p> <p>The items that can be set differ depending on whether [Split] or [Total] is selected for [Copy/Print Count].</p> <p>➔ <a href="#">Copy/Print Count (page 9-36)</a></p>
<b>[Split] selected for Copy/Printer Count</b>	
<b>Copy (Total)</b>	Sets the default restriction on the number of sheets used for copying.
<b>Copy (Full Color)</b>	Sets the default restriction on the number of sheets used for full-color copying.
<b>Printer (Total)</b>	Sets the default restriction on the number of sheets used for printing.
<b>Print. (Full Col.)</b>	Sets the default restriction on the number of sheets used for color printing.
<b>Scan (Others)</b>	Sets the default restriction on the number of sheets used for scanning (excludes copying).
<b>FAX TX<sup>*1</sup></b>	Sets the default restriction on the number of sheets used for sending faxes.
<b>[Total] selected for Copy/Printer Count</b>	
<b>Print (Total)</b>	Sets the default restriction on the total number of sheets used for copying and printing.
<b>Print (Full Col.)</b>	Sets the default restriction on the number of sheets used for full-color printing.
<b>Scan (Others)</b>	Sets the default restriction on the number of sheets used for scanning (excludes copying).
<b>FAX TX<sup>*1</sup></b>	Sets the default restriction on the number of sheets used for sending faxes.

\*1 Only on products with the fax function installed.

## Counting the Number of Pages Printed

This counts the number of pages printed. Counts are classified into Total Job Accounting and Each Job Accounting. A new count can also be started after resetting the count data which was stored for a certain period of time.

[System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key > [▲] [▼] key > [Job Account.Set.] > [OK] key > [▲] [▼] key > [Total Accounting] or [Each Job Account] > [OK] key

### Total Accounting

This counts the number of pages for all accounts and resets the counts for those accounts together at the same time.

### Each Job Account

This counts the number of pages for each account and resets the counts by account. When checking Each Job Accounting, select the account for which you want to check the count.

Types of the counts are as follows.

Item	Descriptions
<b>Printed Pages</b>	Displays the number of pages copied and printed, and the total number of pages used. You can also use [FAX RX Pages] <sup>*1</sup> , [Duplex Pages] and [Combine Pages] to check the number of pages used.
<b>Copy/Print Pages</b>	Displays the number of pages copied and printed, and the total number of pages used. Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.
<b>FAX RX Pages</b>	Displays the number of pages received.
<b>Total PrintPages</b>	Displays the total number of pages used for copying and printing.
<b>Duplex Pages</b>	Displays the number of pages printed in [1-Sided] mode, [2-Sided] mode, and the total pages in both modes. Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.
<b>Combine Pages</b>	Displays the number of pages printed in [None] (no Combine) mode, [2 in 1] mode, [4 in 1] mode, and the total pages in both modes. Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.
<b>Scanned Pages</b>	Displays the number of pages scanned for copying, faxing and other functions, as well as the total number of pages scanned. Select the [▶] key to view the next screen. Select the [◀] key to return to the previous screen.
<b>FAX TX Pages<sup>*1</sup></b>	Displays the number of pages faxed.
<b>FAX TX Time<sup>*1</sup></b>	Displays the total duration of FAX transmissions.
<b>Counter Reset</b>	Resets the counter. Select [Yes] in the confirmation screen.

\*1 Only on products with the fax function installed.


To check other items, select the [OK] key to return to the screen one level higher.

## Print Accounting Report

The total pages counted of all relevant accounts can be printed as an accounting report.

Reports have different formats depending on how the count of copiers and printers is administered.

**When "Individual" is selected for Managing the Copy/Printer Count.**



Use the procedure below to print a job accounting report.

### 1 Prepare paper.

Check that A4 or Letter paper is loaded in the cassette.

### 2 Display the screen.

1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key

#### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

2 [▲] [▼] key > [Job Account.Set.] > [OK] key

### 3 Print the report.

[▲] [▼] key > [Account. Report] > [OK] key > [Yes]

Accounting report is printed.

# Using Job Accounting

This section explains procedures while setting job accounting.

## Login/Logout

If job accounting is enabled, an account ID entry screen appears each time you use this machine.

Use the procedure below to login and logout.

### Login

- 1 In the account ID entry screen, enter the account ID using the numeric keys and select the **[OK]** key.

#### NOTE

- If you entered a wrong character, select the **[Clear]** key and enter the account ID again.
- If the entered account ID does not match the registered ID, a warning beep will sound and login will fail. Enter the correct account ID.
- By selecting **[Counter]**, you can refer to the number of pages printed and the number of pages scanned.

#### **When the screen to enter the login user name and password appears**

If user login administration is enabled, the screen to enter the login user name and password appears. Enter a login user name and password to login. If the user has already registered the account information, the account ID entry would be skipped.

➔ [Adding a User \(Local User List\) \(page 9-6\)](#)

- 2 Proceed to complete the rest of the steps.

### Logout

When the operations are complete, select the **[Authentication/Logout]** key to return to the account ID entry screen.

# Unknown ID Job

This specifies the behavior for handling the jobs sent with unknown or unsend login user names or User ID. If the User Login is set to invalid and Job Accounting is set to valid, follow the procedure when the Account ID is unknown.

The setting items are as follows.

Item	Descriptions
Permit	The job is permitted to be printed.
Reject	The job is rejected (not printed).

## 1 Display the screen.

- 1 [System Menu/Counter] key > [▲] [▼] key > [User/Job Account] > [OK] key



### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [**Login**]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name:** 3000

**Login Password:** 3000

## 2 Configure the settings.

- [▲] [▼] key > [Unknown ID Job] > [OK] key > [▲] [▼] key > [Reject] or [Permit] > [OK] key

# 10 Troubleshooting

This chapter explains the following topics:

Regular Maintenance .....	10-2
Cleaning .....	10-2
Toner Container Replacement .....	10-4
Waste Toner Box Replacement .....	10-8
Replacing Staples .....	10-10
Troubleshooting .....	10-11
Solving Malfunctions .....	10-11
Responding to Messages .....	10-17
Adjustment/Maintenance .....	10-29
Clearing Paper Jams .....	10-34
Clearing a Staple Jam .....	10-49

# Regular Maintenance

## Cleaning

Clean the machine regularly to ensure optimum printing quality.



### CAUTION

For safety, always unplug the power cord before cleaning the machine.


### Glass Platen

Wipe the inside of the document processor and the glass platen with a soft cloth dampened with alcohol or mild detergent.



### IMPORTANT

Do not use thinner or other organic solvents.



### Slit Glass

When using the document processor, clean the slit glass surface and the reading guide with the dry cloth.





### IMPORTANT

Do not use water, soap or solvents for cleaning.



### NOTE

Dirt on the slit glass or the reading guide may cause black streaks to appear in the output.






## Paper Transfer Unit

The paper transfer unit should be cleaned each time the toner container and waste toner box are replaced. To maintain optimum print quality, it is also recommended that the inside of the machine be cleaned once a month as well as when the toner container is replaced.

Print problems such as soiling of the reverse side of printed pages may occur if the paper transfer unit becomes dirty.

### CAUTION

Some parts are very hot inside the machine. Exercise caution as there is a risk of burn injury.



Wipe away the paper dust on the registration roller and the paper ramp using the cloth.

### IMPORTANT

Be careful not to touch the transfer roller and transfer belt during cleaning as this may adversely affect print quality.

## Toner Container Replacement

When toner runs low, "Toner is low. (Replace when empty.)" appears in the message display. Make sure you have a new toner container available for replacement.

When the message displays "Replace the toner.", replace the toner.

### Frequency of Toner Container Replacement

The life of the toner containers depends on the amount of toner required to accomplish your printing jobs. According to ISO/IEC 19798 and EcoPrint switched off the toner container can print as follows (A4/Letter paper is assumed):

Toner Color	Life of the Toner Container (Printable pages)
<b>Black</b>	7,000 images
<b>Cyan</b>	5,000 images
<b>Magenta</b>	5,000 images
<b>Yellow</b>	5,000 images



#### NOTE

- The toner container packed with the new printer has to fill up the system when operating the first time. Therefore only 50% of the first toner kits can be used for printing. (For example: ECOSYS M6030cdn/ECOSYS M6530cdn can print 3,500 Black & White images using the black starter toner container.)
- For the toner container, always use a genuine toner container. Using a toner container that is not genuine may cause image defects and product failure.
- The memory chip in the toner container of this product stores information necessary for improving customer convenience, operation of the recycling system for used toner containers, and planning and development of new products. The stored information does not include information that makes it possible to identify individuals, and is only used anonymously for the above purposes.




#### CAUTION

Do not attempt to incinerate parts which contain toner. Dangerous sparks may cause burns.


## Replacing the Toner Container

Installation procedures of the toner container is same for every color. The procedures here represent the yellow toner container.


1




2




3



4




# 5




✔ **IMPORTANT**


Do not touch the points shown below.




# 6




# 7



8



9



**NOTE**

- If the Scanner Unit does not close, check that the new toner container is installed correctly (in step 7).
- Return the exhausted toner container to your dealer or service representative. The collected toner container will be recycled or disposed in accordance with the relevant regulations.

## Waste Toner Box Replacement


When the waste toner box becomes full, immediately replace the waste toner box.




### CAUTION

Do not attempt to incinerate parts which contain toner. Dangerous sparks may cause burns.


1




2




3



4



5




**NOTE**

Return the exhausted waste toner box to your dealer or service representative. The collected waste toner box will be recycled or disposed in accordance with the relevant regulations.



## Replacing Staples

Add staples to the optional manual stapler.



 **NOTE**

If the Staple Unit runs out of staples, contact your dealer or service representative.

**1**



**2**






# Troubleshooting

## Solving Malfunctions



The table below provides general guidelines for problem solving.







If a problem occurs with your machine, look into the checkpoints and perform procedures indicated on the following pages. If the problem persists, contact your Service Representative.





 **NOTE**






When contacting us, the serial number will be necessary. To check the serial number, refer to the following:



➔ [Checking the Equipment's Serial Number \(page 5-5\)](#)

Symptom	Checkpoints	Corrective Actions	Reference Page
The screen does not respond when the main power switch is turned on.	Check the power cord.	Connect both ends of the power cord securely.	<a href="#">page 2-9</a>
Pressing the <b>[Start]</b> key does not produce copies.	Is there a message on the screen?	Determine the appropriate response to the message and respond accordingly.	<a href="#">page 10-17</a>
	Is the machine in Sleep mode?	Select any key on the operation panel to recover the machine from Sleep mode.	<a href="#">page 2-20</a>
Blank sheets are ejected. 	Are the originals loaded correctly?	When placing originals on the platen, place them face-down and align them with the original size indicator plates.	<a href="#">page 5-2</a>
		When placing originals in the document processor, place them face-up.	<a href="#">page 5-3</a>
	—	Check that the settings of the application software.	—
Printouts are totally too light. 	Is the paper damp?	Replace the paper with new paper.	<a href="#">page 3-2</a>
	Have you changed the density?	Select appropriate density level.	<a href="#">page 6-12</a> <a href="#">page 8-34</a>
	Is the toner distributed evenly within the toner container?	Shake the toner container from side to side several times.	<a href="#">page 10-4</a>
	Is EcoPrint mode enabled?	Disable <b>[EcoPrint]</b> mode.	<a href="#">page 8-13</a>
	—	Select the <b>[System Menu/Counter]</b> key > <b>[Adjust/Maint.]</b> > <b>[Service Setting]</b> > <b>[Drum Refresh]</b> , and then select <b>[Yes]</b> .	—
	—	Make sure the paper type setting is correct for the paper being used.	<a href="#">page 8-12</a>

Symptom	Checkpoints	Corrective Actions	Reference Page
<p>Printouts are too dark even though the background of the scanned original is white.</p> 	<p>Have you changed the density?</p>	<p>Select appropriate density level.</p>	<p><a href="#">page 6-12</a> <a href="#">page 8-34</a></p>
<p>Copies have a moire pattern (dots grouped together in patterns and not aligned uniformly).</p> 	<p>Is the original a printed photograph?</p>	<p>Set the original image to <b>[Photo]</b>.</p>	<p><a href="#">page 6-13</a></p>
<p>Texts are not clearly printed.</p> 	<p>Did you choose appropriate image quality for the original?</p>	<p>Select appropriate image quality.</p>	<p><a href="#">page 6-13</a></p>
<p>Black or color dots appear on the white background when white original is scanned.</p> 	<p>Is the original holder or the glass platen dirty?</p>	<p>Clean the original holder or the glass platen.</p>	<p><a href="#">page 10-2</a></p>
<p>Printouts are fuzzy.</p> 	<p>Is the machine being used in conditions of very humid, or humidity or temperature rapidly changes?</p>	<p>Use in an environment that has suitable humidity.</p>	<p>—</p>
	<p>—</p>	<p>Select the <b>[System Menu/Counter]</b> key &gt; <b>[Adjust/Maint.]</b> &gt; <b>[Service Setting]</b> &gt; <b>[Drum Refresh]</b> &gt; <b>[Yes]</b></p>	<p>—</p>
<p>Images are skewed.</p> 	<p>Are the originals placed correctly?</p>	<p>When placing originals on the platen, align them with the original size indicator plates.</p>	<p><a href="#">page 5-2</a></p>
	<p>—</p>	<p>When placing originals in the document processor, align the original width guides securely before placing the originals.</p>	<p><a href="#">page 5-3</a></p>
	<p>Is the paper loaded correctly?</p>	<p>Check the position of the paper width guides.</p>	<p><a href="#">page 3-4</a> <a href="#">page 3-7</a></p>

Symptom	Checkpoints	Corrective Actions	Reference Page
Irregular horizontal lines appear in the image. 	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>MC</b> ] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	—
The altitude is 1000 m or higher and irregular horizontal white lines appear in the image. 	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>Altitude Adj.</b> ], and set to an elevation one level higher than the current setting.	—
The altitude is 1000 m or higher and dots appear in the image. 	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>Altitude Adj.</b> ], and set to an elevation one level higher than the current setting.	—
Paper often jams.	Is the paper loaded correctly?	Load the paper correctly.	<a href="#">page 3-2</a>
	Is the paper of the supported type? Is it in good condition?	Remove the paper, turn it over, and reload it.	<a href="#">page 3-4</a>
	Is the paper curled, folded or wrinkled?	Replace the paper with new paper.	<a href="#">page 3-4</a>
	Are there any loose scraps or jammed paper in the machine?	Remove any jammed paper.	<a href="#">page 10-34</a>
2 or more sheets are overlaps when ejected. (multi feed) 	—	Load the paper correctly.	<a href="#">page 3-2</a>
Printouts are wrinkled.	Is the paper loaded correctly?	Load the paper correctly.	<a href="#">page 3-2</a>
	Is the paper damp?	Replace the paper with new paper.	<a href="#">page 3-2</a>

Symptom	Checkpoints	Corrective Actions	Reference Page
<p>Printouts are curled.</p> 	Is the paper damp?	Replace the paper with new paper.	<a href="#">page 3-2</a>
Cannot print.	Is the machine plugged in?	Plug the power cord into an AC outlet.	—
	Is the machine powered on?	Turn on the power switch.	<a href="#">page 2-10</a>
	Are the USB cable and network cable connected?	Connect the correct USB cable and network cable securely.	<a href="#">page 2-8</a>
	Is the print job paused?	Resume printing.	<a href="#">page 7-13</a>
Cannot print with USB memory. USB memory not recognized.	Is the USB host blocked?	Select [ <b>Unblock</b> ] in the USB host settings.	<a href="#">page 8-32</a>
	—	Check that the USB memory is securely plugged into the machine.	—
<p>Printouts have vertical lines.</p> 	Is the slit glass dirty?	Clean the slit glass.	<a href="#">page 10-2</a>
<p>Dirt on the top edge or back of the paper.</p> 	Is the interior of the machine dirty?	Clean the interior of the machine.	<a href="#">page 10-3</a>
<p>Part of the image is periodically faint or shows white lines.</p> 	—	Open and then close the rear cover.	<a href="#">page 2-3</a>
	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>MC</b> ] and decrease the adjustment value. Decrease the adjustment value 1 level at a time from the current value. If there is no improvement after the value is decreased by 1 level, decrease by 1 level again. If there is still no improvement, return the setting to the original value.	—
	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>Drum Refresh</b> ] > [ <b>Yes</b> ]	—
<p>Print on the back of the sheet is visible on the front.</p> 	—	Set [ <b>Prevent Bleed-through</b> ] to [ <b>On</b> ].	<a href="#">page 6-18</a> <a href="#">page 8-13</a>

Symptom	Checkpoints	Corrective Actions	Reference Page
Skewed-color printout. 	—	Run [ <b>ColorCalibration</b> ].	<a href="#">page 10-29</a>
	—	Run [ <b>Color Regist.</b> ].	<a href="#">page 10-29</a>
Colors appear different than you anticipated.	Did you choose appropriate image quality for the original?	Select appropriate image quality.	<a href="#">page 6-13</a>
	Have you loaded color copy paper into the paper tray?	Load color copy paper into the paper tray.	—
	—	<b>When making copies</b> Adjust the color balance.	<a href="#">page 6-15</a>
	—	<b>When printing from a computer</b> Adjust the color using the printer driver.	—
The previous image remains and lightly printed. 	—	Select the [ <b>System Menu/Counter</b> ] key > [ <b>Adjust/Maint.</b> ] > [ <b>Service Setting</b> ] > [ <b>MC</b> ] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	—
Cannot send via SMB.	Is the network cable connected?	Connect the correct network cable securely.	<a href="#">page 2-8</a>
	Have the network settings for the equipment been configured properly?	Configure the TCP/IP settings properly.	<a href="#">page 8-26</a>
	Have the folder sharing settings been configured properly?	Check sharing settings and access privileges under the folder properties.	<a href="#">page 3-15</a>
	Has the SMB protocol been set to [ <b>On</b> ]?	Set the SMB protocol setting to [ <b>On</b> ].	<a href="#">page 8-27</a>
	Has [ <b>Host Name</b> ] been entered properly? *1	Check the name of the computer to which data is being sent.	<a href="#">page 5-18</a>
	Has [ <b>Path</b> ] been entered properly?	Check the share name for the shared folder.	<a href="#">page 5-18</a>
	Has [ <b>Login User Name</b> ] been entered properly? *1 *2	Check the domain name and login user name.	<a href="#">page 5-18</a>
	Has the same domain name been used for [ <b>Host Name</b> ] and [ <b>Login User Name</b> ]?	Delete the domain name and backslash ("/") from [ <b>Login User Name</b> ].	<a href="#">page 5-18</a>
	Has [ <b>Login Password</b> ] been entered properly?	Check the login password.	<a href="#">page 5-18</a>
	Have exceptions for Windows Firewall been configured properly?	Configure exceptions for Windows Firewall properly.	<a href="#">page 3-19</a>
	Do the time settings for the equipment, domain server, and data destination computer differ?	Set the equipment, domain server, and data destination computer to the same time.	—
	Is the screen displaying Send error?	Refer to <a href="#">Responding to Send Error</a> .	<a href="#">page 10-26</a>


Symptom	Checkpoints	Corrective Actions	Reference Page
The color toner is empty.	Do you want to continue printing in black and white?	If the black toner is remained, the machine continues printing in black and white by selecting <b>[Print in B &amp; W]</b> of <b>[ColorToner Empty]</b> .	<a href="#">page 8-15</a>
Cannot send via the e-mail.	Is the E-mail send size limit set in the SMTP server registered on the machine?	Check the limit value is entered to "E-mail Size Limit" of <b>[E-mail]</b> setting in Command Center RX and change the value as necessary.	<a href="#">page 2-44</a>
The machine is emitting steam in the area around the paper ejection slot.	Check the room temperature to see if it is low, or if damp paper was used.	Depending on the printing environment and the paper's condition, the heat generated during printing will cause the moisture in the paper to evaporate, and the steam emitted may look like smoke. This is not a problem, and you can continue printing. If the steam concerns you, raise the room temperature, or replace the paper with a newer, dryer paper.	—

\*1 You can also enter a full computer name as the host name (for example, pc001.abcdnet.com).

\*2 You can also enter login user names in the following formats:  
 Domain\_name/user\_name (for example, abcdnet/james.smith)  
 User\_name@domain\_name (for example, james.smith@abcdnet)

## Responding to Messages

If the message display or the computer displays any of these messages, follow the corresponding procedure.

 **NOTE**

When contacting us, the serial number will be necessary. To check the serial number, refer to the following:

➔ [Checking the Equipment's Serial Number \(page 5-5\)](#)

### A

Message	Checkpoints	Corrective Actions	Reference Page
<b>Account error.</b>	—	Failed to specify Job Accounting when processing the job externally. The job is canceled. Select <b>[OK]</b> .	—
<b>Add toner.</b> <b>[C][M][Y]</b> <b>Job is canceled.</b> <b>B&amp;W mode enabled.</b>	—	Replace the toner container to our specified toner container. If not, select <b>[OK]</b> to cancel the job. The device prints in black and white for a while.	<a href="#">page 10-4</a>

### B

Message	Checkpoints	Corrective Actions	Reference Page
<b>Box is not found.</b> <b>Job is canceled.</b>	—	The specified box cannot be found. Job is canceled. Select <b>[OK]</b> .	—
<b>Box limit exceeded. Job is canceled.*1</b>	Is <b>[OK]</b> displayed on the screen?	The specified box is full, and no further storage is available; Job is canceled. Select <b>[OK]</b> . Try to perform the job again after printing or deleting data from the box.	—

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)

### C

Message	Checkpoints	Corrective Actions	Reference Page
<b>Cannot connect to Authentication Server</b> <b>Check the connection with the server.</b>	—	Check the connection status with the server.	—
<b>Cannot connect to Authentication Server</b> <b>Check the domain name.</b>	—	Check the domain name.	<a href="#">page 9-2</a>
<b>Cannot connect to Authentication Server</b> <b>Check the host name.</b>	—	Check the host name.	<a href="#">page 8-26</a>

Message	Checkpoints	Corrective Actions	Reference Page
Cannot connect to Authentication Server Set machine time to match server's time.	—	Set machine time to match the server's time.	<a href="#">page 2-16</a>
Cannot connect to Server. Check the Connection Status. Job is canceled.	—	Check the connection status with the server.	—
Cannot duplex print on this paper. ↑↓ (Displayed alternately) Press OK to continue using cassette #.	Did you select a paper size/type that cannot be duplex printed?	Select [ <b>Paper</b> ] to select the available paper. Select [ <b>OK</b> ] to print without using Duplex function.	<a href="#">page 6-22</a>
Cannot duplex print on this paper. ↑↓ (Displayed alternately) Press OK to continue using MP tray.			<a href="#">page 6-22</a>
Cannot execute this job. Restricted by Group Authorization.	—	This job is canceled because it is restricted by Group Authorization settings. Select [ <b>OK</b> ].	<a href="#">page 9-17</a>
Cannot feed paper. Set cassette #.	—	Cannot feed paper. Set the cassette indicated on the screen.	—
Cannot use this function. >> FAX Transmission	—	This job is canceled because it is restricted by User Authorization or Job Accounting. Select [ <b>OK</b> ].	—
Cannot use this function. >> Print			
Cannot use this function. >> Send			
Cannot use this function. >> Store			
Check cassette #.	—	Open and then close the indicated cassette.	—
Close # cover.	Is there any cover which is open?	Close the cover indicated on the screen.	—
Close document processor.	Is the document processor open?	Close the document processor.	—
Close scanner unit.	—	Close the scanner unit.	—



**E**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Error occurred. Turn the power switch off and on.</b>	—	System error has occurred. Turn the main power switch OFF and then ON.	—

**F**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Failed to store job retention data. Job is canceled.</b>	—	The job is canceled. Select <b>[OK]</b> .	—
<b>File is not found. Job is canceled.</b>	—	The specified file is not found. The job is canceled. Select <b>[OK]</b> .	—

**H**

Message	Checkpoints	Corrective Actions	Reference Page
<b>High temperature. Adjust room temp.</b>	—	Adjust the temperature and the humidity of your room.	—

**I**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Incorrect account ID. Job is canceled.*1</b>	—	The account ID was incorrect when processing the job externally. The job is canceled. Select <b>[OK]</b> .	—
<b>Incorrect box password. Job is canceled.</b>	—	The box password was incorrect when processing the job externally. The job is canceled. Select <b>[OK]</b> .	—
<b>Incorrect Login User Name or Password. Job is canceled.*1</b>	—	The login user name or password was incorrect when processing the job externally. The job is canceled. Select <b>[OK]</b> .	—
<b>Inner tray is full of paper. Remove the paper.</b>	—	Remove paper from the inner tray.	—
<b>Insufficient memory. Cannot start the job.</b>	—	Job cannot be started. Try again later.	—

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)

**J**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Job Accounting restriction exceeded. Job is canceled.</b>	Is the acceptable printing count restricted by Job Accounting exceeded?	The printing count exceeded the acceptable count restricted by Job Accounting. Cannot print any more. This job is canceled. Select [ <b>OK</b> ].	—

**K**

Message	Checkpoints	Corrective Actions	Reference Page
<b>KPDL error. Job is canceled.*1</b>	—	PostScript error has occurred. The job is canceled. Select [ <b>OK</b> ].	—


\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)

**L**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Load paper in cassette #.</b> ↑↓ (Displayed alternately) <b>Press OK to continue using cassette #.</b>	Is the indicated cassette out of paper?	Load paper. Select [ <b>Paper</b> ] to select the other paper source. Select the [ <b>OK</b> ] key to print on the paper in the currently selected paper source.	<a href="#">page 3-4</a>
<b>Load paper in cassette #.</b> ↑↓ (Displayed alternately) <b>Set selected size paper and press [OK].</b>	Is the indicated cassette out of paper?	Load paper. Select [ <b>Paper</b> ] to select the other paper source.	<a href="#">page 3-4</a>
<b>Load paper in MP tray.</b> ↑↓ (Displayed alternately) <b>Press OK to continue using MP tray.</b>	Is the paper of the selected size loaded in the multi purpose tray?	Load paper. Select [ <b>Paper</b> ] to select the other paper source. Select the [ <b>OK</b> ] key to print on the paper in the currently selected paper source.	<a href="#">page 3-7</a>
<b>Load paper in MP tray.</b> ↑↓ (Displayed alternately) <b>Set selected size paper and press [OK].</b>	Is the paper of the selected size loaded in the multi purpose tray?	Load paper. Select [ <b>Paper</b> ] to select the other paper source.	<a href="#">page 3-7</a>
<b>Low temperature. Adjust room temp.</b>	—	Adjust the temperature and the humidity of your room.	—

**M**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Machine failure. Call service.</b>	—	An error has occurred in the machine. Make a note of the error code displayed on the message display, and contact your service representative.	—
<b>Maximum number of scanned pages. Job is canceled.</b>	Is the acceptable scanning count exceeded?	Cannot scan pages any more. Job is canceled. Select <b>[OK]</b> .	—
<b>Memory is full. Job is canceled.</b>	—	The process cannot be performed due to insufficient memory. Select <b>[OK]</b> . The job will be canceled.	—
<b>Memory is full. Print job cannot be processed completely.*1</b>	—	<p>Unable to continue the job as the memory is used up. Select <b>[Continue]</b> to print the scanned pages. The print job cannot be processed completely. Select <b>[Cancel]</b> to cancel the job.</p> <p>The machine may reproduce the same originals by arranging the following settings:</p> <ul style="list-style-type: none"> <li>• Select <b>[On]</b> of RAM Disk Mode in System Menu, and then decrease the RAM Disk Size.</li> <li>• Select <b>[Printer Priority]</b> of Optional Memory in System Menu.</li> </ul> <p> <b>NOTE</b> Before changing the RAM Disk Setting or Optional Memory setting, contact your administrator.</p>	—

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)


**N**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Non-genuine Toner. Press [Help].</b>	Is the installed toner container our own brand?	The manufacturer assumes no responsibility for damage caused by a non-genuine toner. We recommend that you only use genuine toner containers. When you want to use the toner container currently installed, select the <b>[OK]</b> key and the <b>[Stop]</b> key simultaneously for 3 seconds or more.	—

**P**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Paper jammed at MP tray.</b>	—	If a paper jam occurs, the machine will stop and the location of the jam will be indicated on the screen. Leave the machine on and select <b>[Help]</b> . Follow the instruction to remove the jammed paper.	<a href="#">page 10-34</a>
<b>Paper jammed in Cassette #.</b>	—		
<b>Paper jammed in document processor.</b>	—	A paper jam has occurred in the document processor. Leave the machine on and select <b>[Help]</b> on the screen, and follow the instruction to remove the jammed paper.	—
<b>Paper jammed in rear cover #.</b>	—	If a paper jam occurs, the machine will stop and the location of the jam will be indicated on the screen. Leave the machine on and follow the instruction to remove the jammed paper.	<a href="#">page 10-34</a>
<b>Preparing to print.</b>	—	The machine is under the adjustment to maintain its quality. Please wait.	—
<b>Printing multiple copies is not allowed.</b>	—	Multi copies cannot be printed because RAM disk is disabled or the SSD is not installed. The job is canceled. Select <b>[OK]</b> .  Try adding more memory or installing SSD, and configuring the RAM disk settings.	—
<b>Print overrun. Job is paused.</b>	—	Warning. Low printer memory. The job was paused. Re-starting the job. Select <b>[Continue]</b> .	—

R

Message	Checkpoints	Corrective Actions	Reference Page
<b>RAM disk error. Press [OK].</b>	—	An error has occurred on the RAM disk. Job is canceled. Select <b>[OK]</b> . The possible error codes and their descriptions are as follows. 04: Insufficient space on the RAM disk. If the optional RAM disk is installed, increase the RAM Disk Size by changing RAM Disk Mode in System Menu.   <b>NOTE</b> The range of RAM disk size can be increased by selecting <b>[Printer Priority]</b> in Optional Memory.	<a href="#">page 8-19</a>
<b>Removable Memory is full. Job is canceled.*1</b>	—	Job is canceled. Select <b>[OK]</b> . Insufficient free space in the removable memory. Delete unneeded files.	—
<b>Remove original from document processor.</b>	Are there any originals left in the document processor?	Remove originals from the document processor.	—
<b>Replace all originals and press Start key.</b>	—	Remove originals from the document processor, put them back in their original order, and place them again. Press the <b>[Start]</b> key to resume printing. Select <b>[Cancel]</b> to cancel the job.	—
<b>Replace MK.</b>	—	Replacement of the parts in the maintenance kit is necessary at every 200,000 pages (ECOSYS M6030cdn/ECOSYS M6530cdn) of printing and requires professional servicing. Contact your Service Representative.	—
<b>Replace the toner.</b>	—	Replace the toner container to our specified toner container.	<a href="#">page 10-4</a>
<b>Restricted by Job Accounting. Cannot print.</b>	—	This job is canceled because it is restricted by Job Accounting. Select <b>[OK]</b> .	—

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)

**S**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Scanner memory is full. Job is canceled.</b>	—	Scanning cannot be performed any more due to insufficient memory. The job is canceled. Select <b>[OK]</b> .	—
<b>Send Error.*1</b>	—	An error has occurred during transmission. The job is canceled. Select <b>[OK]</b> . Refer to <a href="#">Responding to Send Error</a> for the error code and corrective actions.	<a href="#">page 10-26</a>
<b>Shake the toner container. [C][M][Y][K]</b>	—	Shake the toner container well and reinstall it.	<a href="#">page 10-4</a>
<b>SSD error. Job is canceled.</b>	—	An error has occurred on SSD. Job is canceled. Select <b>[OK]</b> . The possible error codes and their descriptions are as follows. 01: The amount of data that can be saved at once has been exceeded. Turn the power OFF/ON. If the error still occurs, divide the file into smaller files. If the error occurs after the file is divided, the specified file may be damaged. Delete the file. 04: Insufficient space on SSD to complete this operation. Move data or delete unneeded data.	—

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➔ [Auto Err. Clear \(page 8-18\)](#)

**T**

Message	Checkpoints	Corrective Actions	Reference Page
<b>The slit glass requires cleaning.</b>	—	Clean the slit glass using the cleaning cloth supplied with the document processor.	<a href="#">page 10-2</a>
<b>The toner container is not locked or improperly installed.</b>	—	The toner container is not installed correctly. Set it correctly.	<a href="#">page 10-4</a>
<b>This user account is locked out. Contact administrator Job is canceled.</b>	—	Contact administrator. The job is canceled. Select <b>[OK]</b> .	—
<b>Toner is low. [C][M][Y][K] (Replace when empty.)</b>	—	It is almost time to replace the toner container. Obtain a new toner container.	—

**U**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Unknown Toner Installed. PC</b>	Does the installed toner container's regional specification match the machine's?	Install the specified toner container.	—
<b>USB memory error. Job is canceled.</b>	—	An error occurred in the removable memory. The job stopped. Select <b>[OK]</b> .  The possible error codes and their descriptions are as follows.  01: The amount of data that can be saved at once has been exceeded. Turn the power OFF/ON. If the error still occurs, the removable memory is not compatible with the machine.	—





**W**

Message	Checkpoints	Corrective Actions	Reference Page
<b>Waste toner box is full or placed improperly.</b>	—	The waste toner box is not installed correctly. Set it correctly.	<a href="#">page 10-8</a>
	Is the waste toner box full?	Replace the waste toner box.	<a href="#">page 10-8</a>

**Y**

Message	Checkpoints	Corrective Actions	Reference Page
<b>You cannot use this box. Job is canceled.</b>	—	You cannot use the specified box. Job is canceled. Select <b>[OK]</b> .	—

## Responding to Send Error

Error Code	Message	Corrective Actions	Reference Page
1101	Failed to send the e-mail.	Check the host name of the SMTP server on the Command Center RX.	<a href="#">page 2-44</a>
	Failed to send via FTP.	Check the host name of FTP.	<a href="#">page 5-18</a>
	Failed to send via SMB.	Check the host name of SMB.	<a href="#">page 5-18</a>
1102	Failed to send via SMB.	Check the SMB settings. <ul style="list-style-type: none"> <li>Login user name and login password</li> </ul>  <b>NOTE</b> If the sender is a domain user, specify the domain name. <ul style="list-style-type: none"> <li>Host name</li> <li>Path</li> </ul>	<a href="#">page 5-18</a>
	Failed to send the e-mail.	Check the following on the Command Center RX. <ul style="list-style-type: none"> <li>SMTP login user name and login password</li> <li>POP3 login user name and login password</li> <li>E-mail size limit</li> </ul>	<a href="#">page 2-44</a>
	Failed to send via FTP.	Check the FTP settings. <ul style="list-style-type: none"> <li>Login user name and login password</li> </ul>  <b>NOTE</b> If the sender is a domain user, specify the domain name. <ul style="list-style-type: none"> <li>Path</li> <li>Folder share permissions of the recipient</li> </ul>	<a href="#">page 5-18</a>
1103	Failed to send via SMB.	Check the SMB settings. <ul style="list-style-type: none"> <li>Login user name and login password</li> </ul>  <b>NOTE</b> If the sender is a domain user, specify the domain name. <ul style="list-style-type: none"> <li>Path</li> <li>Folder share permissions of the recipient</li> </ul>	<a href="#">page 5-18</a>
	Failed to send via FTP.	Check the FTP settings. <ul style="list-style-type: none"> <li>Path</li> <li>Folder share permissions of the recipient</li> </ul>	<a href="#">page 5-18</a>
1104	Failed to send the e-mail.	Check the e-mail address.  <b>NOTE</b> If the address is rejected by the domain, you cannot send the email.	<a href="#">page 5-17</a>



Error Code	Message	Corrective Actions	Reference Page
1105	Failed to send via SMB.	Check the following settings. [System Menu/Counter] key > [System/Network] > [Network Setting] > [TCP/IP Settings] > [Protocol Detail] > [SMB]	<a href="#">page 8-26</a>
	Failed to send the e-mail.	Select [On] of the SMTP settings on the Command Center RX.	<a href="#">page 2-44</a>
	Failed to send via FTP.	Check the following settings. [System Menu/Counter] key > [System/Network] > [Network Setting] > [TCP/IP Settings] > [Protocol Detail] > [FTP(Client)]	<a href="#">page 8-26</a>
1106	Failed to send the e-mail.	Check the sender address of SMTP on the Command Center RX.	<a href="#">page 2-44</a>
1131	Failed to send via FTP.	Enable the SSL. [System Menu/Counter] key > [System/Network] > [Network Setting] > [Secure Protocol] > [SSL]	<a href="#">page 8-29</a>
1132	Failed to send the e-mail.	Check the following of the SMTP server. • Is SMTP over SSL available? • Is the encryption available?	Refer to the <b>Command Center RX User Guide.</b>
	Failed to send via FTP.	Check the following of the FTP server. • Is FTPS available? • Is the encryption available?	—
2101	Failed to send via SMB.	Check the network and SMB settings. • The network cable is connected. • The hub is not operating properly. • The server is not operating properly. • Host name and IP address • Port number	—
	Failed to send via FTP.	Check the network and FTP settings. • The network cable is connected. • The hub is not operating properly. • The server is not operating properly. • Host name and IP address • Port number	—
	Failed to send the e-mail.	Check the network and Command Center RX. • The network cable is connected. • The hub is not operating properly. • The server is not operating properly. • POP3 server name of the POP3 user • SMTP server name	<a href="#">page 2-44</a>

Error Code	Message	Corrective Actions	Reference Page
<b>2102</b> <b>2103</b>	Failed to send via FTP.	<p>Check the network.</p> <ul style="list-style-type: none"> <li>• The network cable is connected.</li> <li>• The hub is not operating properly.</li> <li>• The server is not operating properly.</li> </ul>	—
		<p>Check the following of the FTP server.</p> <ul style="list-style-type: none"> <li>• Is FTP available?</li> <li>• The server is not operating properly.</li> </ul>	—
	Failed to send the e-mail.	<p>Check the network.</p> <ul style="list-style-type: none"> <li>• The network cable is connected.</li> <li>• The hub is not operating properly.</li> <li>• The server is not operating properly.</li> </ul>	—
<b>2201</b> <b>2202</b> <b>2203</b> <b>2231</b>	<p>Failed to send the e-mail.</p> <p>Failed to send via FTP.</p> <p>Failed to send via SMB.</p>	<p>Check the network.</p> <ul style="list-style-type: none"> <li>• The network cable is connected.</li> <li>• The hub is not operating properly.</li> <li>• The server is not operating properly.</li> </ul>	—
<b>2204</b>	Failed to send the e-mail.	Check the e-mail size limit of the SMTP settings on the Command Center RX.	<a href="#">page 2-44</a>
<b>3101</b>	Failed to send the e-mail.	Check the authentication methods of both the sender and the recipient.	—
	Failed to send via FTP.	<p>Check the network.</p> <ul style="list-style-type: none"> <li>• The network cable is connected.</li> <li>• The hub is not operating properly.</li> <li>• The server is not operating properly.</li> </ul>	—
<b>3201</b>	Failed to send the e-mail.	Check the SMTP user authentication method of the recipient.	—
<b>0007</b> <b>4201</b> <b>4701</b> <b>5101</b> <b>5102</b> <b>5103</b> <b>5104</b> <b>7101</b> <b>7102</b> <b>7103</b> <b>720f</b>	—	Turn the main power switch off and back on. If this error occurs several times, make a note of the displayed error code and contact your service representative.	<a href="#">page 2-10</a>
<b>9181</b>	—	The scanned original exceeds the acceptable number of pages of 999. Send the excess pages separately.	—

## Adjustment/Maintenance

### Color Calibration

This machine contains a calibration function that automatically makes adjustments to compensate for changes that occur over time due to variations in the ambient temperature and humidity. So that the highest quality color printing can be maintained, this color calibration operation is carried out automatically each time the power to the machine is turned on. If color tone does not improve or color drift does not improve after executing this color adjustment, perform color print position correction on the following:

➔ [Color Registration Procedure \(page 10-29\)](#)

#### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Adjust/Maint.] > [OK] key > [▲] [▼] key > [Color Calibration] > [OK] key

#### 2 Perform the Color Calibration.

Select [Yes] to execute Color Calibration.

"Completed." is displayed and the screen returns to the Adjust/Maint. menu.

### Color Registration Procedure

This function is available to resolve color drift. If it is not resolved by normal registration or to perform more detailed settings, use the detailed settings.



#### NOTE

To perform color registration, verify that either Letter or A4 paper is loaded into a cassette.



#### IMPORTANT

Before performing color registration, be sure to perform [Color Calibration on page 10-29](#). If color drift remains, perform color registration. By performing color registration without performing Color Calibration, the color drift will be resolved once, however, it may cause the serious color drift later.

### Normal Registration

#### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Adjust/Maint.] > [OK] key > [▲] [▼] key > [Color Regist.] > [OK] key > [▲] [▼] key > [Normal] > [OK] key


#### 2 Print the chart.

[▲] [▼] key > [Print Chart] > [OK] key > [Yes]

A chart is printed. On the chart, for each of M (magenta), C (cyan) and Y (yellow), 3 chart types are printed on one sheet: H-L (left), V (vertical), H-R (right).

After printing, you will return to the advanced menu for color printing position correction.

### Chart Example




### 3 Display the correction menu

[▲] [▼] key > [Adjust Magenta] > [OK] key

The magenta correction menu appears.

### 4 Enter the appropriate value.

- 1 Find the location on each chart where 2 lines most closely match. If this is the 0 position, registration for that color is not required. For the illustration, B is the appropriate value.



- 2 Select the [◀] or [▶] key to change the H-L, V, and H-R items, select the [▲] or [▼] key to enter the values read from the chart, and select the [OK] key.

Magenta correction is performed. After a brief interval, you will return to the standard menu for color printing position correction.

To increase the value from 0 up to a maximum of 9, select the [▲] key. To decrease the value, select the [▼] key.

Select [▼] to change the value from 0 to an alphabetical letter. Continue selecting to change from A through I. To move in the opposite direction, select [▲].

You cannot use the numeric keys to enter these values.

- 3 Repeat steps 3 to 4 to correct cyan and yellow.

## Detailed Settings

### 1 Display the screen.

[System Menu/Counter] key > [▲] [▼] key > [Adjust/Maint.] > [OK] key > [▲] [▼] key > [Color Regist.] > [OK] key > [▲] [▼] key > [Detail] > [OK] key


### 2 Print the chart.

[▲] [▼] key > [Print Chart] > [OK] key > [Yes]

A chart is printed. On the chart, for each of M (magenta), C (cyan) and Y (yellow), charts for H-1 to 5 and V-1 to 5 are printed.

After printing, you will return to the advanced menu for color printing position correction.

### Chart Example




### 3 Display the correction menu

[▲] [▼] key > [Adjust Magenta] > [OK] key

The magenta correction menu appears.

### 4 Enter the appropriate value.

- 1 Find the location on each chart where 2 lines most closely match. If this is the 0 position, registration for that color is not required. For the illustration, B is the appropriate value.



From charts H-1 to H-5, read the values from H-1 to H-5.

From charts V-1 to V-5, read only the values from V-3 (center).

- 2 Select the [◀] or [▶] key to change the H-1 to H-5 and V-3 items, select the [▲] or [▼] key to enter the values read from the chart, and select the [OK] key.

Magenta correction is performed. After a brief interval, you will return to the advanced menu for color printing position correction.

To increase the value from 0 up to a maximum of 9, select the [▲] key. To decrease the value, select the [▼] key.

Select [▼] to change the value from 0 to an alphabetical letter. Continue selecting to change from A through I. To move in the opposite direction, select [▲].

You cannot use the numeric keys to enter these values.


- 3 Repeat steps 3 to 4 to correct cyan and yellow.

## Clearing Paper Jams

If a paper jam occurs, the message display will display "Paper Jam." and the machine will stop.

Refer to these procedures to remove the jammed paper.

### Jam Location Indicators



- 1 Shows the location of a paper jam.
- 2 Displays the Help screen.


#### NOTE

For details on Help Screen, refer to the following:

➔ [Help Screen \(page 2-13\)](#)



If a paper jam occurs, the location of the jam will be displayed on the message display as well as the clearing instructions.



Paper Jam Location Indicator	Paper Jam Location	Reference Page
<b>A</b>	Multi Purpose Tray	<a href="#">page 10-36</a>
<b>B</b>	Cassettes 1 to 4	<a href="#">page 10-38</a>
<b>C</b>	Rear Cover 1 (Feed)	<a href="#">page 10-39</a>
<b>D</b>	Rear Cover 2	<a href="#">page 10-40</a>
<b>E</b>	Rear Cover 3	<a href="#">page 10-42</a>
<b>F</b>	Rear Cover 1	<a href="#">page 10-43</a>
<b>G</b>	Duplex Unit	<a href="#">page 10-45</a>
<b>H</b>	Document Processor	<a href="#">page 10-47</a>

After you remove the jam, the machine will warm up again and the error message will be cleared. The machine resumes with the page that was printing when the jam occurred.

## Precautions with Paper Jams

- Do not reuse jammed papers.
- If the paper tears during removal, be sure to remove any loose scraps of paper from inside the machine. Scraps of paper left in the machine could cause subsequent jamming.





### CAUTION



The fixing unit is extremely hot. Take sufficient care when working in this area, as there is a danger of getting burned.

## Multi Purpose Tray



1




2





3





4



5




6




## Cassettes 1 to 4

Procedures for handling a paper jam in Cassettes 1 to 4 are all the same. This section explains procedures using Cassette 1 as an example.

1




2



## Rear Cover 1 (Feed)


1




**! CAUTION**

Some parts are very hot inside the machine. Exercise caution as there is a risk of burn injury.


2



3



4



## Rear Cover 2

1




### NOTE



If the paper cannot be removed, do not try to forcefully remove it.

➔ [Rear Cover 1 \(Feed\) \(page 10-39\)](#)


**2**



**3**




**4**



## Rear Cover 3

1




### NOTE

If the paper cannot be removed, do not try to forcefully remove it.

➔ [Rear Cover 1 \(Feed\) \(page 10-39\)](#)


2





## Rear Cover 1


1




### CAUTION

Some parts are very hot inside the machine. Exercise caution as there is a risk of burn injury.


2




3




4



5




6



## Duplex Unit

1




### CAUTION

Some parts are very hot inside the machine. Exercise caution as there is a risk of burn injury.


2




3




4




5




6



7




8





### Document Processor



1




2




3



4




5




## Clearing a Staple Jam


1



2



3



# 11 Appendix

This chapter explains the following topics:








Optional Equipment .....	11-2
Overview of Optional Equipment .....	11-2
Optional Applications .....	11-9
Character Entry Method .....	11-11
Using the Keys .....	11-11
Selecting Type of Characters .....	11-12
Characters That Can be Entered Using the Numeric Keys .....	11-12
Entering Symbols .....	11-13
Entering Characters .....	11-13
Entering Using the Character Selection Screen .....	11-15
Paper .....	11-16
Basic Paper Specifications .....	11-16
Choosing the Appropriate Paper .....	11-17
Special Paper .....	11-20
Specifications .....	11-24
Machine .....	11-24
Copy Functions .....	11-26
Printer Functions .....	11-26
Scanner Functions .....	11-27
Document Processor .....	11-27
Paper Feeder (500-sheet) (Option) .....	11-28
Manual Stapler .....	11-28
Glossary .....	11-29



# Optional Equipment




## Overview of Optional Equipment

The following optional equipment is available for the machine.



Software option
(9) Data Security kit(E)
(10) UG-33

(11) USB Keyboard
-------------------



## **(1) Card Authentication Kit(B) "Card Authentication Kit"**

User login administration can be performed using ID cards. To do so, it is necessary to register ID card information on the previously registered local user list. For more information about how to register this information, refer to the following:

➔ **Card Authentication Kit(B) Operation Guide**

## **(2) PF-5100 "Paper Feeder (500-sheet x1)"**


Up to three additional cassettes identical to the machine's cassettes can be installed in the machine. Loading method are the same as the standard cassettes.

➔ [Loading in the Cassettes \(page 3-4\)](#)

### (3) "Expansion Memory"

The machine can perform the more multiple jobs simultaneously by adding more memories. You can increase the machine's memory up to 2,048 MB by plugging in the optional memory modules.

#### Precautions for Handling the Memory Modules



To protect electronic parts, discharge static electricity from your body by touching a water pipe (faucet) or other large metal object before handling the memory modules. Or, wear an antistatic wrist strap, if possible, when you install the memory modules.

#### Installing the Memory Modules


- 1 Turn off the machine and disconnect the power cord and interface cable.




#### NOTE

If the optional IB-50/51 or HD-6/7 is installed, remove it.

- 2 Remove the covers.



- 3 Remove the memory module from its package.
- 4 With the memory connection terminal pointing toward the socket, align the cut-out part with the socket terminal and insert directly in at an angle.



- 5 Carefully press the inserted memory down and into the machine.
- 6 Reinstall the covers.

### **Removing the Memory Module**

To remove a memory module, remove the right cover and the memory slot cover from the machine. Then, carefully push out the two socket clamps. Ease the memory module out of the socket to remove.

### **Verifying the Expanded Memory**

To verify that the memory module is working properly, test it by printing a status page.

➔ [Report \(page 8-5\)](#)

### **(4) HD-6/HD-7 "SSD"**

With SSD installed in the machine, received data can be rasterized and stored on this SSD. This enables high-speed printing of multiple copies using an electric sort function. Also, you can use the Document Box functions.

➔ [What is Document Box? \(page 5-30\)](#)

### **(5) IB-50 "Network Interface Kit"**

The Network Interface Kit provides a high-speed connection for the Gigabit-per-second interface. Settings are possible for a variety of OS and network protocols.

➔ **IB-50 User's Manual**

### **(6) IB-51 "Wireless Network Interface Kit"**

This is a wireless LAN interface card which supports the wireless LAN specifications IEEE802.11n (Max 300 Mbps) and 11 g/b.

With the utilities supplied, settings are possible for a variety of OS and network protocols.

➔ **IB-51 User's Manual**

## (7) "SD/SDHC Memory Card"

An SD/SDHC memory card is useful for storing fonts, macros, and overlays. The machine is equipped with a slot for an SDHC memory card with a maximum size of 32 GB, and an SD memory card with a maximum size of 2 GB.


### Reading the SD/SDHC Memory Card

Once inserted in the machine's slot, the contents of the SD/SDHC memory card can be read from the operation panel or automatically when you power on or reset the machine.


### Installing and Formatting the SD/SDHC Memory Card

To use an unused SD/SDHC memory card, you must first use the machine to format the SD/SDHC memory card.


- 1 Power off the machine and unplug the power cord.




- 2 Remove the cover.




- 3 Remove the cover.




- 4 Insert the SD/SDHC memory card into the SD/SDHC memory card slot.



- 5 Replace the covers and close the rear cover.



- 6 Insert the power cord into the socket and turn on the power switch.



- 7 Format the SD/SDHC memory card from the operation panel.

For the procedure for formatting, refer to the following:

➔ [Format SD Card \(page 8-16\)](#)

## (8) MS-5100 "Manual stapler"

It can staple the originals or the printouts. The number of sheets that can be stapled together is 20 sheets (80 g/m<sup>2</sup>).

## (9) Data Security Kit(E) "Data Security Kit"

The Data Security Kit overwrites all unnecessary data in the storage area so that it cannot be retrieved. The Data Security Kit encrypts data before storing it in the SSD. It guarantees higher security because no data cannot be decoded by ordinary output or operations.

## (10) UG-33 "ThinPrint Option"

This application allows print data to be printed directly without a print driver.

### **(11) USB Keyboard "USB Keyboard"**

A USB keyboard can be used to enter information into the text fields on the operation panel. A special mount is also available to install the keyboard on the machine. Please contact your dealer or service representative for information on keyboards that are compatible with your machine before you purchase one.

# Optional Applications

## Overview of the Applications

The applications listed below are installed on this machine.

Application
Data Security Kit
Card Authentication Kit* <sup>1</sup>
ThinPrint Option* <sup>1</sup>

\*<sup>1</sup> This can be used on a trial basis for a limited time.

### NOTE

- Restrictions such as the number of times the application can be used during the trial period differ depending on the application.
- If you change the date/time while using the trial version of an application, you will no longer be able to use the application.

## Starting Application Use

Use the procedure below to start using an application.

- 1 [System Menu/Counter] key > [▲] [▼] key > [System/Network] > [OK] key

### NOTE

If the login user name entry screen appears during operations, enter a login user name and password, and select [Login]. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

- 2 [▲] [▼] key > [Op Functions] > [OK] key
- 3 Select the desired application, and select the [OK] key.

### NOTE

You can view detailed information on the selected application by selecting [Menu] > [Detail] > [OK] key.

- 4 [▲] [▼] key > [Official] > [OK] key  
To use the application as a trial, select [Trial] without entering the license key.
- 5 Enter the license key > [OK] key  
Some applications do not require you to enter a license key. If the license key entry screen does not appear, go to Step 6.



- 6 Select **[Yes]**.



**NOTE**

If you started the Security Kit or Thin Print option and entered the license key, turn the power OFF/ON.

## Checking Details of Application

Use the procedure below to check the details of application.

- 1 **[System Menu/Counter]** key > **[▲]** **[▼]** key > **[System/Network]** > **[OK]** key



**NOTE**

If the login user name entry screen appears during operations, enter a login user name and password, and select **[Login]**. For this, you need to login with administrator privileges.

The factory default login user name and login password are set as shown below.

**Login User Name: 3000**

**Login Password: 3000**

- 2 **[▲]** **[▼]** key > **[Op Functions]** > **[OK]** key
- 3 Select the desired application, and select **[Menu]**.
- 4 **[▲]** **[▼]** key > **[Detail]** > **[OK]** key

You can view detailed information on the selected application. Select the **[▶]** key to view the next screen. Select the **[◀]** key to return to the previous screen.

The table below lists the item you can view.

Item
Function Name
License On
Trial Counts
Date of Trial
Status

**Extend the trial period.**

**[◀]** **[▶]** key > **[Date of Trial]** > **[Extend]** > **[Yes]**


The trial period is extended.

# Character Entry Method

This section explains how to enter characters.

## Using the Keys

Use the following keys to enter characters.




No.	Display/Key	Description
1	Message Display	Displays entered characters.
2	Cursor	Characters are entered at the position of the cursor.
3	Right Select key	Select to select the type of characters you want to enter. (When [Text] is displayed)
4	[OK] key	Select to finalize entry and return to the screen before the entry. To enter a symbol, select to confirm the selected symbol.
5	[Clear] key	Select to delete characters.
6	Numeric keys	Select to enter characters and symbols.
7	Arrow keys	Select to select the entry position, or select a character from the character list.

## Selecting Type of Characters

To enter characters, the following three types are available:

Types	Description
<b>ABC</b>	To enter alphabets.
<b>123</b>	To enter numerals.
<b>Symbols</b>	To enter symbols.

In a character entry screen, select **[Text]** to select the type of characters you want to enter.



Each time you select **[Text]**, the character type switches as follows: **[ABC]**, **[123]**, **[Symbols]**, **[ABC]** ...


## Characters That Can be Entered Using the Numeric Keys

The following table lists the characters that can be entered using the numeric keys.


Keys	Characters (Each press of a key changes the character in the order from left to right.)
.@ 1	. @ - _ / : ~ 1 (Repeats from the first character on the left) 1 (During number entry)
ABC 2	a b c A B C 2 (Repeats from the first character on the left) 2 (During number entry)
DEF 3	d e f D E F 3 (Repeats from the first character on the left) 3 (During number entry)
GHI 4	g h i G H I 4 (Repeats from the first character on the left) 4 (During number entry)
JKL 5	j k l J K L 5 (Repeats from the first character on the left) 5 (During number entry)
MNO 6	m n o M N O 6 (Repeats from the first character on the left) 6 (During number entry)
PQRS 7	p q r s P Q R S 7 (Repeats from the first character on the left) 7 (During number entry)
TUV 8	t u v T U V 8 (Repeats from the first character on the left) 8 (During number entry)




- 2 Select the [\*/.] key. [r] changes to [R].




- 3 Select the [▶] key. The cursor moves to the right.




- 4 Select the [#] key. Displays the symbol list.




- 5 Select the [▲] or [▼] key to move the cursor and select [&].




- 6 Select the [OK] key. [&] is entered.



- 7 Select the [3] key four times. [D] is entered.



- 8 Select the [▶] key.




## Entering Using the Character Selection Screen


If "Login Operation" is [Select Character], then the screen is displayed to enter details by selecting from the characters on the message display. For details on changing the login operation method, refer to the following:

➔ [Login Operation \(page 8-20\)](#)

- 1 Select the [▲], [▼], [▶] or [◀] key to move the cursor and select the character to be entered.




- 2 Select the [OK] key. The selected character is entered.



You can go back one character by selecting the [Clear] key.

- 3 When the entry is complete, select [Complete].



# Paper

This section explains the paper sizes and types that can be used in the paper source.

For details on the sizes, types, and number of sheets of paper that can be loaded in each paper tray, refer to the following:

➔ [Specifications \(page 11-24\)](#)

## Basic Paper Specifications

This machine is designed to print on standard copy paper as used in regular ('dry') copiers and page printers such as laser printers. It also supports a variety of other types of paper that conform to the specifications given in this appendix.

Be careful when choosing paper. Paper unsuitable for the machine may cause jams or may be wrinkled.

### Supported Paper

Use standard copy paper for regular copiers or laser printers. The printing quality will be affected by the quality of paper. Poor quality paper may result in unsatisfactory output.

### Basic Paper Specifications

The following table lists the specifications of paper that is supported with this machine. Refer to the subsequent sections for further details.

Criteria	Specifications
Weight	Cassettes: 60 to 163 g/m <sup>2</sup>
	Multi purpose tray: 60 to 220 g/m <sup>2</sup> , 230 g/m <sup>2</sup> (Cardstock)
Dimensional accuracy	±0.7 mm
Squareness of corners	90° ±0.2°
Moisture content	4 to 6%
Pulp content	80% or more



#### NOTE

Some recycled paper does not meet requirements for use with this machine as listed in the Basic Paper Specifications shown below, such as moisture or pulp content. For this reason, we recommend purchasing a small amount of recycled paper as a sample for testing prior to use. Choose recycled paper that gives the best printing results and contains low levels of paper dust.

We are not responsible for the problems occurred from the use of paper that does not conform to our specifications.

## Choosing the Appropriate Paper

This section describes guidelines for choosing paper.

### Condition

Avoid using paper with bent corners or that is curled, dirty, or torn. Do not use paper that has a rough surface or paper fiber lint, or that is especially delicate. Use of paper in any of these conditions will not only deliver poor copies but may also cause jams and shorten the useful life of the machine. Choose paper with a smooth and even surface; however, avoid coated paper or paper with a treated surface as it may damage the drum or fusing unit.

### Ingredients

Do not use paper such as paper that has been coated or surface-treated or paper that contains plastic or carbon. Those types of paper may produce harmful fumes from the heat of printing and may damage the drum.

Be sure to use the standard paper that contains at least 80% pulp, i.e., not more than 20% of the total paper content consists of cotton or other fibers.

### Supported Paper Sizes

Paper of the following sizes is supported by the machine.

Measurements in the table take into account a  $\pm 0.7$  mm dimensional accuracy for length and width. Corner angles must be  $90^\circ \pm 0.2^\circ$ .

Paper Size	Cassette 1	Cassettes 2 to 4	Multi Purpose Tray
Envelope Monarch (3-7/8 × 7-1/2")	×	○	○
Envelope #10 (4-1/8 × 9-1/2")	×	○	○
Envelope DL (110 × 220 mm)	×	○	○
Envelope C5 (162 × 229 mm)	×	○	○
Executive (7-1/4 × 10-1/2")	○	○	○
Letter	○	○	○
Legal	○	○	○
A4 (297 × 210 mm)	○	○	○
B5 (257 × 182 mm)	○	○	○
A5 (210 × 148 mm)	○	○	○
A6 (148 × 105 mm)	○	×	○
B6 (182 × 128 mm)	○	○	○
Envelope #9 (3-7/8 × 8-7/8")	×	○	○
Envelope #6 (3-5/8 × 6-1/2")	×	○	○
ISO B5 (176 × 250 mm)	○	○	○
Hagaki (Cardstock) (100 × 148 mm)	×	×	○
Oufuku hagaki (Return postcard) (148 × 200 mm)	×	×	○
Oficio II	○	○	○
216 × 340 mm	○	○	○
16K (273 × 197 mm)	○	○	○



Paper Size	Cassette 1	Cassettes 2 to 4	Multi Purpose Tray
Statement	○	○	○
Folio (210 × 330 mm)	○	○	○
Youkei 4 (105 × 235 mm)	×	○	○
Youkei 2 (114 × 162 mm)	×	○	○
Custom	Cassette 1: 105 × 148 to 216 × 356 mm Cassettes 2 to 4: 92 × 162 to 216 × 356 mm Multi Purpose Tray: 70 × 148 to 216 × 356 mm		

## Smoothness

The paper surface should be smooth, but it must be uncoated. With paper that is too smooth and slippery, several sheets may accidentally be supplied at once, causing jams.

## Basis Weight

In countries that use the metric system, basis weight is the weight in grams of one sheet of paper one square meter in area. In the United States, basis weight is the weight in pounds of one ream (500 sheets) of paper cut to the standard size (or trade size) for a specific grade of paper. Paper that is too heavy or too light may be supplied incorrectly or cause paper jams, which may cause excessive wear of the machine. Mixed paper weight (i.e., thickness) may cause several sheets to be supplied at once accidentally and may also cause blurring or other printing problems if the toner fails to adhere correctly.

## Moisture Content

Paper moisture content is the ratio of moisture to dryness expressed as a percentage. Moisture affects how the paper is supplied, the electrostatic chargeability of the paper, and how the toner adheres.

Paper moisture content varies depending on the relative humidity in the room. High relative humidity causes paper to become damp, making the edges expand so it appears wavy. Low relative humidity causes paper to lose moisture, making the edges tighten and weakening print contrast.

Wavy or tight edges may cause the paper to slip when it is supplied. Try to keep the moisture content between 4 to 6%.

To maintain the right level of moisture content, bear in mind the following considerations.

- Store paper in a cool, well-ventilated place.
- Store paper flat and unopened in the package. Once the package is opened, reseal it if the paper is not to be used for a while.
- Store paper sealed in the original package and box. Put a pallet under the carton to keep it raised above the floor. Especially during rainy seasons keep the paper a sufficient distance away from wooden or concrete floors.
- Before using paper that has been stored, keep it at the proper moisture level for at least 48 hours.
- Do not store paper where it is exposed to heat, sunlight, or dampness.

## Other Paper Specifications

**Porosity:** The density of the paper fibers.

**Stiffness:** Paper must be stiff enough or it may buckle in the machine, causing jams.

**Curl:** Most paper naturally tends to curl after the package is opened. When paper passes through the fixing unit, it curls upward slightly. To deliver flat printouts, load the paper so that the curl faces towards the bottom of the paper tray.

**Static electricity:** During printing, paper is electrostatically charged so that the toner adheres. Choose paper that can be discharged quickly so that copies do not cling together.

**Whiteness:** Paper whiteness affects print contrast. Use whiter paper for sharper, brighter copies.

**Quality:** Machine problems may occur if sheet sizes are not uniform or if corners are not square, edges are rough, sheets are uncut, or edges or corners are crushed. In order to prevent these problems, be especially careful when you cut the paper yourself.

**Packaging:** Choose paper that is properly packaged and stacked in boxes. Ideally, the packaging itself should have been treated with a coating to inhibit moisture.

**Specially treated paper:** We do not recommend printing onto the following types of paper, even if it conforms to the basic specifications. When you use these kinds of paper, purchase a small amount first as a sample to test.

- Glossy paper
- Watermarked paper
- Paper with an uneven surface
- Perforated paper

## Special Paper

This section describes printing onto special paper and print media.

The following paper and media can be used.

- Transparencies
- Preprinted paper
- Bond paper
- Recycled paper
- Thin paper
- Letterhead
- Colored paper
- Prepunched paper
- Envelopes
- Hagaki (Cardstock)
- Thick paper
- Labels
- Coated
- High-quality paper

When using these paper and media, choose those that are designed specifically for copiers or page printers (such as laser printers). Use the multi purpose tray for transparencies, thick paper, envelopes, cardstocks, and label paper.

### Choosing Special Paper

Although special paper that meets the following requirements can be used with the machine, print quality will vary considerably due to differences in the construction and quality of special paper. Thus, special paper is more likely than regular paper to cause printing problems. Before purchasing special paper in volume, try testing a sample to ensure the print quality is satisfactory. General precautions when printing onto special paper are given below. Note that we are not responsible for any harm to the user or damage to the machine caused by moisture or specifications of special paper.

Select a cassette or multi purpose tray for special paper.

### Transparencies

Transparencies must be able to withstand the heat of printing. Transparencies must meet the following conditions.

<b>Heat resistance</b>	Must withstand at least 190°C
<b>Thickness</b>	0.100 to 0.110 mm
<b>Material</b>	Polyester
<b>Dimensional accuracy</b>	±0.7 mm
<b>Squareness of corners</b>	90° ±0.2°

To avoid problems, use the multi purpose tray for transparencies and load transparencies with the long side facing the machine.


If transparencies jam frequently at output, try pulling the leading edge of sheets gently as they are ejected.

## Label

Be sure to feed labels from the multi purpose tray.

For selecting labels, use extreme care so that the adhesive may not come in direct contact with any part of the machine and that the labels are not easily peeled from the carrier sheet. Adhesives that stick to the drum or rollers and peeled labels remaining in the machine may cause a failure.


When printing onto labels, you must be liable for the print quality and possible trouble.



Labels consist of three layers as shown in the illustration. The adhesive layer contains materials that are easily affected by the force applied in the machine. The carrier sheet bears the top sheet until the label is used. This composition of labels may cause more problems.

The label surface must be covered completely with the top sheet. Gaps between labels may cause peeling of labels, resulting in a serious failure.


Some label paper has large margins on the top sheet. When using such paper, do not peel these margins from the carrier sheet before completing output.



Use label paper that conforms to the following specifications.

<b>Top sheet weight</b>	44 to 74 g/m <sup>2</sup>
<b>Basis weight (overall paper weight)</b>	104 to 151 g/m <sup>2</sup>
<b>Top sheet thickness</b>	0.086 to 0.107 mm
<b>Overall paper thickness</b>	0.115 to 0.145 mm
<b>Moisture content</b>	4 to 6 % (composite)

## Hagaki (Cardstock)



Before loading Hagaki (Cardstock) into the multi purpose tray, fan them and align the edges. If the Hagaki (Cardstock) paper is curled, straighten it before loading. Printing onto curled Hagaki (Cardstock) may cause jams.

Use unfolded Oufuku hagaki (Return postcard) (available at post offices). Some Hagaki (Cardstock) may still have rough edges developed by a paper cutter on the back side. Remove any such rough edges by placing the Hagaki (Cardstock) on a flat surface and rubbing the edges gently a few times with a ruler.

## Envelopes

Envelopes should be fed from the MP tray with the print-side up or the optional paper feeder with the print-side up.



### NOTE

Do not load paper above the load limits located on the paper width guide of the optional paper feeder.

Due to the structure of envelopes, printing evenly over the entire surface may not be possible in some cases. Thin envelopes in particular may be wrinkled by the machine in some cases as they pass through. Before purchasing envelopes in volume, try testing a sample to ensure the print quality.

Storing envelopes for a long period may cause them to become wrinkled. Thus, keep the package sealed until you are ready to use them.

Keep the following points in mind.

- Do not use envelopes with exposed adhesive. In addition, do not use the type of envelope in which the adhesive is exposed after the top layer is peeled off. Serious damage may be caused if the paper covering the adhesive comes off in the machine.
- Do not use envelopes with certain special features. For example, do not use envelopes with a grommet for winding a string to close the flap or envelopes with an open or film-covered window.
- If paper jams occur, load fewer envelopes at once.

## Thick Paper

Before loading thick paper in the multi purpose tray, fan it and align the edges. Some thick paper may still have rough edges developed by a paper cutter on the back side. Remove any such rough edges just as with Hagaki (Cardstock) by placing the paper on a flat surface and rubbing the edges gently a few times with a ruler. Printing onto paper with rough edges may cause jams.



### NOTE

If the paper is not supplied correctly even after it is smoothed, load the paper in the multi purpose tray with the leading edge raised a few millimeters.

## Colored Paper

Colored paper must conform to the specifications.

➔ [Basic Paper Specifications \(page 11-16\)](#)

In addition, the pigments in the paper must be able to withstand the heat of printing (up to 200°C or 392°F).

## Preprinted Paper

Preprinted paper must conform to the specifications.

➔ [Basic Paper Specifications \(page 11-16\)](#)

The colored ink must be able to withstand the heat of printing. It must be resistant to silicone oil as well. Do not use paper with a treated surface such as glossy paper used for calendars.

## Recycled Paper

Recycled paper must conform to the specifications; however, its whiteness may be considered separately.

➔ [Basic Paper Specifications \(page 11-16\)](#)



### NOTE

Before purchasing recycled paper in volume, try testing a sample to ensure satisfactory print quality.

## Coated Paper

Coated paper is created by treating the surface of the base paper with a coating that provides higher printing quality than plain paper. Coated paper is used for particularly high quality printing.

The surface of high-quality or medium-quality paper is coated with special agents that improve ink adhesion by making the paper surface smoother. These agents are used either to coat both sides of the paper or just one side. The coated side appears slightly glossy.




### IMPORTANT

**When printing on coated paper in very humid environments, ensure that the paper is kept dry as moisture may cause sheets to stick together when they are fed into the machine. If printing in very humid environments, set coated paper for one sheet each.**

# Specifications

 **IMPORTANT**

Specifications are subject to change without notice.

 **NOTE**

For more information on using the FAX, refer to the following:

➔ **FAX Operation Guide**

## Machine

Item		Description
<b>Type</b>		Desktop
<b>Printing Method</b>		Electrophotography by semiconductor laser
<b>Paper Weight</b>	<b>Cassette</b>	60 to 163 g/m <sup>2</sup>
	<b>Multi Purpose Tray</b>	60 to 220 g/m <sup>2</sup> , 230 g/m <sup>2</sup> (Cardstock)
<b>Paper Type</b>	<b>Cassette</b>	Plain, Rough, Recycled, Vellum, Preprinted, Bond, Color (Colour), Prepunched, Letterhead, Thick, High Quality, Custom 1 to 8 (Duplex: Same as Simplex)
	<b>Multi Purpose Tray</b>	Plain, Transparency (OHP film), Rough, Vellum, Labels, Recycled, Preprinted, Bond, Cardstock, Coated, Color (Colour), Prepunched, Letterhead, Envelope, Thick, High Quality, Custom 1 to 8
<b>Paper Size</b>	<b>Cassette</b>	A4, A5, A6, B5, B6, Letter, Legal, Statement, Executive, Oficio II, Folio, 216 × 340 mm, 16K, B5 (ISO), Custom (105 × 148 mm to 216 × 356 mm)
	<b>Multi Purpose Tray</b>	A4, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, B5 (ISO), Envelope #10, Envelope #9, Envelope #6 3/4, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom (70 × 148 mm to 216 × 356 mm)
<b>Warm-up Time (22°C/71.6°F, 60%)</b>	<b>Power on</b>	26 seconds or less
	<b>Sleep</b>	17 seconds or less
<b>Paper Capacity</b>	<b>Cassette</b>	250 sheets (80 g/m <sup>2</sup> )* <sup>1</sup>
	<b>Multi Purpose Tray</b>	100 sheets (80 g/m <sup>2</sup> )

\*1 Up to upper limit height line in the cassette.

Item		Description
<b>Output Tray Capacity</b>	<b>Inner tray</b>	250 sheets (80 g/m <sup>2</sup> )
<b>Image Write System</b>		Semiconductor laser and electrophotography
<b>Memory</b>		1024 MB
<b>Interface</b>	<b>Standard</b>	USB Interface Connector: 1 (Hi-Speed USB) Network interface: 1 (10 BASE-T/100 BASE-TX/1000 BASE-T) USB Port: 2 (Hi-Speed USB) Fax: 1 (ECOSYS M6530cdn only)
	<b>Option</b>	eKUIO: 1
<b>Operating Environment</b>	<b>Temperature</b>	10 to 32.5°C/50 to 90.5°F
	<b>Humidity</b>	10 to 80 %
	<b>Altitude</b>	3,500 m/11,482 ft maximum
	<b>Brightness</b>	1,500 lux maximum
<b>Dimension (W × D × H)</b>		18 45/64 × 21 31/32 × 24 17/64" 475 × 558 × 616 mm
<b>Weight</b>		ECOSYS M6030cdn: Approx. 76.3 lb/Approx. 34.6 kg ECOSYS M6530cdn: Approx. 76.5 lb/Approx. 34.7 kg (without toner container)
<b>Space Required (W × D) (Using multi purpose tray)</b>		18 45/64 × 29 39/64 475 × 751.8 mm
<b>Power Source</b>		120 V Specification Model: 120 V ~ 60 Hz 9.0 A 230 V Specification Model: 220 to 240 V ~ 50/60 Hz 5.0 A
<b>The power consumption of the product in networked standby (If all network ports are connected.)</b>		2.5 W
<b>Options</b>		➔ <a href="#">Optional Equipment (page 11-2)</a>



## Copy Functions

Item		Description		
<b>Copy Speed</b>		Black and White Copying	Full Color Copying	
		A4	30 sheets/min	30 sheets/min
		Letter	32 sheets/min	32 sheets/min
		Legal	26 sheets/min	26 sheets/min
		B5	27 sheets/min	27 sheets/min
		A5	27 sheets/min	27 sheets/min
		A6	27 sheets/min	27 sheets/min
<b>First Copy Time (A4, place on the platen, feed from Cassette)</b>	<b>Black and White</b>	9.5 seconds or less		
	<b>Color</b>	11.5 seconds or less		
<b>Zoom Level</b>		Manual mode: 25 to 400%, 1% increments Auto mode: Preset Zoom		
<b>Continuous Copying</b>		1 to 999 sheets		
<b>Resolution</b>		600 × 600 dpi		
<b>Supported Original Types</b>		Sheet, Book, 3-dimensional objects (maximum original size: Legal/Folio)		
<b>Original Feed System</b>		Fixed		

## Printer Functions

Item		Description	
<b>Printing Speed</b>		Same as Copying Speed.	
<b>First Print Time (A4, feed from Cassette)</b>	<b>Black and White</b>	7.0 seconds or less	
	<b>Color</b>	8.5 seconds or less	
<b>Resolution</b>		600 × 600 dpi, 9600 dpi equivalent × 600 dpi	
<b>Operating System</b>		Windows XP, Windows Server 2003, Windows Vista, Windows 7, Windows 8, Windows 8.1, Windows Server 2008/R2, Windows Server 2012/R2, Mac OS 10.5 or later	
<b>Interface</b>		USB Interface Connector: 1 (Hi-Speed USB) Network interface: 1 (10 BASE-T/100 BASE-TX/1000 BASE-T) Optional Interface (Option): 1 (For IB-50/IB-51 mounting)	
<b>Page Description Language</b>		PRESCRIBE	
<b>Emulations</b>		PCL6 (PCL-XL, PCL5c), KPDL3, XPS	

## Scanner Functions

Item	Description
<b>Resolution</b>	600 dpi, 400 dpi, 300 dpi, 200×400 dpi, 200 dpi, 200×100 dpi
<b>File Format</b>	TIFF (MMR/JPEG compression), JPEG, PDF (MMR/JPEG compression), XPS, PDF/A, High compressive PDF, Encrypted PDF, OPEN XPS
<b>Scanning Speed<sup>*1</sup></b>	1-sided    B/W 40 Images/min Color 30 Images/min 2-sided    B/W 17 Images/min Color 13 Images/min (A4 landscape, 300 dpi, Image quality: Text/Photo original)
<b>Interface</b>	Ethernet (10 BASE-T/100 BASE-TX/1000 BASE-T), USB
<b>Transmission System</b>	SMB, SMTP, FTP, FTP over SSL, USB, TWAIN <sup>*2</sup> , WIA <sup>*3</sup> , WSD

\*1 When using the document processor (except TWAIN and WIA scanning)

\*2 Available Operating System: Windows XP/Windows Vista/Windows Server 2003/Windows Server 2008/Windows Server 2008 R2/Windows 7/Windows 8/Windows 8.1/Windows Server 2012/Windows Server 2012 R2

\*3 Available Operating System: Windows Vista/Windows Server 2008/Windows Server 2008 R2/Windows 7/Windows 8/Windows 8.1/Windows Server 2012/Windows Server 2012 R2

## Document Processor

Item	Description
<b>Supported Original Types</b>	Sheet originals
<b>Paper Size</b>	Maximum: Legal/Folio Minimum: Statement-R/A6-R
<b>Paper Weight</b>	1-sided: 50 to 120 g/m <sup>2</sup> 2-sided: 50 to 120 g/m <sup>2</sup>
<b>Loading Capacity</b>	75 sheets (50 to 80 g/m <sup>2</sup> ) maximum <sup>*1</sup>

\*1 Up to upper limit height line in the document processor

## Paper Feeder (500-sheet) (Option)

Item	Description
<b>Paper Supply Method</b>	Friction roller feeder (No. Sheets: 500, 80 g/m <sup>2</sup> )
<b>Paper Size</b>	A4, A5, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement, Executive, Oficio II, 16K, B5 (ISO), Envelope #10, Envelope #9, Envelope #6 3/4, Envelope Monarch, Envelope DL, Envelope C5, Youkei 4, Youkei 2, Custom (92 × 162 to 216 × 356 mm)
<b>Supported Paper</b>	Paper weight: 60 to 220 g/m <sup>2</sup> Media types: Plain, Rough, Recycled, Preprinted, Labels, Bond, Vellum, Color (Colour), Prepunched, Letterhead, Envelope, Coated, Thick, High Quality, Custom 1 to 8
<b>Dimensions (W) × (D) × (H)</b>	15 23/64 × 20 61/64 × 4 37/64 390 × 532 × 116 mm
<b>Weight</b>	9.0 lbs. or less/ 4.1 kg or less

## Manual Stapler

Item	Description
<b>Paper Weight</b>	90 g/m <sup>2</sup> or less
<b>Number of stapled sheets</b> *1	20 sheets (80 g/m <sup>2</sup> ) maximum, 15 sheets (80 g/m <sup>2</sup> or less) maximum
<b>Dimensions (W) × (D) × (H)</b>	2 41/64 × 6 1/2 × 5 21/64 67 × 165 × 135 mm
<b>Weight</b>	1.3 lbs. or less/ 0.6 kg or less

\*1 Paper stack up to 2mm thick.



### NOTE

Consult your dealer or service representative for recommended paper types.

# Glossary

## Accessibility

The machine is designed featuring good accessibility even for the elderly and those who are physically challenged or visually impaired.

## Apple Talk

AppleTalk offers file sharing and printer sharing and it also enables you to utilize application software that is on another computer on the same AppleTalk network.

## Auto Form Feed Timeout

During data transmission, the machine may sometimes have to wait until receiving the next data. This is the auto form feed timeout. When the preset timeout passes, the machine automatically prints output. However, no output is performed if the last page has no data to be printed.

## Auto-IP

Auto-IP is a module that enables dynamic IPv4 addresses to be assigned to a device on startup. However, DHCP requires a DHCP server. Auto-IP is a server-less method of choosing an IP address. IP addresses between 169.254.0.0 to 169.254.255.255 are reserved for Auto-IP and assigned automatically.

## Auto Paper Selection

A function to automatically select paper in the same size as originals when printing.

## Auto Sleep

A mode designed for electrical power saving, activated when the machine is left unused or there is no data transfer for a specific period. In Sleep mode, power consumption is kept to a minimum.

## Bonjour

Bonjour, also known as zero-configuration networking, is a service that automatically detects computers, devices and services on an IP network. Bonjour, because an industry-standard IP protocol is used, allows devices to automatically recognize each other without an IP address being specified or DNS server being set. Bonjour also sends and receives network packets by UDP port 5353. If a firewall is enabled, the user must check that UDP port 5353 is left open so that Bonjour will run correctly. Some firewalls are set up so as to reject only certain Bonjour packets. If Bonjour does not run stably, check the firewall settings and ensure that Bonjour is registered on the exceptions list and that Bonjour packets are accepted. If you install Bonjour on Windows XP Service Pack 2 or later, the Windows firewall will be set up correctly for Bonjour.

## Custom Box

The Custom Box function stores print data for each individual user on the printer and allows the user to print single or multiple copies of the stored data later using the printer's operation panel.

## Default Gateway

This indicates the device, such as a computer or router, that serves as the entrance/exit (gateway) for accessing computers outside the network that you are on. When no specific gateway is designated for a destination IP address, data is sent to the host designated as the Default Gateway.

## **DHCP (Dynamic Host Configuration Protocol)**

Dynamic Host Configuration Protocol (DHCP) that automatically resolves IP addresses, subnet masks, and gateway addresses on a TCP/IP network. DHCP minimizes the load of network management employing a large number of client computers because it relieves individual clients including printers from the IP address being assigned.

## **DHCP (IPv6)**

DHCP (IPv6) is the next-generation of the Internet's Dynamic Host Configuration Protocol and supports IPv6. It extends the BOOTP startup protocol that defines the protocols used for transferring configuration information to hosts on the network. DHCP (IPv6) permits the DHCP server to use its expanded functionality to send configuration parameters to an IPv6 node. Because the network addresses that can be used are allocated automatically, the IPv6 node management workload is reduced in systems where the administrator has to exercise close control over IP address allocation.

## **dpi (dots per inch)**

A unit for resolution, representing the number of dots printed per inch (25.4 mm).

## **EcoPrint Mode**

A printing mode that helps save toner. Copies made in this mode are thus lighter than normal.

## **Emulation**

The function to interpret and execute other printers' page description languages. The machine emulates operation of PCL6, KPDL3 (PostScript 3 compatible).

## **FTP (File Transfer Protocol)**

A protocol to transfer files on the TCP/IP network, whether the Internet or an intranet. Along with HTTP and SMTP/POP, FTP is now frequently used on the Internet.

## **Grayscale**

A computer color expression. Displayed images of this sort are typically composed of shades of gray, varying from black at the weakest intensity to white at the strongest, without any other colors. Gray levels are displayed in numerical levels: that is, white and black only for 1 bit; 256 gray levels (including white and black) for 8 bits; and 65,536 gray levels for 16 bits.

## **IP Address**

An Internet protocol address is a unique number that represents a specific computer or related device on the network. The format of an IP address is four sets of numbers separated by dots, e.g. 192.168.110.171. Each number should be between 0 and 255.

## **IPP**

IPP (Internet Printing Protocol) is a standard that uses TCP/IP networks such as the Internet to enable print jobs to be sent between remote computers and printers. IPP is an extension of the HTTP protocol used to view websites and enables printing to be carried out via routers on printers in remote locations. It also supports the HTTP authentication mechanisms along with SSL server and client authentication as well as encryption.

## **Job Box**

The Job Box function stores print data on the printer and allows users to print single or multiple copies of the stored data later using the printer's operation panel.

## **KPDL (Kyocera Page Description Language)**

Kyocera's PostScript page description language compatible with Adobe PostScript Level 3.

## **Multi Purpose (MP) Tray**

The paper supply tray on the front side of the machine. Use this tray instead of the cassettes when printing onto envelopes, Hagaki (Cardstock), transparencies, or labels.

## **NetBEUI (NetBIOS Extended User Interface)**

An interface, developed by IBM in 1985, as an update from NetBIOS. It enables more advanced functions on smaller networks than other protocols such as TCP/IP, etc. It is not suitable for larger networks due to lack of routing capabilities to choose the most appropriate routes. NetBEUI has been adopted by IBM for its OS/2 and Microsoft for its Windows as a standard protocol for file sharing and printing services.

## **Outline font**

With outline fonts, character outlines are represented with numerical expressions and fonts can be enlarged or reduced in different ways by changing the numeric values of those expressions. Printing remains clear even if you enlarge fonts, since the characters are defined with outlines represented with numerical expressions. You can specify the font size in steps of 0.25 points up to 999.75 points.

## **PDF/A**

This is "ISO 19005-1. Document management - Electronic document file format for long-term preservation - Part 1: Use of PDF (PDF/A)", and is a file format based on PDF 1.4. It has been standardized as ISO 19005-1, and is a specialization of PDF, which has been mainly used for printing, for long-term storage. A new part, ISO 19005-2 (PDF/A-2), is currently being prepared.

## **POP3 (Post Office Protocol 3)**

A standard protocol to receive E-mail from the server in which the mail is stored on the Internet or an intranet.

## **PostScript**

A page description language developed by Adobe Systems. It enables flexible font functions and highly-functional graphics, allowing higher quality printing. The first version called Level 1 was launched in 1985, followed by Level 2 that enabled color printing and two-byte languages (e.g. Japanese) in 1990. In 1996, Level 3 was released as an update for the Internet access and PDF format as well as gradual improvements in implementation technologies.

## **PPM (prints per minute)**

This indicates the number of A4 size printouts made in one minute.

## **Printer Driver**

The software to enable you to print data created on any application software. The printer driver for the machine is contained in the DVD enclosed in the package. Install the printer driver on the computer connected to the machine.

## **RA(Stateless)**

The IPv6 router communicates (transmits) information such as the global address prefix using ICMPv6. This information is the Router Advertisement (RA).

ICMPv6 stands for Internet Control Message Protocol, and is a IPv6 standard defined in the RFC 2463 "Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification".

## **RAM Disk**

Using part of the printer's memory as a virtual disk, you can set any amount of memory from overall printer memory as a RAM disk in order to use features such as electronic sorting (shortening print time).

## **Send as E-mail**

A function to send the image data stored in the machine as an E-mail attachment. E-mail addresses can be selected from the list or entered at each time.

## **SMTP (Simple Mail Transfer Protocol)**

A protocol for E-mail transmission over the Internet or an intranet. It is used for transferring mail between mail servers as well as for sending mail from clients to their servers.

## **Status Page**

The page lists machine conditions, such as the memory capacity, total number of prints and scans, and paper source settings.

## **Subnet Mask**

The subnet mask is a way of augmenting the network address section of an IP address.

A subnet mask represents all network address sections as 1 and all host address sections as 0. The number of bits in the prefix indicates the length of the network address. The term "prefix" refers to something added to the beginning and, in this context, indicates the first section of the IP address. When an IP address is written, the length of the network address is indicated by the prefix length after a forward slash (/). For example, "24" in the address "133.210.2.0/24". In this way, "133.210.2.0/24" denotes the IP address "133.210.2.0" with a 24-bit prefix (network section). This new network address section (originally part of the host address) made possible by the subnet mask is referred to as the subnet address. When you enter the subnet mask, be sure to set the "DHCP" setting to "Off".

## **TCP/IP (Transmission Control Protocol/Internet Protocol)**

TCP/IP is a suite of protocols designed to define the way computers and other devices communicate with each other over a network.

## **TCP/IP (IPv6)**

TCP/IP (IPv6) is based on the current Internet protocol, TCP/IP (IPv4). IPv6 is the next-generation Internet protocol and expands the available address space, which resolves the problem of the lack of addresses under IPv4, while also introducing other improvements such as additional security functionality and the capacity to prioritize data transmission.

## **TWAIN (Technology Without An Interesting Name)**

A technical specification for connecting scanners, digital cameras, and other image equipment to computers. The TWAIN compatible devices enable you to process image data on any relevant application software. TWAIN is adopted on a large amount of graphic software (e.g. Adobe Photoshop) and OCR software.

## **USB (Universal Serial Bus) 2.0**

A USB interface standard for Hi-Speed USB 2.0. The maximum transfer rate is 480 Mbps. This machine is equipped with USB 2.0 for high-speed data transfer.

## **WIA (Windows Imaging Acquisition)**

A function to import images supported after Windows Me/XP from digital cameras and other peripheral devices. This function replaces what TWAIN used to do. The feature is provided as a part of Windows functions and improves ease of operation, so that you import images directly to My Computer without using any application.

---

# Index

## A

- Accessibility 11-29
- Address Book 3-23
  - Adding 3-23
  - Contact 3-23
  - Editing and Deleting 3-28
  - Group 3-26
- Address Book/One Touch 8-23
- Adjustment/Maintenance 8-34
- AirPrint 4-7
- Apache License (Version 2.0) 1-10
- Apple Talk 11-29
- Auto Error Clear 8-18
- Auto Form Feed Timeout 11-29
- Auto Panel Reset 8-18
- Auto Paper Selection 11-29
- Auto Sleep 2-20, 11-29
- AutoColorCorrect 8-34
- Auto-IP 11-29
  - Settings 8-26
- Automatic 2-Sided Print Function 1-13

## B

- Background Density Adjustment 6-17, 8-34
  - Default 8-13
- Bonjour 11-29
  - Settings 8-26
- Border Line 6-20
  - Default 8-14

## C

- Cables 2-7
- Card Authentication Kit 11-3
- Cassette
  - Loading Paper 3-4
  - Paper Size and Media Type 3-10, 8-11
- Cassette 1 2-2
- Cassette Settings 3-10
- Cassettes 2 to 4 2-6
- Character Entry Method 11-11
- Checking the Counter 2-35
- Checking the Remaining Amount of Toner 7-15
- Cleaning 10-2
  - Glass Platen 10-2
  - Paper Transfer Unit 10-3
  - Slit Glass 10-2
- Coated Paper 11-23
- Collate 6-12
  - Default 8-13
- Color
  - Color Balance 6-15
  - Saturation 6-17
- Color Balance 6-15
- Color Regist. 8-35
- Color Selection 6-14
  - Default 8-13

- ColorCalibration 8-35
- Combine 6-20
- Command Center RX 2-38
- Common Settings 8-7
  - ColorToner Empty 8-15
  - Date Setting 8-17
  - Default Screen 8-7
  - Display Brightness 8-7
  - Display Status/Log 8-17
  - Error Handling 8-15
  - Format SD Card 8-16
  - Format SSD 8-16
  - Function Defaults 8-13
  - Language 8-7
  - Login Operation 8-20
  - Measurement 8-15
  - Optional Memory 8-19
  - Orig./Paper Set. 8-8
  - Preset Limit 8-15
  - RAM Disk Mode 8-19
  - Sound 8-7
  - Timer Setting 8-18
  - TonerAlert Level 8-16
  - USB Keyboard Type 8-16
- Connecting
  - LAN Cable 2-8
  - Power Cable 2-9
  - USB cable 2-9
- Connection Method 2-7
- Continuous Scan 6-24
  - Default 8-14
- Contrast 6-16, 8-34
- Contrast (Copy) 8-34
- Contrast (Send) 8-34
- Conventions Used in This Guide xvii
- Copy 5-10
- Copy Denst. Adj. 8-34
- Copy Settings 8-20
  - Auto % Priority 8-20
  - AutoPaperSelect. 8-20
  - DP Read Action 8-20
  - Paper Selection 8-20
  - Reserve Priority 8-20
  - Select Key Setting 8-20
- Copy Speed 11-26
- Correct. Bk Line 8-34
- Counting the Number of Pages Printed
  - Counter 2-35
  - Each Job Account 9-37
  - Print Accounting Report 9-38
  - Total Accounting 9-37
  - Unknown ID Job 9-40
- Custom Box 11-29
  - Creating a New Box 5-32
  - Deleting Documents 5-37
  - Editing and Deleting Custom Box 5-34
  - Editing Documents 5-36
  - Printing Documents 5-35
  - Storing Documents 5-34



## D

- Data Security [8-33](#)
- Data Security Kit [11-7](#)
- DataSanitization [8-33](#)
- Date Format [8-17](#)
- Date Setting
  - Date Format [8-17](#)
  - Date/Time [8-17](#)
  - Summer Time [8-17](#)
  - Time Zone [8-17](#)
- Date/Time [8-17](#)
- Default Gateway [11-29](#)
  - Settings [8-26](#)
- Default Screen [8-7](#)
- Del. after Print [6-33](#)
- Density [6-12](#)
- Destination
  - Adding a Destination [3-23](#)
  - Address Book [5-15](#)
  - Checking and Editing [5-21](#)
  - Confirmation Screen of Destinations [5-22](#)
  - Destination Check [8-21](#)
  - Entering a New E-mail Address [5-17](#)
  - Multi Sending [5-24](#)
  - One Touch Key [3-29](#)
  - Search [5-16](#)
  - Sort [8-23](#)
  - Specifying a New PC Folder [5-18](#)
- Destination Check
  - Check before Send [8-21](#)
  - Check New Destination [8-21](#)
- Device [7-14](#)
- DHCP [11-30](#)
  - Settings [8-26](#)
- DHCP (IPv6) [11-30](#)
- Display Brightness [8-7](#)
- Display Status/Log [8-17](#)
- Document Box
  - Custom Box [5-30](#), [5-32](#)
  - Job Box [4-9](#), [5-30](#)
  - Removable Memory Box [5-31](#)
  - What is Document Box? [5-30](#)
- Document Box Settings [8-22](#)
  - Custom Box [8-22](#)
  - Job Box [8-22](#)
  - Polling Box [8-22](#)
  - Select Key Setting [8-22](#)
  - Sub Address Box [8-22](#)
- Document Processor [2-2](#)
  - How to Load Originals [5-3](#)
  - Loading Originals [5-3](#)
  - Originals Not Supported by the Document Processor [5-3](#)
  - Originals Supported by the Document Processor [5-3](#)
  - Part Names [2-2](#)
- dpi [11-30](#)
- Duplex [6-22](#)
- Duplex (2-sided Original) [6-26](#)

## E

- EcoPrint [6-13](#), [11-30](#)
  - Default [8-13](#)
  - Printer [8-24](#)
- Edit Destination [8-23](#)
  - Address Book [3-23](#)
  - Address Book Defaults [8-23](#)
  - Contact [3-23](#)
  - Group [3-26](#)
  - One Touch Key [3-29](#)
- E-mail Settings [2-44](#)
- E-mail Subject/Body
  - Default [8-14](#)
- Emulation [11-30](#)
  - Selection [8-24](#)
- Encrypted PDF [6-34](#)
- Energy Saving Control Function [1-13](#)
- Energy Star (ENERGY STAR®) Program [1-14](#)
- Entry
  - File Name [6-24](#)
  - Subject [6-32](#)
- Environment [1-3](#)
- Err. Clear Timer [8-19](#)
- Error Handling [8-15](#)
- Expansion Memory [11-4](#)

## F

- FAX [8-23](#)
- Feed Cover [2-4](#)
- File
  - Format [6-28](#)
  - PDF [6-30](#)
  - Separation [6-32](#)
- File Format [6-28](#)
  - Default [8-13](#)
- File Name Entry [6-24](#)
  - Default [8-14](#)
- File Separation [6-32](#)
  - Default [8-13](#)
- Finishing Binding [6-23](#)
- First Copy Time [11-26](#)
- First Print Time [11-26](#)
- FTP [11-30](#)
- FTP Encrypted TX [6-33](#)
- FTP(Client)
  - Protocol Detail [8-27](#)
- FTP(Server)
  - Protocol Detail [8-27](#)
- Function Defaults [8-13](#)
- Fuser Cover [2-4](#)

## G

- Glossary [11-29](#)
- Google Cloud Print [4-8](#)
- GPL/LGPL [1-8](#)
- Grayscale [11-30](#)
- Group Authorization Set. [9-17](#)
  - Group Authorization [9-17](#)
- Guest Authorization Set. [9-18](#)
  - Guest Authorization [9-18](#)

Guest Property [9-19](#)  
Guides Provided with the Machine [xiv](#)

## H

Handle [2-2](#), [2-3](#)  
Help [11-30](#)  
Help Screen [2-13](#)  
High Compression PDF [6-29](#)  
Host Name [8-26](#)  
HTTP  
    Protocol Detail [8-27](#)  
HTTPS  
    Protocol Detail [8-27](#)

## I

I/F Block Set. [8-32](#)  
Image Quality [6-28](#)  
Inner Tray [2-2](#)  
Install  
    Macintosh [2-30](#)  
    Software [2-22](#)  
    Windows [2-23](#)  
IP Address [11-30](#)  
    Settings [8-26](#)  
IPP [11-30](#)  
    Protocol Detail [8-27](#)  
IPP over SSL  
    Protocol Detail [8-27](#)  
IPSec  
    Settings [8-28](#)

## J

Job  
    Available Status [7-2](#)  
    Canceling [7-13](#)  
    Checking History [7-8](#)  
    Checking Status [7-2](#)  
    Displaying History Screen [7-9](#)  
    Displaying Status Screens [7-2](#)  
    Pause and Resumption [7-13](#)  
    Sending the Log History [7-12](#)  
Job Accounting [9-24](#)  
    Adding an Account [9-27](#)  
    Counting the Number of Pages Printed [9-37](#)  
    Default Setting [9-36](#)  
    Deleting an Account [9-31](#)  
    Editing an Account [9-30](#)  
    Enabling Job Accounting [9-25](#)  
    FAX Driver [9-35](#)  
    Job Accounting Access [9-26](#)  
    Login [9-39](#)  
    Logout [9-39](#)  
    Overview of Job Accounting [9-24](#)  
    Print Accounting Report [9-38](#)  
    Printing [9-32](#)  
    Restricting the Use of the Machine [9-29](#)  
    TWAIN [9-33](#)  
    WIA [9-34](#)  
Job Box [11-30](#)

Deletion of Job Retention [8-22](#)  
Private Print Box [4-10](#)  
Proof and Hold Box [4-16](#)  
Quick Copy Box [4-14](#)  
Quick Copy Jobs [8-22](#)  
Specifying the Job Box from a Computer and Storing  
    the Job [4-9](#)  
Storage Media [8-22](#)  
Stored Job Box [4-12](#)  
Job Finish Notice [6-24](#)  
JPEG/TIFF Print [6-35](#)  
    Default [8-14](#)

## K

Knopflerfish License [1-10](#)  
KPD L [11-31](#)

## L

Label [11-21](#)  
LAN Cable [2-7](#)  
    Connecting [2-8](#)  
LAN Interface [8-29](#)  
Language [8-7](#)  
LDAP  
    Protocol Detail [8-27](#)  
Legal Information [1-7](#)  
Legal Restriction on Copying [1-6](#)  
Legal Restriction on Scanning [1-6](#)  
LINE Connector [2-4](#)  
Loading Originals [5-2](#)  
    Loading Originals in the Document Processor [5-3](#)  
    Placing Originals on the Platen [5-2](#)  
Local Authorization [9-16](#)  
Login [2-14](#)  
Login Operation [8-20](#)  
Logout [2-15](#)  
LPD  
    Protocol Detail [8-27](#)

## M

Management [9-1](#)  
Manual stapler [2-6](#), [11-7](#)  
Measurement [8-15](#)  
Media Type Setting [8-12](#)  
Mixed Size Originals [6-12](#)  
Monotype Imaging License Agreement [1-9](#)  
MP Tray Settings [8-11](#)  
Multi Purpose Tray [2-4](#), [11-31](#)  
    Paper Size and Media Type [3-11](#), [8-11](#)  
Multi Sending [5-24](#)

## N

NetBEUI [11-31](#)  
    Protocol Detail [8-27](#)  
Network  
    Preparation [2-17](#)  
    Settings [8-26](#)  
Network Interface [2-7](#)  
Network Interface Connector [2-4](#)

- Network Interface Kit [11-5](#)
  - New E-mail Address [5-17](#)
  - New PC Folder [5-18](#)
  - Notice [1-2](#)
  - NW InterfaceSend [8-32](#)
- O**
- One Touch Key
    - Adding [3-29](#)
    - Editing and Deleting [3-30](#)
  - OpenSSL License [1-8](#)
  - Operation Panel [2-2](#)
  - Option
    - Card Authentication Kit [11-3](#)
    - Data Security Kit [11-7](#)
    - Expansion Memory [11-4](#)
    - Manual stapler [11-7](#)
    - Network Interface Kit [11-5](#)
    - Overview [11-2](#)
    - Paper Feeder [11-3](#)
    - SD Card [11-6](#)
    - SSD [11-5](#)
    - ThinPrint Option [11-7](#)
    - USB Keyboard [11-8](#)
    - Wireless Network Interface Kit [11-5](#)
  - Option Interface [2-4](#)
  - Optional Applications [11-9](#)
  - Optional Function [8-34](#)
  - Optional Memory [8-19](#)
  - Optional Network
    - Basic [8-30](#)
  - Orig./Paper Set. [8-8](#)
  - Original
    - Custom Orig. Size [8-8](#)
    - Default Original Size [8-8](#)
    - Settings [8-8](#)
  - Original Binding [6-23, 6-26](#)
  - Original eject table [2-2](#)
  - Original Image [6-13](#)
    - Default [8-13](#)
  - Original Orientation [6-11](#)
    - Default [8-13](#)
  - Original Size [6-9](#)
  - Original Size Indicator Plates [2-2](#)
  - Original SSLeay License [1-8](#)
  - Original Stopper [2-2, 5-4](#)
  - Original Table [2-2](#)
  - Original Width Guides [2-2](#)
  - Outline font [11-31](#)
- P**
- Panel Reset Timer [8-18](#)
  - Paper
    - Checking the Remaining Amount of Paper [7-15](#)
    - Appropriate Paper [11-17](#)
    - Cassette [8-11](#)
    - Custom Paper Size [8-9](#)
    - Default Paper Source [8-10](#)
    - Loading Cardstock [3-9](#)
    - Loading Envelopes [3-9](#)
    - Loading Paper [3-2](#)
    - Loading Paper in the Cassettes [3-4](#)
    - Loading Paper in the Multi Purpose Tray [3-7](#)
    - Media for Auto [8-10](#)
    - Media Type Setting [8-10](#)
    - Multi Purpose Tray [8-11](#)
    - Precaution for Loading Paper [3-3](#)
    - Size and Media Type [3-10, 11-16](#)
    - Special Paper [11-20](#)
    - Special Paper Action [8-10](#)
    - Specifications [11-16](#)
    - Weight [8-12](#)
  - Paper Feed Mode [8-25](#)
  - Paper Feeder [11-3](#)
  - Paper Jams [10-34](#)
    - Cassettes 1 to 4 [10-38](#)
    - Document Processor [10-47](#)
    - Duplex Unit [10-45](#)
    - Inside the Machine [10-43](#)
    - Jam Location Indicators [10-34](#)
    - Multi Purpose Tray [10-36](#)
    - Rear Cover 1 [10-43](#)
    - Rear Cover 1 (Feed) [10-39](#)
    - Rear Cover 2 [10-40](#)
    - Rear Cover 3 [10-42](#)
  - Paper Length Guide [2-4, 3-5](#)
  - Paper Selection [6-10](#)
  - Paper Stopper [2-2, 3-12](#)
  - Paper Width Guides [2-4, 3-4](#)
  - Part Names [2-2](#)
  - PDF/A [6-28, 11-31](#)
  - Ping [8-29](#)
  - Platen [2-2](#)
  - POP3 [11-31](#)
    - Protocol Detail [8-27](#)
  - PostScript [11-31](#)
  - Power Cable
    - Connecting [2-9](#)
  - Power Management [1-13](#)
  - Power Off [2-10](#)
  - Power On [2-10](#)
  - Power Switch [2-2](#)
  - PPM [11-31](#)
  - Precaution for Loading Paper [3-3](#)
  - Precautions for Use [1-4](#)
  - Preset Limit [8-15](#)
  - Prevent Bleed-thru [6-18](#)
    - Default [8-13](#)
  - Print Override [6-25](#)
  - Print Settings [4-5](#)
  - Printer [8-24](#)
    - Auto Cassette Change [8-25](#)
    - Color Setting [8-24](#)
    - Copies [8-24](#)
    - CR Action [8-24](#)
    - Duplex [8-24](#)
    - EcoPrint [8-24](#)
    - Emulation Set. [8-24](#)
    - Form Feed TimeOut [8-24](#)
    - Gloss Mode [8-25](#)

- Job Name [8-25](#)
- LF Action [8-24](#)
- MP Tray Priority [8-25](#)
- Orientation [8-24](#)
- Override A4/Letter [8-24](#)
- Paper Feed Mode [8-25](#)
- Print setting [4-5](#)
- User Name [8-25](#)
- Wide A4 [8-24](#)
- Printer Driver [11-31](#)
  - Help [4-6](#)
- Printing Documents Stored in Removable USB Memory [5-38](#)
- Printing from PC [4-2](#)
- Printing Speed [11-26](#)
- Product Library [xv](#)
- Program [5-6](#)
  - Confirming [5-7](#)
  - Deleting [5-8](#)
  - Overwriting [5-8](#)
  - Recalling [5-7](#)
  - Registering [5-6](#)

## Q

- Quiet Mode [6-25, 8-34](#)

## R

- RA (Stateless) [11-31](#)
- RAM Disk [11-32](#)
- RAM Disk Mode [8-19](#)
- Raw Port
  - Protocol Detail [8-27](#)
- Rear Cover 1 [2-3](#)
- Rear Cover 2 to 4 [2-6](#)
- Recycled Paper [11-23](#)
- Regarding Trade Names [1-7](#)
- Regular Maintenance [10-2](#)
  - Toner Container Replacement [10-4](#)
  - Waste Toner Box Replacement [10-8](#)
- Report [8-5](#)
  - Admin Report Settings [8-6](#)
  - Job Log History [8-6](#)
  - Report Print [8-5](#)
  - Result Report Settings [8-6](#)
- Report Print
  - Font List [8-5](#)
  - Menu Map [8-5](#)
  - Opt NW Status [8-5](#)
  - Status Page [8-5](#)
- Resolution [6-32, 11-26](#)
- Resource Saving - Paper [1-13](#)
- Responding to Messages [10-17](#)
- Restart [8-33](#)
- Restart Network [8-29](#)

## S

- Safety Conventions in This Guide [1-2](#)
- Saturation [6-17](#)
- Saving Documents to USB Memory [5-40](#)

- Scan Resolution [6-32](#)
  - Default [8-13](#)
- Scanner Unit Open Lever [2-2](#)
- SD Card [11-6](#)
  - Format [8-16](#)
- Secure Protocol [8-29](#)
- Security Level [8-33](#)
- Select Key Setting [8-20, 8-21, 8-22](#)
- Send and Forward [8-21](#)
- Send as E-mail [5-13](#)
- Send Result [8-6](#)
- Send Settings [8-21](#)
  - Default Screen [8-21](#)
  - Destination Check [8-21](#)
  - New Destination Entry [8-21](#)
  - Recall Destination [8-21](#)
  - Select Key Setting [8-21](#)
  - Send and Forward [8-21](#)
- Send to Folder (FTP) [5-13](#)
- Send to Folder (SMB) [5-13](#)
- Send/Box Density [8-34](#)
- Sending [5-13](#)
  - Preparation for Sending a Document to a PC [3-13](#)
- Sending Size [6-27](#)
- Service Setting [8-35](#)
- Setting Date and Time [2-16](#)
- Sharpness [6-16](#)
- Simple Login [2-15](#)
- Size Dial [2-4](#)
- Skip Blank Page [6-25](#)
- Sleep [2-20](#)
- Sleep Level [2-21, 8-18](#)
- Sleep Rules [2-21, 8-18](#)
- Sleep Timer [8-18](#)
- Slit Glass [2-2](#)
- SMB
  - Protocol Detail [8-27](#)
- SMTP [11-32](#)
  - Protocol Detail [8-27](#)
- SNMP
  - Protocol Detail [8-27](#)
- SNMPv3
  - Protocol Detail [8-27](#)
- Solving Malfunctions [10-11](#)
- Sound [8-7](#)
- Specifications [11-24](#)
  - Copy Functions [11-26](#)
  - Document Processor [11-27](#)
  - Machine [11-24](#)
  - Manual Stapler [11-28](#)
  - Paper Feeder (500-sheet) (Option) [11-28](#)
  - Printer Functions [11-26](#)
  - Scanner Functions [11-27](#)
- Specifying Destination [5-15](#)
- SSD [11-5](#)
  - Format [8-16](#)
- SSD Initializ. [8-33](#)
- SSL [8-29](#)
- Status Page [11-32](#)
- Status/Job Cancel [7-1](#)

- Storing Size [6-34](#)
  - Subject/Body [6-32](#)
    - Default [8-14](#)
  - Subnet Mask [11-32](#)
    - Settings [8-26](#)
  - Supplies
    - Checking the Remaining Amount [7-15](#)
  - Symbols [1-2](#)
  - System Menu [8-2](#)
    - Address Book/One Touch [8-23](#)
    - Adjustment/Maintenance [8-34](#)
    - Common Settings [8-7](#)
    - Copy [8-20](#)
    - Document Box [8-22](#)
    - Edit Destination [8-23](#)
    - FAX [8-23](#)
    - Printer [8-24](#)
    - Report [8-5](#)
    - Send [8-21](#)
    - System/Network [8-26](#)
    - User Login/Job Accounting [8-23](#)
    - User Property [8-6, 9-10](#)
  - System/Network [8-26](#)
    - Data Security [8-33](#)
    - I/F Block Set. [8-32](#)
    - Network Setting [8-26](#)
    - NW InterfaceSend [8-32](#)
    - Optional Function [8-34](#)
    - Optional Network [8-29](#)
    - Restart [8-33](#)
    - Security Level [8-33](#)
    - Wireless Network [8-30](#)
- T**
- TCP/IP [11-32](#)
    - Settings [8-26](#)
  - TCP/IP (IPv4)
    - Settings [2-17, 8-26](#)
  - TCP/IP (IPv6) [11-30](#)
    - Settings [8-26](#)
  - TEL Connector [2-4](#)
  - ThinPrint
    - Protocol Detail [8-28](#)
  - ThinPrint Option [11-7](#)
  - ThinPrint Over SSL
    - Protocol Detail [8-28](#)
  - Time Zone [8-17](#)
  - Timer Setting
    - Auto Error Clear [8-18](#)
    - Auto Panel Reset [8-18](#)
    - Err. Clear Timer [8-19](#)
    - PanelReset Timer [8-18](#)
    - Ping Timeout [8-19](#)
    - Sleep Level [8-18](#)
    - Sleep Rules [8-18](#)
    - Sleep Timer [8-18](#)
    - Unusable Time [8-19](#)
  - Toner Container (Black) [2-5](#)
  - Toner Container (Cyan) [2-5](#)
  - Toner Container (Magenta) [2-5](#)
  - Toner Container (Yellow) [2-5](#)
  - Toner Container Lock Lever [2-5](#)
  - Toner Container Replacement [10-4](#)
  - TonerAlert Level [8-16](#)
  - Troubleshooting [10-11](#)
  - TWAIN [11-32](#)
    - Scanning using TWAIN [5-28](#)
    - Setting TWAIN Driver [2-32](#)
- U**
- USB [11-32](#)
  - USB Cable
    - Connecting [2-9](#)
  - USB Interface [2-7](#)
  - USB Interface Connector [2-4](#)
  - USB Keyboard [11-8](#)
  - USB Keyboard Type [8-16](#)
  - USB Memory
    - Printing [5-38](#)
    - Remove [5-42](#)
    - Save [5-40](#)
  - USB Memory Slot [2-2](#)
  - USB Port [2-4](#)
  - User Login Administration [9-2](#)
    - Adding a User [9-6](#)
    - Changing User Properties [9-9](#)
    - Enabling User Login Administration [9-3](#)
    - FAX Driver [9-15](#)
    - Group Authorization Set. [9-17](#)
    - Guest Authorization Set. [9-18](#)
    - ID Card Settings [9-22](#)
    - Local Authoriz. [9-16](#)
    - Login [2-14](#)
    - Logout [2-15](#)
    - Obtain NW User Property [9-21](#)
    - Overview of User Login Administration [9-2](#)
    - Printing [9-11](#)
    - TWAIN [9-13](#)
    - User Account Lockout Setting [9-5](#)
    - WIA [9-14](#)
  - User Login/Job Accounting [8-23](#)
    - Job Accounting [9-24](#)
    - Unknown ID Job [9-40](#)
    - User Login [9-2](#)
  - User Property [8-6](#)
- W**
- Waste Toner Box [2-5](#)
  - Waste Toner Box Replacement [10-8](#)
  - Waste Toner Cover [2-5](#)
  - WIA [11-32](#)
    - Setting WIA Driver [2-34](#)
  - Wireless Network [8-30](#)
    - Basic [8-30](#)
    - Setup [8-30](#)
  - Wireless Network Interface Kit [11-5](#)
  - WSD Scan [5-26](#)
  - WSD-PRINT [8-28](#)
  - WSD-SCAN [8-28](#)

---

## X

XPS FitTo Page 6-35  
Default 8-14

## Z

Zoom 6-18  
Default 8-13

**QUALITY  
CERTIFICATE**

This machine has passed  
all quality controls and  
final inspection

# PASSIONATE PEOPLE. FROM ALL OVER THE WORLD.



## **KYOCERA Document Solutions Europe B.V.**

Bloemlaan 4, 2132 NP Hoofddorp,  
The Netherlands  
Phone: +31-20-654-0000  
Fax: +31-20-653-1256



## **KYOCERA Document Solutions Nederland B.V.**

Beechavenue 25, 1119 RA Schiphol-Rijk,  
The Netherlands  
Phone: +31-20-5877200  
Fax: +31-20-5877260



## **KYOCERA Document Solutions (U.K.) Limited**

Eldon Court, 75-77 London Road,  
Reading, Berkshire RG1 5BS,  
United Kingdom  
Phone: +44-118-931-1500  
Fax: +44-118-931-1108



## **KYOCERA Document Solutions Italia S.p.A.**

Via Verdi, 89/91 20063 Cernusco s/N.(MI),  
Italy  
Phone: +39-02-921791  
Fax: +39-02-92179-600



## **KYOCERA Document Solutions Belgium N.V.**

Sint-Martinusweg 199-201 1930 Zaventem,  
Belgium  
Phone: +32-2-7209270  
Fax: +32-2-7208748



## **KYOCERA Document Solutions France S.A.S.**

Espace Technologique de St Aubin  
Route de l'Orme 91195 Gif-sur-Yvette CEDEX,  
France  
Phone: +33-1-69852600  
Fax: +33-1-69853409



## **KYOCERA Document Solutions Espana, S.A.**

Edificio Kyocera, Avda. de Manacor No.2,  
28290 Las Matas (Madrid), Spain  
Phone: +34-91-6318392  
Fax: +34-91-6318219



## **KYOCERA Document Solutions Finland Oy**

Atomitie 5C, 00370 Helsinki,  
Finland  
Phone: +358-9-47805200  
Fax: +358-9-47805390



## **KYOCERA Document Solutions Europe B.V., Amsterdam (NL) Zürich Branch**

Hohlstrasse 614, 8048 Zürich,  
Switzerland  
Phone: +41-44-9084949  
Fax: +41-44-9084950



## **KYOCERA Document Solutions Deutschland GmbH**

Otto-Hahn-Strasse 12, 40670 Meerbusch,  
Germany  
Phone: +49-2159-9180  
Fax: +49-2159-918100



## **KYOCERA Document Solutions Austria GmbH**

Eduard-Kittenberger-Gasse 95, 1230 Vienna,  
Austria  
Phone: +43-1-863380  
Fax: +43-1-86338-400



## **KYOCERA Document Solutions Nordic AB**

Esbogatan 16B 164 75 Kista,  
Sweden  
Phone: +46-8-546-550-00  
Fax: +46-8-546-550-10



## **KYOCERA Document Solutions Norge Nuf**

Postboks 150 Oppsal, 0619 Oslo,  
Norway  
Phone: +47-22-62-73-00  
Fax: +47-22-62-72-00



## **KYOCERA Document Solutions Danmark A/S**

Ejby Industrivej 60, DK-2600 Glostrup,  
Denmark  
Phone: +45-70223880  
Fax: +45-45765850



## **KYOCERA Document Solutions Portugal Lda.**

Rua do Centro Cultural, 41 (Alvalade) 1700-106 Lisboa,  
Portugal  
Phone: +351-21-843-6780  
Fax: +351-21-849-3312



## **KYOCERA Document Solutions South Africa (Pty) Ltd.**

KYOCERA House, Hertford Office Park,  
90 Bekker Road (Cnr. Allandale), Midrand, South Africa  
Phone: +27-11-540-2600  
Fax: +27-11-466-3050



## **KYOCERA Document Solutions Russia LLC.**

Building 2, 51/4, Schepkina St., 129110, Moscow,  
Russia  
Phone: +7(495)741-0004  
Fax: +7(495)741-0018



## **KYOCERA Document Solutions Middle East**

Dubai Internet City, Bldg. 17,  
Office 157 P.O. Box 500817, Dubai,  
United Arab Emirates  
Phone: +971-04-433-0412



## **KYOCERA Document Solutions Inc.**

2-28, 1-chome, Tamatsukuri, Chuo-ku  
Osaka 540-8585, Japan  
Phone: +81-6-6764-3555  
<http://www.kyoceradocumentsolutions.com>



